




1. TYPE 2SCR523V1
2. STRUCTURE NPN SILICON EPITAXIAL PLANAR TRANSISTOR
3. APPLICATIONS GENERAL PURPOSE SMALL SIGNAL AMPLIFIER
4. ABSOLUTE MAXIMUM RATINGS [Ta=25°C]


COLLECTOR-BASE VOLTAGE	V_{CBO}	...	50V
COLLECTOR-EMITTER VOLTAGE	V_{CEO}	...	50V
EMITTER-BASE VOLTAGE	V_{EBO}	...	5V
COLLECTOR CURRENT	I_C	...	100mA
	I_{CP}	...	200mA
			$P_W=10ms$ SINGLE PULSE
POWER DISSIPATION	P_D	...	100mW
			* EACH TERMINAL MOUNTED ON A REFERENCE LAND
JUNCTION TEMPERATURE	T_j	...	150°C
RANGE OF STORAGE TEMPERATURE	T_{stg}	...	-55~150°C

DESIGN	CHECK	APPROVAL	DATE : 23/ JUL / 2012	SPECIFICATION No. TSQ03131-2SCR523V1
			REV. : 0	ROHM Co.,Ltd.


5. ELECTRICAL CHARACTERISTICS [Ta=25°C]

PARAMETER	SYMBOL	CONDITION	MIN.	TYP.	MAX.
COLLECTOR-EMITTER BREAKDOWN VOLTAGE	BV_{CEO}	$I_C=1mA$	50V	-	-
COLLECTOR-BASE BREAKDOWN VOLTAGE	BV_{CBO}	$I_C=50\mu A$	50V	-	-
EMITTER-BASE BREAKDOWN VOLTAGE	BV_{EBO}	$I_E=50\mu A$	5V	-	-
COLLECTOR CUT-OFF CURRENT	I_{CBO}	$V_{CB}=50V$	-	-	0.1 μA
EMITTER CUT-OFF CURRENT	I_{EBO}	$V_{EB}=5V$	-	-	0.1 μA
COLLECTOR-EMITTER SATURATION VOLTAGE	$V_{CE(sat)}$	$I_C=50mA / I_B=5mA$	-	0.10V	0.30V
DC CURRENT GAIN	h_{FE}	$V_{CE}=6V / I_C=1mA$	120	-	560
TRANSITION FREQUENCY	f_T	$V_{CE}=10V / I_E=-10mA$ $f=100MHz$	-	350MHz	-
OUTPUT CAPACITANCE	C_{ob}	$V_{CB}=10V / I_E=0A$ $f=1MHz$	-	1.6pF	-

6. INTERNAL CIRCUIT



TOP VIEW



7. MARKING



“NB” MEANS 2SCR523V1

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Bipolar Transistors - BJT category](#):

Click to view products by [ROHM manufacturer](#):

Other Similar products are found below :

[619691C](#) [MCH4017-TL-H](#) [BC546/116](#) [BC557/116](#) [BSW67A](#) [NTE158](#) [NTE187A](#) [NTE195A](#) [NTE2302](#) [NTE2330](#) [NTE63](#) [C4460](#)
[2SA1419T-TD-H](#) [2SA1721-O\(TE85L,F\)](#) [2SA2126-E](#) [2SB1204S-TL-E](#) [2SC5488A-TL-H](#) [2SD2150T100R](#) [SP000011176](#) [FMMTA92QTA](#)
[2N2369ADCSM](#) [2SC2412KT146S](#) [2SC5490A-TL-H](#) [2SD1816S-TL-E](#) [2SD1816T-TL-E](#) [CMXT2207 TR](#) [CPH6501-TL-E](#) [MCH4021-TL-E](#)
[US6T6TR](#) [732314D](#) [CMXT3906 TR](#) [CPH3121-TL-E](#) [CPH6021-TL-H](#) [873787E](#) [IMZ2AT108](#) [UMX21NTR](#) [EMT2T2R](#) [MCH6102-TL-E](#)
[FP204-TL-E](#) [NJL0302DG](#) [2N3583](#) [2SA1434-TB-E](#) [2SC3143-4-TB-E](#) [2SD1621S-TD-E](#) [NTE103](#) [30A02MH-TL-E](#) [NSV40301MZ4T1G](#)
[NTE101](#) [NTE13](#) [NTE15](#)