

Technical Data Sheet

Power Management Module RRC-PMM240



Power Management Module for Mobile Applications

Features:

- 240 Watt max. output power to application
- 82 Watt max. output power to battery
- Automatic power source selection
- Wide DC input voltage range
- 3D data available of power management module and batteries for easy integration into user application
- Fits to standard smart batteries from RRC (e.g. RRC2020, RRC2024, RRC2040, RRC2040-2, RRC2054, RRC2057, ...)

Applications:

- Power management and smart battery charging capability for medical and industrial applications

Specification

Power supply Input	
Input voltage range	Min. Battery charge voltage+1V Max. 24VDC
Total input power	192W max.
Input current	8A max.
Input fuse	12A
Protection	Reverse polarity, short current

Power Management	
Automatic power source selection with seamless transition between ext. DC power supply and battery	

Environmental Condition	
Operating Temperature	-20° to +60°C
Transport & Storage Temperature	-20° to +60°C
Relative Humidity	5% - 95% non-condensing
Ambient pressure	500-1070hPa

Recommended Voltage for External AC/DC Power Supplies			
Battery architecture	DC input voltage	Power supply wattage @ 4A max input current	Power supply wattage @ 8A max input current
1SxP	6VDC	≥30W	≥60W
2SxP	12VDC	≥48W	≥96W
3SxP	15VDC	≥64W	≥128W
4SxP	19VDC	≥80W	≥160W

Regulatory Approvals	
International: IEC 60601-1(ed.3), IEC 60601-1(ed.3);am1	USA: ANSI/AAMI ES60601-1:2005/(R)2012 Canada: CAN/CSA-C22.2 NO. 60601-1:14

Mechanical Details	
Board dimensions (LxWxH)	60mm x 50mm x 11mm, without cables and connectors
Weight	Typical 22g
Connectors:	DC input & DC output (2 pin) / User interface (6 pin) / Battery connector (5 pin smart battery connector)

To facilitate a fast design-in process for developers, RRC is providing 3D data of the power management module RRC-PMM240 and the battery housings of RRC smart battery. For an application note related to the power management module with additional details contact your RRC representative. For further information on the RRC smart batteries please refer to the RRC website (www.rrc-ps.com).

Germany/Headquarters	USA	Hong Kong	China
RRC power solutions GmbH Technologiepark 1 D-66424 Homburg / Saar	RRC power solutions Inc. 18340 Yorba Linda Blvd., Suite 107-437 Yorba Linda, CA 92886-4104	RRC power solutions Ltd. S-V,6/F, Valiant Industrial Centre 2-12 Au Pui Wan Street Fo Tan, N.T., Hong Kong	RRC power solutions Ltd. Room 520, Yuanlin Building, Aiguo Road No. 3066, Luohu District, Shenzhen 518021
Tel.: +49 6841 98090	Tel.: +1 714 777 3604	Tel.: +852 2376 0106	Tel.: +86 755 8374 1908
Fax: +49 6841 9809280	Fax: +1 714 777 3658	Fax: +852 2375 0107	Fax: +86 755 8374 1861
Email: sales@rrc-ps.de	Email: usa@rrc-ps.com	Email: hkrrc@rrc-ps.cn	Email: hkrrc@rrc-ps.cn
Web: www.rrc-ps.de	Web: www.rrc-ps.com	Web: www.rrc-ps.com	Web: www.rrc-ps.com

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Battery Chargers](#) category:

Click to view products by [RRC Power Solutions](#) manufacturer:

Other Similar products are found below :

[CH0011](#) [CB1210A](#) [PS-034052](#) [GP X411 AA/AAA + 4X R6 2700MAH RECYKO](#) [CB123A](#) [CB12245A](#) [DA60U-240A-R](#) [DA200U-250A-R](#)
[MC2](#) [MC1](#) [BQ-CC55E](#) [VP4 PLUS DRAGON](#) [LCD MULTI CHARGER](#) [MINI-CHARGER](#) [5V 2.1A](#) [PB320](#) [PB50](#) [PB550 + 4XAA](#)
[2700MAH](#) [VC4](#) [POCKET-CHARGER + 4XAA 2100MAH](#) [PB-300P-12](#) [VC2](#) [MINI CHARGER + 2XAA 2100MAH](#) [CHFC3](#) [GC30U-5P1J](#)
[TSP-BCM48](#) [SBP-001](#) [PB-300N-12](#) [GC30B-11P1J](#) [GC220A12-AD1](#) [PSC-122000A-C](#) [TSP-BCM12](#) [TSP-BCMU360](#) [TSP-BCM48A](#) [H-](#)
[TRONIC AL 2000PLUS](#) [H-TRONIC HTDC 5000](#) [ES360A](#) [LS-CR45-PQ](#) [LS-CR45-PD WHITE](#) [5V 1A](#) [PB2 BLUE](#) [SC1](#) [SC2](#) [VC2S](#) [X2](#)
[X4](#) [CEF14 2XAA 2XAAA](#) [CEF27 2XAA 2XAAA](#) [CL14.4VDC-0.4A](#) [CL14.4VDC-0.7A](#)