

Low Voltage

EasyPact CVS

Moulded-case circuit breakers and switch-disconnectors
from 16 to 630 A

Catalogue
2016



Life Is On

Schneider
Electric

> Safe

> Reliable

> Simple



EasyPact CVS is...Safe

Isolation

- EasyPact CVS circuit breakers are suitable for Isolation* as defined in IEC standards 60947-2. The aim of isolation is to separate a circuit or apparatus from the remainder of a system which is energized in order the personnel may carry out work on the isolated part with complete safety.
- MCCB locking with external pad locks* enables user to isolate and undertake maintenance with utmost safety.



Isolation




Locking in OFF position

- Key locks enables to lock the breaker in OFF position ensuring safety and better control on installation.
- It also helps in interlocking multiple circuit breakers in an installation.



Class II front Face

- All EasyPact CVS* MCCBs are class II Front face devices, they may be installed through the door of class II switchboards without downgrading the switchboard insulation. Installation requires no special operation, even when the Circuit Breaker is equipped with a rotary handle.




Class II panel with circuit breaker having a class II front face





EasyPact CVS is...Reliable



Conforms to IEC 60947-2 for circuit breaker

- Tested at renown international laboratories like KEMA
- Complete range with $I_{cs} = 100\% I_{cu}$



High electrical & Mechanical endurance

- 30000 mechanical operations for 100A
- 12000 electrical operations for 100A



Reliable accessories

- Continuous rated shunt coils
- Multifunctional Aux./Alarm contact
- Unique electrical fault trip indication (SDE)




EasyPact CVS offer protection for human as well as Electrical installation


- Earth leakage protection through Vigi Module to protect human against leakage current

Fault current limitation technology

- EasyPact CVS Double break mechanism ensures high fault current limitation
 - @ Reduces thermal stresses on electrical distribution network
 - @ Increases the life of cable installation



Current limitation technology



EasyPact CVS Double break Roto mechanism




EasyPact CVS is...Simple

Only two frame sizes up to 630A

Frame - I	100 - 250 A
Frame - II	400 - 630A

- Common and snap fit accessories up to 630A
- Single OF contact for ON/OFF , Trip indication
- Single Shunt coil for remote tripping
- Single Under Voltage coil

- EasyPact CVS share same foot print of Compact Family MCCBs.
 - mounting dimensions
 - easy retrofitting
 - system upgradeability



EasyPact CVS stands for customer value

EasyPact CVS 100 to 630 A



Panel builders

- Only two frame sizes up to 630A
- Common accessories for complete range (ON/OFF Auxiliaries/Shunt/UV etc)
- Line load reversibility for entire range
- Suitable for class II switchboards



End Users

- Isolation as a standard feature enhances safety
- Excellent current limiting capability reduces stresses on cables, busbars and loads
- Continuous rated accessories increase system reliability
- Modular earth leakage protection ensure human/injury protection



OEMs

- High endurance's and maintenance free operation ensure continuous performance of machines
- Unique common accessories help standardisation of components



Contractors

- Sufficient pole pitch helps to terminate Copper and Aluminium busbars or cables
- Easy availability of the product due to less number of components and size
- Designed to perform in demanding applications

The easy choice for quality and value

EasyPact CVS

LV circuit breakers from 100 to 630A



Schneider
Ele

- > Do you strain to find circuit breakers that are simple as well as flexible and safe?
- > Has it been difficult to find high quality circuit breakers at the right price point?
- > Do you need the reach, support and accessibility of a global leader, with the value of a local supplier?



Buildings



Industry

Gain peace of mind,
quality, and value for
your installations





Over 75% of Schneider Electric
manufactured products awarded
Green Premium eco-mark

Green Premium, stamping the most
eco-friendly products of the industry



Green
Premium™
Product

Green Premium is the only label
allowing you to develop effectively an
environmental policy and to promote it,
while preserving your business efficiency.

It guarantees compliance with the most
up-to-date environmental regulations,
but it is more than this.

With Green Premium eco-mark,
Schneider Electric helps you:

- Calculate the carbon footprint of
the solutions you offer
- Ensure full regulation compliance about
substances and chemical components
- Deliver all appropriate information
to certify eco-design of your solutions
- Easily manage products end of life,
while ensuring optimized recycling.

With Green Premium, Schneider Electric commits to be transparent and
provide extensive and reliable information on environmental impacts of its products.

RoHS

Schneider Electric applies RoHS requirements to all its products and works to reduce
the numerous ones which are not in the scope of the regulation. Compliance
documents are available for all products involved.

REACH

Schneider Electric applies REACH regulation worldwide, and releases all information
about presence of Substances of Very High-Concern (SVHC) in its products.

PEP: Product Environmental Profile

For all its products, Schneider Electric publishes the most complete set of
data, including carbon footprint and energy consumption for each of the product
phases, in compliance with ISO 14025 PEPecopassport program.

EoLI: End of Life Instructions

Available at a click, these documents provide:

- Recyclability rates of the products
- Information to mitigate personnel hazards during dismantling and before
recycling operations
- Parts identification either for re-use, or for selective treatment to mitigate
hazards, or incompatibility with usual recycling process.



Discover what we
mean by green
and

CHECK a PRODUCT!

Presentation

Functions
and characteristics

Installation
recommendations

Dimensions
and connection

Additional characteristics

Catalogue numbers

EasyPact CVS100BS

Functions and characteristics



Introduction

General characteristics

Characteristics and performance

Protection of distribution systems

TM-D thermal-magnetic trip units

TM-G thermal-magnetic trip units

ETS 2.3 electronic trip unit and accessories

Earth-leakage protection

Motor protection

MA instantaneous trip units

Switch-disconnectors

Accessories and auxiliaries

Overview

Device installation

Connection of devices

Selection of auxiliaries

Indication contacts

Remote tripping

Rotary handles

Locks and sealing accessories

Escutcheons and protection collars


Installation recommendations

Dimensions and connection

Additional characteristics


Catalogue numbers

EasyPact CVS100BS



Standardised characteristics indicated on the rating plate:

- 1 Type of device: frame size and breaking capacity class
- 2 U_i: rated insulation voltage.
- 3 U_{imp}: rated impulse withstand voltage.
- 4 I_{cs}: service breaking capacity.
- 5 I_{cu}: ultimate breaking capacity for various values of the rated operational voltage U_e
- 6 U_e: operational voltage.
- 7 Colour label indicating the breaking capacity class.



- 8 Suitable for Isolation symbol.
- 9 Reference standard.

Note: when the circuit breaker is equipped with an extended rotary handle, the door must be opened to access the rating plate.

Compliance with standards

EasyPact CVS circuit breakers and auxiliaries comply with the following recommendations:

- IEC 60947-1: general rules
- IEC 60947-2: circuit breakers
- IEC 60947-3: switch-disconnectors

Pollution degree

EasyPact CVS circuit breakers are certified for operation in pollution-degree environments as defined by IEC standards 60947-1 and 60664-1 (industrial environments).

Climatic withstand

EasyPact CVS circuit breakers have successfully passed the tests defined in the following standards for extreme atmospheric conditions:

- IEC 60068-2-1: dry cold (-55°C)
- IEC 60068-2-2: dry heat (+85°C)
- IEC 60068-2-30: damp heat (95 % relative humidity at 55°C)
- IEC 60068-2-52 severity level 2: salt mist.

Environment

EasyPact CVS respects the European environment directive EC/2002/95 on the restriction of hazardous substances (RoHS). All EasyPact CVS production sites have set up an ISO 14001 certified environmental management system.

Ambient temperature

- EasyPact CVS circuit breakers can be used between -25°C and +70°C. At temperatures higher than 40°C (65°C for circuit breakers used to protect feeders), devices must be derated (see page B-2).
- Circuit breakers should be put into service under normal ambient, operating temperature conditions. Exceptionally, the circuit breaker can be put into service when the ambient temperature is between -35°C and -25°C.
- The permissible storage-temperature range for EasyPact CVS circuit breakers is the original packing is -50°C and +85°C.

Suitable for isolation with positive contact indication

All EasyPact CVS circuit breakers are suitable for isolation as defined in standard 60947-2:

- The isolation position corresponds to the O (OFF) position.
 - The operating handle cannot indicate the OFF position unless the contacts are effectively open.
 - Padlocks cannot be installed unless the contacts are open.
- Installation of a rotary handle does not alter the reliability of the position-indication system.

The isolation function is certified by tests guaranteeing:

- The mechanical reliability of the position-indication system
- The absence of leakage currents
- Over voltage withstand capacity between upstream and downstream

The tripped position does not ensure isolation with positive contact indication. Only the OFF position guarantees isolation.

Installation in class II switchboards

All EasyPact CVS circuit breakers are class II front face devices. They can be installed through the door of class II switchboards (as per IEC standards 60664-1 and 60664-1) without downgrading switchboard insulation. Installation in special operations, even when the circuit breaker is equipped with a rotary handle.

Degree of protection

The following indications are in accordance with standards IEC 60529 (IP protection) and IEC 62262 (IK protection against external mechanical impact).

Bare circuit breaker with Escutcheon:

- with toggle: IP40, IK07 front face
- with extended rotary handle: IP 54, IK08

Circuit breaker installed in a switchboard:

- with toggle: IP40, IK07 front face
- with extended rotary handle: IP 54, IK08

PE106447



EasyPact CVS100/160/250

PE106448



EasyPact CVS400/630

Common characteristics

Rated voltages		
Insulation voltage (V)	Ui	
Impulse withstand voltage (kV)	Uimp	
Operational voltage (V)	Ue	AC 50/60 Hz
Suitability for isolation		IEC/EN 60947-2
Utilisation category		
Pollution degree		IEC 60664-1

Circuit breakers

Performance

Electrical characteristics as per IEC 60947-2

Rated current (A)	In	40 °C
-------------------	-----------	-------

Number of poles

Breaking capacity levels

Breaking capacity (kA rms)		
Icu	AC 50/60 Hz	220/240 V 380/415 V 440 V

Service breaking capacity (kA rms)		
Ics	AC 50/60 Hz	220/240 V 380/415 V 440 V

Durability (C-O cycles)	Mechanical	
	Electrical	415V

Protection

Short-circuit protection	Magnetic only
Overload/short-circuit protection	Thermal magnetic
	Electronic
	with neutral protection
Earth-leakage protection	By Vigi module

Installation/connections

Dimensions and weights

Dimensions (mm)	Fixed, front connections	3P
W x H x D		4P
Weight (kg)	Fixed, front connections	3P
		4P


Connections

Connection terminals	Pitch	Without
Large Cu or Al cables	Cross-section	mm ²

CVS100		CVS160		CVS250		CVS400		CVS630	
100		160		250		400		630	
3, 4		3, 4		3, 4		3, 4		3, 4	
B	F	B	F	B	F	F	N	F	N
40	70	40	70	40	70	40	70	40	70
25	36	25	36	25	36	36	50	36	50
20	36	20	36	20	36	30	42	30	42
40	70	40	70	40	70	40	70	40	70
25	36	25	36	25	36	36	50	36	50
15	18	15	18	15	18	23	32	23	32
30000		25000		20000		15000		15000	
30000		25000		20000		12000		8000	
12000		12000		10000		6000		4000	
■		■		■		■		■	
■		■		■		■		■	
-		-		-		■		■	
-		-		-		■		■	
■		■		■		■		■	
105 x 161 x 86		105 x 161 x 86		105 x 161 x 86		140 x 255 x 110		140 x 255	
140 x 161 x 86		140 x 161 x 86		140 x 161 x 86		185 x 255 x 110		185 x 255	
1.8		1.8		2.0		4.7		5.2	
2.2		2.3		2.6		6.3		7.1	
35/45 mm		35/45 mm		35/45 mm		45/52.5 mm		45/52.5 mm	
						45/70 mm		45/70 mm	
300		300		300		4 x 240		4 x 240	

TM-D thermal-magnetic trip units can be used on EasyPact CVS100-630 circuit breakers with performance levels B/F/N.

TM-D thermal-magnetic trip units



Protection

TM-D trip units are used mainly in electrical distribution applications for protection of cables supplied by transformers.

Thermal protection (Ir)

Thermal protection operates according to:

- Ir that can be adjusted in amps from 0.7 to 1 times the rating of the trip unit (250 A), corresponding to settings from 11 to 250 A for the range of trip units up to 250 A
- a non-adjustable time delay.

Magnetic protection (Im)

Short-circuit protection with a fixed or adjustable pick-up Im that initiates tripping if exceeded.

- TM-D: fixed pick-up, Im, for 16 to 250 A ratings and adjustable from 190 to 800 A for 320 to 600 A ratings, 4.2 to 8.3 x In for 600 A rating.

Protection versions

- 3-pole:
 - 3P 3D: 3-pole frame (3P) with detection on all 3 poles (3D)
 - 4P 3D: 4-pole frame (4P) with detection on 3 poles (3D).
- 4P 4D: 4-pole frame (4P) with detection on all 4 poles (same threshold for phase and neutral).

Thermal-magnetic trip units		TM16D to 250D										TM320D to 600D					
Ratings (A)	In at 40 °C ⁽¹⁾	16	25	32	40	50	63	80	100	125	160	200	250	320	400	500	600
Circuit breaker	CVS100	■	■	■	■	■	■	■	■	-	-	-	-				
	CVS160	-	-	-	-	-	-	-	■	■	■	-	-				
	CVS250	-	-	-	-	-	-	-	-	-	■	■	■				
	CVS400													■	■	-	-
	CVS630													-	-	■	■
Magnetic protection																	
Pick-up (A)	Im	fixed												adjustable			
accuracy ±20 %	CVS100	190	300	400	500	500	500	640	800								
	CVS160/250								800	1250	1250	2000	2500				
	CVS400													1600 to 3200 (320A), 2000 to 2500			
	CVS630													2500 to 5000			
Thermal protection																	
Pick-up (A) tripping between 1.05 and 1.30 Ir	Ir = In x ...	adjustable in amps from 0.7 to 1 x In															
Neutral protection																	
Unprotected neutral	4P 3D	no detection															
Fully protected neutral	4P 4D	1 x Ir															

(1) For temperatures not equal to 40°C, the thermal protection characteristics are modified. See the temperature derating table on page B-2.


Note: All the trip units have a transparent lead-sealable cover that protects access to the adjustment dials.

Protection of distribution systems

TM-G thermal-magnetic trip units

TM-G thermal-magnetic trip units can be used on EasyPact CVS160-250 circuit breakers with performance levels B for the protection of generators or long cable length.

TM-G thermal-magnetic trip units



Protection

TM-G, with a low pick-up for generators (lower short-circuit currents than transformers) and distribution system with long cable lengths (fault current limited by impedance of the cable).

Thermal protection (Ir)

Thermal protection operates according to:

- Ir that can be adjusted in amps from 0.7 to 1 times the rating of the trip unit (160 to 250 A), corresponding to settings from 56 to 250 A for the range of trip unit ratings
- a non-adjustable time delay.

Magnetic protection (Im)

Short-circuit protection with a fixed Im that initiates instantaneous tripping.

- TM-G: fixed pick-up, Im, for 80 to 250 A ratings.


Protection versions

- 3-pole:
 - 3P 3D: 3-pole frame (3P) with detection on all 3 poles (3D)
- 4-pole:
 - 4P 3D: 4-pole frame (4P) with detection on 3 poles (3D).

Thermal-magnetic trip units		TM80G to 250G			
Ratings (A)	In at 40 °C ⁽¹⁾	80	100	125	160
Circuit breaker	CVS160	■	■	■	■
	CVS250	-	-	-	-
Magnetic protection					
Pick-up (A)	Im				
accuracy ±20 %	CVS160/250	200	320	440	500
Thermal protection					
Pick-up (A)	Ir = In x ...	adjustable in amps from 0.7 to 1 x In			
tripping between	1.05 and 1.30 Ir				
Neutral protection					
Unprotected neutral	4P 3D	no detection			

Note: All the trip units have a transparent lead-sealable cover that protects access to the trip unit dials.

ETS 2.3 electronic trip unit



Protection

The protection functions can be set using the adjustment dials.

Overload protection

Long-time protection with an adjustable threshold and fixed tripping delay

- Ir base setting (6-position dial from 0.5 to 1)

Short-circuit protection

Short-time and instantaneous protection:

- short-time protection with an adjustable pick-up and fixed tripping delay
- instantaneous protection with fixed pick-up.

Protection of the fourth pole

On 4-pole circuit breakers, neutral protection is set using a three-position dial: 4P 3D (neutral unprotected), 4P 3D + N/2 (neutral protection at 0.5 In), 4P 4D (neutral protection at In).

Trip units		ETS 2.3
Ratings (A) of circuit breaker	In 20 to 70 °C	400 630
Circuit breaker	CVS400 F/N CVS630 F/N	■ - - ■
Overload protection (Long time)		
Current setting	$I_r = I_n \times \dots$	0.5...1 adj., 6 settings
Time delay (s) (min....max.)	at 1.5 x Ir at 6 x Ir at 7.2 Ir	fixed 90...180 5...7.5 3.2...5.0
Short-circuit protection (Short time)		
Pick-up (A) accuracy ± 15 %	$I_{sd} = I_r \times \dots$	2...10 adj, 8 settings
Time delay (ms)	max. resettable time max. break time	fixed ≤ 40 ≤ 60
Short-circuit protection (instantaneous)		
Pick-up (A)	$I_i = I_n \times \dots$	11
Protection of the fourth pole		
Neutral unprotected	4P 3D	no protection
Neutral protection at 0.5 In	4P 3D + N/2	0.5 x Ir
Neutral protection at In	4P 4D	1 x Ir
Thermal memory		
	CVS400 F/N CVS630 F/N	Yes Yes

Test equipment for ETS electronic trip unit

Mini test kit

The mini test kit is a portable unit requiring no external power supply, used for the operation of the electronic trip unit and circuit breaker tripping. It connects to the test connector on the front of the circuit breaker. Required power source: five 9 V alkaline batteries (not supplied).

Portable test kit

The portable test kit is used to check all aspects of the protection functions.

- long time protection
- short time protection
- instantaneous protection
- earth-fault protection.

Required power source: 110 or 220 V AC, 50/60 Hz.

Spare test plug and wiring kit

A spare test plug and wiring kit are available for this offer.

Earth-leakage protection

Add-on protection against insulation faults on a Vigi module

A Vigi module can be added to any three or four-pole CVS100 to 630 circuit breaker to form a Vigi CVS.



Vigi CVS100 to 630



PB1103580-36

Circuit breaker with add-on Vigi module (Vigi CVS)

- For general characteristics of circuit breakers, see pages A-2 and A-3.
- Add-on Vigi modules: Earth-leakage protection is achieved by installing a Vigi module (characteristics and selection criteria on next page) directly on the circuit breaker terminals. It directly actuates the trip unit (magnetic, thermal-magnetic, electronic, etc.).

Vigi CVS100 to 630 circuit breakers with earth-leakage protection

Addition of the Vigi module does not alter circuit-breaker characteristics.


- compliance with standards
- degree of protection, class II front-face insulation
- positive contact indication
- electrical characteristics
- trip-unit characteristics
- installation and connection modes
- indication, measurement and control auxiliaries
- installation and connection accessories.

Dimensions and weights		CVS100/160/250	CVS400/630
Dimensions	3-pole	105 x 236 x 86	140 x 355 x 86
W x H x D (mm)	4-pole	140 x 236 x 86	185 x 355 x 86
Weight (kg)	3-pole	2.5	8.8
	4-pole	3.2	10.8

Vigi earth-leakage protection modules

Compliance with standards

- IEC 60947-2, annex B.
- Decree dated 14 November 1988 (for France).
- IEC 60755, class A, immunity to DC components up to 6 mA
- operation down to -25 °C as per VDE 664.



- 1 Sensitivity setting
- 2 Time-delay setting (for selective earth-leakage protection).
- 3 Lead-seal fixture for controlled access to settings.
- 4 Test button simulating an earth-fault for regular checks on the tripping function
- 5 Reset button (reset required after earth-fault tripping).
- 6 Rating plate

Vigi module selection

Type	Vigi ME	Vigi MH	Vigi ME
Number of poles	3, 4 ⁽¹⁾	3, 4 ⁽¹⁾	3, 4 ⁽¹⁾
CVS100	■	■	-
CVS160	■	■	-
CVS250	-	■	-
CVS400	-	-	■
CVS630	-	-	■

Protection characteristics

Sensitivity	fixed	adjustable	adjustable
$I_{\Delta n}$ (A)	0.3	0.03 - 0.3 - 1 - 3 - 10	0.3 - 1 - 3
Time delay	fixed	adjustable	adjustable
Intentional delay (ms)	< 40	0 - 60 ⁽²⁾ - 150 ⁽²⁾ - 310 ⁽²⁾	0 - 60 - 150
Max. break time (ms)	< 40	< 40 < 140 < 300 < 800	< 40 < 140
Rated voltage V AC 50/60 Hz	200...440	200... 440	200...440

- ⁽¹⁾ Vigi 3P modules may also be used on 3P circuit breakers used for two-phase systems.
⁽²⁾ If the sensitivity is set to 30 mA, there is no time delay, whatever the time-delay setting.


Operating safety

The Vigi module is a user safety device. It must be tested at regular intervals (every 6 months) via the test button.

Motor protection

MA instantaneous trip units

MA magnetic trip units for EasyPact CVS100



Circuit breakers with an MA trip unit are combined with a thermal relay contactor or a starter.

Protection

Magnetic protection (Im)

Short-circuit protection with an adjustable pick-up I_m that initiates instantaneous tripping if exceeded.

■ $I_m = I_n \times \dots$ is set on an adjustment dial in multiples of the rating:


- 6 to 14 x I_n (2.5 to 100 A ratings)
- 9 to 14 x I_n (150 to 220 A ratings)
- 6 to 13 x I_n (320 to 500 A ratings)

Protection version

■ 3-pole (3P 3D): 3-pole frame (3P) equipped with detection on all 3 poles

Motor protection up to 250 kW

Motor protection rating (kW)			
CVS 100/160/250		1.1...110	
CVS 400/630			18.5...250
Breaking capacity (kA rms)	B	25	25
	F	36	36
	N	-	-



CVS100 to 630 circuit breakers, equipped with an MA magnetic trip unit with adjustable thresholds, offer:

- short-circuit protection
- suitability for isolation.

CVS100 to 630 circuit breakers with trip unit are supplied ready-assembled.

MA trip units											
Ratings (A)	I_n at 65 °C	2.5	6.3	12.5	25	50	100	150	220	320	
Circuit breaker	CVS100	■	■	■	■	■	■	-	-	-	
	CVS160	-	-	-	-	-	■	■	-	-	
	CVS250	-	-	-	-	-	-	■	■	-	
	CVS400	-	-	-	-	-	-	-	-	■	
	CVS630	-	-	-	-	-	-	-	-	-	
Short-circuit protection (magnetic)											
Pick-up (A)	$I_m = I_n \times \dots$	setting						setting		setting	
CVS100		6...14 x I_n									
CVS160/250		-						9...14 x I_n		-	
CVS400/630		-						-		6...13 x I_n	

Installation standards require upstream protection. However EasyPact CVS100 to 630 NA switch-disconnectors are self-protected by their high-set magnetic release.

PB106451



EasyPact CVS100 to 250 NA

PB106452



EasyPact CVS400 to 630 NA

Switch-disconnectors

Electrical characteristics as per IEC 60947-3 and EN 60947-3

Conventional thermal current (A)	I_{th}	50 °C
Number of poles		
Operational current (A) depending on the utilisation category	I_e	AC 50/60 Hz 220/240 V 380/415 V 440 V
Short-circuit making capacity (kA peak)	I_{cm}	min. (switch-disconnector alone) max. (protection by upstream breaker)
Rated short-time withstand current (A rms)	I_{cw}	for 1 s 3 s 20 s
Durability (C-O cycles)	mechanical	
	electrical	AC 415 V

Protection

Add-on earth-leakage protection By Vigi module

Additional indication and control auxiliaries

Indication contacts

Voltage releases MX shunt release
MN undervoltage release

Installation/connections



Dimensions (mm)	fixed, front connections	3P
W x H x D		4P
Weight (kg)	fixed, front connections	3P 4P

CVS100NA	CVS160NA	CVS250NA	CVS400NA	CVS630NA
100	160	250	400	630
3, 4	3, 4	3, 4	3, 4	3, 4
AC22A / AC23A	AC22A / AC23A	AC22A / AC23A	AC22A / AC23A	AC22A / AC23A
100	160	250	400	630/500
100	160	250	400	630/500
100	160	250	400	630/500
2.6	3.6	4.9	7.1	8.5
75	75	75	105	105
1800	2500	3500	5000	6000
1800	2500	3500	5000	6000
690	960	1350	1930	2320
30000	25000	20000	15000	15000
AC22A / AC23A	AC22A / AC23A	AC22A / AC23A	AC22A / AC23A	AC22A / AC23A
8000	8000	6500	4000	2500
■			■	
■			■	
■			■	
■			■	
105 x 161 x 86			140 x 255 x 110	
140 x 161 x 86			185 x 255 x 110	
1.5 to 1.8			5.2	
2.0 to 2.2			6.8	


Insulation accessories ▶ E-9, E-19

Connection ▶ A-14


DE400001




Sealable terminal shields



Interphase barriers



Terminal extensions



Cable connectors

Cable connectors


Electrical auxiliaries ▶ A-17




Indication contact



Voltage release




Monitoring ▶ A-8




Earth leakage protection (VigiCVS)

Control accessories ▶ A-19



Direct rotary handle



Extended rotary handle


Accessories and auxiliaries

Device installation


CVS circuit breakers may be installed horizontally, vertically or flat on their back, without derating performance levels.

Fixed circuit breakers


Fixed circuit breakers are designed for standard connection using bars and lugs. Bare-cable connectors are available for connection to bare copper cables.




Mounting on a backplate.



Mounting on rails.




Mounting on a rail (with adaptor).



Mounting on a Prisma mounting plate.

Fixed circuit breakers are designed for standard front connection using bars or cables with lugs. Cable connectors are available for bare cables. Rear connection is also possible.




DB400013




DB112169

Insulated bar.




DB112170

Small lug for copper cables.




DB112171

Small lug for Al cables.




DB112172

Straight terminal extensions.



DB112173

Right-angle terminal extensions



DB112177

Spreaders.

Front connection

Bars or cables with lugs

Standard terminals

EasyPact CVS100 to 630 come with terminals comprising snap-in nuts

- EasyPact CVS100: M6 nuts and screws.
- EasyPact CVS160/250: M8 nuts and screws
- EasyPact CVS400/630: M10 nuts and screws.

These terminals may be used for:

- direct connection of insulated bars or cables with lugs
- terminal extensions.

Interphase barriers or terminal shields are recommended. They are mandatory for certain connection accessories (in which case the interphase barriers are

Bars

When the switchboard configuration has not been tested, insulated bars are mandatory.

Maximum size of bars

EasyPact CVS circuit breaker	100/160/250	400	
Without spreaders	pitch (mm)	35	45
	maximum bar size (mm)	20 x 3	32
With spreaders	pitch (mm)	45	52
	maximum bar size (mm)	32 x 2	40

Crimp lugs

There are two modules of lugs, for aluminium and copper cables.

Interphase barriers or long terminal shields must be used with narrow lugs. They are supplied with interphase barriers.

EasyPact CVS circuit breaker	100/160/250	400	
Copper cables	size (mm ²)	150, 185	240
	crimping	hexagonal barrels or p	
Aluminium cables	size (mm ²)	150, 185	240
	crimping	hexagonal barrels	

Terminal extensions

Extensions with anti-rotation ribs can be attached to the standard terminals. They provide numerous connection possibilities in little space:

- straight terminal extensions
- right-angle terminal extensions

Spreaders

Spreaders may be used to increase the pitch:


- CVS100 to 250: the 35 mm pitch can be increased to 45 mm
 - CVS400/630: the 45 mm pitch can be increased to 52 or 70 mm.
- Bars, cable lugs or cable connectors can be attached to the ends.

Pitch (mm) depending on the type of spreader

EasyPact CVS circuit breaker	CVS100 to 250	CVS400/630
Without spreaders	35	45
With spreaders	45	52

Accessories and auxiliaries

Connection of devices



Bare cables

Bare-cable connectors may be used for both copper and aluminium cables.

1-cable connectors for EasyPact CVS100 to 250

The connectors snap directly on to the device terminals or are secured with right-angle and straight terminal extensions as well as spreaders.

1-cable connectors for EasyPact CVS400 to 630


The connectors are screwed directly to the device terminals.

2-cable connectors for EasyPact CVS100 to 250 and 400/630

The connectors are screwed to device terminals or right-angle terminal

Maximum size of cables depending on the type of connector

EasyPact CVS circuit breaker		100/160	250	400/630
Steel connectors	1.5 to 95 mm ²	■		
Aluminium connectors	25 to 95 mm ²	■	■	
	120 to 185 mm ²	■	■	
	2 cables 50 to 120 mm ²	■	■	
	2 cables 35 to 240 mm ²			■
	35 to 300 mm ²			■



Rear connection


Device mounting on a backplate with suitable holes enables rear connection.

Bars or cables with lugs

Rear connections for bars or cables with lugs are available in two lengths and can be positioned flat, on edge or at 45° angles depending on how the rear connections are positioned.

The rear connections are simply fitted to the device connection terminals. Various combinations of rear connection lengths and positions are possible on the device.

DB11593



EasyPact CVS100/160/250

Standard

All EasyPact CVS100/160/250 circuit breakers and switch-disconnectors for the electrical auxiliaries listed below.

5 indication contacts (see page A-17)


- 2 ON/OFF (OF1 and OF2)
- 1 trip indication (SD)
- 1 fault-trip indication (SDE)
- 1 earth-fault indication (SDV), when the device is equipped with a V

1 remote-tripping release (see page A-18)

- either 1 MN undervoltage release
- or 1 MX shunt release.

All these auxiliaries can be installed with a rotary handle.

DB115590



EasyPact CVS400/630

Standard

All EasyPact CVS400/630 circuit breakers and switch-disconnectors for the electrical auxiliaries listed below.

6 indication contacts (see page A-17)

- 3 ON/OFF (OF3)
- 1 trip indication (SD)
- 1 fault-trip indication (SDE)
- 1 earth-fault indication (SDV), when the device is equipped with a V

1 remote-tripping release (see page A-18)

- either 1 MN undervoltage release
- or 1 MX shunt release.

All these auxiliaries can be installed with a rotary handle.

The illustration shown (TMD, MA, NA and ETS 2.3 standard) indicates possibilities depending on the type of trip unit.

Accessories and auxiliaries

Indication contacts

One contact model provides circuit-breaker status indications (OF - SD - SDE - SDV).

DB125540



Indication contacts.

These common-point changeover contacts provide remote circuit-breaker information.

They can be used for indications, electrical locking, relaying, etc. They comply with the IEC 60947-5 international recommendation.

Functions

Breaker-status indications, during normal operation or after a fault

A single type of contact provides all the different indication functions:

- OF (ON/OFF) indicates the position of the circuit breaker contacts
- SD (trip indication) indicates that the circuit breaker has tripped due to
 - an overload
 - a short-circuit
 - an earth fault (Vigi)
 - operation of a voltage release
 - operation of the “push to trip” button
 - disconnection when the device is ON.

The SD contact returns to de-energised state when the circuit breaker is reset.

- SDE (fault-trip indication) indicates that the circuit breaker has tripped due to
 - an overload
 - a short-circuit
 - an earth fault (Vigi)
- SDV indicates that the circuit breaker has tripped due to an earth fault. It returns to de-energised state when the Vigi module is reset.

Installation

■ OF, SD, SDE and SDV functions: a single type of contact provides all the different indication functions, depending on where it is inserted in the circuit breaker. The contacts clip into slots behind the front cover of the circuit breaker (or the terminal block for the SDV function).


The SDE function on a CVS100 - 630 A equipped with a magnetic, thermal or ETS2.3 trip unit requires the SDE adaptor.

Electrical characteristics of auxiliary contacts

Contacts		Standard				Low level	
Types of contacts		All				OF, SD, SDE	
Rated thermal current (A)		6				5	
Minimum load		100 mA at 24 V DC				1 mA at 4 V DC	
Utilisation cat. (IEC 60947-5-1)		AC12	AC15	DC12	DC14	AC12	AC15
Operational current (A)	24 V AC/DC	6	6	6	1	5	3
	48 V AC/DC	6	6	2.5	0.2	5	3
	110 V AC/DC	6	5	0.6	0.05	5	2.5
	220/240 V AC	6	4	-	-	5	2
	250 V DC	-	-	0.3	0.03	5	-
	380/440 V AC	6	2	-	-	5	1.5




MX or MN voltage release.



Opening conditions of the MN release.




Closing conditions of the MN release.



MN release with a time-delay unit.

Wiring diagram for emergency-off function with MN + time-delay unit.



Opening conditions of the MX release.

MN undervoltage release

- This release trips the circuit breaker when the control voltage drops below the tripping threshold
- The tripping threshold is between 0.35 and 0.7 times the rated voltage
- Circuit breaker closing is possible only if the voltage exceeds 0.85 times the rated voltage.

Characteristics

Power supply	V AC	50/60 Hz: 24 - 48 - 100/130 - 200
		50 Hz: 380/415 60 Hz: 208/220
Operating threshold	V DC	12 - 24 - 30 - 48 - 60 - 125 - 250
	Opening	0.35 to 0.7 Un
	Closing	0.85 Un
Operating range		0.85 to 1.1 Un
Consumption (VA or W)		Pick-up: 10 - Hold: 5
Response time (ms)		50

Time-delay unit for an MN release

A time delay unit for the MN release eliminates the risk of nuisance tripping during a transient voltage dip lasting ≤ 200 ms. For shorter micro-outages, a capacitor provides temporary supply to the MN at $U > 0.7$ to ensure closing. The correspondence between MN releases and time-delay units is shown in the table below.

Power supply	Corresponding MN release
Unit with fixed delay 200 ms	
48 V AC	48 V DC
220 / 240 V AC	250 V DC
Unit with adjustable delay (0.5s, 0.9s, 1.5s, 3s)	
48 - 60 V AC/DC	48 V DC
100 - 130 V AC/DC	125 V DC
220 - 250 V AC/DC	250 V DC

MX shunt release

The MX release opens the circuit breaker via an impulse-type (≥ 20 ms) maintained order.

Opening conditions

When the MX release is supplied, it automatically opens the circuit breaker. This is ensured for a voltage $U \geq 0.7 \times U_n$.

Characteristics

Power supply	V AC	50/60 Hz: 24 - 48 - 100/130 - 200
		50 Hz: 380/415 60 Hz: 208/220
	V DC	12 - 24 - 30 - 48 - 60 - 125 - 250
Operating range		0.7 to 1.1 Un
Consumption (VA or W)		Pick-up: 10
Response time (ms)		50

Circuit breaker control by MN or MX

When the circuit breaker has been tripped by an MN or MX release, it cannot be reclosed before it can be reclosed.

MN or MX tripping takes priority over manual closing.

In the presence of a standing trip order, closing of the contacts, even if it is not possible.

Connection using wires up to 1.5mm² to integrated terminal blocks.

Note: circuit breaker opening using an MN or MX release must be reserved for safety functions. This type of tripping increases wear on the opening mechanism. Repeated use reduces the mechanical endurance of the circuit breaker by 50 %.

Accessories and auxiliaries

Rotary handles

There are two types of rotary handle:

- direct rotary handle
- extended rotary handle.

PB106483



EasyPact CVS with a rotary handle.

PB106484



EasyPact CVS with an extended rotary handle installed at the back of a switchboard, with the keylock option and key.

PB106485



PB106486



Direct rotary handle

Standard handle

Degree of protection IP40, IK07.

The direct rotary handle maintains:

- visibility of and access to trip-unit settings
- suitability for isolation
- indication of the three positions O (OFF), I (ON) and tripped
- access to the "push to trip" button.

Device locking

The rotary handle facilitates circuit-breaker locking.

■ Padlocking:

- standard situation, in the OFF position, using 1 to 3 padlocks, shackle 8 mm, not supplied



Extended rotary handle

Degree of protection IP54, IK08.

The extended rotary handle makes it possible to operate circuit breaker from the back of switchboards, from the switchboard front.

It maintains:

- visibility of and access to trip-unit settings
- suitability for isolation
- indication of the three positions O (OFF), I (ON) and tripped.

Device and door padlocking

Padlocking locks the circuit-breaker handle and disables door opening

- standard situation, in the OFF position, using 1 to 3 padlocks, shackle 8 mm, not supplied

Parts of the extended rotary handles

- A unit that replaces the front cover of the circuit breaker (secured by a key)
- An assembly (handle and front plate) on the door that is always secured in the same position, whether the circuit breaker is installed vertically or horizontally
- An extension shaft that must be adjusted to the distance. The min/max distance between the back of circuit breaker and door is:
 - 185...600 mm for EasyPact CVS100 to 250
 - 209...600 mm for EasyPact CVS 400/630.


Manual source-changeover systems

An additional accessory interlocks two devices with rotary handles to create a manual source-changeover system. Closing of one device is possible only if the other is open.

This function is compatible with direct or extended rotary handles.


Up to three padlocks can be used to lock in the OFF or ON position.

DB400025




Toggle locking using padlocks and an accessory:
Removable device

DB400026




Fixed device attached to the case.

DB400027




Rotary-handle locking using a keylock.

DB400028




DB400029



Rotary-handle locking using a padlock or a keylock.

DB115033



Sealing accessories.

Locks

Locking in the OFF position guarantees isolation as per IEC 60947-2. Locking systems can receive up to three padlocks with shackle diameters ranging from 8 mm (padlocks not supplied). Certain locking systems require an additional accessory.

Control device	Function	Means	Required accessories
Toggle	Lock in OFF position	Padlock	Removable device
	Lock in OFF or ON position	Padlock	Fixed device
Direct rotary handle	Lock in	Padlock	-
	<ul style="list-style-type: none"> ■ OFF position ■ OFF or ON position ⁽¹⁾ 	Keylock	Locking device
Extended rotary handle	Lock in	Padlock	-
	<ul style="list-style-type: none"> ■ OFF position ■ OFF or ON position ⁽¹⁾ 		
	<ul style="list-style-type: none"> ■ OFF or ON position ⁽¹⁾ with door opening prevented ⁽²⁾		
	Lock in OFF position	Padlock	UL508 control device
	<ul style="list-style-type: none"> ■ OFF or ON position ⁽¹⁾ inside the switchboard	Keylock	Locking device


⁽¹⁾ Following a simple modification of the mechanism.

⁽²⁾ Unless door locking has been voluntarily disabled.

Sealing accessories


Toggle control

DB400017




Rotary handle

DB400018



Access to Vigi-module settings

DB400019



Types of seals

Protected operations

Protection cover for settings

■ modification of settings.

Accessories and auxiliaries



Escutcheons and protection collars

Escutcheons are an optional feature mounted on the switchboard door. They increase the degree of protection to IP40, IK07. Protection collars maintain the degree of protection, whatever the position of the device (connected, disconnected).


IP40 escutcheons for fixed devices

There are three types of escutcheon with a gasket which are screwed to the cut-out:

- three escutcheons for all control types (toggle, handle or motor mechanism)
- a wide model for Vigi modules that can be combined with the above.



Escutcheon for toggle without and with access to the trip unit.



Escutcheon for Vigi module.

Installation recommendations



Functions and characteristics

Operating conditions and temperature derating

Installation in switchboards

Power supply and weights

Safety clearances and minimum distances

Installation example

Power loss/Resistance

Dimensions and connection


Additional characteristics

Catalogue numbers


EasyPact CVS100BS

Installation recommendations


When thermal-magnetic trip units are used at ambient temperatures other than 40 °C, the Ir pick-up is modified.



Electronic trip units are not affected by variations in temperature. If the trip units are used in high-temperature environments, the ETS setting must nevertheless take into account the temperature limits of the circuit breaker.



Temperature derating curve for CVS100.



Reflex tripping.

Thermal-protection curve with minimum and maximum values.

Operating conditions and temperature derating

Altitude derating

Altitude does not significantly affect the characteristics of EasyPact CVS breakers up to 2000 m. Above this altitude, it is necessary to take into account a decrease in the dielectric strength and cooling capacity of air.

Altitude (m)	2000	3000	4000	5000
Impulse withstand voltage U _{imp} (kV)	8	7	6	5.2
Current ratio	1,00	0,96	0,93	0,90
U _i	690	600	520	450
U _e	440	400	400	380

Vibrations

CVS devices resist electromagnetic or mechanical vibrations. Tests are carried out in compliance with standard IEC 60068-2-6 for the required by merchant-marine inspection organisations (Veritas, Lloyd's Register).
 ■ 2 to 13.2 Hz: amplitude ±1 mm
 ■ 13.2 to 100 Hz: constant acceleration 0.7 g.
 Excessive vibration may cause tripping, breaks in connections or damage to mechanical parts.

Degree of protection

CVS circuit breakers have been tested for degree of protection (IP) and impact protection (IK). See page A-3.

The overload protection is calibrated at 40 °C in the lab. This means that the ambient temperature is less than or greater than 40 °C, the Ir protection is slightly modified.

To obtain the tripping time for a given temperature:

- see the tripping curves for 40 °C (see pages D-2 and D-3)
- determine tripping times corresponding to the Ir value (thermal setting device), corrected for the ambient temperature as indicated in the table.

Settings of CVS100 to 630 equipped with TM-D or TM-G trip units as a function of the temperature

The table indicates the real Ir (A) value for a given rating and temperature.

Rat.	Temperature (°C)									
	(A) 10	15	20	25	30	35	40	45	50	55
16	18.4	18	18	18	17	16.6	16	15.6	15.2	14.8
25	28.8	28	27.5	27	26.3	25.6	25	24.5	24	23.5
32	36.8	36	35.2	34.4	33.6	32.8	32	31.3	30.5	30
40	46	45	44	43	42	41	40	39	38	37
50	57.5	56	55	54	53	51	50	49	47	46
63	73	72	70	68	67	65	63	61	59	57
80	92	90	88	86	84	82	80	78	75.5	73
100	114	112	110	107	105	102.5	100	97	95	92.0
125	144	141	138	134	131	128	125	122	119	116
160	184	180	176	172	168	164	160	156	152	148
200	230	225	220	215	210	205	200	195	190	185
250	288	281	277	269	263	256	250	244	238	231
320	365	358	350.5	343	335.6	328	320	312	303.6	295
400	456.6	447.7	438.6	429	419.7	410	400	390	379.3	368.5
500	558.6	549	539.7	530	520.3	510.2	500	489.6	479	468
600	672	660.5	649	637	625	612.6	600	587	574	560.6

* For TM-G, the rating is from 80A to 250A.

CVS400 and 630 (equipped with ETS2.3 electronic trip)

The table below indicates the maximum long-time (LT) protection setting depending on the ambient temperature.


Type of device	Rating (A)	Temperature (°C)				
		40	45	50	55	60
CVS400						
Fixed	400	400	400	400	390	380
CVS630						
Fixed	630	630	615	600	585	570

Additional derating coefficient for an add-on module

For fixed circuit breakers equipped with a Vigi module, the coefficients below must be applied.

Circuit breaker	Trip unit	Coefficient
CVS400	TMD320	0.98
	TMD400	0.94
	ETS2.3	0.97
CVS630	TMD500	0.9
	TMD600	0.89
	ETS2.3	0.9

DE400038



Power supply from the top or bottom

CVS circuit breakers can be supplied from either the top or the bottom, equipped with a Vigi earth-leakage protection module, without any reduction in performance. This capability facilitates connection when installed in a switchboard. All connection and insulation accessories can be used on circuit breakers supplied either from the top or bottom.

Weight

The table below presents the weights (in kg) of the circuit breakers and their accessories.

Type of device		Circuit breakers		
		CVS with TM-D	CVS with TM-G	CVS with ETS
CVS100	3P 3D	1.64	-	-
	4P 4D	2.01	-	-
	4P 3D	2.01	-	-
CVS160	3P 3D	1.60	1.60	-
	4P 4D	2.08	-	-
	4P 3D	2.08	2.08	-
CVS250	3P 3D	1.79	1.79	-
	4P 4D	2.39	-	-
	4P 3D	2.39	2.39	-
CVS400	3P 3D	4.37	-	4.71
	4P 4D	5.83	-	6.32
	4P 3D	5.83	-	6.32
CVS630	3P 3D	4.80	-	5.24
	4P 4D	6.40	-	7.14
	4P 3D	6.40	-	7.14

General rules

When installing a circuit breaker, minimum distances (safety clearances) must be maintained between the device and panels, bars and other protection devices installed nearby. These distances, which depend on the ultimate breaking capacity, are defined by tests carried out in accordance with standard IEC 60947-1. If installation conformity is not checked by type tests, it is also necessary to:

- use insulated bars for circuit-breaker connections
- segregate the busbars using insulating screens.

For CVS100 to 630 devices, terminal shields and interphase barriers are recommended and may be mandatory depending on the operating voltage of the device and type of installation (fixed, withdrawable, etc.).

Power connections

The table below indicates the rules to be respected for CVS100 to 630 devices to ensure insulation of live parts for fixed devices.


CVS100 to 630: rules to be respected to ensure insulation of live parts

Type of connection	Fixed, front connection			Fixed, rear connection
Possible, recommended or mandatory accessories:	No insulating accessory	Interphase barriers	Long terminal shields ⁽¹⁾	Shielded busbars
With:				
operating voltage	type of conductor			
≤ 440 V	Insulated bars 	Possible	Possible	Possible
	Extension terminals Cables + crimp lugs 	No	Mandatory (supplied)	Possible (instead of ph. barriers)
	Bare cables + connectors 	Possible for CVS100 to 250 No	Possible for CVS100 to 250 Mandatory (supplied)	Possible for CVS100 to 250 Possible (instead of ph. barriers)


⁽¹⁾ Long terminal shields provide a degree of protection of IP40 (ingress and IK08 impact).

Safety clearance

Minimum distance between two adjacent circuit breakers






Minimum distance between breaker and front or rear



Bare or painted sheet metal

Note: if $F < 8$ mm: an insulating terminal shield is mandatory.

Minimum distance between circuit breaker and top, bottom or side




Devices without accessories.

Devices with interphase barriers or long terminals.

Minimum safety clearances for CVS100 to 630

Dimensions (mm)	Insulation, insulated bars or painted sheet metal			Bare sheetmetal		
	C1	D1	D2	C1	D1	D2
Compact circuit breaker						
CVS100-250 $U \leq 440V$	0	30	30	5	35	35
CVS400-630 $U \leq 440V$	0	30	30	5	60	60



Live busbars.

Clearances with respect to live bare busbar


Minimum clearances for CVS100 to 630

Operating voltage	Clearances with respect to live bare busbar		
	spacing ≤ 60 mm	F2	spacing > 60 mm
U < 440 V	F1	350	80
U = 440 V	F1	350	120

These clearances can be reduced for special installations as long as the configuration is approved by tests.

Installation recommendations

EasyPact CVS thermal power loss values are used to calculate total temperature rise in the switchboard in which the circuit breakers are installed.



With a Vigi module, the deviation of the N and L3 bars required to pass through the toroid results in higher power losses compared to those of the L1 and L2 bars.

Power loss/Resistance EasyPact CVS equipped with thermalmagnetic trip units

The values indicated in the tables below are typical values for a device load and 50/60 Hz.

Power loss per pole (P/pole) in Watts (W)

The value indicated is the power loss at I_N , 50/60 Hz, for a three-pole or circuit breaker. Measurement and calculation of power loss are carried out in compliance with the recommendations of Annex G of standard IEC 60947-3.

Resistance per pole (R/pole) in milliohms (mΩ)

The value of the resistance per pole is provided as a general indication for the device.

The value of the contact resistance must be determined on the basis of the measured voltage drop, in accordance with the manufacturer's test procedure (see instruction document no. 1 - BEE - 02.2 -A).

Note: this measurement is not sufficient to determine the quality of the contacts, of the circuit breaker to carry its rated current.

Additional power loss

Additional power loss is equal to the sum of the power dissipated by the

- Vigi module: note that the deviation of the N and L3 bars required to pass through the toroid results in higher power losses compared to those of the L1 and L2 bars (diagram opposite). When calculating total power loss, use L1, L2, L3 and N, L1, L2, L3 for a 4P device

- disconnecting contacts (plug-in and withdrawable devices)
- ammeter module
- transformer module.

Calculation of total power loss

Total power loss at full rated load and 50/60 Hz is equal to the sum of the power loss per pole multiplied by the number of poles (2, 3 or 4) plus the additional power losses per pole multiplied by the number of poles (2, 3 or 4). If a Vigi module is installed, it is necessary to differentiate between N and L3 on one hand and L1 and L2 on the other.

EasyPact CVS100 to 630 equipped with TM-D trip units

Type of device 3/4 poles	Fixed device			Additional Vigi (N,L3)
	Rat. (A)	R/pole	P/pole	
CVS100	16	11.91	3.05	0
	25	6.91	4.32	0
	32	4.43	4.54	0.06
	40	4.125	6.60	0.1
	50	3.30	8.25	0.15
	63	1.92	7.62	0.3
	80	1.86	11.90	0.4
CVS160	100	1.37	13.70	0.7
	100	0.77	7.70	0.7
	125	0.69	10.78	1.1
CVS250	160	0.55	14.08	1.8
	160	0.46	11.78	1.8
	200	0.39	15.60	2.8
CVS400	250	0.3	18.75	4.4
	320	0.24	24.00	2.05
CVS630	400 ⁽¹⁾	0.19	30.00	2.86
	500 ⁽²⁾	0.17	40.80	4.08
	600 ⁽³⁾	0.15	53.80	5.7

(1) The power loss value for Vigi module is given for 378A

(2) The power loss value for Vigi module is given for 451A

(3) The power loss value for Vigi module is given for 534A

EasyPact CVS100 to 630 equipped with MA trip units

Type of device 3/4 poles	Fixed device			Additional Vigi (N,L3)
	Rat. (A)	R/pole	P/pole	
CVS100	2.5	148.91	0.93	0
	6.3	99.51	3.95	0
	12.5	4.54	0.71	0
	25	2.15	1.34	0
	50	1.16	2.90	0.2
	100	0.52	5.20	0.7
CVS160	150	0.38	8.55	1.35
CVS250	220	0.3	14.52	2.9
CVS400	320	0.15	15.40	3.2
CVS630	500	0.13	32.20	13.99

The values indicated in the table below are typical values for a device at full load and 50/60 Hz. The definitions and information are the same as those for breakers equipped with thermal-magnetic trip units.

CVS400 to 630 equipped with electronic trip units

Type of device 3/4 poles	Fixed device			Additional Vigi (N,L3)
	Rat. (A)	R/pole	P/pole	
CVS400	400	0.15	24.00	3.2
CVS630	630 ⁽⁴⁾	0.12	47.63	6.5

⁽⁴⁾ The power loss value for Vigi module is given for 570A

Dimensions and connections



Functions and characteristics

Installation recommendations

Dimensions and mounting

EasyPact CVS100 to 630

Vigi CVS100 to 630

Direct rotary handle for EasyPact and Vigi CVS100 to 630

Extended rotary handle for EasyPact CVS100 to 630

Front-panel accessories

EasyPact CVS100 to 630

Front-panel cutouts

EasyPact CVS100 to 630

Vigi CVS100 to 630

Direct rotary handle for EasyPact and Vigi CVS100 to 630

Power connections

EasyPact and Vigi CVS100 to 630



Connection of insulated bars or cables with lugs to EasyPact and Vigi CVS100 to 630

Connection of bare cables to EasyPact and Vigi CVS100 to 630


Additional characteristics

Catalogue numbers


EasyPact CVS100BS



(1) The ØT holes are required for rear connection only.



On DIN rail with adaptor plate (CVS100 to 250)







Dimensions and mounting

Vigi CVS100 to 630

Dimensions

3/4P

3/4P



Mounting

CVS100 to 250

CVS400/630





CVS100 to 630

On backplate

3P

3P

4P







(1) The ØT holes are required for rear connection only.

On rails

3P

3P

4P



Type	A	A1	A2	A3	A4	A5	A6	A7	A8	A9	B	B1	B2	C1	C2	C3
CVS100/160/250	80.5	161	94	145	178.5	155.5	236	169	220	253.5	52.5	105	140	81	86	110
CVS400/630	127.5	255	142.5	200	237	227.5	355	242.5	300	337	70	140	185	95.5	110	160
Type	E2	E3	E4	E5	E6	E7	E8	F1	F2	F3	G1	G2	G3	G4	G5	Ø
CVS100/160/250	125	70	140	137.5	200	145	215	35	17.5	70	95	75	13.5	23	17.5	24
CVS400/630	200	113.5	227	200	300	213.5	327	45	22.5	90	-	-	-	-	-	32



(2) C3=126mm for EasyPact CVS250B/F.

Dimensions



3P

4P

Fixed circuit breaker



C8: without keylock
C9: with keylock





Type	A14	A15	A18	B8	B9	B10	C7	C8
CVS100/160/250	27.5	73	9	45.5	91	9.25	121	155
CVS400/630	40	123	24.6	61.5	123	5	145	179

Dimensions and mounting

Extended rotary handle for EasyPact CVS100 to 630

Dimensions



Fixed circuit breakers



Cutout for shaft (mm)

Type	...
CVS100/160/250	r
CVS400/630	r

Dimensions and front-panel cutout




Type	A18	B10
CVS100/160/250	9	9.25
CVS400/630	24.6	5


IP40 front-panel escutcheons

For toggle


DB400041




EZ1641



EZ1642




EZ1643




For rotary handle or module and protection collar


DB400089




DB115010



DB115011




DB115012




For Vigi


DB400097




DB115018



DB115019



DB115020



Type	A1	A2	A3	B1	M2	M3
CVS100/160/250	91	114	101	157	115	102
CVS400/630	123	164	151	189	155	142

Front-panel cutouts





EasyPact CVS100 to 630

Bare sheet metal





CVS100 to 250

CVS400/630

For toggle



For toggle with access to trip unit







Type	P3	P4	R	R1
CVS100/160/250	88	83	14.5	29
CVS400/630	112	107	31.5	63

Bare sheet metal





CVS100 to 250

CVS400/630

For toggle



For toggle with access to trip unit



Front-panel cutouts


Direct rotary handle for EasyPact and Vigi CVS100 to 630

Fixed circuit breakers


CVS100 to 250

CVS400/630


Bare sheet metal




DB400173



DB400174




DB115145




DB115146


Bare sheet metal with access to the trip unit




DB400175



DB400176




DB115125




DB115126


With IP30 front-panel escutcheon




DB400177



DB400178



DB115145



DB115146

Dimensions and connection


Front-panel cutouts Direct rotary handle for EasyPact and Vigi CVS100 to 630

Fixed circuit breakers (cont.)


CVS100 to 250

CVS400/630

With IP30 front-panel escutcheon with access to the trip unit



With IP40 front-panel escutcheon





Type	P10	P11	P12
CVS100/160/250	89	90	123
CVS400/630	112	113	147

Power connections

EasyPact and Vigi CVS100 to 630


Connection locations




Type	A1	A2	B1	C1	C2
CVS100/160	70	140	35	19.5	19.5
CVS250	70	140	35	21.5	19.5
CVS400/630	113.5	227	45	26	26

Type	A1	A3	B1	C1	C2
CVS100/160 + Vigi	70	215	35	19.5	21.5
CVS250 + Vigi	70	215	35	21.5	21.5
CVS400/630 + Vigi	113.5	327	45	26	26

Front connection without accessories




CVS100 to 250



Cables with lugs/bars


CVS400/630




Bars/cables with lugs

Connection with accessories


Long and short rear connectors



CVS100 to 250




CVS400/630




Connection with accessories (cont.)

Bare-cable connectors


DB400138




DB115451 **CVS100 to 250**




DB115462




DB400139



DB115454 **CVS400/630**




DB115455




Distribution connectors (for CVS100 to 250 only)

DB115456




DB115457




(a) Vigi module or CVS250.

Right-angle terminal extensions (upstream only)

DB400140




DB115459 **CVS100 to 250**




(b) CVS250.

DB115460 **CVS400/630**




Straight terminal extensions (for CVS100 to 250 only)

DB400141



DB115462



Power connections

EasyPact and Vigi CVS100 to 630





Connection with accessories (cont.)

Spreaders


3P

4P

CVS100 to 250



CVS400/630




Type	C3	C4	E1	E2	E3	F1	F2
CVS100/160	23.5	-	114	45	159	100	11
CVS250	25.5	-	114	45	159	100	11
CVS400/630	-	44	135 170	52.5 70	187.5 240	152.5 166	15

Dimensions and connection

Power connections

Connection of insulated bars or cables with EasyPact and Vigi CVS100 to 630



Accessories for CVS100 to 250

Straight terminal extensions



Tinned copper


Spreaders: separate parts



Tinned copper

Accessories for CVS400 and 630


Spreaders made up of separate parts for 52.5 and 70 mm pitch



Tinned copper

Accessories for CVS100 to 630

Right-angle terminal extensions



Tinned copper
To be mounted on upstream side.

Direct connection to CVS100 to 630

Dimensions	CVS100	CVS160/250	CVS400/630	
Bars	L (mm)	≤ 25	≤ 25	≤ 25
	l (mm)	d + 10	d + 10	d + 10
	d (mm)	≤ 10	≤ 10	≤ 10
	e (mm)	≤ 6	≤ 6	≤ 6
	Ø (mm)	6.5	8.5	10.5
Lugs	L (mm)	≤ 25	≤ 25	≤ 25
	Ø (mm)	6.5	8.5	10.5
Torque (Nm) ⁽¹⁾	10	15	50	
Torque (Nm) ⁽²⁾	5/5	5/5	5/5	

(1) Tightening torque on the circuit breaker for lugs or bars.

(2) Tightening torque on fixed devices for rear connectors.

Connection with accessories to CVS100 to 250 (IEC)

Pole pitch

Without spreaders	35 mm
With spreaders	45 mm

Dimensions

Dimensions	With spreaders or terminal extensions	CVS100	CVS160/250
Bars	L (mm)	≤ 25	≤ 25
	l (mm)	20 ≤ l ≤ 25	20 ≤ l ≤ 25
	d (mm)	≤ 10	≤ 10
	e (mm)	≤ 6	≤ 6
	Ø (mm)	6.5	8.5
Lugs	L (mm)	≤ 25	≤ 25
	Ø (mm)	6.5	8.5
Torque (Nm) ⁽¹⁾	10	15	50

(1) Tightening torque on the circuit breaker for spreaders or terminal extensions.

Spreaders and straight, right-angle, 45°, double-L and edgewise terminal extensions are supplied with flexible interphase barriers.

Connection with accessories to CVS400 and 630 (IEC)

Pole pitch


Without spreaders	45 mm
With spreaders	52.5 or 70 mm

Dimensions

Dimensions	With spreaders	With terminal extensions	
Bars	L (mm)	≤ 40	≤ 32
	l (mm)	d + 15	30 ≤ l ≤ 34
	d (mm)	≤ 20	≤ 15
	e (mm)	3 ≤ e ≤ 10	3 ≤ e ≤ 10
	Ø (mm)	12.5	10.5
Lugs	L (mm)	≤ 40	≤ 32
	Ø (mm)	12.5	10.5
Torque (Nm) ⁽¹⁾	50	50	

(1) Tightening torque on the circuit breaker for spreaders or terminal extensions.

Spreaders and right-angle, 45° and edgewise terminal extensions are supplied with flexible interphase barriers.




Mounting detail: 2 cables with lugs.



Power connections

Connection of bare cables to EasyPact and Vigi CVS100 to 630

DE400149



Connection for CVS100 to 250



1-cable connector

2-cable connector


DB115863



	1-cable connector	Steel ≤ 160 A	Aluminium ≤ 250 A	
L (mm)		25	25	
S (mm ²) Cu/Al		1.5 to 95 ⁽¹⁾	25 to 50	70 to 95
Torque (Nm)		12	20	26
2-cable connector				
L (mm)		25 or 50		
S (mm ²) Cu/Al		2 x 50 to 2 x 120		
Torque (Nm)		22		

(1) For flexible cables from 1.5 to 4 mm², connection with crimped or self-crimping terminals.

Connection to CVS400 and 630



1-cable connector

2-cable connector

DB115863



	1-cable connector	2-cable connector
L (mm)	30	30 or 60
S (mm ²) Cu/Al	35 to 300 rigid 240 max. flex.	2 x 35 to 2 x 240 240 max. flex.
Torque (Nm)	31	31

Conductor materials and electrodynamic stresses

EasyPact CVS circuit breakers can be connected indifferently with bare tinned-copper and tinned-aluminium conductors (flexible or rigid bars). In the event of a short-circuit, thermal and electrodynamic stresses will be applied to the conductors. They must therefore be correctly sized and held in place. Electrical connection points on switchgear devices (switch-disconnectors, contactors, circuit breakers, etc.) should not be used for mechanical support. Any partition between upstream and downstream connections of the switchgear must be made of non-magnetic material.

Additional characteristics



Functions and characteristics
Installation recommendations
Dimensions and connection

Tripping curves

EasyPact CVS100 to 630 Protection of distribution systems

EasyPact CVS100 to 250 Protection of generator systems


EasyPact CVS100 to 250 Motor protection

Current and energy limiting curves


Catalogue numbers
EasyPact CVS100BS

TM magnetic trip units


TM16D




TM25D



TM32D



TM40D



Reflex tripping.


Tripping curves

EasyPact CVS100 to 630

Protection of distribution systems


TM magnetic trip units (cont.)

TM50D




Reflex tripping.

TM63D




Reflex tripping.


TM80D/100D




TM125D/160D



TM200D/250D




TM320D/400D




Reflex tripping.

TM500D



Reflex tripping.

TM600D




Reflex tripping.

Tripping curves

EasyPact CVS400 to 630


Protection of distribution systems

ETS 2.3 electronic trip units




TM magnetic trip units

TM80G




Reflex tripping.

TM100G




Reflex tripping.

TM125G



Reflex tripping.

TM160G




Reflex tripping.

Tripping curves

EasyPact CVS100 to 250


Protection of generator systems

TM200G and TM250G




MA magnetic trip units

MA2.5... MA100




Reflex tripping.

MA150 and MA220




MA320



Reflex tripping.

MA500




Reflex tripping.

Tripping curves

Current and energy limiting curves

The limiting capacity of a circuit breaker is its aptitude to let through a current, during a short-circuit, that is less than the prospective short-circuit current.



The exceptional limiting capacity of the EasyPact CVS range is due to the rotating double-break technique (very rapid natural repulsion of contacts and the appearance of two arc voltages in-series with a very steep wave front).

Ics = 100 % Icu

The exceptional limiting capacity of the EasyPact CVS range greatly reduces the forces created by fault currents in devices.

The result is a major increase in breaking performance.

In particular, the service breaking capacity Ics is equal to 100 % of Icu.

The Ics value, defined by IEC standard 60947-2, is guaranteed by tests through the following steps:

- break three times consecutively a fault current equal to 100% of Icu
- check that the device continues to function normally, that is:
 - it conducts the rated current without abnormal temperature rise
 - protection functions perform within the limits specified by the standard
 - suitability for isolation is not impaired.

Longer service life of electrical installations

Current-limiting circuit breakers greatly reduce the negative effects of short-circuits on installations.

Thermal effects

Less temperature rise in conductors, therefore longer service life for cables.

Mechanical effects

Reduced electrodynamic forces, therefore less risk of electrical contact deformation or broken.

Electromagnetic effects

Fewer disturbances for measuring devices located near electrical circuit.

Current and energy limiting curves

The limiting capacity of a circuit breaker is expressed by two curves which are a function of the prospective short-circuit current (the current which would flow if no protection devices were installed):


- the actual peak current (limited current)
- thermal stress (A^2s), i.e. the energy dissipated by the short-circuit in a conductor with a resistance of 1Ω .

Maximum permissible cable stresses


The table below indicates the maximum permissible thermal stresses for cables depending on their insulation, conductor (Cu or Al) and their cross-section (CSA). CSA values are given in mm^2 and thermal stresses in A^2s .

CSA		1.5 mm ²	2.5 mm ²	4 mm ²	6 mm ²
PVC	Cu	2.97x10 ⁴	8.26x10 ⁴	2.12x10 ⁵	4.76x10 ⁵
	Al				
PRC	Cu	4.10x10 ⁴	1.39x10 ⁵	2.92x10 ⁵	6.56x10 ⁵
	Al				
CSA		16 mm ²	25 mm ²	35 mm ²	50 mm ²
PVC	Cu	3.4x10 ⁶	8.26x10 ⁶	1.62x10 ⁷	3.31x10 ⁷
	Al	1.39x10 ⁶	3.38x10 ⁶	6.64x10 ⁶	1.35x10 ⁷
PRC	Cu	4.69x10 ⁶	1.39x10 ⁷	2.23x10 ⁷	4.56x10 ⁷
	Al	1.93x10 ⁶	4.70x10 ⁶	9.23x10 ⁶	1.88x10 ⁷

Current-limiting curves



Energy-limiting curves



Notes

Catalogue numbers



Functions and characteristics
Installation recommendations
Dimensions and connection
Additional characteristics

EasyPact CVS100 to 250

EasyPact CVS400 to 630

EasyPact CVS100BS

CVS100/160/250B: complete fixed/FC device

EasyPact and Vigi CVS100/160/250B (25 kA 380/415 V)
EasyPact CVS160/250B (25 kA 380/415 V)
EasyPact and Vigi CVS100/160/250F (36 kA 380/415 V)

CVS100/160/250F: complete fixed/FC device

Vigi CVS100/160/250F (36 kA 380/415 V)

CVS100/160/250NA: complete fixed/FC device

EasyPact CVS100/160/250NA

Add-on Vigi module: EasyPact and Vigi


CVS100/160/250

Accessories

EasyPact and Vigi CVS100/160/250

EasyPact CVS100/160/250B


With TM-D thermal-magnetic trip unit



EasyPact CVS100B (25 kA at 380/415 V)			
Rating	3P 3d	4P 3d	4P 4d
TM16D	LV510300	LV510310	LV510320
TM25D	LV510301	LV510311	LV510321
TM32D	LV510302	LV510312	LV510322
TM40D	LV510303	LV510313	LV510323
TM50D	LV510304	LV510314	LV510324
TM63D	LV510305	LV510315	LV510325
TM80D	LV510306	LV510316	LV510326
TM100D	LV510307	LV510317	LV510327
EasyPact CVS160B (25 kA at 380/415 V)			
Rating	3P 3d	4P 3d	4P 4d
TM100D	LV516301	LV516311	LV516321
TM125D	LV516302	LV516312	LV516322
TM160D	LV516303	LV516313	LV516323
EasyPact CVS250B (25 kA at 380/415 V)			
Rating	3P 3d	4P 3d	4P 4d
TM160D	LV525301	LV525311	LV525321
TM200D	LV525302	LV525312	LV525322
TM250D	LV525303	LV525313	LV525323

EasyPact CVS100/160/250B


With Magnetic trip unit MA



EasyPact CVS100B (25 kA at 380/415 V)	
Rating	3P 3d
MA2,5	LV510430
MA6,3	LV510431
MA12,5	LV510432
MA25	LV510433
MA50	LV510434
MA100	LV510435
EasyPact CVS160B (25 kA at 380/415 V)	
Rating	3P 3d
MA100	LV516430
MA150	LV516431
EasyPact CVS250B (25 kA at 380/415 V)	
Rating	3P 3d
MA150	LV525435
MA220	LV525436

Vigi CVS100/160/250B

With TM-D thermal-magnetic trip unit




Vigi CVS100B (25 kA at 380/415 V) equipped with MH Vigi module (200 to 440 V)			
Rating	3P 3d	4P 3d	4P 4d
TM16D	LV510360	LV510370	LV510380
TM25D	LV510361	LV510371	LV510381
TM32D	LV510362	LV510372	LV510382
TM40D	LV510363	LV510373	LV510383
TM50D	LV510364	LV510374	LV510384
TM63D	LV510365	LV510375	LV510385
TM80D	LV510366	LV510376	LV510386
TM100D	LV510367	LV510377	LV510387
Vigi CVS160B (25 kA at 380/415 V) equipped with MH Vigi module (200 to 440 V)			
Rating	3P 3d	4P 3d	4P 4d
TM100D	LV516361	LV516371	LV516381
TM125D	LV516362	LV516372	LV516382
TM160D	LV516363	LV516373	LV516383
Vigi CVS250B (25 kA at 380/415 V) equipped with MH Vigi module (200 to 440 V)			
Rating	3P 3d	4P 3d	4P 4d
TM160D	LV525361	LV525371	LV525381
TM200D	LV525362	LV525372	LV525382
TM250D	LV525363	LV525373	LV525383

CVS160/250B: complete fixed/FC device EasyPact CVS160/250B (25 kA 380/415 V)

EasyPact CVS160/250B

With TM-G thermal-magnetic trip unit



EasyPact CVS160B (25 kA at 380/415 V)

Rating	3P 3d	4P 3d
TM80G	LV510736	LV510748
TM100G	LV510737	LV510749
TM125G	LV516732	LV516742
TM160G	LV516733	LV516743

EasyPact CVS250B (25 kA at 380/415 V)


Rating	3P 3d	4P 3d
TM200G	LV525732	LV525742
TM250G	LV525733	LV525743

CVS100/160/250F: complete fixed/FC device EasyPact and Vigi CVS100/160/250F (36 kA 380/415 V)

EasyPact CVS100/160/250F

With TM-D thermal-magnetic trip unit

DB400150



EasyPact CVS100F (36 kA at 380/415 V)

Rating	3P 3d	4P 3d	4P 4d
TM16D	LV510330	LV510340	LV510350
TM25D	LV510331	LV510341	LV510351
TM32D	LV510332	LV510342	LV510352
TM40D	LV510333	LV510343	LV510353
TM50D	LV510334	LV510344	LV510354
TM63D	LV510335	LV510345	LV510355
TM80D	LV510336	LV510346	LV510356
TM100D	LV510337	LV510347	LV510357

EasyPact CVS160F (36 kA at 380/415 V)

Rating	3P 3d	4P 3d	4P 4d
TM100D	LV516331	LV516341	LV516351
TM125D	LV516332	LV516342	LV516352
TM160D	LV516333	LV516343	LV516353


EasyPact CVS250F (36 kA at 380/415 V)

Rating	3P 3d	4P 3d	4P 4d
TM160D	LV525331	LV525341	LV525351
TM200D	LV525332	LV525342	LV525352
TM250D	LV525333	LV525343	LV525353

EasyPact CVS100/160/250F

With MA magnetic trip unit

DB400155



EasyPact CVS100F (36 kA at 380/415 V)

Rating	3P 3d
MA2.5	LV510440
MA6.3	LV510441
MA12.5	LV510442
MA25	LV510443
MA50	LV510444
MA100	LV510445

EasyPact CVS160F (36 kA at 380/415 V)

Rating	3P 3d
MA100	LV516439
MA150	LV516440

EasyPact CVS250F (36 kA at 380/415 V)


Rating	3P 3d
MA150	LV525438
MA220	LV525439

CVS100/160/250F: complete fixed/FC device (cont.) Vigi CVS100/160/250F (36 kA 380/415 V)

Vigi CVS100/160/250F

With TM-D thermal-magnetic trip unit

DB4001ES




Vigi CVS100F (36 kA at 380/415 V) equipped with MH Vigi module (200 to 440 V)			
Rating	3P 3d	4P 3d	4P 4d
TM16D	LV510390	LV510400	LV510410
TM25D	LV510391	LV510401	LV510411
TM32D	LV510392	LV510402	LV510412
TM40D	LV510393	LV510403	LV510413
TM50D	LV510394	LV510404	LV510414
TM63D	LV510395	LV510405	LV510415
TM80D	LV510396	LV510406	LV510416
TM100D	LV510397	LV510407	LV510417
Vigi CVS160F (36 kA at 380/415 V) equipped with MH Vigi module (200 to 440 V)			
Rating	3P 3d	4P 3d	4P 4d
TM100D	LV516391	LV516401	LV516411
TM125D	LV516392	LV516402	LV516412
TM160D	LV516393	LV516403	LV516413
Vigi CVS250F (36 kA at 380/415 V) equipped with MH Vigi module (200 to 440 V)			
Rating	3P 3d	4P 3d	4P 4d
TM160D	LV525391	LV525401	LV525411
TM200D	LV525392	LV525402	LV525412
TM250D	LV525393	LV525403	LV525413

CVS100/160/250NA: complete fixed/FC device EasyPact CVS100/160/250NA

EasyPact CVS100/160/250NA switch-disconnector

With NA switch-disconnector unit

DB400155




EasyPact CVS100NA		
Rating	3P	4P
100	LV510425	LV510426
EasyPact CVS160NA		
Rating	3P	4P
160	LV516425	LV516426
EasyPact CVS250NA		
Rating	3P	4P
250	LV525425	LV525426

VigiCompact CVS100/160/250NA switch-disconnector

With NA switch-disconnector unit

DB400153



EasyPact CVS100NA		
Rating	3P	4P
100	LV510427	LV510428
EasyPact CVS160NA		
Rating	3P	4P
160	LV516427	LV516428
EasyPact CVS250NA		
Rating	3P	4P
250	LV525427	LV525428

Add-on Vigi module


EasyPact and Vigi

CVS100/160/250

+ Vigi module

Vigi module


DB111464








ME type for CVS100/160 (200 to 440V)	3P LV429212	4P LV429213
MH type for CVS100/160 (220 to 440 V)	LV429210	LV429211
MH type for CVS250 (220 to 440 V)	LV431535	LV431536

Connection accessories (Cu or Al)


Rear connections

DB112225		2 short		LV429235
		2 long		LV429236

Bare cable connectors

DB112226		Steel connectors	1 x (1.5 to 95 mm ²) ; ≤ 160 A	Set of 3	LV429242
				Set of 4	LV429243
DB112225		Aluminium connectors	1 x (25 to 95 mm ²) ; ≤ 250 A	Set of 3	LV429227
			1 x (120 to 185 mm ²) ; ≤ 250 A	Set of 4	LV429228
DB112226		Clips for connectors		Set of 3	LV429259
				Set of 4	LV429260
DB112227		Aluminium connectors for 2 cables ⁽¹⁾	2 x (50 to 120 mm ²) ; ≤ 250 A	Set of 3	LV429218
				Set of 4	LV429219
DB112724		6.35 mm voltage tap for steel or aluminium connectors		Set of 10	LV429348

Terminal extensions

DB112231		Edgewise terminal extensions ⁽¹⁾		Set of 3	LV429308
				Set of 4	LV429308
DB112232		Right-angle terminal extensions ⁽¹⁾		Set of 3	LV429261
				Set of 4	LV429262
DB112233		Straight terminal extensions ⁽¹⁾		Set of 3	LV429263
				Set of 4	LV429264
DB112235		Spreaders from 35 to 45 mm pitch ⁽¹⁾		Set of 3	LV431563
				Set of 4	LV431564


⁽¹⁾ Supplied with 2 or 3 interphase barriers.

Accessories

EasyPact and Vigi CVS100/160/250

Crimp lugs for copper cable ⁽¹⁾


DB112237



For cable 120 mm ²	Set of 3	LV429252
	Set of 4	LV429256
For cable 150 mm ²	Set of 3	LV429253
	Set of 4	LV429257
For cable 185 mm ²	Set of 3	LV429254
	Set of 4	LV429258

Crimp lugs for aluminium cable ⁽¹⁾


DB112228



For cable 150 mm ²	Set of 3	LV429504
	Set of 4	LV429505
For cable 185 mm ²	Set of 3	LV429506
	Set of 4	LV429507


Insulation accessories

DB400045




1 short terminal shield for breaker	3 P	LV429515
	4 P	LV429516

DB400060




1 long terminal shield for breaker	3 P	LV429517
	4 P	LV429518

DB400061



Interphase barriers for breaker	Set of 6	LV429329
---------------------------------	----------	----------

DB400103



2 insulating screens for breaker (45 mm pitch)	3P	LV429330
	4P	LV429331

⁽¹⁾ Supplied with 2 or 3 interphase barriers.

Electrical auxiliaries

Auxiliary contacts (changeover)

DB112254



OF or SD or SDE or SDV	29450
OF or SD or SDE or SDV low level	29452
SDE adaptor, mandatory for trip unit TM, MA	LV429451


Voltage releases

DB111454



	Voltage	MX	MN
AC	24 V 50/60 Hz	LV429384	LV429404
	48 V 50/60 Hz	LV429385	LV429405
	110-130 V 50/60 Hz	LV429386	LV429406
	220-240 V 50/60 Hz and 208-277 V 60 Hz	LV429387	LV429407
	380-415 V 50 Hz and 440-480 V 60 Hz	LV429388	LV429408
DC	12 V	LV429382	LV429402
	24 V	LV429390	LV429410
	30 V	LV429391	LV429411
	48 V	LV429392	LV429412
	60 V	LV429383	LV429403
	125 V	LV429393	LV429413
	250 V	LV429394	LV429414

DB115631



MN 48 V 50/60 Hz with fixed time delay			
Composed of:	MN 48 V DC		LV429412
	Delay unit 48 V 50/60 Hz		LV429426
MN 220-240 V 50/60 Hz with fixed time delay			
Composed of:	MN 250 V DC		LV429414
	Delay unit 220-240 V 50/60 Hz		LV429427
MN 48 V DC/AC 50/60 Hz with adjustable time delay			
Composed of:	MN 48 V DC		LV429412
	Delay unit 48 V 50/60 Hz		33680
MN 110-130 V DC/AC 50/60 Hz with adjustable time delay			
Composed of:	MN 125 V DC		LV429413
	Delay unit 110-130 V 50/60 Hz		33681
MN 220-250 V 50/60 Hz with adjustable time delay			
Composed of:	MN 250 V DC		LV429414
	Delay unit 220-250 V 50/60 Hz		33682


Accessories

EasyPact and Vigi CVS100/160/250

Rotary handles

Direct rotary handle

DB112269




With black handle

LV429337

Extended rotary handle

DB112260




With black handle

LV429338

Locks

Toggle locking device for 1 to 3 padlocks


DB400164



By removable device

29370

DB400165




By fixed device

29371

Locking of rotary handle

DB112263



Keylock adaptor (keylock not included)

LV429344

Keylock (keylock adaptor not included)

Ronis 1351B.500



41940

Profalux KS5 B24 D4Z

42888

Interlocking


Mechanical interlocking for circuit breakers



With toggles 29354

With rotary handles LV429369


Interlocking with key (2 keylocks / 1 key) for rotary handles



Keylock kit (keylock not included) ⁽¹⁾ LV429344
 1 set of 2 keylocks (1 key only, keylock kit not included) 41950
 Ronis 1351B.500 42878
 Profalux KS5 B24 D4Z

Installation accessories

Front-panel escutcheons



IP40


IP40 toggle escutcheon (small cut-out) 29315
 IP40 escutcheon for Rotary handle LV429317
 IP40 escutcheon for Vigi module LV429316

Lead-sealing accessories




Bag of accessories LV429375

Din rail adaptor



1 adaptor LV429305

Spare parts



10 toggle extensions LV429313
 Bag of screws LV429312
 12 snap-in nuts (fixed/FC) LV510100
 M6 for CVS100B/F LV516060
 M8 for CVS160/250B/F LV429226
 1 set of 10 identification labels

⁽¹⁾ For only 1 device.

CVS400/630: complete fixed/FC device

EasyPact and Vigi CVS400/630F/N
EasyPact CVS400/630F/N (36 kA 380/415 V)
EasyPact CVS400/630NA

**Add-on Vigi module: EasyPact and Vigi
CVS400/630**

Accessories

EasyPact and Vigi CVS400/630


CVS400/630: complete fixed/FC device

EasyPact and Vigi
CVS400/630F/N

EasyPact CVS400/630F

With TM-D thermal-magnetic trip unit

DB400008



EasyPact CVS400F (36 kA at 380/415 V)

Rating	3P 3d	4P 3d	4P 4d
TM320D	LV540305	LV540308	LV540311
TM400D	LV540306	LV540309	LV540312


EasyPact CVS630F (36 kA at 380/415 V)

Rating	3P 3d	4P 3d	4P 4d
TM500D	LV563305	LV563308	LV563311
TM600D	LV563306	LV563309	LV563312

EasyPact CVS400/630N

With TM-D thermal-magnetic trip unit

DB400008



EasyPact CVS400N (50 kA at 380/415 V)

Rating	3P 3d	4P 3d	4P 4d
TM320D	LV540315	LV540318	LV540321
TM400D	LV540316	LV540319	LV540322


EasyPact CVS630N (50 kA at 380/415 V)

Rating	3P 3d	4P 3d	4P 4d
TM500D	LV563315	LV563318	LV563321
TM600D	LV563316	LV563319	LV563322

Vigi add-on module CVS400/630F

With TM-D thermal-magnetic trip unit

DB400016



Vigi CVS400F (36 kA at 380/415 V)

Rating	3P 3d	4P 3d	4P 4d
TM320D	LV540335	LV540338	LV540341
TM400D	LV540336	LV540339	LV540342


Vigi CVS630F (36 kA at 380/415 V)

Rating	3P 3d	4P 3d	4P 4d
TM500D	LV563335	LV563338	LV563341
TM600D	LV563336	LV563339	LV563342

Vigi add-on module CVS400/630N

With TM-D thermal-magnetic trip unit

DB400016



Vigi CVS400N (50 kA at 380/415 V)

Rating	3P 3d	4P 3d	4P 4d
TM320D	LV540345	LV540348	LV540351
TM400D	LV540346	LV540349	LV540352

Vigi CVS630N (50 kA at 380/415 V)


Rating	3P 3d	4P 3d	4P 4d
TM500D	LV563345	LV563348	LV563351
TM600D	LV563346	LV563349	LV563352

CVS400/630: complete fixed/FC device EasyPact and Vigi CVS400/630F/N

EasyPact CVS400/630F/N

With MA magnetic trip unit

D18400020



EasyPact CVS400F (36 kA at 380/415 V)

Rating	3P 3D
MA320	LV540550

EasyPact CVS400N (50 kA at 380/415 V)

Rating	
MA320	LV540552

EasyPact CVS630F (36 kA at 380/415 V)

Rating	
MA500	LV563550

EasyPact CVS630N (50 kA at 380/415 V)


Rating	
MA500	LV563552

CVS400/630: complete fixed/FC device EasyPact CVS400/630F/N (36 kA 380/415 V)

EasyPact CVS400/630F

ETS 2.3 electronic trip unit (LS₀I protection)

DB400021




EasyPact CVS400F (36 kA at 380/415 V)	400 A	3P 3d LV540505	4P 3d, 4d, 3d + LV540506
EasyPact CVS630F (36 kA at 380/415 V)	630 A	LV563505	LV563506

EasyPact CVS400/630N

ETS 2.3 electronic trip unit (LS₀I protection)

DB400021




EasyPact CVS400N (50 kA at 380/415 V)	400 A	3P 3d LV540510	4P 3d, 4d, 3d + LV540511
EasyPact CVS630N (50 kA at 380/415 V)	630 A	LV563510	LV563511

Vigi add-on module CVS400/630F

ETS 2.3 electronic trip unit (LS₀I protection)

DB400022




Vigi CVS400F (36 kA at 380/415 V)	400 A	3P 3d LV540520	4P 3d, 4d, 3d + LV540521
Vigi CVS630F (36 kA at 380/415 V)	630 A	LV563520	LV563521

Vigi add-on module CVS400/630N

ETS 2.3 electronic trip unit (LS₀I protection)

DB400022




Vigi CVS400N (50 kA at 380/415 V)	400 A	3P 3d LV540524	4P 3d, 4d, 3d + LV540525
Vigi CVS630N (50 kA at 380/415 V)	630 A	LV563524	LV563525

CVS400/630: complete fixed/FC device EasyPact CVS400/630NA

EasyPact CVS400/630 NA switch-disconnector


DE400023



	3P	4P
EasyPact CVS400 NA	LV540400	LV540401
EasyPact CVS630 NA	LV563400	LV563401

Vigi CVS400/630 NA switch-disconnector

DE400024




	3P	4P
Vigi CVS400 NA	LV540402	LV540403
Vigi CVS630 NA	LV563402	LV563403

+ Vigi module

Vigi module

DB11464













Type MB	200 to 440 V	3P LV432455	4P LV432456
---------	--------------	----------------	----------------

Accessories

EasyPact and Vigi CVS400/630

Connection accessories (Cu or Al)

DB112225		2 short			LV432475
		2 long			LV432476
Cable connectors ⁽¹⁾					
E22040		Aluminium connector 1x (35 to 300 mm ²)		Set of 3	LV432479
				Set of 4	LV432480
E22041		Aluminium connector 2x (35 to 240 mm ²)		Set of 3	LV432481
				Set of 4	LV432482
		Voltage plug for aluminium connector 1 or 2 cables		Set of 10	LV429348
Terminal extension ⁽¹⁾					
E21276		Right-angle terminal extension		Set of 3	LV432484
				Set of 4	LV432485
E21276		Edgewise terminal extensions		Set of 3	LV432486
				Set of 4	LV432487
E21012		Spreaders	52.5 mm	3P	LV432490
				4P	LV432491
			70 mm	3P	LV432492
				4P	LV432493
Crimp lugs for copper cable ⁽¹⁾					
E18602		For cable 240 mm ²		Set of 3	LV432500
				Set of 4	LV432501
		For cable 300 mm ²		Set of 3	LV432502
				Set of 4	LV432503
		Supplied with 2 (or 3) interphase barriers			
Crimp lugs for aluminium cable ⁽¹⁾					
E30908		For cable 240 mm ²		Set of 3	LV432504
				Set of 4	LV432505
		For cable 300 mm ²		Set of 3	LV432506
				Set of 4	LV432507
		Supplied with 2 (or 3) interphase barriers			
Insulation accessories					
E18618		Short terminal shield, 45 mm (1 piece)		3P	LV432591
				4P	LV432592
		Long terminal shield, 45 mm (1 piece)		3P	LV432593
				4P	LV432594
E18606		Interphase barriers		Set of 6	LV432570
		Long terminal shielded for spreaders, 52,5mm (1 piece) (supplied with insulating plate)		3P	LV432595
				4P	LV432596
		2 insulating screens (70 mm pitch)		3P	LV432578
				4P	LV432579

⁽¹⁾ supplied with 2 or 3 interphase barriers

Electrical auxiliaries

Auxiliary contacts (changeover)

ET18628



OF or SD or SDE or SDV	29450
OF or SD or SDE or SDV low level	29452
SDE adaptor mandatory for trip unit TM, MA and ETS2.3	LV540050

Voltage releases

ET18609



	Voltage	MX	MN
AC	24 V 50/60 Hz	LV429384	LV429404
	48 V 50/60 Hz	LV429385	LV429405
	110-130 V 50/60 Hz	LV429386	LV429406
	220-240 V 50/60 Hz and 208-277 V 60 Hz	LV429387	LV429407
	380-415 V 50 Hz and 440-480 V 60 Hz	LV429388	LV429408
DC	Voltage		
	12 V	LV429382	LV429402
	24 V	LV429390	LV429410
	30 V	LV429391	LV429411
	48 V	LV429392	LV429412
	60 V	LV429383	LV429403
	125 V	LV429393	LV429413
	250 V	LV429394	LV429414
MN 48 V 50/60 Hz with fixed time delay			
Composed of:	MN 48 V DC		LV429412
	Delay unit 48 V 50/60 Hz		LV429426
MN 220-240 V 50/60 Hz with fixed time delay			
Composed of:	MN 250 V DC		LV429414
	Delay unit 220-240 V 50/60 Hz		LV429427
MN 48 V DC/AC 50/60 Hz with adjustable time delay			
Composed of:	MN 48 V DC		LV429412
	Delay unit 48 V 50/60 Hz		33680
MN110-130 V DC/AC 50/60 Hz with adjustable time delay			
Composed of:	MN 125 V DC		LV429413
	Delay unit 110-130 V 50/60 Hz		33681
MN 220-250 V 50/60 Hz with adjustable time delay			
Composed of:	MN 250 V DC		LV429414
	Delay unit 220-250 V 50/60 Hz		33682


Accessories

EasyPact and Vigi CVS400/630

Rotary handle

Direct rotary handle

E18611




Standard black handle

LV432597

Extended rotary handle

E18612



Standard extended rotary handle

LV432598

Locks

Toggle locking device for 1 to 3 padlocks

E18621



By removable device

29370

E18613



By fixed device

32631

Locking of the rotary handle

E18620



Keylock adaptor (keylock not included)

LV432604

Keylock (keylock adaptor not included)

Ronis 1351B.500

41940


Profalux KS5 B24 D4Z

42888

Interlocking

Mechanical interlocking for circuit breakers


E21298



With toggles

32614

E18780




With rotary handles

LV432621

Interlocking with key (2 keylocks/1 key) for rotary handles

E20766



Keylock kit (keylock not included)⁽¹⁾

LV432604

1 set of 2 keylocks (1 key only, keylock kit not included)

Ronis 1351B.500

41950

Profalux KS5 B24 D4Z

42878

(1) for only 1 device

Installation accessories

Front-panel escutcheons

E21841



IP40 Toggle escutcheon (small cut-out)

32556

IP40 escutcheon for rotary handle

LV432558

IP40 escutcheon for Vigi module

LV429316

Lead-sealing accessories

LV429375

Spare parts

Front-panel escutcheons

Toggle extension

LV432553

Bag of screws

LV432552

1 set of 10 identification labels

LV429226

Test

Test kits

E21290



Mini test kit for STR trip units

43362

E38271



Portable test kit for STR trip units

34547

Spare test plug for portable test kit 34547

34503

Wiring kit (spare part)

34546

Notes

EasyPact CVS100BS



Functions and characteristics
Installation recommendations
Dimensions and connection
Additional characteristics
Catalogue numbers

Presentation

EasyPact CVS100BS

Overview

Optimal Combination

Functions and Characteristics

General characteristics
Selection Guide
Protection of LV Power Distribution System
EasyPact CVS100BS
Installation and Connection
EasyPact CVS100BS
Electrical and Mechanical Accessories
EasyPact CVS100BS

Technical Data Supplement


Tripping Curve EasyPact CVS100BS
Power Distribution Protection System
Temperature and Altitude Derating
Current-limiting
Capacitor protection

Catalogue numbers

EasyPact CVS100BS
Accessories

Dimensions and Installation

EasyPact CVS100BS
Accessories EasyPact CVS100BS



EasyPact CVS100BS

Simplicity and perfection – That's what Schneider Electric brings to you. EasyPact CVS100BS not only reflects high quality of Schneider Electric but also features performance, protection functions, and performance/price ratio.

EasyPact CVS100BS


- up to 100A 3 Pole/4Pole products
- Icu 25kA, Ics 17kA
- Reliable protections of power distribution systems
- Flexible installation solutions including fixed, plug-in types
- Complete solutions for AC and DC networks

More reliable and safer

Powerful current-limiting capacity to ensure more cost-effective and more protection.

Modularized System

As shown below, wide range of modules or accessories are available.



1. breaking unit
2. MN and MX voltage releases
3. Direct rotary handle
4. Extended rotary handle
5. Short terminal shield
6. Long terminal shield
7. Connection accessories

PF108445



EasyPact CVS100BS

Compliance with standards

- IEC 947-1: General rules (GB/T 14048.1)
- IEC 947-2: Circuit Breakers (GB/T 14048.2)
- IEC 947-4: Contactors and Motor Starters (GB 14048.4)
- IEC 946-5.1: Control circuit Devices and Switching elements; automatic Components (GB 14048.5)

Tropicalisation

EasyPact CVS100BS circuit breakers have successfully passed the tests by following standards for extreme atmospheric conditions:

- IEC 68-2-30, damp heat(95% relative humidity at 55°C)
- QIEC 68-2-52 Salt mist (severity level 2)

Positive contact indication

All EasyPact CVS100BS circuit breakers are suitable for isolation as per standard 60947-2:

- the isolation position corresponds to the O (OFF) position
- the operating handle cannot indicate the "OFF" position unless the contacts are effectively open
- padlocks may not be installed unless the contacts are open

Installation of a rotary handle or a motor mechanism does not alter the position-indication system.

The isolation function is certified by tests guaranteeing:

- the mechanical reliability of the position indication system
- the absence of leakage currents
- overvoltage withstand capacity between upstream and downstream



EasyPact CVS100BS (Protection of distribution system)

Selection guide

CVS

Range name

100

current 100

BS

Breaking capacity
BS: 25 kA

/

3P

3P: 3 poles

100

Rated current:
16, 20, 25, 32, 40,
50, 63, 80, 100

MX


Accessories

PB106445



EasyPact CVS100BS

EasyPact circuit breaker				
Number of Poles	3			
Control	Manual	Toggle		
Connection	Fixed	Direct or extended rotary handle		
	Plug-in	Front connection		
Electrical characteristics as per IEC 60947-2 and EN 60947-2				
Rated current (A)	In	40 °C		
Rated insulation voltage (V)	Ui	6		
Rated impulse withstand voltage (kV)	Uimp	6		
Rated operational voltage (V)	Ue	AC 50/60 Hz	4	
		DC		
Circuit breaker type				
Ultimate breaking capacity (kA rms)	Icu	AC 50/60 Hz	220/240 V	5
			380/400 V	2
			415 V	2
Service breaking capacity (kA)	Ics		220/230 V	2
			380/400 V	1
Suitability for Isolation				
Utilisation category				
Durability (C-O cycles)	Mechanical			
	Electrical	415 V	In	4
Protection				
Trip units				
Overload protection	Long time	Ir (In x ...)	0	
Short-circuit protection	Short time	I _{sd} (Ir x ...)	-	
	Instantaneous	I _i (In x ...)	-	
Indication and control auxiliaries				
Auxiliary switch				
MX shunt release				
MN under-voltage release				
Installation				
Accessories	Terminal extensions and spreaders			
	Terminal shields			
	interphase barriers			
Dimensions (mm) W×H×D	Fixed, front connection 3P/4P			7
Weight (kg)	Fixed, front connection 3P/4P			0




EasyPact CVS100BS

Connection of electrical auxiliaries

Fixed configuration

Auxiliary circuits exit the device through a knock-out in the front cover



Each auxiliary device is equipped with a terminal block with numbered terminals for connection of wires up to:

- 1.5mm² for auxiliary contacts and voltage releases



EasyPact CVS100BS auxiliary contacts

All auxiliary contacts can be used to switch on/off electronic loads.

EasyPact CVS100BS auxiliary switch

This auxiliary contacts can display status of circuit breakers remotely, can be used for indications electrical interlocking, relay control. etc.

Functions

- OF (On/off): Indicate position of circuit breaker contacts.
- SD (Trip indication): Indicate trip conditions of circuit breakers due to short-circuit, under-voltage or operation of the "push to trip" button. It re-energised state when the circuit breaker is reset.

EasyPact CVS100BS multifunctional auxiliary switch

- OF/SD (Auxiliary + alarm): Indicate position of circuit breaker contact conditions of circuit breakers.

Standard

This auxiliary contacts comply with IEC 947-5.

Installation and connection

- This auxiliary contacts clip into slot behind the front cover of the circuit breaker.
- The conductor connected to the central terminal block has a cross section of 1.0mm².

Electrical characteristics		In: 100A
Rated thermal current (A)		5
Minimum load		10mA, 24V
Utilisation (IEC 947-4-1)		AC12
Operating current (A)	110V	5
	220~240V	3
	380~440V	-

Voltage tripping

The voltage releases can trip the circuit breaker.

Under-voltage release (MN) trips the circuit breaker:

- When the tripping threshold drops below the rated voltage of the trip.
- The tripping threshold is 0.35 to 0.7 times the rated voltage.
- If the circuit breaker can be closed when the voltage exceeds 0.85 times the rated voltage.

Circuit breaker tripping by an MN release meets the requirements of IEC60947-2.

Shunt releases (MX)

The circuit breaker will trip by this release if the control voltage exceeds the rated voltage. Control signals can be of the impulse type (≥ 20 ms) or maintained.

Operation

- The circuit breaker can be reset locally or remotely after tripping by a release.
- MN or MX tripping is faster than manual tripping (or trip by electric magnet) in the presence of a standing trip order, other operations will not be executed.
- Endurance:
 - EasyPact CVS100BS circuit breaker, typically 50% of the rated mechanical endurance of the circuit breaker

Installation and connection

- The circuit breaker panel has MX and MN releases at the rear part.
- Connection using wires up to 1.5mm².

For EasyPact CVS100BS		EasyPact CVS100BS	
		AC	DC
Consumption	Pick-up (MX)	< 10VA	< 5VA
	Seal-in (MN, MNR)	< 5VA	< 5VA
Response time (ms)		< 50	< 50

Note: 1. CVS100BS: select any two from three auxiliary switches (OF, SD, OF/SD).



EasyPact CVS100BS with a direct rotary handle

Rotary handle

Two types of rotary handle are available:

- Direct rotary handle
- Extended rotary handle

Direct rotary handle

Protection degree: IP40, IK07, IP54

Operation

- Function:
 - Suitability for isolation
 - Indications of three positions including O (OFF), I (ON) and Tripped
 - Access to "push-to-trip" button
 - Circuit breaker locking capability in the OFF position by 1 to 3 padlocks (shackle diameter 5 to 8 mm (not supplied))

Installation

The front cover of the circuit breaker can be removed and replaced by the rotary handle.

EasyPact CVS100BS series

The direct rotary handle is used in the following cases:

- Switchboards in motor control center (MCC):
 - Circuit-breaker closing is disabled if the door is open.
 - Door opening is disabled when the circuit breaker is ON.
 - Protection degree: IP43, IK07 (IP54, IK08)
 - Machine tool control, in compliance with CNOMO E03.81.501N, with a protection degree of IP54, IK08

Extended rotary handle

The circuit breaker on the switch cabinet can be operated with the rotary handle from the front.

Protection degree: IP55, IK08, IP54

Operation/Functions:

- Suitability for isolation
 - Indications of three positions including O (OFF), I (ON) and Tripped
 - Access to trip unit settings, when the switchboard door is open.
 - Circuit breaker closing is disabled if the door is open.
 - Circuit breaker locking capability in the OFF position by 1 to 3 padlocks (shackle diameter 5 to 8 mm (not supplied)). These are used to prevent the door from being opened.


The extended rotary handle is made up of:

- A unit that replaces the front cover of the circuit breaker ⁽¹⁾.
- An assembly (handle and front plate) on the door that is always secured in the closed position, whether the circuit breaker is horizontally or vertically installed.
- An extension shaft that must be adjusted to the distance. The distance between the back of the circuit breaker and door is:
 - EasyPact CVS100BS: 145~422mm




EasyPact CVS100BS with an extended rotary handle


16 A




20 A




25 A




32 A




40 A




50 A




63 A



80 A



100 A



Temperature derating of trip units

EasyPact CVS100BS

Rating (A)	40°C	45°C	50°C	55°C	60°C	65°C
16	16.7	16.3	16.0	15.7	15.6	15.5
20	20.4	20.2	20.0	19.7	19.2	18.8
25	25.7	25.3	25.0	24.7	24.5	24.3
32	33.5	32.7	32.0	31.4	31.0	30.6
40	40.9	40.4	40.0	39.5	38.0	37.5
50	52.1	51.0	50.0	49.3	48.1	47.0
63	64.9	63.9	63.0	62.0	60.4	59.4
80	82.2	81.1	80.0	78.6	77.3	76.0
100	103.0	101.0	100.0	99.0	94.0	94.0


Altitude Derating of trip units

Altitude does not significantly affect circuit-breaker characteristics up to 2000 m. Above this altitude, it is necessary to take into account the decrease in dielectric strength and cooling capacity of air. It should be noted that the breaking capacity remained unchanged.

EasyPact CVS100BS

Height (m)	2000	2600
Dielectric strength (V)	3000	2850
Maximum operation voltage (V)	690	655.5
Nominal current at 40°C(A)	1 x I _n	0.95 x I _n

Current-limiting capacity refers to the ability of a circuit breaker to limit short-circuit current.



Ics 17kA

Current-limiting performance of EasyPact CVS100BS series helps lower the temperature rise caused by fault current, and consequently improves breaking capacity of a circuit breaker. Ics 17kA.

Extension of service life of electrical installation

Circuit breaker current-limiting technology greatly reduces damage to electrical installation caused by short-circuit current.

Thermal effect

lowers temperature rise and extend service life of cable.

Mechanical effect

Risks of contact and busbar distortion and damage are greatly reduced. The electrodynamic force is decreased.

Electromagnetic effect

Disturbance on surrounding measurement instrument is relieved.

Current-limiting curve

Current-limiting capacity of a circuit breaker can be represented by two curves. One curve varies with the value of prospective short-circuit current (short-circuit current without any protective device).



- Actual peak current (current-limiting)
- Thermal effect (A²s), which means energy loss of a 1Ω conductor caused by short-circuit current.

Maximum allowable thermal stress of cable

The maximum allowable overheating values (in A²s), dependent on cable material (Cu or Al) and cross section (mm²), are listed in the following table.

Cross section (mm ²)		1.5	2.5	4	6
PVC	Copper	2.97 x 10 ⁴	8.26 x 10 ⁴	2.12 x 10 ⁵	4.76 x 10 ⁵
	Aluminum				
PRC	Copper	4.10 x 10 ⁴	1.39 x 10 ⁵	2.92 x 10 ⁵	6.56 x 10 ⁵
	Aluminum				
Cross section (mm ²)		16	25	35	50
PVC	Copper	3.4 x 10 ⁶	8.26 x 10 ⁶	1.62 x 10 ⁷	3.31 x 10 ⁷
	Aluminum	1.39 x 10 ⁶	3.38 x 10 ⁶	6.64 x 10 ⁶	1.35 x 10 ⁷
PRC	Copper	4.69 x 10 ⁶	1.39 x 10 ⁷	2.23 x 10 ⁷	4.56 x 10 ⁷
	Aluminum	1.93 x 10 ⁶	4.70 x 10 ⁶	9.23 x 10 ⁶	1.88 x 10 ⁷


Current-limiting curves of EasyPact CVS100BS



PE106445



EasyPact CVS100BS



EasyPact CVS100BS circuit breaker is suitable for capacitor protection following the rules below:

■ **Inc = Nominal current of the capacitor**

$$I_{nc} = \frac{Q_c}{U\sqrt{3}}$$

I_{nc} = Nominal Current Capacitor (A)
 Q_c = Reactive power (kVAR)
 U = Nominal Voltage (V)

■ **Inb = Nominal current of the circuit breaker**

- $I_{nb} = 1.36 \times I_{nc}$ for standard equipment
- $I_{nb} = 1.5 \times I_{nc}$ for overrated type equipment
- $I_{nb} = 1.12 \times I_{nc}$ for detuned type equipment: 2.7 tuning
- $I_{nb} = 1.19 \times I_{nc}$ for detuned type equipment: 3.8 tuning
- $I_{nb} = 1.31 \times I_{nc}$ for detuned type equipment: 4.3 tuning
- the short-circuit (magnetic) protection-setting thresholds must enable the energising transients: $10 \times I_{nc}$ for standard, overrated and detuned equipment.

■ **Icu = Ultimate breaking capacity of the circuit breaker**

I_{cu} short-circuit level is given by the installation.

Example:



Table at 400 V AC - 3 phases 50 Hz for standard equipment.

Reactive power (kVAR)	I_{nc} (A)	I_{nb} (A)	Breaking capacity to Circuit Breaker 30 kA
7.5	11	16	CVS100BS3016
10	14	20	CVS100BS3020
15	22	30	CVS100BS3030
20	29	40	CVS100BS3040
30	43	60	CVS100BS3060
40	58	80	CVS100BS3080
50	72	100	CVS100BS3100


Product specification	In	Catalogue number	
		3P3D	4P3D
CVS100BS			
	16	LV510930	LV510950
	20	LV510931	LV510951
	25	LV510932	LV510952
	32	LV510933	LV510953
	40	LV510934	LV510954
	50	LV510935	LV510955
	63	LV510936	LV510956
	80	LV510937	LV510957
	100	LV510938	LV510958

Connection accessories



Cable lugs

DB100821.eps 	≤ 50 A	Cables from 2.5 to 16 mm ²	Set of 2	EZALUG0502
			Set of 3	EZALUG0503
DB100822.eps 	> 50 A	Cables from 10 to 50 mm ²	Set of 2	EZALUG1002
			Set of 3	EZALUG1003


Spreaders

DB11674.eps 	Spreaders for 3P breaker		Set of 3	EZASPDR3P
	Spreaders for 4P breaker		Set of 4	EZASPDR4P

Terminal shields




DB100824.eps 	Terminal shields for 3P breaker		Set of 2	EZATSHD3P
	Terminal shields for 4P breaker		Set of 2	EZATSHD4P
				

Phase barriers

DB100826.eps 	Phase barriers		Set of 2	EZAFASB2
---	----------------	--	----------	-----------------

Electrical auxiliaries


Indication contacts

DB116822.eps 	Auxiliary switch (AX)			EZAUX10
DB116890.eps 	Alarm switch (AL)			EZAUX01
DB116890.eps 	Auxiliary switch + alarm switch (AX + AL)			EZAUX11

Electrical auxiliaries (cont.)

Voltage releases


Db100830.eps



Shunt trip (SHT)

	Voltage	MX/SHT
AC	100-130 V	EZASHT100AC
	200-277 V	EZASHT200AC
	380-480 V	EZASHT380AC
DC	24 V	EZASHT024DC
	48 V	EZASHT048DC

Db100831.eps



Under voltage release (UVR)

	Voltage	MN/UVR
AC	110-130 V	EZAUVR110AC
	200-240 V	EZAUVR200AC
	380-415 V	EZAUVR380AC
DC	24 V	EZAUVR024DC
	48 V	EZAUVR048DC

Rotary handles

Direct rotary handle (for 3/4P breaker)


Db100832.eps



Direct rotary handle (black)	EZAROTDS
Direct rotary handle (red/yellow)	EZAROTDSRY

Extended rotary handle (for 3/4P breaker)

Db100833.eps



Extended rotary handle (black)	EZAROTE
Extended rotary handle (red/yellow)	EZAROTERY

Locks

Padlocking system

Db100834.eps




Padlocking system	EZALOCK
-------------------	---------

Installation accessory

DIN rail adaptor


Db100835.eps




For 2 x 1P or 1 x 2P or 1 x 3P breaker	EZADINR
Note: for 4P breaker, use 2 adaptors	

Dimensions and Installation EasyPact CVS100BS


Dimensions



3P




4P




Backplate mounting




3P



4P




DIN rail mounting




Dimensions and Installation EasyPact CVS100BS


Front panel cutout (small)




3P




4P




Front panel cutout (large)






3P






4P







Terminal shield






Interphase barrier



Direct rotary handle



Extended rotary handle



Notes

Schneider Electric Industries SAS
35, rue Joseph Monier
CS 30323
F- 92506 Rueil Malmaison Cedex

RCS Nanterre 954 503 439
Capital social 896 313 776
www.schneider-electric.com

LVED210011EN

As standards, specifications and designs change from time to time, please ask for confirmation of the information given in this publication.



This document has been printed on ecological paper

Design: Schneider Electric
Photos: Schneider Electric
Printed:

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Terminals](#) category:

Click to view products by [Schneider](#) manufacturer:

Other Similar products are found below :

[HT-13-10](#) [71M-250-32-NB](#) [01-2065-1-0216](#) [00581P0075](#) [M10-10RX](#) [M10BCK](#) [60205-1](#) [604200-1](#) [60598-1-CUT-TAPE](#) [60617-1-C](#) [60873-1](#) [M14-516R/SK](#) [M14-6RSX](#) [M18-10FLX](#) [M18-8FBX](#) [M18-8R/LX](#) [M18BCK](#) [61314-6-C](#) [61-S](#) [61-SN-A](#) [62149-1](#) [62-NBM-A](#) [63-S](#) [640179-1](#) [640917-2-CUT-TAPE](#) [6501550002](#) [66107-2-C](#) [66107-4-C](#) [696683-1](#) [696834-1](#) [696861-1](#) [696931-1](#) [696999-1](#) [M8-516RK](#) [M86700006](#) [MA250DMFMX-A](#) [701-2007](#) [701-2307](#) [701-7761-03](#) [70F-110-32-PB](#) [718-N-A](#) [71M-187-20-NBL](#) [71M-250-32-NBL](#) [72F-187-20-NBL](#) [72M-250-32-NBL](#) [7310](#) [73F-250-32](#) [73F-250-32-NBL](#) [73F-250-32-NL](#) [F14-10C](#)