

Commercial status

End-of-Sale Notice : JUN 21, 2021

 End-of-Sale Notice

Main

Range of product	Telemecanique Photoelectric sensors XU
Series name	Application assembly
Electronic sensor type	Photo-electric sensor transmitter
Sensor name	XUM
Sensor design	Miniature
Detection system	Thru beam
Material	Metal
Supply circuit type	DC
Electrical connection	Cable
Cable length	2 M
Product specific application	-
Emission	Infrared thru beam
[Sn] nominal sensing distance	15 M need a receiver

Complementary

Enclosure material	Zamak and stainless steel
Lens material	Glass
Wire insulation material	PVC
Status LED	Stability: 1 LED (green) Transmitter: 1 LED (orange) Receiver/Supply on: 1 LED (red/green)
[Us] rated supply voltage	12...24 V DC with reverse polarity protection
Supply voltage limits	10...30 V DC
Switching capacity in mA	<= 100 mA (overload and short-circuit protection)
Switching frequency	1000 Hz
Maximum voltage drop	<3 V (closed state)
Current consumption	11 mA
Maximum delay first up	100 Ms
Maximum delay response	0.5 Ms
Maximum delay recovery	0.5 Ms
Net weight	0.128 Kg

Environment

Product certifications	CULus CE CTick
Ambient air temperature for operation	-40...70 °C
Ambient air temperature for storage	-30...60 °C
Vibration resistance	+/- 1.5 mm (f = 10...55 Hz)2 hours in each direction X, Y and Z conforming- to IEC 60068-2-6
Shock resistance	500 m/s ² for 10 x in each direction X, Y and Z conforming to IEC 60068-2-27
IP degree of protection	IP65 conforming to IEC 60529 IP67 conforming to IEC 60529 IP69K conforming to DIN 40050

Packing Units

Package 1 Weight	0.130 Kg
Package 1 Height	1.020 Dm
Package 1 width	1.020 Dm
Package 1 Length	0.470 Dm

Contractual warranty

Warranty	18 months
----------	-----------

Product Life Status : **End of commercialisation**

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Photoelectric Sensors](#) category:

Click to view products by [Schneider](#) manufacturer:

Other Similar products are found below :

[7442AD2X5FRX](#) [EX-19B-LP](#) [EX-19SB-PN](#) [7443AR0X5FRX](#) [7452AD4D4NNX](#) [F3WD052C5M](#) [7655AR-04-F-1-2-RX](#) [7694ADE04DS2X](#)
[FE7C-FRC6S-M](#) [FX-305](#) [PM-R24-R](#) [Q45VR2FPQ](#) [13104RQD07](#) [E3JUXM4MN](#) [E3L2DC4](#) [E3S3LE21](#) [E3SCT11M1J03M](#) [E3SDS20E21](#)
[E3VDS70C43S](#) [E3XNM16](#) [BR23P](#) [HOA6563-001](#) [OJ-3307-30N8](#) [OS-311A-30](#) [P32013](#) [P34036](#) [P43004](#) [P56001](#) [P60001](#) [PB10CNT15PO](#)
[S14132](#) [935286-000](#) [S52101](#) [S56258](#) [SH-21E](#) [EX-L261-P](#) [FD-SN500](#) [FE7B-FDRB6-M](#) [SU-79](#) [T36342](#) [T40300](#) [T60001](#) [PD60CNX20BP](#)
[FX-302-HY](#) [FZS](#) [PM-T64W](#) [PX-22](#) [PZ2-51P](#) [CX-491-P-J](#) [CYNUTX10](#)