

## MW3366

### Clamp Meter 600A TRMS AC + DC

The MW3366 multimeter clamp is a must-have for any toolbox. It is a multifunctional clamp allowing to realize TRMS AC+DC measurements in current and in voltage. It allows a current measurement up to 600A with two sensitivities in order to measure low currents with a high accuracy. It can also measure AC and DC voltages up to 600V. With advanced functions such as frequency measurement, resistance measurement up to 40M $\Omega$ , capacitance measurement up to 2000 $\mu$ F, continuity measurement or temperature measurement, it will answer to all your inspections or troubleshooting diagnosis needs.

#### ■ Features :

- Current measurement up to 600A TRMS AC + DC
- Voltage measurement up to 600V TRMS AC+DC
- Voltage measurement on Variable Frequency Drives (VFD) up to 600V
- Low current measurement AC + DC function
- Frequency measurement up to 400Hz
- Resistance measurement up to 40M $\Omega$
- Capacitance measurement up to 2500 $\mu$ F
- Diode testing
- Continuity function with buzzer
- Jaw opening : 35mm maximum
- Non-Contact voltage detection (Electric Field detection)
- Auto-ranging mode
- Backlighted LCD display
- Auto-Power-Off mode after 32 minutes of inactivity
- Capture Peak RMS 80ms mode for inrush currents
- Relative-zero mode (offset)
- Fonction HOLD
- 6000 counts display
- Safety : CAT III 600V and CAT IV 300V



MW3366

## Clamp Meter 600A TRMS AC +DC

Specifications	MW3366
<b>AC + DC current (clamp-on)</b>	
<b>Range</b>	<b>Accuracy</b>
	<b>DC, 50Hz-100Hz</b>
60.00A - 600.0A	± (2.2% reading + 7dgt)
	<b>100Hz-400Hz</b>
60.00A - 600.0A	± (2.7% reading + 5dgt)
<b>DC current (clamp)</b>	
<b>Range</b>	<b>Accuracy</b>
60.00A - 600.0A	± (2.0% reading + 5dgt)
<b>AC current (clamp)</b>	
<b>Range</b>	<b>Précision</b>
	<b>50Hz-100Hz</b>
60.00A - 600.0A	± (1.8% reading + 5dgt)
	<b>100Hz-400Hz</b>
60.00A - 600.0A	± (2.0% reading + 5dgt)
<b>DC current (clamp-on)</b>	
<b>Range</b>	<b>Accuracy</b>
60.00A	<b>DC, 50Hz-60Hz</b>
	± (2.0% reading + 7dgt)
<b>AC current (clamp-on)</b>	
<b>Range</b>	<b>Accuracy</b>
60.00A	± (2.0% reading + 5dgt)
<b>Low AC current (clamp)</b>	
<b>Range</b>	<b>Accuracy</b>
60.00A	<b>DC, 50Hz-60Hz</b>
	± (1.5% reading + 5dgt)
<b>AC voltage (with digital low pass filter)</b>	
<b>Bandwith</b>	50Hz-60Hz
<b>Ranges</b>	600.0V
<b>Accuracy</b>	± (1.2% reading + 5dgt)
<b>Impedance</b>	10MΩ // 100pF
<b>DC Voltage</b>	
<b>Ranges</b>	600.0V
<b>Accuracy</b>	± (0.5% reading + 5dgt)
<b>Impedance</b>	10MΩ // 100pF
<b>AC + DC Voltage (with digital low pass filter)</b>	
<b>Bandwith</b>	DC, 50Hz-60Hz
<b>Ranges</b>	600.0V
<b>Accuracy</b>	±(1.2% reading + 7dgt)
<b>Impedance</b>	10MΩ // 100pF
<b>Resistance</b>	
<b>Range</b>	<b>Accuracy</b>
600.0Ω-6.000kΩ, 60.00kΩ	± (1.0% reading + 5dgt)
<b>Frequency</b>	
<b>Function</b>	<b>Accuracy</b>
600V	5.00Hz - 999.9Hz
6A (low current mode)	50.00Hz - 400.0Hz
60A, 600A	50.00Hz - 400.0Hz
<b>Accuracy</b>	± (1% reading + 5dgt)
<b>Non-contact EF-Detection</b>	
<b>Voltage</b>	<b>Bar-graph indication</b>
20V (tolerance : 10V - 36V)	-
55V (tolerance : 23V - 83V)	--
110V (tolerance : 59V-165V)	---
220V (tolerance : 124V-330V)	----
440V (tolerance : 250V-600V)	-----
Indication : Bar-graph segments & audible beep tones proportional to the field strength	
Detection frequency : 50/60Hz	

# MW3366

# Sefram

## Clamp Meter 600A TRMS AC +DC

Specifications		MW3366
<b>Continuity</b>		
Audible Threshold : between 10Ω and 250Ω		
Response time 32ms		
<b>Capacitance</b>		
<b>Range</b>		<b>Accuracy</b>
200.0μF, 2500μF		± (2.0% reading + 4dgt)
<b>Diode testing</b>		
<b>Range</b>		<b>Accuracy</b>
2.000V		± (1.5% reading + 5dgt)
<b>General specifications</b>		
Screen display		LCD screen
Measurement display		6000 counts
Jaw opening		35mm max
Update rate		5 measurements/s
APO (Auto-Power-Off)		after 32 minutes
Operating temperature		0°C to 40°C
Storage temperature		-20°C to 60°C < 80% R.H
Operating altitude		Under 2000m
Safety		CAT III 600V and CAT IV 300V
Power supply		2 batteries 1,5V AAA
Power consumption		13 mA
Dimensions		223mm x 76mm x 37mm
Weight		234g
Warranty		1 an

Accessories provided : Test lead set, User's manual, Soft carrying pouch.

For assistance and ordering



MW3366 A 00 - Specifications can be updated without notice

# Sefram

32, rue Edouard Martel - BP55- 42009 - St Etienne - cedex 2  
Tél. +33 (0) 4.77.59.01.01 / Fax. +33 (0) 4.77.57.23.23  
Web : [www.sefram.com](http://www.sefram.com) - e-mail : [sales@sefram.com](mailto:sales@sefram.com)



Follow us on :



Visit our website: [www.sefram.com](http://www.sefram.com)

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Clamp Multimeters & Accessories](#) category:*

*Click to view products by [Sefram](#) manufacturer:*

Other Similar products are found below :

[2840265](#) [2840283](#) [A 1019](#) [UT219M](#) [MW3366](#) [P 4205](#) [P 1636](#) [BM038F](#) [FMHT82564-0](#) [FLK-393-IRR-PVLEAD](#) [FLK-393FC-PVLEAD](#)  
[1000-303](#) [1000-304](#) [1005-572](#) [1010-516](#) [TESTO 770-3 0590 7703](#) [AX-3550](#) [BM079](#) [BM089](#) [BM157](#) [BM162](#) [BM197](#) [UT204](#) [FLUKE 80I-](#)  
[110S](#) [FLUKE A3002FC](#) [FLUKE I200](#) [FLUKE I200S](#) [FLUKE I310S](#) [FLUKE I400](#) [CIE600](#) [TESTO 770-2 0590 7702](#) [KEW2433R](#) [FLUKE](#)  
[772](#) [BK316](#) [ACDC-100](#) [MA440](#) [FLUKE-374 FC](#) [CM55](#) [I400S](#) [CM46](#) [I200](#) [ACD-6 PRO](#) [T5-1000 USA](#) [FLUKE-1630-2FC](#) [I410](#) [CM42](#)  
[FLUKE-376 FC](#) [ACD-14-PRO](#) [A193 \(800 MM\)](#) [F201](#)