

# Sefram

# SEFRAM 7335

**Make sure to visit  
our Website**

<http://www.sefram.fr>

**6000 counts - TRMS AC+DC Multimeter**

## Robust, reliable and high performance multimeter

TRMS AC+DC

### Capabilities :

- Basic accuracy of 0.08% in V DC
- Voltage measurement up to 1000V AC, DC and TRMS AC+DC
- Current measurement from 60mA to 10A for AC, DC and TRMS AC+DC
- Resistance measurement up to 40Mohms
- Capacitance measurement up to 10mF
- Frequency counter up to 100kHz
- Continuity test with buzzer
- Temperature measurement (for K thermocouple)
- Autoranging
- Diode test
- Panoramic LCD with backlight and 65 segments bargraph
- Functions: Hold, Peak-Hold (1ms), Min-Max
- Safety : CAT IV - 600V and CAT III - 1000V



### Specifications

DC voltages	
Ranges	60mV to 600V (in 6 ranges)
Basic accuracy	$\pm(0.08\% + 2\text{dgt})$
Resolution	10 $\mu$ V to 1V
AC voltages	
Ranges	60mV to 1000V (in 6 ranges)
Basic AC accuracy	$\pm(0.8\% + 5\text{dgt})$
Basic TRMS AC+DC accuracy	$\pm(2\% + 5\text{dgt})$
Resolution	10 $\mu$ V to 1V
Bandwidth	50Hz to 1000Hz
AC and DC voltages, Lo impedance mode	
Ranges	600V and 1000V
Basic AC accuracy	$\pm(0.8\% + 3\text{dgt})$
Input impedance	3 kohms
DC currents	
Ranges	60mA, 600mA, 6A and 10A
Basic accuracy	$\pm(0.8\% + 3\text{dgt})$
Resolution	10 $\mu$ A to 10mA
Protection	HBC fuse 440mA /1000V - 10kA HBC fuse 11A / 1000V - 20kA
AC currents	
Ranges	60mA, 600mA, 6A and 10A
Basic AC accuracy	$\pm(1.2\% + 3\text{dgt})$
Basic TRMS AC+DC accuracy	$\pm(2\% + 5\text{dgt})$
Resolution	10 $\mu$ A to 10mA
Protection	HBC fuse 440mA /1000V - 10kA HBC fuse 11A / 1000V - 20kA
Resistance	
Ranges	600 ohms to 40Mohms (in 6 ranges)
Basic accuracy	$\pm(0.8\% + 2\text{dgt})$
Open circuit voltage	2.5V max
Continuity test	yes, with buzzer
Diode test	yes, under 0.4mA typical

### Sefram 7335

Capacitance	
Ranges	1 $\mu$ F to 10mF in 5 ranges
Basic accuracy	$\pm(1.2\% + 2\text{dgt})$
Temps de mesure	from 0.7s to 3 s (according to range)
Resolution	1nF to 10 $\mu$ F
Frequency (on AC current and voltage ranges)	
Ranges	100Hz to 100kHz in 4 ranges
Accuracy de base	$\pm(0.1\% + 2\text{dgt})$
Temperature (K type thermocouple)	
Ranges	-40°C to +400°C
Accuracy	$\pm(1\% + 10\text{dgt})$ , excluding the thermocouple accuracy
Resolution	0.1°
Peak-Hold (1ms)	
Accuracy	Add 150 digits to the accuracy of the selected range/function
Functions	
	Hold, Min-Max
General specifications	
Display	LCD, backlighted
Display counts	3 digits 3/4, 6000 counts with 65 segments bargraph
Measurement rate	3 meas./s
Operating temperature	-10°C to 50°C (RH<70%)
Storage temperature	-20°C to 60°C (without battery and RH<80%)
Protection	electronic and HBC fuses for current ranges
Safety	600V - CAT IV and 1000V CAT III
Power supply	1 single 9V - 6F22
Autonomy	150h typical (with alkaline battery and backlight off)
Auto power-off	after 20mn
Dimensions	190 x 94 x 48mm
Weight	460g

**Supplied with :** a test lead set, battery (installed) and manual.

FT 7335A00 - Specifications can be updated without notice



# Sefram

32, rue Edouard Martel - BP55- 42009 - St Etienne - cedex 2  
Tél. +33 (0) 4.77.59.01.01 / Fax. +33 (0) 4.77.57.23.23  
Web : [www.sefram.com](http://www.sefram.com) - e-mail : [sales@sefram.com](mailto:sales@sefram.com)



**For assistance and ordering**

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Digital Multimeters](#) category:*

*Click to view products by [Sefram](#) manufacturer:*

Other Similar products are found below :

[2727795](#) [2727486](#) [6111-517](#) [40705X](#) [3026976](#) [P 8100](#) [OW18D](#) [OW18E](#) [OW18B](#) [UT334A](#) [1833C](#) [UT611](#) [1832C](#) [BM2807CSE](#) [45218](#)  
[MM200](#) [UT52](#) [FMHT82565-0](#) [UT802](#) [UT12E-EU](#) [SEFRAM7212](#) [UT8805E](#) [UT60EU](#) [BM2803CSE](#) [45215](#) [UT8804E](#) [RS3250](#)  
[BM2805CSE](#) [STHT0-77364](#) [RS3251](#) [NP40 000M0](#) [NP45 100M0](#) [BK391B](#) [BK393B](#) [BK390B](#) [FLK-87VMAX-PVLEAD1](#) [1664FC](#) [SCH](#)  
[FTT KIT](#) [BK394B](#) [KPS-MT720](#) [KPS-MT460](#) [KPS-MT440](#) [KPS-MT700](#) [KPS-MT480](#) [KPS-SL100](#) [KPS-MT920](#) [KPS-MT470](#) [RS3248](#)  
[UT267B](#) [KPSMT490CBINT](#) [RS3252](#)