

Sefram

Make sure to visit
our Website

<http://www.sefram.fr>

SEFRAM 7357

Process Multimeter 50.000 counts TRMS AC+DC, high accuracy

Capabilities

Multimeter

- Measure voltages up to 1000V TRMS AC+DC and 1000V DC
- Basic accuracy: 0,05%
- Measure currents up to 1A
- Frequency counter
- Measure resistance up to 50 Mohms
- Continuity test with buzzer
- Diode test
- Digital filter for high accuracy and stability

Process calibrator

- Current source 4-20mA or 0-20mA
- Step mode with pre-defined values or user defined
- Automatic or manual ranges
- Simulator mode with % and Delta %
- Loop power mode (24V/24mA) and HART mode

General capabilities

- Memory : 1000 measures
- Functions: MIN/MAX/AVG, REL, HOLD, Auto HOLD
- Opto isolated USB interface
- PC software WINDMM507 (supplied)
- Safety: 600V CAT IV and 1000V CAT III

Unique ergonomoy with navigator

The SEFRAM 7357 process multimeter uses a unique navigator to access and navigate in the menus and functions provided. All basic functions (V, A Ω , ...) are kept with direct access for time saving.

Process functions

The SEFRAM 7357 offers not only a current source (4-20mA or 0-20mA), but can work in simulate mode in your process loop. Current ramps can be generated automatically with standard parameters or user defined parameters. The SEFRAM 7357 can be used as a loop power and can supply sensors, measuring the sourced current. In HARTmode, a 250 ohms resistor is inserted in the loop in order to communicate with HART sensors or intelligent instruments.

TRMS AC+DC



TRMS
AC+DC

4-20mA
and
0-20mA

Loop power

600V CAT IV
1000V CAT III

SEFRAM 7357

Hi-accuracy and TRMS AC+DC measurements

The Process DMM SEFRAM 7357 provides a basic accuracy of 0,05% in V DC. In AC mode, TRMS AC and TRMS AC+DC mode permit measurements on complex signals with large bandwidth (10kHz).



Sefram



SEFRAM 7357

Process Multimeter 50.000 counts

Specifications Sefram 7357

DC voltages	
Ranges	50mV to 1000V in 6 ranges
Basic accuracy	$\pm(0,05\% + 5\text{dgt})$
Resolution	1 μ V to 0,1V
AC voltages (TRMS AC et TRMS AC+DC)	
Ranges	50mV to 1000V in 6 ranges
Resolution	1 μ V to 0,01V
Basic accuracy (AC)	$\pm(0,5\% + 20\text{dgt})$ from 5% to 100% of the range
Basic accuracy in AC, AC+DC	$\pm(1,55\% + 25\text{dgt})$ from 5% to 100% of the range
Bandwidth	40Hz to 10kHz (according to range)
DC currents	
Ranges	50mA and 1A
Basic accuracy	$\pm(0,05\% + 5\text{dgt})$
Resolution	from 1 μ A to 50mA
Protection	with HBC fuse 0.44A / 1000V
AC current (TRMS AC et TRMS AC+DC)	
Ranges	50mA and 1A
Resolution	from 1 μ A to 50mA
Basic accuracy	$\pm(1,0\% + 20\text{dgt})$ from 5% to 100% of the range
Bandwidth	40Hz to 10kHz
Protection	with HBC fuse 0.44A / 1000V
Frequency (AC currents and voltages)	
Ranges	500Hz to 100kHz (10kHz for AC currents)
Basic accuracy	$\pm(3\text{dgt})$
Sensitivity	1V p-p from 5Hz to 100kHz and 10mA/300mA in current from 5Hz to 10kHz
Protection	same as current or voltage ranges
Resistance	
Ranges	500ohms to 50Mohms in 6 ranges
Basic accuracy	$\pm(0,2\% + 10\text{dgt})$
Protection	1000Vrms or DC
Continuity test	
yes, with buzzer (threshold 30 ohms), $\pm(0,1\% + 30\text{dgt})$	
Diode test	
yes, with 1mA test current	
Accuracy	$\pm(1\% + 20\text{dgt})$
Functions	
MIN, MAX, AVG (average), REL, HOLD, Auto Hold	
Process calibrator	
Current source mode	
Ranges	0 to 20mA or 4mA to 20mA (overrange possible up to 24mA)
Basic accuracy	$\pm(0,05\% + 5\text{dgt})$
Resolution	1 μ A
Protection	with HBC fuse 0.44A / 1000V
Current ramp (source mode)	
Ramps	linear, 0% to 100% and back to 0% in 40s
	linear, 0% to 100% and back to 0% in 20s
	25% steps, 0 to 100%, 15s for each step
	25% steps, 0 to 100%, 5s for each step
	same as current accuracy and protection
Basic accuracy, protection	same as source mode, but DMM uses external power supply (6 to 48V)
Current ramp (simulator mode)	
Loop supply	
Ranges	current: 50mA / voltage: 30V / Impedance: 1,25k Ω
Accuracy	$\pm(0,05\% + 5\text{dgt})$
Protection	with HBC fuse 0.44A / 1000V
Loop supply - 250 HART mode	
Ranges	current: 50mA / voltage: 24V / Impedance: 1k Ω
Accuracy	$\pm(0,05\% + 5\text{dgt})$
Protection	with HBC fuse 0.44A / 1000V

General specifications

Display type	LCD, with automatic backlight
Display counts	5 digits, 50.000 counts
Measurement rate	10 measures/s
Memory	100 measures
Operating temperature	-10°C to 50°C
Storage temperature	-20°C to 60°C (without batteries), RH < 80%
Protection	electronic, except current ranges protected with HBC fuse
Power supply	4 x 1.5V - LR6 AA batteries / Autonomy: 120h typical
Auto Power-off	with alkaline batteries / 10h typical in current source mode
Dimensions	after 20mn approx. Or disabled
Weight	95 x 52 x 207mm
Safety	630g, with holster
Warranty	600V CAT IV and 1000V CAT III
	1 year




Supplied with: a set of safety test leads, user manual, opto-isolated USB cable, WINDMM507 software for PC, batteries (installed).




SFT7357 A 00- Specifications can be updated without notice



32, rue Edouard Martel - BP55- 42009 - St Etienne - cedex 2
 Tél. +33 (0) 4.77.59.01.01
 Fax. +33 (0) 4.77.57.23.23
 Web : www.sefram.com - e-mail : sales@sefram.com

Follow us on :   

For assistance and ordering



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Sefram](#) manufacturer:

Other Similar products are found below :

[BK312C](#) [BK313C](#) [DAS220BAT](#) [DAS240BAT](#) [DAS50](#) [GE 1521](#) [GE 3121](#) [MW3035](#) [MW9520](#) [SC521](#) [SEFRAM12](#) [SEFRAM40](#)
[SEFRAM62](#) [SEFRAM66](#) [SEFRAM7202](#) [SEFRAM7203](#) [SEFRAM7204](#) [SEFRAM7220](#) [SEFRAM7223](#) [SEFRAM7303](#) [SEFRAM7334](#)
[SEFRAM7335](#) [SEFRAM80](#) [SEFRAM82](#) [SEFRAM86](#) [SEFRAM95](#) [SEFRAM96](#) [SEFRAM9816B](#) [SEFRAM9819](#) [SEFRAM9836](#)
[SEFRAM9862](#) [SEFRAM LOG 1601](#) [SEFRAM LOG 1620](#)