

**Sefram**  
Sefram

Visitez our  
Web site

<http://www.sefram.fr>

# SEFRAM 80

---

# SEFRAM 86

**Trust the new SEFRAM phase sequence indicators to check all electrical installations, in complete safety.**

## SEFRAM 80

With the SEFRAM 80, you can check the order of the phases in all electrical installations. Having a robust design, the SEFRAM 80 is also very easy to use. It is the ideal tool for rapidly testing your industrial equipment.

**Supplied with :** a protection bag.

## SEFRAM 86

The SEFRAM 86 meets all your requirements for a phase sequence indicator :

- Identifies open phases.
- Shows direction of motor rotation.
- Identifies correct phase sequence.

This model is ideal for installing motors in conveyor lines, pump systems and electronic drives.

**Supplied with :** SE 710, set of three cables, three croc clips and battery.




**CEI 1010**  
600 V CAT.III  
1000 V CAT.II



Technical Specifications :	SEFRAM 80	SEFRAM 86
AC voltage	200 - 600 V	100 - 600 V
Bandwidth	50 à 60 Hz	45 à 70 Hz
Power request	-	Battery 9 V (006P)
Size, weight	134 x 85 x 45 mm, 530 g	153 x 72 x 35 mm, 182 g
Warranty	1 year	1 year
IEC 1010 safety standard	IEC 1010 - CAT.III 600 V	IEC 1010 - CAT.III 600 V

Specifications subject to change without notice - FT908000M/00

**For assistance and ordering**



**Sefram**  
INSTRUMENTS & SYSTEMES



32, rue Edouard Martel • 42100 - St Etienne  
**Direct sales line : +33 (0)4.77.59.36.81**  
 Fax. +33 (0)4.77.57.23.23  
 Web : [www.sefram.fr](http://www.sefram.fr) • e-mail : [sales@sefram.fr](mailto:sales@sefram.fr)

## **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Sefram](#) manufacturer:*

Other Similar products are found below :

[SEFRAM LOG 1620](#) [SEFRAM7334](#) [SEFRAM7303](#) [SEFRAM7335](#) [SEFRAM95](#) [SEFRAM9816B](#) [SEFRAM9836](#) [DAS220BAT](#)

[DAS240BAT](#) [DAS50](#) [BK313C](#) [BK312C](#) [MW3035](#) [SC521](#) [SEFRAM86](#) [SEFRAM LOG 1601](#) [SEFRAM7203](#) [SEFRAM7220](#) [SEFRAM7204](#)

[SEFRAM7223](#) [SEFRAM9819](#) [SEFRAM9862](#) [MW9520](#) [SEFRAM66](#) [SEFRAM80](#) [SEFRAM82](#) [GE 3121](#) [SEFRAM7202](#) [SEFRAM96](#)

[SEFRAM12](#) [GE 1521](#) [SEFRAM40](#) [SEFRAM62](#)