


MMBT9012H-H35

PNP Silicon Epitaxial Planar Transistors

for switching and amplifier applications.




1. Base 2. Emitter 3. Collector
TO-236 Plastic Package

Absolute Maximum Ratings ($T_a = 25^\circ\text{C}$)

Parameter	Symbol	Value	Unit
Collector Base Voltage	$-V_{\text{CBO}}$	40	V
Collector Emitter Voltage	$-V_{\text{CEO}}$	30	V
Emitter Base Voltage	$-V_{\text{EBO}}$	5	V
Collector Current	$-I_{\text{C}}$	500	mA
Power Dissipation	P_{tot}	200	mW
Junction Temperature	T_{j}	150	$^\circ\text{C}$
Storage Temperature Range	T_{stg}	- 55 to + 150	$^\circ\text{C}$

Characteristics at $T_a = 25^\circ\text{C}$

Parameter	Symbol	Min.	Max.	Unit
DC Current Gain at $-V_{\text{CE}} = 1 \text{ V}$, $-I_{\text{C}} = 50 \text{ mA}$	h_{FE}	230	350	-
Collector Base Cutoff Current at $-V_{\text{CB}} = 35 \text{ V}$	$-I_{\text{CBO}}$	-	100	nA
Emitter Base Cutoff Current at $-V_{\text{EB}} = 5 \text{ V}$	$-I_{\text{EBO}}$	-	100	nA
Collector Base Breakdown Voltage at $-I_{\text{C}} = 100 \mu\text{A}$	$-V_{(\text{BR})\text{CBO}}$	40	-	V
Collector Emitter Breakdown Voltage at $-I_{\text{C}} = 1 \text{ mA}$	$-V_{(\text{BR})\text{CEO}}$	30	-	V
Emitter Base Breakdown Voltage at $-I_{\text{E}} = 100 \mu\text{A}$	$-V_{(\text{BR})\text{EBO}}$	5	-	V
Collector Emitter Saturation Voltage at $-I_{\text{C}} = 500 \text{ mA}$, $-I_{\text{B}} = 50 \text{ mA}$	$-V_{\text{CE}(\text{sat})}$	-	0.6	V
Base Emitter Saturation Voltage at $-I_{\text{C}} = 500 \text{ mA}$, $-I_{\text{B}} = 50 \text{ mA}$	$-V_{\text{BE}(\text{sat})}$	-	1.2	V
Base Emitter Voltage at $-V_{\text{CE}} = 1 \text{ V}$, $-I_{\text{C}} = 100 \text{ mA}$	$-V_{\text{BE}}$	-	1	V
Gain Bandwidth Product at $-V_{\text{CE}} = 6 \text{ V}$, $-I_{\text{C}} = 20 \text{ mA}$	f_{T}	100	-	MHz



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Bipolar Transistors - BJT category](#):

Click to view products by [Semtech manufacturer](#):

Other Similar products are found below :

[619691C](#) [MCH4017-TL-H](#) [MMBT-2369-TR](#) [BC546/116](#) [BC557/116](#) [BSW67A](#) [NJVMJD148T4G](#) [NTE123AP-10](#) [NTE153MCP](#) [NTE16](#)
[NTE195A](#) [NTE92](#) [2N4401-A](#) [2N6728](#) [2SA1419T-TD-H](#) [2SA2126-E](#) [2SB1204S-TL-E](#) [2SC2712S-GR,LF](#) [SP000011176](#) [2N2907A](#) [2N3904-](#)
[NS](#) [2N5769](#) [2SC2412KT146S](#) [CPH6501-TL-E](#) [MCH4021-TL-E](#) [MJE340](#) [Jantx2N5416](#) [US6T6TR](#) [NJL0281DG](#) [732314D](#) [CPH3121-TL-E](#)
[CPH6021-TL-H](#) [873787E](#) [IMZ2AT108](#) [MMST8098T146](#) [UMX21NTR](#) [MCH6102-TL-E](#) [NJL0302DG](#) [30A02MH-TL-E](#) [NTE13](#) [NTE26](#)
[NTE282](#) [NTE323](#) [NTE350](#) [NTE81](#) [STX83003-AP](#) [JANTX2N2920L](#) [JANSR2N2222AUB](#) [CMLT3946EG TR](#) [2SA1371D-AE](#)