


● Features

- High collector current
- 1.3 W power dissipation.



● Absolute Maximum Ratings $T_a = 25^\circ\text{C}$

Parameter	Symbol	Rating	Unit	
Collector-base voltage (open emitter)	BCP51 BCP52 BCP53	V_{CB0}	-45 -60 -100	V V V
Collector-emitter voltage(open base)	BCP51 BCP52 BCP53	V_{CE0}	-45 -60 -80	V V V
Emitter-base voltage(open collector)	V_{EB0}	-5	V	
Collector current	I_C	-1	A	
Peak collector current	I_{CM}	-1.5	A	
Peak base current	I_{BM}	-0.2	A	
Total power dissipation $T_{amb} \leq 25^\circ\text{C}$	P_{tot}	1.3	W	
Storage temperature	T_{stg}	-65 to +150	$^\circ\text{C}$	
Junction temperature	T_j	150	$^\circ\text{C}$	
Operating ambient temperature	R_{amb}	-65 to +150	$^\circ\text{C}$	
Thermal resistance from junction to ambient	$R_{th(j-a)}$	95	K/W	
Thermal resistance from junction to solder point	$R_{th(j-s)}$	14	K/W	

● Electrical Characteristics Ta = 25°C

Parameter	Symbol	Testconditons	Min	Typ	Max	Unit
Collector cutoff current	ICBO	V _{CB} = -30 V, I _E = 0			-100	nA
		V _{CB} = -30 V, I _E = 0; T _j = 125°C			-10	μA
Emitter cutoff current	IEBO	VEB = -5 V, I _C = 0			-100	nA
DC current gain	h _{FE}	I _C = -5 mA; V _{CE} = -2 V	63			
		I _C = -150 mA; V _{CE} = -2 V	63		250	
		I _C = -500 mA; V _{CE} = -2 V	40			
DC current gain BCP51-10,BCP52-10,BCP53-10 BCP51-16,BCP52-16,BCP53-16	h _{FE}	I _C = -150 mA; V _{CE} = -2 V	63		160	
		I _C = -150 mA; V _{CE} = -2 V	100		250	
Collector-emitter saturation voltage	V _{CE(sat)}	I _C = -500 mA; I _B = -50 mA			-0.5	V
Base to emitter voltage	V _{BE}	I _C = -500 mA; V _{CE} = -2 V			-1	V
Transition frequency	f _T	I _C = -10 mA; V _{CE} = -5 V; f = 100 MHz		115		MHz

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Bipolar Transistors - BJT category](#):

Click to view products by [Shikues manufacturer](#):

Other Similar products are found below :

[BC559C](#) [MCH4017-TL-H](#) [MMBT-2369-TR](#) [BC546/116](#) [NJVMJD148T4G](#) [NTE16](#) [NTE195A](#) [IMX9T110](#) [2N4401-A](#) [2N4403](#) [2N6728](#)
[2SA1419T-TD-H](#) [2SA2126-E](#) [2SB1204S-TL-E](#) [FMC5AT148](#) [2N2369ADCSM](#) [2N2907A](#) [2N3904-NS](#) [2N5769](#) [2SC4618TLN](#) [CPH6501-](#)
[TL-E](#) [MCH4021-TL-E](#) [Jantx2N5416](#) [US6T6TR](#) [BAX18/A52R](#) [BC556/112](#) [IMZ2AT108](#) [MMST8098T146](#) [UMX21NTR](#) [MCH6102-TL-E](#)
[TTA1452B,S4X\(S](#) [2N3879](#) [NTE13](#) [NTE282](#) [NTE323](#) [NTE350](#) [NTE81](#) [JANTX2N2920L](#) [JANTX2N3735](#) [JANSR2N2222AUB](#)
[CMLT3946EG TR](#) [SNSS40600CF8T1G](#) [CMLT3906EG TR](#) [GRP-DATA-JANS2N2907AUB](#) [GRP-DATA-JANS2N2222AUA](#)
[MMDT3946FL3-7](#) [2N4240](#) [JANS2N3019](#) [MSB30KH-13](#) [2N2221AUB](#)