**Data sheet** 

6EP3436-3SB00-0AX0



SITOP PSU4200/3AC/24VDC/20A

Siemens EcoTech

SITOP PSU4200 3AC 24 V/20 A stabilized power supply PSU4200 input: 400/500 V AC output: 24 V DC/20 A



type of the power supply network	3-phase AC	
supply voltage at AC minimum rated value	400 500 V	
supply voltage at AC maximum rated value		
supply voltage at AC	320 550 V	
wide range input	Yes	
buffering time for rated value of the output current in the event of power failure minimum	5 ms	
operating condition of the mains buffering	at Vin = 400/500 V	
line frequency	50/60 Hz	
line frequency	47 63 Hz	
input current		
<ul> <li>at rated input voltage 400 V</li> </ul>	1.4 A	
<ul> <li>at rated input voltage 500 V</li> </ul>	1.2 A	
current limitation of inrush current at 25 °C maximum	36 A	
duration of inrush current limiting at 25 °C		
• typical	20 ms	
I2t value maximum	0.9 A²·s	
fuse protection type in the feeder	three-poled coupled circuit breaker from 6 A characteristic C to 16 A characteristic C or circuit breaker 3RV2011-1GA10 (setting 6 A) or 3RV2711-1GD10 (UL 489)	
output		
voltage curve at output	Controlled, isolated DC voltage	
output voltage at DC rated value	24 V	
output voltage		
at output 1 at DC rated value	24 V	
output voltage adjustable	Yes; via potentiometer	
adjustable output voltage	24 28 V	
relative overall tolerance of the voltage	3 %	
relative control precision of the output voltage		
on slow fluctuation of input voltage	0.2 %	
on slow fluctuation of ohm loading	0.3 %	
residual ripple		
• maximum	150 mV	
	25 mV	
• typical	20	
typical  voltage peak		

• typical	10 mV	
display version for normal operation	Green LED for 24 V OK	
type of signal at output	Signal contact (signal load capacity: 5 mA) for DC OK	
behavior of the output voltage when switching on	Overshoot of Vout approx. 1 %	
response delay maximum	1.5 s	
voltage increase time of the output voltage		
• typical	230 ms	
• maximum	500 ms	
output current		
• rated value	20 A	
• rated range	0 20 A; +55 +70 °C: Derating 2%/K	
supplied active power typical	480 W	
bridging of equipment	Yes	
number of parallel-switched equipment resources for increasing	2	
the power	2	
efficiency in percent	91 %	
power loss [W]		
at rated output voltage for rated value of the output	48 W	
current typical		
<ul> <li>during no-load operation maximum</li> </ul>	3.5 W	
closed-loop control		
relative control precision of the output voltage with rapid fluctuation of the input voltage by +/- 15% typical	0.2 %	
relative control precision of the output voltage load step of resistive load 50/100/50 % typical	0.5 %	
relative control precision of the output voltage at load step of resistive load 10/90/10 % typical	1 %	
setting time		
<ul> <li>load step 10 to 90% typical</li> </ul>	1 ms	
● load step 90 to 10% typical	1 ms	
protection and monitoring		
design of the overvoltage protection	< 32 V	
property of the output short-circuit proof	Yes	
design of short-circuit protection	Constant current characteristic	
• typical	23.4 A	
enduring short circuit current RMS value		
• typical	23.5 A	
safety	20.071	
-	Yes	
galvanic isolation between input and output galvanic isolation	ES1 output voltage Vout according to EN 62368-1 (Safety extra low output voltage Vout according to EN 60950-1)	
operating resource protection class	Class I	
leakage current	CIACO I	
maximum	0.8 mA	
• typical	0.4 mA	
protection class IP	IP20	
standard	11 20	
	EN 55022 Class A	
• for emitted interference	EN 55032 Class A	
• for mains harmonics limitation	EN 61000-3-2	
for interference immunity	EN 61000-6-2	
standards, specifications, approvals		
certificate of suitability	Ñ.	
• CE marking	Yes	
• UL approval	Yes; cULus-Listed (UL 508, CSA C22.2 No. 107.1), File E197259; cCSAus (UL 62368-1, CSA C22.2 No. 62368-1-19)	
CSA approval	Yes; cULus-Listed (UL 508, CSA C22.2 No. 107.1), File E197259; cCSAus (UL 62368-1, CSA C22.2 No. 62368-1-19)	
UKCA marking	Yes	
EAC approval	Yes	
<ul> <li>Regulatory Compliance Mark (RCM)</li> </ul>	Yes	
NEC Class 2	No	
type of certification		
• BIS	No	

CB-certificate	Yes
MTBF at 40 °C	815 000 h
standards, specifications, approvals hazardous environments	
certificate of suitability	
• IECEx	No
• ATEX	No
ULhazloc approval	No
• cCSAus, Class 1, Division 2	No
FM registration	No
standards, specifications, approvals marine classification	
shipbuilding approval	No
Marine classification association	
<ul> <li>American Bureau of Shipping Europe Ltd. (ABS)</li> </ul>	No
French marine classification society (BV)	No
<ul> <li>Det Norske Veritas (DNV)</li> </ul>	No
<ul> <li>Lloyds Register of Shipping (LRS)</li> </ul>	No
standards, specifications, approvals Environmental Product Dec	claration
Environmental Product Declaration	Yes
Global Warming Potential [CO2 eq]	
• total	1 054.8 kg
during manufacturing	32.8 kg
<ul> <li>during operation</li> </ul>	1 020.9 kg
after end of life	0.5 kg
Siemens Eco Profile (SEP)	Siemens EcoTech
ambient conditions	
ambient temperature	
<ul> <li>during operation</li> </ul>	-25 +70 °C; with natural convection
<ul> <li>during transport</li> </ul>	-40 +85 °C
during storage	-40 +85 °C
environmental category according to IEC 60721	Climate class 3K3, 5 95% no condensation
connection method	
type of electrical connection	push-in terminals
type of electrical connection	pusit-in terminais
type or electrical connection  • at input	L1, L2, L3, PE: push-in for 0.5 4 mm <sup>2</sup>
•	·
• at input	L1, L2, L3, PE: push-in for 0.5 4 mm²
<ul><li>at input</li><li>at output</li></ul>	L1, L2, L3, PE: push-in for 0.5 4 mm <sup>2</sup> +, -: push-in for 0.5 6 mm <sup>2</sup>
<ul><li>at input</li><li>at output</li><li>for signaling contact</li></ul>	L1, L2, L3, PE: push-in for 0.5 4 mm <sup>2</sup> +, -: push-in for 0.5 6 mm <sup>2</sup>
<ul> <li>at input</li> <li>at output</li> <li>for signaling contact</li> </ul> mechanical data	L1, L2, L3, PE: push-in for 0.5 4 mm <sup>2</sup> +, -: push-in for 0.5 6 mm <sup>2</sup> 13, 14: push-in for 0.2 1.5 mm <sup>2</sup>
<ul> <li>at input</li> <li>at output</li> <li>for signaling contact</li> </ul> mechanical data width × height × depth of the enclosure	L1, L2, L3, PE: push-in for 0.5 4 mm <sup>2</sup> +, -: push-in for 0.5 6 mm <sup>2</sup> 13, 14: push-in for 0.2 1.5 mm <sup>2</sup> 95 × 135 × 150 mm 95 × 225 mm
at input     at output     for signaling contact  mechanical data  width × height × depth of the enclosure installation width × mounting height	L1, L2, L3, PE: push-in for 0.5 4 mm <sup>2</sup> +, -: push-in for 0.5 6 mm <sup>2</sup> 13, 14: push-in for 0.2 1.5 mm <sup>2</sup> 95 × 135 × 150 mm 95 × 225 mm
<ul> <li>at input</li> <li>at output</li> <li>for signaling contact</li> </ul> mechanical data width × height × depth of the enclosure installation width × mounting height required spacing <ul> <li>top</li> <li>bottom</li> </ul>	L1, L2, L3, PE: push-in for 0.5 4 mm <sup>2</sup> +, -: push-in for 0.5 6 mm <sup>2</sup> 13, 14: push-in for 0.2 1.5 mm <sup>2</sup> 95 × 135 × 150 mm 95 × 225 mm 45 mm 45 mm
<ul> <li>at input</li> <li>at output</li> <li>for signaling contact</li> </ul> mechanical data width × height × depth of the enclosure installation width × mounting height required spacing <ul> <li>top</li> <li>bottom</li> <li>left</li> </ul>	L1, L2, L3, PE: push-in for 0.5 4 mm <sup>2</sup> +, -: push-in for 0.5 6 mm <sup>2</sup> 13, 14: push-in for 0.2 1.5 mm <sup>2</sup> 95 × 135 × 150 mm  95 × 225 mm  45 mm 45 mm 0 mm
<ul> <li>at input</li> <li>at output</li> <li>for signaling contact</li> </ul> mechanical data width × height × depth of the enclosure installation width × mounting height required spacing <ul> <li>top</li> <li>bottom</li> <li>left</li> <li>right</li> </ul>	L1, L2, L3, PE: push-in for 0.5 4 mm <sup>2</sup> +, -: push-in for 0.5 6 mm <sup>2</sup> 13, 14: push-in for 0.2 1.5 mm <sup>2</sup> 95 × 135 × 150 mm  95 × 225 mm  45 mm 45 mm 0 mm 0 mm
<ul> <li>at input</li> <li>at output</li> <li>for signaling contact</li> </ul> mechanical data width × height × depth of the enclosure installation width × mounting height required spacing <ul> <li>top</li> <li>bottom</li> <li>left</li> <li>right</li> </ul> fastening method	L1, L2, L3, PE: push-in for 0.5 4 mm <sup>2</sup> +, -: push-in for 0.5 6 mm <sup>2</sup> 13, 14: push-in for 0.2 1.5 mm <sup>2</sup> 95 × 135 × 150 mm  95 × 225 mm  45 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15
<ul> <li>at input</li> <li>at output</li> <li>for signaling contact</li> </ul> mechanical data width × height × depth of the enclosure installation width × mounting height required spacing <ul> <li>top</li> <li>bottom</li> <li>left</li> <li>right</li> </ul> fastening method <ul> <li>standard rail mounting</li> </ul>	L1, L2, L3, PE: push-in for 0.5 4 mm² +, -: push-in for 0.5 6 mm² 13, 14: push-in for 0.2 1.5 mm²  95 × 135 × 150 mm  95 × 225 mm  45 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes
at input at output for signaling contact  mechanical data  width × height × depth of the enclosure installation width × mounting height  required spacing top bottom left right fastening method standard rail mounting S7 rail mounting	L1, L2, L3, PE: push-in for 0.5 4 mm² +, -: push-in for 0.5 6 mm² 13, 14: push-in for 0.2 1.5 mm²  95 × 135 × 150 mm  95 × 225 mm  45 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No
at input at output for signaling contact  mechanical data  width × height × depth of the enclosure installation width × mounting height required spacing top bottom left right fastening method standard rail mounting S7 rail mounting wall mounting	L1, L2, L3, PE: push-in for 0.5 4 mm² +, -: push-in for 0.5 6 mm² 13, 14: push-in for 0.2 1.5 mm²  95 × 135 × 150 mm 95 × 225 mm  45 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No
at input at output for signaling contact  mechanical data  width × height × depth of the enclosure installation width × mounting height required spacing  top bottom left right fastening method standard rail mounting S7 rail mounting wall mounting housing can be lined up	L1, L2, L3, PE: push-in for 0.5 4 mm² +, -: push-in for 0.5 6 mm² 13, 14: push-in for 0.2 1.5 mm²  95 × 135 × 150 mm  95 × 225 mm  45 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No
<ul> <li>at input</li> <li>at output</li> <li>for signaling contact</li> </ul> mechanical data <ul> <li>width × height × depth of the enclosure</li> <li>installation width × mounting height</li> <li>required spacing</li> <li>top</li> <li>bottom</li> <li>left</li> <li>right</li> </ul> fastening method <ul> <li>standard rail mounting</li> <li>\$7 rail mounting</li> <li>wall mounting</li> </ul> housing can be lined up <ul> <li>net weight</li> </ul>	L1, L2, L3, PE: push-in for 0.5 4 mm² +, -: push-in for 0.5 6 mm² 13, 14: push-in for 0.2 1.5 mm²  95 × 135 × 150 mm 95 × 225 mm  45 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No
at input at output for signaling contact  mechanical data  width × height × depth of the enclosure installation width × mounting height  required spacing top bottom left right fastening method standard rail mounting S7 rail mounting wall mounting housing can be lined up net weight  further information internet links	L1, L2, L3, PE: push-in for 0.5 4 mm² +, -: push-in for 0.5 6 mm² 13, 14: push-in for 0.2 1.5 mm²  95 × 135 × 150 mm  95 × 225 mm  45 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No
<ul> <li>at input</li> <li>at output</li> <li>for signaling contact</li> </ul> mechanical data <ul> <li>width × height × depth of the enclosure</li> <li>installation width × mounting height</li> <li>required spacing</li> <li>top</li> <li>bottom</li> <li>left</li> <li>right</li> </ul> fastening method <ul> <li>standard rail mounting</li> <li>S7 rail mounting</li> <li>wall mounting</li> </ul> housing can be lined up <ul> <li>net weight</li> </ul> further information internet links <ul> <li>internet link</li> </ul>	L1, L2, L3, PE: push-in for 0.5 4 mm² +, -: push-in for 0.5 6 mm² 13, 14: push-in for 0.2 1.5 mm²  95 × 135 × 150 mm 95 × 225 mm  45 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No Yes 1.66 kg
<ul> <li>at input</li> <li>at output</li> <li>for signaling contact</li> </ul> mechanical data <ul> <li>width × height × depth of the enclosure</li> <li>installation width × mounting height</li> <li>required spacing</li> <li>top</li> <li>bottom</li> <li>left</li> <li>right</li> </ul> fastening method <ul> <li>standard rail mounting</li> <li>S7 rail mounting</li> <li>wall mounting</li> <li>housing can be lined up</li> <li>net weight</li> </ul> further information internet links <ul> <li>internet link</li> <li>to web page: selection aid TIA Selection Tool</li> </ul>	L1, L2, L3, PE: push-in for 0.5 4 mm² +, -: push-in for 0.5 6 mm² 13, 14: push-in for 0.2 1.5 mm²  95 × 135 × 150 mm  95 × 225 mm  45 mm 45 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No Yes 1.66 kg
<ul> <li>at input</li> <li>at output</li> <li>for signaling contact</li> </ul> mechanical data <ul> <li>width × height × depth of the enclosure</li> <li>installation width × mounting height</li> <li>required spacing</li> <li>top</li> <li>bottom</li> <li>left</li> <li>right</li> </ul> fastening method <ul> <li>standard rail mounting</li> <li>S7 rail mounting</li> <li>wall mounting</li> <li>housing can be lined up</li> <li>net weight</li> </ul> further information internet links <ul> <li>internet link</li> <li>to web page: selection aid TIA Selection Tool</li> <li>to website: Industrial communication</li> </ul>	L1, L2, L3, PE: push-in for 0.5 4 mm² +, -: push-in for 0.5 6 mm² 13, 14: push-in for 0.2 1.5 mm²  95 × 135 × 150 mm  95 × 225 mm  45 mm 45 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No Yes 1.66 kg
<ul> <li>at input</li> <li>at output</li> <li>for signaling contact</li> </ul> mechanical data width × height × depth of the enclosure <ul> <li>installation width × mounting height</li> </ul> required spacing <ul> <li>top</li> <li>bottom</li> <li>left</li> <li>right</li> </ul> fastening method <ul> <li>standard rail mounting</li> <li>S7 rail mounting</li> <li>wall mounting</li> </ul> housing can be lined up <ul> <li>net weight</li> </ul> further information internet links <ul> <li>internet link</li> <li>to web page: selection aid TIA Selection Tool</li> <li>to website: Industrial communication</li> <li>to website: CAx-Download-Manager</li> </ul>	L1, L2, L3, PE: push-in for 0.5 4 mm² +, -: push-in for 0.5 6 mm² 13, 14: push-in for 0.2 1.5 mm²  95 × 135 × 150 mm  95 × 225 mm  45 mm 45 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No Yes 1.66 kg
at input at output for signaling contact  mechanical data  width × height × depth of the enclosure installation width × mounting height  required spacing top bottom left right fastening method standard rail mounting S7 rail mounting wall mounting housing can be lined up net weight  further information internet links internet link to web page: selection aid TIA Selection Tool to website: Industrial communication to website: CAx-Download-Manager additional information	L1, L2, L3, PE: push-in for 0.5 4 mm² +, -: push-in for 0.5 6 mm² 13, 14: push-in for 0.2 1.5 mm²  95 × 135 × 150 mm  95 × 225 mm  45 mm 45 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No Yes 1.66 kg  https://siemens.com/tst http://www.siemens.com/cax
<ul> <li>at input</li> <li>at output</li> <li>for signaling contact</li> </ul> mechanical data <ul> <li>width × height × depth of the enclosure</li> <li>installation width × mounting height</li> <li>required spacing</li> <li>top</li> <li>bottom</li> <li>left</li> <li>right</li> </ul> fastening method <ul> <li>standard rail mounting</li> <li>S7 rail mounting</li> <li>wall mounting</li> </ul> housing can be lined up <ul> <li>net weight</li> </ul> further information internet links <ul> <li>internet link</li> <li>to web page: selection aid TIA Selection Tool</li> <li>to website: Industrial communication</li> <li>to website: CAx-Download-Manager</li> </ul>	L1, L2, L3, PE: push-in for 0.5 4 mm² +, -: push-in for 0.5 6 mm² 13, 14: push-in for 0.2 1.5 mm²  95 × 135 × 150 mm 95 × 225 mm  45 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No Yes 1.66 kg  https://siemens.com/tst http://www.siemens.com/simatic-net http://www.siemens.com/cax
at input at output for signaling contact  mechanical data  width × height × depth of the enclosure installation width × mounting height  required spacing top bottom left right fastening method standard rail mounting S7 rail mounting wall mounting housing can be lined up net weight  further information internet links internet link to web page: selection aid TIA Selection Tool to website: Industrial communication to website: CAx-Download-Manager additional information other information	L1, L2, L3, PE: push-in for 0.5 4 mm² +, -: push-in for 0.5 6 mm² 13, 14: push-in for 0.2 1.5 mm²  95 × 135 × 150 mm  95 × 225 mm  45 mm 45 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No Yes 1.66 kg  https://siemens.com/tst http://www.siemens.com/cax
at input at output for signaling contact  mechanical data  width × height × depth of the enclosure installation width × mounting height  required spacing top bottom left right fastening method standard rail mounting S7 rail mounting wall mounting housing can be lined up net weight  further information internet links internet link to web page: selection aid TIA Selection Tool to website: Industrial communication to website: CAx-Download-Manager additional information	L1, L2, L3, PE: push-in for 0.5 4 mm²  +, -: push-in for 0.5 6 mm²  13, 14: push-in for 0.2 1.5 mm²  95 × 135 × 150 mm  95 × 225 mm  45 mm  45 mm  0 mm  Snaps onto DIN rail EN 60715 35x7.5/15  Yes  No  No  Yes  1.66 kg  https://siemens.com/tst http://www.siemens.com/simatic-net http://www.siemens.com/cax  Specifications at rated input voltage and ambient temperature +25 °C (unless

threats, it is necessary to implement – and continuously maintain – a holistic, state-of-the-art industrial cybersecurity concept. Siemens' products and solutions constitute one element of such a concept. Customers are responsible for preventing unauthorized access to their plants, systems, machines and networks. Such systems, machines and components should only be connected to an enterprise network or the internet if and to the extent such a connection is necessary and only when appropriate security measures (e.g. firewalls and/or network segmentation) are in place. For additional information on industrial cybersecurity measures that may be implemented, please visit www.siemens.com/cybersecurity-industry. Siemens' products and solutions undergo continuous development to make them more secure. Siemens strongly recommends that product updates are applied as soon as they are available and that the latest product versions are used. Use of product versions that are no longer supported, and failure to apply the latest updates may increase customer's exposure to cyber threats. To stay informed about product updates, subscribe to the Siemens Industrial Cybersecurity RSS Feed under https://www.siemens.com/cert. (V4.7)

Classifications

Version	Classification
12	27-04-07-01
9.1	27-04-07-01
9	27-04-07-01
8	27-04-90-02
7.1	27-04-90-02
6	27-04-90-02
9	EC002540
8	EC002540
7	EC002540
4	4130
15	39-12-10-04
	12 9.1 9 8 7.1 6 9 8 7

Approvals Certificates

**General Product Approval** 

Environment



Manufacturer Declaration







Siemens EcoTech



last modified:

4/5/2024

## **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

Click to view similar products for DIN Rail Power Supplies category:

Click to view products by Siemens manufacturer:

Other Similar products are found below:

PS-3015 DVP01PU-S DVPPS01 PS-C24024 ADNB040-24-1PM-C SS14011524 PSW-12024 PSC-6024 S8T-BUS03 PS-S4024 PS-10024
PS-C12024 PS-C48024 PS-C480P24 PSC-2024 PSC-4048 PSC-15124 PSC-48148 TRIO-PS-2G/1AC/12DC/5/C2LP PSS18/24/0.75 PSDA120W12 NDR-7524 AMED75-48SJZ 787-1007 ISVR427043R1200 50995 50903 50997 EL50-D 18924-9989 50996 HDN-3024
ISEDR-120-24 1335699 1335698 SPE3103U SPM3051 P4305-USB SPE6053U DT30P5 SPM6053 POS DIN30W24 SPB-015-12 EL50-B
50905 DRB240-48-1 CFM50S360-SD POS DIN30W15 POS MDIN60W12 18924-9988