

# 150-2 AC Amp-Clamp Adapters

## Amp-Clamp Adapters

Amp-Clamp current probes, used with analog VOMS provide accurate measurements of high AC current found in power systems and related control circuitry.

The Amp-Clamp jaws are closed over a conductor in the circuit and the current load is indicated on the connected meter.

The 150-2 has six ranges (up to 300 ACA) and is available with banana and reverse banana plugs.



Specifications	
<b>AC Amp-Clamp Adapter</b>	
<b>Model</b>	150-2
<b>Ranges</b>	5A, 10A, 50A, 100A, 250A (on 2.5 VAC Meter Range), 6A, 12A, 30A, 60A, 120A, 300A (on 3 VAC Meter Range)
<b>Accuracy</b>	± 3% Full Scale

## PHYSICAL

Dimensions: 7.8" x 3" x 1.1"

Weight: 12 oz.

Max. Cable Dimension: 1.125" diameter

Max. Bus Bar Dimensions: 2.38" x 0.38"

Ordering Information	
Amp-Clamp	Catalog No.
150-2 AC Clamp, VOM Banana Plug	00541
150-2 AC Clamp, VOM Reverse Plug	00545
Cable, replacement, reverse banana (used with 00545)	00529
Cable, replacement, banana (used with 00541)	00533

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Frequency Counters](#) category:*

*Click to view products by [Simpson](#) manufacturer:*

Other Similar products are found below :

[3.060.200.383](#) [HK46.55.230VAC/50HZ + HK46DIN](#) [HK47.C.10-80VDC](#) [3.130.251.071.056](#) [3.220.401.075](#) [3.220.401.085](#) [3.223.401.075](#)  
[3.223.401.351](#) [3.242.201.075](#) [3.245.201.351](#) [TFG-3610E](#) [AX-DG105](#) [AX-DG2010AF](#) [3.100.200.383](#) [3.130.251.075.056](#) [BZ1224](#) [BZ220A](#)  
[3.220.401.351](#) [3.240.201.351](#) [3.241.201.351](#) [3.242.201.351](#) [3.245.201.075](#) [3.474.901.075](#) [3.474.911.373](#) [DDS-3X25](#) [0.170.000.075](#)  
[0.135.200.373](#) [TF960](#) [TFG-3620E](#) [0.170.000.351](#) [TGF4162](#) [TGF4242](#) [GFG-3015 + RS232](#) [HK30.G.48.24VAC/50HZ](#) [0.135.200.302](#) [1856D](#)  
[53210A/903](#) [BG4017-1248](#) [BW4018-23050](#) [BW4018-2450](#) [190.003](#) [BW4018-23060](#) [MFG-2230M](#) [AFG-2012](#) [AFG-2105](#) [AFG-2112](#) [AFG-](#)  
[2225](#) [TGF4042](#) [TGF4082](#) [UTG1010A](#)