

三菱J3/ES/JE 系列伺服电缆线 X300

三菱J3/ES/JEシリーズ用サーボケーブル
Servo cable for Mitsubishi J3/ES/JE series



非在庫品
Items in the library of non-

询问胜蓝
0755-8886 0059 当日出货


● 特点 Features

- * 电缆护套由低粘性高耐磨材料制成;
- * 具有高抗弯曲强度及高柔韧性;
- * 耐油和冷却剂, 耐划痕;
- * 适用于一般布线场所及拖链。
- * ケーブルのカバーは低粘り高耐摩耗材料でつくられます;
- * 高い曲げ強度と高柔軟性;
- * 耐油和冷却剂, 耐划痕, 冷却剂と並に強い, 耐きず;
- * 普通の配線場所およびローチェーンに適用。
- * Cable oversheath is made of low tack and high wear-resistance material;
- * With high flexural strength and high flexibility;
- * With oil and refrigerant resistance function, easy to leave scratch;
- * Applicable to general wiring situation and towing transmission places.

▲ 注意事项 Note

- 请参照下表, 选择伺服马达的规格;
- 请不要随意更改线束内部部品;
- Please refer to the table below to choose the wiring harness of the servo motor.
- Please don't change the wiring harness internal component of will.

● 订货范例 Order



注意: 全长默认长度为1000mm, 如需增加长度以1000mm递增。
Notice: The shortest length is 1000mm, such as increased to increase to 1000mm for increasing unit.

注意: 以上为标准型号。如需使用拖链线材, 请在型号后加“T”, 详情请咨询相关销售人员。

Notice: The above is standard cable model. If you want to use chain wire, please sign "T" after the model. Please contact sales for more details.

● 端口对应列表 Port corresponding list

| 型号 Model | 对应功率 Corresponding power | 驱动器 Drive | 对应马达(W) Corresponding motor | 原厂型号 Original model |
|---------------------|--------------------------|-----------------|---|---------------------|
| X300-1 X300-1T | 100~600W | J3, J4 E, JE | HF-MP HG-MR HF-KP HG-KR HF-KE HG-KN HF-KN (13/23/43) | MR-PWS1CBL0-A1-L |
| X300-1H X300-1HT | 750W | J3, J4 E, JE | HF-MP HG-KE HF-KR HG-KN HF-KP HG-KR HF-MR (73) | MR-PWS1CBL0-A1-L |
| X300-2/2T | 100~750W | J3, J4 E, JE | HF-MP HG-KN HF-KP HG-KR HF-KE HG-MR HF-KW HF-KN (13/23/43/73) | B-MR-J3ENCBL0-L |
| X300-3 | 600~1000W | J3, J4 E, JE | HF-SP (51/52/81/102) HG-SR (51/52/81/102) HF-SN (52/102) HF-SE2JWI-S100 HF-SE102JWI-10 | 插头: MR-PWCNS4 |
| X300-4H | 2000W | J3, J4 E, JE | HF-SP (152) HF-SN (152) HG-SR (152) HF-SE152JWI-S100 | 插头: MR-PWCNS5 |
| X300-5 | 2000~3000W | J3, J4 E, JE | HF-SP1(21/201/202/352) HF-SN(202/302) HG-SR(121/201/202/301/352) | 插头: MR-PWCNS5 |
| X300-5H | 5000W | J3, J4 | HF-SP(502) HG-SR(502) | |
| X300-6 | 600~5000W | J3, J4 JE | HF-SP (51/52/81/102/121/152 /201/202/352/502) HG-SR(51/52/81/102/121/152 /202/201/301/352) HF-SN (52/102/152/202/302) | MR-J3ENSCBL0-L |
| X300-7 | 750~2000W | E | HF-SE0JWI-S100 (52/102/152/302) HG-JR701M(4) HG-JR37K1M(4) HG-JR45K1M4HG JR5K1M4HG-JR601(4) HG-JR37K1(4) | / |
| X300-8 | 600~5000W | J3, J4 E, JE | HF-SP (51/52/102/121/152/201 /202/352/502) HF-SN (52/102/152/202) HG-SR (51/52/81/102/121/152/ 201/202/301) | 插头: MR-BKCNS1 |

● 外形图 Outline

| 型号 Model | 功能 Functions | 缆线规格 Cable specification | 外形图 Dimensions | 电路图 Wiring Diagram |
|---------------------|-------------------------------|--------------------------|----------------|--------------------|
| X300-1 X300-1T | 伺服动力线 Servo drive cable | AWG20 | | |
| X300-1H X300-1HT | 伺服动力线 Servo drive cable | AWG18 | | |
| X300-2 X300-2T | 伺服编码器线 Servo encoder cable | AWG24 | | |
| X300-3 | 伺服刹车线 Servo brake cable | AWG22 | | |
| X300-4 | 伺服动力线 Servo drive cable | AWG17 | | |
| X300-4H | 伺服动力线 Servo drive cable | AWG13 | | |
| X300-5 | 伺服动力线 Servo drive cable | AWG13 | | |
| X300-5H | 伺服动力线 Servo drive cable | AWG10 | | |
| X300-6 | 伺服编码器线 Servo encoder cable | AWG24 | | |
| X300-7 | 伺服编码器线 Servo encoder cable | AWG24 | | |
| X300-8 | 伺服刹车线 Servo brake cable | AWG17 | | |

电缆线
ケーブル
Cable
伺服电机
Servo Motor
电缆线系列
Cables Series

- 分类
- T 总线模块
 - T 端子台
 - Y 电气控制
 - X 连接电缆
 - D 照明
 - H 电气配件
 - P 开关电源
 - G 辅材配件
 - F 气动附件

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [siron manufacturer](#):

Other Similar products are found below :

[H410-1](#) [H410-2](#) [H410-3](#) [H420-4-3000](#) [H420-4T-3000](#) [H420-6-3000](#) [H420-6T-3000](#) [H420-8-3000](#) [H450-4F-3000/100](#) [H450-4TF-3000/100](#)
[H450-6F-3000/100](#) [H450-6TF-3000/100](#) [H450-8TF-3000/100](#) [T001](#) [T003-D](#) [T007](#) [T008](#) [T009](#) [T010](#) [T011](#) [T021-D](#) [T022](#) [T023](#) [T024](#) [T033](#)
[T034](#) [T041](#) [T042](#) [T043](#) [T044](#) [T055](#) [T056](#) [T057](#) [T058](#) [T063](#) [T064](#) [T066](#) [T068](#) [T070](#) [T071](#) [T072](#) [T072-10](#) [T072-20](#) [T075](#) [T075-2](#) [T076](#)
[T078](#) [T080](#) [T081-T](#) [T087](#)