



FABBRICA CAVI - ANTENNE - ACCESSORI TV

RG 213 U-ZH


50 OHM RF COAXIAL CABLE

MANUFACTURED IN COMPLIANCE WITH MIL-C-17F STANDARDS

COMPLIANCE IEC 60754-1 IEC 60754-2 IEC 61034-2

Class CPR **E_{ca}**

CU PE CU Pet LSZH
7 x 0,75 mm ø 7,25 mm ø 8,00 mm h. 27 mm ø 10,3 mm



A B C D E

MECHANICAL DATA

A	INNER CONDUCTOR	PLAIN COPPER	7 x 0,75 mm
B	DIELECTRIC	LOW DENSITY POLYETHYLENE	ø 7,25 ± 0,18 mm
C	BRAID	PLAIN COPPER	192 x 0,18 mm
		- COVERAGE	97%
D	NON-MIGRATING	POLYESTER TAPE	h. 27 mm
E	SHEATH	FLAME RETARDANT NON-CORROSIVE		ø 10,3 ± 0,18 mm
		THERMOPLASTIC FREE OF HALOGENS		
	- COLOUR	BLACK - RAL 9004		
	- PRINTING	M1774-RG213 MIL-C-17G RG 213 U-ZH 50 Ohm LSZH		
		MADE IN ITALY CE 56 WEEK/YEAR EN 50575:2014 + A1:2016 Eca		

MINIMUM BENDING RADIUS (mm)

- SINGLE	ø EXTERNAL X 5
- REPEATED	ø EXTERNAL X 10

TEMPERATURE RANGE

-40 °C / +80 °C

CABLE WEIGHT (Kg/Km)

- COPPER	77,4
- PLASTIC	87,8
- TOTAL	165,7

ELECTRICAL PROPERTIES at 20°C

IMPEDANCE 50 ± 2 Ohm

CAPACITANCE 100 pF/m

VELOCITY RATIO 66%

RESISTANCE

- INNER CONDUCT.	6 Ohm/Km
- BRAID	4,4 Ohm/Km

TENSION

- SHEATH	5,5 kV
- SPARK TESTING	

ATTENUATIONS dB/100 m.

		dB	W
5	MHz	1,2	
10	MHz	1,8	
50	MHz	4,3	
100	MHz	6,4	
200	MHz	9,5	
400	MHz	13,7	

MAX. POWER RATING W

		dB	W
500	MHz	15,3	
600	MHz	16,9	
800	MHz	20,4	
1000	MHz	23,2	
1350	MHz	28,4	
1500	MHz	30,4	

		dB	W
1750	MHz	33,7	
2150	MHz	38,9	
2250	MHz	39,7	
2500	MHz	42,7	
2750	MHz	45,7	
3000	MHz	48,9	

STRUCTURAL RETURN LOSS dB

30 ÷ 300	MHz	>31	1000 ÷ 2000	MHz	>24
300 ÷ 600	MHz	>28	2000 ÷ 3000	MHz	>22
600 ÷ 1000	MHz	>27 ÷	MHz	-

SCREENING EFFECTIVENESS dB

100 ÷ 900	MHz	>57
900 ÷ 2000	MHz	-
2000 ÷ 3000	MHz	-

The producer reserves himself to make modification on the item without any notice.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Coaxial Cables](#) category:

Click to view products by [Siva Cavi](#) manufacturer:

Other Similar products are found below :

[89880-003-1000](#) [7810SB-010-1000](#) [9116-010-U500](#) [9272-006-500](#) [1807A-B59-U1000](#) [2020K8421-9X-CS3417](#) [275604-000](#) [935240-000](#)
[9659-010-1000](#) [980704-001](#) [33312-010-500](#) [CZ1589-000](#) [5022W0809-0CS3263](#) [10610-4-4](#) [EF8108-000](#) [1673B TIN100](#) [672525-001](#)
[735A1-008-1000](#) [8212-010-U500](#) [8263 010U500](#) [TCC-75-2](#) [9248 010U1000](#) [1694A 0081000](#) [8241F J5C1000](#) [7805R 008100](#) [9271 0061000](#)
[5339Q5 009U500](#) [89207 010100](#) [1369R 004500](#) [7915R 0101000](#) [833101-000](#) [1152A-A8R-500](#) [9907-E4X-U1000](#) [3092A-X7E-500](#) [100066-](#)
[0049](#) [5021K1011-0](#) [ECJ5048-L](#) [4505R 0071000](#) [T-RAD-400-FR](#) [2410329-4](#) [L01030B0021](#) [60.7500-23](#) [51305](#) [BU-4150031024](#) [0026010](#)
[L01001C0003](#) [BU-4150030024](#) [BU-4150032048](#) [SMBM-SMBM17410](#) [50942](#)