



FABBRICA CAVI - ANTENNE - ACCESSORI TV

RG 58 CK

50 OHM RF COAXIAL CABLE

Class CPR **E_{ca}**

CS PE CS PVC2
19 x 0,18 mm ø 2,95 mm ø 3,35 mm ø 5,00 mm



A B C D

MECHANICAL DATA

A	INNER CONDUCTOR	TINNED COPPER	19 x 0,18 mm
B	DIELECTRIC	LOW DENSITY POLYETHYLENE	ø 2,95 ± 0,10 mm
C	BRAID	TINNED COPPER	96 x 0,10 mm
	- COVERAGE		75%
D	SHEATH	NON-CONTAMINATING POLYVINYL-CHLORIDE	ø 5,00 ± 0,10 mm
	- COLOUR	BLACK - RAL 9004	
	- PRINTING	M17/28-RG058 RG 58 CK 50 Ohm	
		MADE IN ITALY CE 56 WEEK/YEAR EN 50575:2014 + A1:2016 Eca	

MINIMUM BENDING RADIUS (mm)

- SINGLE ø EXTERNAL X 5
- REPEATED ø EXTERNAL X 10

TEMPERATURE RANGE -30 °C / +70 °C

CABLE WEIGHT (Kg/Km)

- COPPER 11,5
- PLASTIC 22,2
- TOTAL 33,7

ELECTRICAL PROPERTIES at 20°C

IMPEDANCE	50 ± 3 Ohm	RESISTANCE	
		- INNER CONDUCT.	36,5 Ohm/Km
CAPACITANCE	100 pF/m	- BRAID	25 Ohm/Km
VELOCITY RATIO	66%	TENSION	
		- SHEATH	4,0 kV
		SPARK TESTING	

ATTENUATIONS dB/100 m.

		dB	W
5	MHz	2,9	849
10	MHz	4,3	600
30	MHz	8,0	346
50	MHz	10,3	268
150	MHz	18,4	155
220	MHz	22,5	128

MAX. POWER RATING W

		dB	W
450	MHz	33,4	89
600	MHz	39,4	77
800	MHz	46,4	67
900	MHz	49,5	63
1000	MHz	53,1	60
1500	MHz	67,8	49

		dB	W
1800	MHz	75,5	44
2000	MHz	80,7	43
2500	MHz	97,9	38
3000	MHz	112,5	35
5200	MHz	177,3	26
5800	MHz	193,8	25

STRUCTURAL RETURN LOSS dB

30 ÷ 450 MHz	>27	2000 ÷ 3000 MHz	>18
450 ÷ 1000 MHz	>25	3000 ÷ 4000 MHz	>15
1000 ÷ 2000 MHz	>20	4000 ÷ 5800 MHz	>11

SCREENING EFFECTIVENESS dB

100 ÷ 900 MHz	>53
900 ÷ 2000 MHz	
2000 ÷ 3000 MHz	

The producer reserves himself to make modification on the item without any notice.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Coaxial Cables](#) category:

Click to view products by [Siva Cavi](#) manufacturer:

Other Similar products are found below :

[89880-003-1000](#) [7810SB-010-1000](#) [9116-010-U500](#) [1807A-B59-U1000](#) [2020K8421-9X-CS3417](#) [275604-000](#) [935240-000](#) [9659-010-1000](#)
[980704-001](#) [33312-010-500](#) [CZ1589-000](#) [5022W0809-0CS3263](#) [10610-4-4](#) [EF8108-000](#) [1673B TIN100](#) [672525-001](#) [735A1-008-1000](#)
[8212-010-U500](#) [8263 010U500](#) [TCC-75-2](#) [9248 010U1000](#) [1694A 0081000](#) [8241F J5C1000](#) [7805R 008100](#) [9271 0061000](#) [5339Q5 009U500](#)
[89207 010100](#) [1369R 004500](#) [7915R 0101000](#) [833101-000](#) [1152A-A8R-500](#) [9907-E4X-U1000](#) [3092A-X7E-500](#) [100066-0049](#) [5021K1011-](#)
[0 ECJ5048-L](#) [4505R 0071000](#) [T-RAD-400-FR](#) [2410329-4](#) [L01030B0021](#) [60.7500-23](#) [51305](#) [BU-4150031024](#) [0026010](#) [L01001C0003](#) [BU-](#)
[4150030024](#) [BU-4150032048](#) [SMBM-SMBM17410](#) [50942](#) [L01000B0001](#)