

DESCRIPTION

- With TO-3PN packaging
- Reliable performance at higher powers
- Accurate reproduction of Input signal
- Greater dynamic range
- Minimum Lot-to-Lot variations for robust device performance and reliable operation

APPLICATIONS



- Switching regulators
- High frequency inverters
- General purpose power amplifiers

ABSOLUTE MAXIMUM RATINGS($T_a=25^\circ\text{C}$)

SYMBOL	PARAMETER	VALUE	UNIT
V_{CBO}	Collector-Base Voltage	250	V
V_{CEO}	Collector-Emitter Voltage	250	V
V_{CEX}	Collector-Emitter Voltage $V_{EB}=5\text{V}$	250	V
V_{EBO}	Emitter-Base Voltage	5	V
I_C	Collector Current-Continuous	15	A
I_{CM}	Collector Current-Peak	30	A
I_B	Base Current-Continuous	1.6	A
P_T	Total Power Dissipation @ $T_C=25^\circ\text{C}$	200	W
T_J	Junction Temperature	150	$^\circ\text{C}$
T_{stg}	Storage Temperature Range	-65~150	$^\circ\text{C}$

THERMAL CHARACTERISTICS

SYMBOL	PARAMETER	MAX	UNIT
$R_{th\ j-c}$	Thermal Resistance, Junction to Case	0.63	$^\circ\text{C/W}$



Ordering Information

Product	Package	Packaging
NJW3281GT4TL	TO-3PN	Tube

ELECTRICAL CHARACTERISTICS

$T_C=25^\circ\text{C}$ unless otherwise specified

SYMBOL	PARAMETER	CONDITIONS	MIN	TYP.	MAX	UNIT
$V_{CEO(SUS)}$	Collector-Emitter Sustaining Voltage	$I_C= 100\text{mA}; I_B= 0$	250			V
$V_{CE(sat)}$	Collector-Emitter Saturation Voltage	$I_C= 8\text{A}; I_B= 0.8\text{A}$			0.6	V
$V_{BE(on)}$	Base-Emitter On Voltage	$I_C= 8\text{A}; V_{CE}= 5\text{V}$			1.5	V
I_{CBO}	Collector Cutoff Current	$V_{CB}= 250\text{V}$			50	mA
I_{CEO}	Collector Cutoff Current	$V_{CE}= 250\text{V}$			50	mA
I_{EBO}	Emitter Cutoff Current	$V_{EB}= 5\text{V}$			5	mA
h_{FE-1}	DC Current Gain	$I_C= 0.1\text{A}; V_{CE}= 5\text{V}$	75		150	
h_{FE-2}	DC Current Gain	$I_C= 1\text{A}; V_{CE}= 5\text{V}$	75		150	
h_{FE-3}	DC Current Gain	$I_C= 3\text{A}; V_{CE}= 5\text{V}$	75		150	
h_{FE-4}	DC Current Gain	$I_C= 5\text{A}; V_{CE}= 5\text{V}$	60			
h_{FE-5}	DC Current Gain	$I_C= 8\text{A}; V_{CE}= 5\text{V}$	45			

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Bipolar Transistors - BJT category](#):

Click to view products by [SPS manufacturer](#):

Other Similar products are found below :

[619691C](#) [MCH4017-TL-H](#) [MJ15024/WS](#) [MJ15025/WS](#) [BC546/116](#) [BC556/FSC](#) [BC557/116](#) [BSW67A](#) [HN7G01FU-A\(T5L,F,T](#)
[NJVMJD148T4G](#) [NSVMMBT6520LT1G](#) [NTE187A](#) [NTE195A](#) [NTE2302](#) [NTE2330](#) [NTE2353](#) [NTE316](#) [IMX9T110](#) [NTE63](#) [NTE65](#)
[C4460](#) [SBC846BLT3G](#) [2SA1419T-TD-H](#) [2SA1721-O\(TE85L,F\)](#) [2SA1727TLP](#) [2SA2126-E](#) [2SB1202T-TL-E](#) [2SB1204S-TL-E](#) [2SC5488A-](#)
[TL-H](#) [2SD2150T100R](#) [SP000011176](#) [FMC5AT148](#) [2N2369ADCSM](#) [2SB1202S-TL-E](#) [2SC2412KT146S](#) [2SC4618TLN](#) [2SC5490A-TL-H](#)
[2SD1816S-TL-E](#) [2SD1816T-TL-E](#) [CMXT2207 TR](#) [CPH6501-TL-E](#) [MCH4021-TL-E](#) [BC557B](#) [TTC012\(Q\)](#) [BULD128DT4](#) [JANTX2N3810](#)
[Jantx2N5416](#) [US6T6TR](#) [KSF350](#) [068071B](#)