

SPTECH Silicon NPN Power Transistor


BU931T

DESCRIPTION

- High Voltage
- DARLINGTON

APPLICATIONS


- High ruggedness electronic ignitions
- High voltage ignition coil driver

**ABSOLUTE MAXIMUM RATINGS ($T_a=25^\circ\text{C}$)**

SYMBOL	PARAMETER	VALUE	UNIT
V_{CBO}	Collector-Base Voltage	500	V
V_{CEO}	Collector-Emitter Voltage	400	V
V_{EBO}	Emitter-Base Voltage	5	V
I_c	Collector Current	10	A
I_{CM}	Collector Current-peak	15	A
I_B	Base Current	1	A
I_{BM}	Base Current-peak	5	A
P_c	Collector Power Dissipation @ $T_c=25^\circ\text{C}$	125	W
T_j	Junction Temperature	150	°C
T_{stg}	Storage Temperature Range	-65~150	°C

THERMAL CHARACTERISTICS

SYMBOL	PARAMETER	MAX	UNIT
$R_{th j-c}$	Thermal Resistance, Junction to Case	1.2	°C/W



SPTECH Product Specification

SPTECH Silicon NPN Power Transistor

BU931T

ELECTRICAL CHARACTERISTICS

T_c=25°C unless otherwise specified

SYMBOL	PARAMETER	CONDITIONS	MIN	TYP.	MAX	UNIT
V _{CEO(sus)}	Collector-Emitter Sustaining Voltage	I _C = 50mA; I _B = 0	400			V
V _{CE(sat)-1}	Collector-Emitter Saturation Voltage	I _C = 7A; I _B = 70mA			1.6	V
V _{CE(sat)-2}	Collector-Emitter Saturation Voltage	I _C = 8 A; I _B = 100mA			1.8	V
V _{BE(sat)-1}	Base-Emitter Saturation Voltage	I _C = 7A; I _B = 70mA			2.2	V
V _{BE(sat)-2}	Base-Emitter Saturation Voltage	I _C = 8 A; I _B = 100mA			2.4	V
I _{CES}	Collector Cutoff Current	V _{CE} = 500V; V _{BE} = 0 V _{CE} = 500V; V _{BE} = 0; T _j = 125°C			0.1 0.5	mA
I _{CEO}	Collector Cutoff Current	V _{CE} = 450V; I _B = 0 V _{CE} = 450V; I _B = 0; T _j = 125°C			0.1 0.5	mA
I _{EBO}	Emitter Cutoff Current	V _{EB} = 5V; I _C = 0			20	mA
h _{FE}	DC Current Gain	I _C = 5A ; V _{CE} = 10V	300			
V _{ECF}	C-E Diode Forward Voltage	I _F = 10A			2.5	V

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Bipolar Transistors - BJT category:

Click to view products by SPTECH manufacturer:

Other Similar products are found below :

[619691C](#) [MCH4017-TL-H](#) [MJ15024/WS](#) [MJ15025/WS](#) [BC546/116](#) [BC556/FSC](#) [BC557/116](#) [BSW67A](#) [HN7G01FU-A\(T5L,F,T\)](#)
[NJVMJD148T4G](#) [NSVMMBT6520LT1G](#) [NTE187A](#) [NTE195A](#) [NTE2302](#) [NTE2330](#) [NTE2353](#) [NTE316](#) [IMX9T110](#) [NTE63](#) [NTE65](#)
[C4460](#) [SBC846BLT3G](#) [2SA1419T-TD-H](#) [2SA1721-O\(TE85L,F\)](#) [2SA1727TLP](#) [2SA2126-E](#) [2SB1202T-TL-E](#) [2SB1204S-TL-E](#) [2SC5488A-TL-H](#)
[2SD2150T100R](#) [SP000011176](#) [FMC5AT148](#) [2N2369ADCSM](#) [2SB1202S-TL-E](#) [2SC2412KT146S](#) [2SC4618TLN](#) [2SC5490A-TL-H](#)
[2SD1816S-TL-E](#) [2SD1816T-TL-E](#) [CMXT2207 TR](#) [CPH6501-TL-E](#) [MCH4021-TL-E](#) [BC557B](#) [TTC012\(Q\)](#) [BULD128DT4](#) [JANTX2N3810](#)
[Jantx2N5416](#) [US6T6TR](#) [KSF350](#) [068071B](#)