


# SMD Power Inductor

## CD3015MB/DS



### Description

- Ferrite core construction
- Low profile resin-shielded
- LxWxH: 3.2x3.2x1.5mm Max.
- Product weight: 0.052g (Ref.)
- Moisture Sensitivity Level: 1



### Environmental Data

- Operating temperature range: -40°C~+105°C (including coil's self temperature rise)
- Storage temperature range: -40°C~+105°C


### Packaging

- Carrier tape and reel packaging
- 2000pcs per reel


### Applications

- DC/DC converter for CPU in notebook PC, smartphones, LCD displays, HDDs, DVDs, SSDs, DVCs, DSCs, PDAs etc.


### Dimension - [mm]



### Recommended Land pattern - [mm]



### Wire Connection



# SMD Power Inductor

## CD3015MB/DS



### Electrical Characteristics

Part Number	Inductance [Within] ( $\mu$ H) ※1	D.C.R. at 20°C Max.(Typ.) (m $\Omega$ )	Saturation Current (A) Max.(Typ.) ※2	Temperature Rise Current (A) Max.(Typ.) ※3
CD3015MBDS-1R0NC	1.00	41.00 (34.00)	2.50 (2.90)	(2.60)
CD3015MBDS-1R5NC	1.50	52.00 (43.00)	1.90 (2.30)	(2.30)
CD3015MBDS-2R2MC	2.20	72.00 (60.00)	1.80 (2.10)	(2.00)
CD3015MBDS-4R7MC	4.70	155 (129)	1.30 (1.50)	(1.40)
CD3015MBDS-6R8MC	6.80	228 (190)	1.10 (1.30)	(1.10)
CD3015MBDS-100MC	10.00	321 (267)	0.81 (0.95)	(0.90)
CD3015MBDS-220MC	22.00	678 (565)	0.52 (0.62)	(0.65)
CD3015MBDS-330MC	33.00	1097 (914)	0.44 (0.52)	(0.50)



※1 Measuring frequency inductance at 100kHz 1V.

※2 Saturation current: This indicates the value of D.C. current when the inductance becomes 30% lower than its initial value.

※3 Temperature rise current: The actual value of D.C. current when the temperature of coil becomes

$\Delta T=40^{\circ}\text{C}$  ( $T_a=25^{\circ}\text{C}$ ).

### Solder Reflow Condition




# SMD Power Inductor

## CD3015MB/DS




### Saturation Current & Temperature Rise Graph


1. CD3015MBDS-1R0NC




2. CD3015MBDS-1R5NC




3. CD3015MBDS-2R2MC




4. CD3015MBDS-4R7MC




5. CD3015MBDS-6R8MC




6. CD3015MBDS-100MC



7. CD3015MBDS-220MC



8. CD3015MBDS-330MC



# SMD Power Inductor

## CD3015MB/DS



Recommended Type



For sales office information, please [click here](#) to visit our website.

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Fixed Inductors](#) category:*

*Click to view products by [Sumida](#) manufacturer:*

Other Similar products are found below :

[CR32NP-100KC](#) [70F224AI](#) [MHQ1005P10NJ](#) [MHQ1005P1N0S](#) [MHQ1005P2N4S](#) [MHQ1005P3N6S](#) [MHQ1005P5N1S](#) [MHQ1005P8N2J](#)  
[PE-53601NL](#) [PE-53602NL](#) [PG0936.113NLT](#) [9220-20](#) [9310-16](#) [PM06-2N7](#) [PM06-39NJ](#) [A01TK](#) [1206CS-471XJ](#) [HC2-R47-R](#) [HC8-1R2-R](#)  
[HCF1305-3R3-R](#) [1206CS-151XG](#) [RCH664NP-4R7M](#) [RCP1317NP-391L](#) [DH2280-4R7M](#) [DS1608C-106](#) [B10TJ](#) [B82498B3101J000](#) [ELJ-](#)  
[RE27NJF2](#) [1812CS-153XJ](#) [1812CS-183XJ](#) [1812CS-223XJ](#) [1812LS-104XJ](#) [1812LS-105XJ](#) [1812LS-124XJ](#) [1812LS-154XJ](#) [1812LS-223XJ](#)  
[1812LS-224XJ](#) [1812LS-563XJ](#) [1812LS-683XJ](#) [1812LS-824XJ](#) [NIN-FB101JTR110F](#) [NIN-FB471JTR62F](#) [NIN-FC1R5JTR220F](#) [NIN-](#)  
[HCR15JTRF](#) [NIN-HCR33JTRF](#) [NIN-HDR22JTRF](#) [NIN-HDR82JTRF](#) [NIN-HK2N7STRF](#) [NIN-PA150KTR370F](#) [NIN-PB100KTR550F](#)