

# SMD Power Inductor CDRH60D45B/T150



Provisional

## Description


- Ferrite drum core construction
- Magnetically shielded
- Qualified AEC-Q200
- Operating Temperature: -55°C to +150°C (including self-heating)




## Applications

- LED Head light for Automobile
- ECU, DC/DC converter
- Automotive and other high temperature, high reliability application


## Dimension [mm]



## Reference Land pattern [mm]



## Connection



Note : This specification is subject to change without notice. Please contact your nearest sales office for updated information when placing an order.

# SMD Power Inductor

## CDRH60D45B/T150



Provisional

### Electrical Characteristics

Part No.	Inductance ( $\mu$ H) ※1	D.C.R (m $\Omega$ ) ( $\pm$ 30%)	Saturation Current (A) at 20°C TYP. ※2	Temperature Rise Current (A) TYP. ※3
CDRH60D45BT150NP -1R0NC	1.0 $\pm$ 30%	11.0	8.50	4.80
CDRH60D45BT150NP -1R5NC	1.5 $\pm$ 30%	13.0	7.20	4.50
CDRH60D45BT150NP -2R2NC	2.2 $\pm$ 30%	15.0	5.70	4.10
CDRH60D45BT150NP -3R3NC	3.3 $\pm$ 30%	18.0	5.00	3.70
CDRH60D45BT150NP -4R7NC	4.7 $\pm$ 30%	23.0	4.10	3.40
CDRH60D45BT150NP -6R8NC	6.8 $\pm$ 30%	27.0	3.60	3.10
CDRH60D45BT150NP -100MC	10 $\pm$ 20%	38.0	2.80	2.60
CDRH60D45BT150NP -150MC	15 $\pm$ 20%	64.0	2.30	2.00
CDRH60D45BT150NP -220MC	22 $\pm$ 20%	82.0	1.90	1.70
CDRH60D45BT150NP -330MC	33 $\pm$ 20%	105	1.56	1.60
CDRH60D45BT150NP -470MC	47 $\pm$ 20%	130	1.28	1.40
CDRH60D45BT150NP -680MC	68 $\pm$ 20%	210	1.07	1.10
CDRH60D45BT150NP -101MC	100 $\pm$ 20%	340	0.90	0.86
CDRH60D45BT150NP -151MC	150 $\pm$ 20%	480	0.74	0.72
CDRH60D45BT150NP -221MC	220 $\pm$ 20%	720	0.62	0.57
CDRH60D45BT150NP -331MC	330 $\pm$ 20%	970	0.50	0.49

※ Measuring frequency inductance at 100kHz,1V.

※ Saturation current: DC current which becomes inductance value drop by 30% from the nominal value.

※ Temperature rise current: The value of D.C. current when the temperature of coil becomes  $\Delta T=40^{\circ}\text{C}$  ( $T_a=20^{\circ}\text{C}$ ).

Please note that when using the product for automotive while applying current with audio-frequency (AF) signals may result in audible noises due to magnetostriction. Also, in order to avoid noise problem, operating with Non-AF signals would be recommended. The noise may amplify depending on the coil mount area on the PCB.

Note : This specification is subject to change without notice. Please contact your nearest sales office for updated information when placing an order.


# SMD Power Inductor CDRH60D45B/T150




Provisional

Saturation Current & Temperature Rise Graph — L (25°C) — L (150°C) —  $\Delta T$


CDRH60D45BT150NP-1R0NC




CDRH60D45BT150NP-1R5NC




CDRH60D45BT150NP-2R2NC




CDRH60D45BT150NP-3R3NC




CDRH60D45BT150NP-4R7NC




CDRH60D45BT150NP-6R8NC




CDRH60D45BT150NP-100MC



CDRH60D45BT150NP-150MC



CDRH60D45BT150NP-220MC



Note : This specification is subject to change without notice. Please contact your nearest sales office for updated information when placing an order.


# SMD Power Inductor CDRH60D45B/T150




Provisional

Saturation Current & Temperature Rise Graph — L (25°C) — L (150°C) —  $\Delta T$


CDRH60D45BT150NP-330MC




CDRH60D45BT150NP-470MC




CDRH60D45BT150NP-680MC




CDRH60D45BT150NP-101MC




CDRH60D45BT150NP-151MC



CDRH60D45BT150NP-221MC



CDRH60D45BT150NP-331MC



For sales office information, please [click here](#) to visit our website.

Note : This specification is subject to change without notice. Please contact your nearest sales office for updated information when placing an order.

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Fixed Inductors](#) category:*

*Click to view products by [Sumida](#) manufacturer:*

Other Similar products are found below :

[CR32NP-100KC](#) [CR32NP-151KC](#) [CR32NP-180KC](#) [CR32NP-181KC](#) [CR32NP-1R5MC](#) [CR32NP-390KC](#) [CR32NP-3R9MC](#) [CR32NP-680KC](#) [CR32NP-820KC](#) [CR32NP-8R2MC](#) [CR43NP-390KC](#) [CR43NP-560KC](#) [CR43NP-680KC](#) [CR54NP-181KC](#) [CR54NP-470LC](#) [CR54NP-820KC](#) [CR54NP-8R5MC](#) [70F224AI](#) [MGDQ4-00004-P](#) [MHL1ECTTP18NJ](#) [MHQ1005P10NJ](#) [MHQ1005P1N0S](#) [MHQ1005P2N4S](#) [MHQ1005P3N6S](#) [MHQ1005P5N1S](#) [MHQ1005P8N2J](#) [PE-51506NL](#) [PE-53601NL](#) [PE-53602NL](#) [PE-53630NL](#) [PE-53824SNLT](#) [PE-92100NL](#) [PG0434.801NLT](#) [PG0936.113NLT](#) [9220-20](#) [9310-16](#) [PM06-2N7](#) [PM06-39NJ](#) [A01TK](#) [1206CS-471XJ](#) [HC2LP-R47-R](#) [HC2-R47-R](#) [HC3-2R2-R](#) [HCF1305-3R3-R](#) [1206CS-151XG](#) [RCH664NP-140L](#) [RCH664NP-4R7M](#) [RCH8011NP-221L](#) [RCP1317NP-332L](#) [RCP1317NP-391L](#)