

# **SPECIFICATION**

#### **PATENT PENDING**

| Part No.     | : | WDP.2458.25.4.B.02                           |
|--------------|---|--|
| Product Name | : | Wi-Fi Dual-band 2.4/5 GHz                    |
|              |   | Embedded Ceramic Patch Antenna               |
|              |   | 6dBi+ at 2.4GHz                              |
|              |   | 6dBi+ on 5 to 6 GHz                          |
|              |   |  |
| Features     | : | 25mm*25mm*4mm                                |
|              |   | 2400MHz to 2500MHz/5150MHz to 5850Mhz        |
|              |   | Pin Type                                     |
|              |   | Supports IEEE 802.11 Dual-band Wi-Fi systems |
|              |   | Dual linear polarization                     |
|              |   | Tuned for 70x70mm ground plane               |

**RoHS** Compliant







## **1. Introduction**

This unique patent pending high gain, high efficiency embedded ceramic patch antenna is designed for professional Wi-Fi dual-band IEEE 802.11 applications. It is mounted via pin and double-sided adhesive. The passive patch offers stable high gain response from 4 dBi to 6dBi on the 2.4GHz band and from 5dBi to 8dBi on the 5 ~6 GHz band. Efficiency values are impressive also across the bands with on average 60%+.

The WDP.25's high gain, high efficiency performance is the perfect solution for directional dual-band WiFi application which need long range but which want to use small compact embedded antennas. The much higher gain and efficiency of the WDP.25 over smaller less efficient more omni-directional chip antennas (these typically have no more than 2dBi gain, 30% efficiencies) means it can deliver much longer range over a wide sector.

Typical applications are Access Points Tablets High definition high throughput video streaming routers High data MIMO bandwidth routers Automotive Home and industrial in-wall WiFi automation Drones/Quad-copters UAV Long range WiFi remote control applications

The WDP patch antenna has two distinct linear polarizations, on the 2.4 and 5GHz bands, increasing isolation between bands.

Custom tuned versions for different ground-planes and housing environments can be made subject to a minimum order quantity.

Contact your regional Taoglas office for support to integrate and test this antenna performance in your device.



# 2. Specification

| ELECTRICAL                      |                      |               |  |  |  |  |
|---------------------------------|----------------------|---------------|--|--|--|--|
| Frequency Range (MHz)           | 2400-2500            | 5150-5850     |  |  |  |  |
| Return Loss (dB)                | Min19, -2 at edge    | <-5           |  |  |  |  |
| Antenna Efficiency (%)          | Max. 80, 25+ at edge | 50+ in bands  |  |  |  |  |
| Antenna Peak Gain (dBi)         | 6                    | 8             |  |  |  |  |
| Antenna Polarization Linear     |                      |               |  |  |  |  |
| Impedance                       | 50 ohm               |               |  |  |  |  |
| Input Power                     | 10W                  |               |  |  |  |  |
| MECHANICAL                      |                      |               |  |  |  |  |
| Dimension (mm)                  | 25x25x4              |               |  |  |  |  |
| ENVIRONMENTAL RATINGS           |                      |               |  |  |  |  |
| Frequency Temp Coefficient (Tf) | 0±20ppm/°C           |               |  |  |  |  |
| Operating Temperature           | -40°C to +105°C      |               |  |  |  |  |
| Humidity                        | Non-condensing       | g 65°C 95% RH |  |  |  |  |

\*All tests done on a 70mm\*70mm ground plane.





## **3. Antenna Characteristics**



#### 3.1 Return Loss

#### 3.2 Peak Gain





### 3.4 Efficiency



#### 3.3 Average Gain

••

taoglas antenna solutions

;

•••



## **4. Antenna Radiation Patterns**

#### 4.1 Antenna setup

The antenna radiation pattern measurement setup as shown below,





### 4.2 Antenna radiation patterns













## **5. DRAWING**

### 5.1 Patch



|   | Name                               | P/N            | Materla | Finish | QTY |
|---|------------------------------------|----------------|---------|--------|-----|
| 1 | 25x25x4 2400~5850MHz Patch Antenna | 001514A020007A | Ceramic | N/A    | 1   |



### **5.2 Evaluation Board**



#### Notes

1. Soldermask:

|   | Name                                 | Material | Finish | QTY |
|---|--------------------------------------|----------|--------|-----|
| 1 | EMPCB SMA(F) ST                      | Brass    | Gold   | 1   |
| 2 | WDP.2458.25.4.B.02 Patch (25x25x4mm) | Ceramic  | Clear  | 1   |
| 3 | WDPD.2458.B EVB PCB (70x70x0.8mm)    | FR4 0.8t | Black  | 1   |



# 6. Packaging

### 6.1 Inner Tray

50 pieces per tray



Ο

0

ο

ο

ο

ο

Ο

ο

ο

0

0

ο



Ο

0

ο

П

Л

0

0

ο

0

0

0



### 6.2 Carton

4 Inside Boxes per Outer Carton -Outer Carton contains 800 pieces



### **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Antennas category:

Click to view products by Taoglas manufacturer:

Other Similar products are found below :

 GAN30084EU
 930-033-R
 GW17.07.0250E
 1513563-1
 EXE902SM
 APAMPG-117
 MAF94383
 W3908B0100
 W6102B0100
 YE572113 

 30RSMM
 108-00014-50
 66089-2406
 SPDA17RP918
 A09-F8NF-M
 A09-F5NF-M
 RGFRA1903041A1T
 W3593B0100
 W3921B0100

 SIMNA-868
 SIMNA-915
 SIMNA-433
 W1044
 W1049B090
 A75-001
 WTL2449CQ1-FRSMM
 CPL9C
 EXB148BN
 0600-00060

 TRA9020S3PBN-001
 Y4503
 GD5W-28P-NF
 MA9-7N
 GD53-25
 GD5W-21P-NF
 C37
 MAF94051
 MA9-5N
 EXD420PL
 B1322NR

 QWFTB120
 MAF94271
 MAF94300
 GPSMB301
 FG4403
 A0-AGSM-OM54
 5200232
 MIKROE-2349
 WCM.01.0111
 MIKROE-2393

 MIKROE-2352
 MIKROE-2352
 MIKROE-2352
 MIKROE-2349
 WCM.01.0111
 MIKROE-2393