

DEUTSCH* Field Service Crimp Tool

HDT-1561

Crimping Instructions

This ratcheting crimp tool is designed to crimp Deutsch solid pin and socket contacts as listed on **Chart A** below:

Chart A

Contact Size	Contact Type	Deutsch Part Number	Wire AWG Range	Crimp Nest	Recommended Strip Length
20	Pin	0460-202-20141	20	Front	.156"-.218"
20	Socket	0462-201-20141	20	Front	.156"-.218"
16	Pin	0460-202-16141	16-18	Middle	.250"-.312"
16	Socket	0462-201-16141	16-18	Middle	.250"-.312"
16	Pin	0460-215-16141	14	Middle	.250"-.312"
16	Socket	0462-209-16141	14	Middle	.250"-.312"
12	Pin	0460-204-12141	12-14	Rear	.222"-.284"
12	Socket	0462-203-12141	12-14	Rear	.222"-.284"

Illustration A



Assembly Instructions:

1. Cycle the tool to open position by completely closing handle grips.
2. Refer to **Chart A** to select the appropriate crimp nest.
3. Grasp crimp barrel end of contact (short end with bleed hole). Place contact through front of tool (**Illustration A**). Align contact shoulder with locating slot (**Illustration B**). Close tool slightly, holding contact in place.
4. Insert properly stripped wire (refer to **Chart A**) into the crimp barrel of contact. Hold wire in place while completely closing handle grips.
5. Remove crimped contact. Inspect for quality; a) copper strands should be visible in bleed hole of crimp and b) no copper strands should be loose outside the crimp barrel.

Illustration B (Locating Slot)




Chart B (Crimp Height/Width)

Nominal Cavity Sizes			
	20	16	12
H	.037 REF.	.054 REF.	.086 REF.
W	.072 REF.	.098 REF.	.154 REF.

Chart C (Current Ratings)

Size	Wire AWG Range	Maximum Current Rating	Crimp Tensile Strength
20	20	7.5 amps	20 lbs.
16	16-18	13 amps	25 lbs.
16	14	13 amps	25 lbs.
12	12-14	25 amps	70 lbs.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Crimpers / Crimping Tools](#) category:

Click to view products by [TE Connectivity](#) manufacturer:

Other Similar products are found below :

[010-0096](#) [CT150-2-D02](#) [CT150-6-RH07](#) [622-6441LF](#) [63484-3701](#) [63800-8355](#) [63819-1875](#) [63819-2875](#) [63819-4475](#) [63827-5375](#) [64005-0175](#) [662903-2](#) [690602-6](#) [7-23471-1](#) [734611-1](#) [762637-1](#) [811242-5](#) [91362-1](#) [1-21002-3](#) [1-21002-7](#) [12118040](#) [12085270](#) [12387119-6](#) [1-22548-4](#) [125442-1](#) [DCE.91.073.BVC](#) [DCE.91.090.3MVM](#) [DCE.91.162.BVCM](#) [DCE.91.202.BVCM](#) [1310G2](#) [1333249-1](#) [1-354003-0](#) [1338301-1](#) [DF62/RE-MD](#) [142321](#) [AP105-DF11-2428S\(64\)](#) [1456088-1](#) [1-45804-6](#) [15397700](#) [AX100749](#) [1-59619-7](#) [1596970-1](#) [1-59619-8](#) [1901238-2](#) [2119581-1](#) [K761](#) [KTH-1079](#) [KTH-2022](#) [KTH-2260](#) [904139-1](#)