



RECOMMENDED HOLE LAYOUT

- 1 ASSEMBLY MAY BE BROKEN TO THE DESIRED NUMBER OF POSITIONS.
- 2 TRUE POSITION TOLERANCE OF THE POST TIPS APPLIES WHEN THE HEADERS ARE HELD FLAT AGAINST THE PRINTED CIRCUIT BOARD
- 3 .000100-.000200 MATTE TIN-LEAD OVER .000050 NICKEL ENTIRE POST
- 4 BREAKAWAY NOTCH ANGLE CAN BE ORIENTED TO THE RIGHT (AS SHOWN) OR TO THE LEFT
- 5 .000100-.000200 MATTE TIN OVER .000050 NICKEL ENTIRE POST
- 6 OBSOLETE PARTS: OBSOLETE CIS STREAMLINING PER D.RENAUD/D.SINISI

	5	3.984	3.900	39	40	9-103759-0
	5	3.484	3.400	34	35	8-0
	5	2.984	2.900	29	30	8-0
	5	2.484	2.400	24	25	7-5
	5	1.984	1.900	19	20	7-0
	5	1.484	1.400	14	15	6-5
	5	1.384	1.300	13	14	6-4
	5	1.284	1.200	12	13	6-3
	5	1.184	1.100	11	12	6-2
	5	1.084	1.000	10	11	6-1
	5	.984	.900	9	10	6-0
	5	.884	.800	8	9	5-9
	5	.784	.700	7	8	5-8
	5	.684	.600	6	7	5-7
	5	.584	.500	5	6	5-6
	5	.484	.400	4	5	5-5
	5	.384	.300	3	4	5-4
	5	.284	.200	2	3	5-3
	5	.184	.100	1	2	5-2
	5	.084			1	5-103759-1
	3	3.984	3.900	39	40	4-103759-0
	3	3.884	3.800	38	39	3-9
	3	3.784	3.700	37	38	3-8
	3	3.684	3.600	36	37	3-7
	3	3.584	3.500	35	36	3-6
	3	3.484	3.400	34	35	3-5
	3	3.284	3.300	33	34	3-4
	3	3.284	3.200	32	33	3-3
	3	3.184	3.100	31	32	3-2
	3	3.084	3.000	30	31	3-1
	3	2.984	2.900	29	30	3-0
	3	2.884	2.800	28	29	2-9
	3	2.784	2.700	27	28	2-8
	3	2.684	2.600	26	27	2-7
	3	2.584	2.500	25	26	2-6
	3	2.484	2.400	24	25	2-5
	3	2.384	2.300	23	24	2-4
	3	2.284	2.200	22	23	2-3
	3	2.184	2.100	21	22	2-2
	3	2.084	2.000	20	21	2-1
	3	1.984	1.900	19	20	2-0
	3	1.884	1.800	18	19	1-9
	3	1.784	1.700	17	18	1-8
	3	1.684	1.600	16	17	1-7
	3	1.584	1.500	15	16	1-6
	3	1.484	1.400	14	15	1-5
	3	1.384	1.300	13	14	1-4
	3	1.284	1.200	12	13	1-3
	3	1.184	1.100	11	12	1-2
	3	1.084	1.000	10	11	1-1
	3	.984	.900	9	10	1-0
	3	.884	.800	8	9	0-9
	3	.784	.700	7	8	0-8
	3	.684	.600	6	7	0-7
	3	.584	.500	5	6	0-6
	3	.484	.400	4	5	0-5
	3	.384	.300	3	4	0-4
	3	.284	.200	2	3	0-3
	3	.184	.100	1	2	0-2
	3	.084			1	0-103759-1

PLATING	C	B	A	NO OF POS	ASSEMBLY PART NUMBER
---------	---	---	---	-----------	----------------------

THIS DRAWING IS A CONTROLLED DOCUMENT.

DIN L. D. RINGLEY 23JUL85
CHK R. FLICKER 12NOV87
APVD R. FLICKER 12NOV87

TE Connectivity

ASSEMBLY, MOD II, HEADER, BREAKAWAY, SINGLE ROW, RIGHT ANGLE 100CL, WITH .025 SQUARE POSTS

SIZE A1 00779 C=103759

SCALE 4:1 SHEET 1 OF 1 REV H

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Headers & Wire Housings](#) category:

Click to view products by [TE Connectivity](#) manufacturer:

Other Similar products are found below :

[892-18-020-10-001101](#) [58102-G61-06LF](#) [582553-1](#) [0009485154](#) [009176003701906](#) [0050291907](#) [LY20-4P-DT1-P1E-BR](#) [02.125.8002.8](#)
[609-3404](#) [61062-3](#) [61082-181009](#) [622-3653LF](#) [63453-116](#) [636-1030](#) [636-1427](#) [636-3427](#) [636-4007](#) [641938-9](#) [641991-4](#) [644827-2](#) [65817-](#)
[010LF](#) [65817-015LF](#) [65863-015LF](#) [66207-023LF](#) [67095-007LF](#) [67601157](#) [68645-018](#) [68648-049](#) [70.362.1628.0](#) [70-4210](#) [70-4226B](#) [70-](#)
[4853B](#) [707-5020](#) [707-5028](#) [71.350.2428.0](#) [71918-208LF](#) [71961-016LF](#) [733-134](#) [733-162](#) [754199-000](#) [760-3052](#) [79531-3000](#) [FCN-](#)
[360C032-B](#) [FCN-367T-T012/H](#) [FCN-723D010/2](#) [80.063.4001.1](#) [800-90-010-10-002000](#) [801-43-002-10-013000](#) [801-43-006-10-002000](#)
[801-93-011-10-001000](#)