



CM57 & CM55 Flexible Clamp Meters

# FLIR CM55/57

## Flexible Clamp Meters

The FLIR Flexible Clamp Meters with Bluetooth® are ergonomic tools designed to simplify difficult current measurements. Made with a narrow flexible coil clamp, the CM55 and CM57 let you easily take measurements in tight or awkward spots—a difficult task with a traditional hard jaw clamp meter. With Bluetooth communication for remote viewing and data transfer to iOS® and Android™ devices via the FLIR Tools Mobile App, you can analyze and share data fast right from the jobsite.

### TAKE ACCURATE MEASUREMENTS IN TIGHT OR AWKWARD SPOTS.

*Tricky conductors conquered*

- Snake the coil around obstacles with ease, even in deep, crowded cabinets
- True RMS AC Current up to 3,000 Amps for multiple conductor measurements
- Inrush current function for equipment start-up spikes

### EASY INSPECTION AND NAVIGATION.

*Designed with your convenience in mind*

- Standalone flexible clamp meter displays the readings you need
- Bright, dual LED worklights provide built-in illumination for dark cabinets
- Drop tested to 3 meters, portable, lightweight, and tangle-free without compromising measurement range

### REMOTE VIEWING FROM A SAFE DISTANCE.

*Transfer & view data on mobile devices with FLIR Tools Mobile App*

- Connect to iOS and Android smartphones or tablets
- Multiple units wirelessly connect for remote viewing of multiphase systems
- Data recording for trend analysis transferable via Bluetooth

### CHOOSE FROM TWO FLEXIBLE COIL LENGTHS:

- **CM55 - 10"** (25.4cm) for easy maneuverability and compact convenience
- **CM57 - 18"** (45.72 cm) for larger and multiple conductor measurements, double-wrap requirements, and deeper access



FLIR CM57's Flexible Cable works into tight areas



Bluetooth capability gives readings at safe distances

## Specifications

Flexible Clamp Meters	CM55	CM57
Maximum AC current	3000A	
AC response	True RMS	
AC current ranges and resolution	30.00A, 300.0A, 3000A	
Basic AC current accuracy (of reading)	± 3.0% + 5 digits	
Maximum resolution	0.01A	
AC current bandwidth	45Hz – 500Hz (sine wave)	
Inrush current	Min 0.5A, 100mS	
Data record mode	20,000 points , 1 min sample rate	
Positional error (distance from optimum)	0.6" (15mm) ± 2.0% 1.0" (25mm) ± 2.5% 1.4" (35mm) ± 3.0%	1.4" (35mm) ± 1.0% 2.0" (50mm) ± 1.5% 2.4" (60mm) ± 2.0%
Meter Data		
Display	3000 count LCD with backlight and multi-function indicators	
Max conductor diameter	2.4" (6cm)	4.7" (12cm)
Flex coil length	10" (25cm)	18" (45cm)
Flex coil diameter	0.3" (7.5mm)	
Flex coil tip diameter	0.5" (13mm)	
Worklight	Two white LEDs	
Bluetooth range max	32' (10m)	
Wireless ID# max	Up to 20	
Power supply	(2) 1.5V "AAA"	
Drop test	9.8' (3m)	
Agency approvals	FCC Class B, CE, UL	
Safety rating	CAT IV 600V, CAT III 1000V	
Standards	EN61010-1, EN61010-2-032, EN61326-1	
Warranty	Limited lifetime with registration*	

\* Register within 60 days of purchase at [www.flir.com/testwarranty](http://www.flir.com/testwarranty)

Ordering Information	CM55	CM57
UPC	793950370551	793950370575
EAN	0793950370551	0793950370575



**PORTLAND**  
Corporate Headquarters  
FLIR Systems, Inc.  
27700 SW Parkway Ave.  
Wilsonville, OR 97070  
USA  
PH: +1 866.477.3687

**NASHUA**  
FLIR Systems, Inc.  
9 Townsend West  
Nashua, NH 03063  
USA  
PH: +1 866.477.3687

**EUROPE**  
FLIR Systems  
Luxemburgstraat 2  
2321 Meer  
Belgium  
PH: +32 (0) 3665 5100

**SWEDEN**  
FLIR Systems, AB  
Täby, Sweden  
PH: +68.8.753.2500

[www.flir.com](http://www.flir.com)  
NASDAQ: FLIR

Equipment described herein may require US Government authorization for export purposes. Diversion contrary to US law is prohibited. Imagery for illustration purposes only. Specifications are subject to change without notice. ©2015 FLIR Systems, Inc. All rights reserved. [Updated 11/17/15]

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Clamp Multimeters & Accessories](#) category:*

*Click to view products by [Teledyne FLIR / Extech](#) manufacturer:*

Other Similar products are found below :

[I800](#) [MT-8006B](#) [3PK-NT023N](#) [MT-7057N](#) [TESTO 770-3 0590 7703](#) [AX-3550](#) [AX-M266C](#) [BM079](#) [BM089](#) [BM162](#) [BM197](#) [KEW2210R](#)  
[FLUKE 80I-110S](#) [FLUKE A3002FC](#) [FLUKE I200](#) [FLUKE I310S](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [ACDC-100](#) [MA440](#) [MA443](#)  
[MA445](#) [FLUKE-374 FC](#) [FLUKE-1630-2FC](#) [CM42](#) [FLUKE-376 FC](#) [A193 \(800 MM\)](#) [F201](#) [F205](#) [F65](#) [DIGIFLEX 4000A 350MM](#)  
[DIGIFLEX 400A 170MM](#) [DIGIFLEX 400A 250MM](#) [MN93A](#) [FLUKE I6000SFLEX-24](#) [KEW2010](#) [P1670](#) [FLK-A3004FC](#) [AMP-330-EUR](#)  
[APPA SFLEX-18D](#) [UT200A](#) [UT201](#) [UT205](#) [UT205A](#) [UT206](#) [UT206A](#) [UT210A](#) [UT210B](#) [UT213A](#)