



TRIPLE ALARM CAT IV NON-CONTACT VOLTAGE DETECTOR WITH FLASHLIGHT

FLIR VP52-2™



The FLIR VP52-2 is a durable, CAT IV-rated non-contact voltage detector featuring light, vibration, and beeper feedback alarms and a powerful LED flashlight. Use the VP52-2 to reliably check whether an AC circuit is live before beginning work; detect voltage on exposed conducting parts or through insulation; identify live wires within switchboxes, switches, and outlets; or trace live wires and map circuits. With an ergonomic and drop-tested design, the FLIR VP52-2 is the right choice for professionals performing field troubleshooting and verification of electrical installations within residential, commercial, and industrial buildings.

www.flir.com/vp52-2



RUGGED AND RELIABLE

Designed for long-term, trouble-free operation, the FLIR VP52-2 will last for years to come

- Detect voltage in electrical systems in both large industrial facilities and residential low-voltage installations
- Reliably test for voltage in the latest safety outlets
- Never miss voltage presence with tactile vibration, sound, and LED alarms—even in dark or noisy areas
- Durable to withstand a 3 m (9.8 ft) drop



EASY TO USE

Offers an ergonomic design that's easy to grip and operate

- Avoid touching live wires with non-contact voltage (NCV) technology
- Reduce risk of dropping the VP52-2 with double molded slip-resistant grip and anti-roll case
- Place the sensor closer to electrical sources with the low-profile probe tip



TROUBLESHOOT QUICKLY

Provides high-end features that improve work efficiency

- See target area clearly in poor lighting conditions with the bright flashlight and tip light
- Eliminate interruption from a dead battery with the low-battery indication feature
- Maximize battery life with the auto power off feature

SPECIFICATIONS

Measurement	
AC Voltage Range (default, solid green light)	190 to 1000 V AC
High-Sensitivity Mode (solid amber light)	24 to 1000 V AC
Frequency Range	45 to 65 Hz
Meter Data	
Sound Alert	Yes
Flashing LED Alert	Yes
Vibration Alert	Yes
Flashlight	Yes
Tip Light	Yes
Category Rating	CAT IV 1000 V
General Information	
Warranty	Limited 3-year
Certifications	CE, RCM
Power System	
Power Requirements	2 × AAA (LR03) alkaline batteries
Battery Life	~5 hours continuous (flashlight off)
Low Battery Voltage	Status LED flashes amber color
Auto Power Off	After 3 minutes of inactivity
Environmental Data	
Drop Test	3 m (9.8 ft)
Operating Ambient Temperatures	-10 to 50°C (14 to 122°F)
Storage Temperature	-20 to 60°C (-4 to 140°F)
Physical Data	
Weight	59 g (2.1 oz) including batteries
Dimensions (L × W × H)	158.5 × 26 × 29 mm (6.24 × 1.02 × 1.14 in)

Specifications are subject to change without notice. For the most up-to-date specs, go to www.flir.com

CORPORATE HEADQUARTERS

FLIR Systems, Inc.
27700 SW Parkway Ave.
Wilsonville, OR 97070
USA
PH: +1 866.477.3687

EUROPE

FLIR Commercial Systems
Luxemburgstraat 2
2321 Meer
Belgium
Tel. : +32 (0) 3665 5100
Fax : +32 (0) 3303 5624
E-mail : flir@flir.com

LATIN AMERICA

FLIR Systems Brasil
Av. Antonio Bardella, 320
Sorocaba, SP 18085-852
Brasil
PH: +55 15 3238 8070

www.flir.com
NASDAQ: FLIR

Equipment described herein is subject to US export regulations and may require a license prior to export. Diversion contrary to US law is prohibited. Imagery for illustration purposes only. Specifications are subject to change without notice. ©2020 FLIR Systems, Inc. All rights reserved. 03/20

20-0289-INS-EMEA-A4



The World's Sixth Sense®

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Component Testers](#) category:

Click to view products by [Teledyne FLIR / Extech](#) manufacturer:

Other Similar products are found below :

[FLUKE 9062](#) [BK894](#) [BK895](#) [BK880](#) [2840](#) [2841](#) [BK2840](#) [BK2841](#) [NCVT-4IR](#) [BK830C](#) [LCR55A](#) [ET30B](#) [ET40B](#) [VS-AVT-C08-L10](#)
[ET26B](#) [ET25](#) [ET60](#) [ET28B](#) [ET20B](#) [C.A 6608](#) [C.A 6609](#) [72-13540](#) [815](#) [FLUKE-9040EUR](#) [881](#) [891](#) [575](#) [880](#) [890C](#) [AK57X](#) [BC885](#) [IT-](#)
[E151](#) [35121](#) [770734](#) [410-413](#) [ET15](#) [DV20](#) [ET10](#) [ET30A](#) [LCR200](#) [LCR203](#) [PRT200](#) [FLK2AC/90-1000V](#) [FLK2AC/90-1000V5PK](#) [VT-](#)
[1100](#) [E4980AL/032/N1970A-900/E4980AL-PLG](#) [69127](#) [NCVT2P](#) [NCVT3P](#) [RT310](#)