

PM-100 POCKET MULTIMETER

TESTING | TROUBLESHOOTING | ACCURACY

Product Features:

Small and perfectly formed with all the basic measurement features you're likely to need, including fully automatic operation by default: the Pocket Multimeter (PM-100) from Tempo Communications is a great addition to any toolbox.

Carry it everywhere.

Truly pocket sized, yet immensely useful and built to international safety standards, the PM-100 will easily become your go-to tool for quickly checking electrical supplies and basic continuity.

Supplied in a convenient zipper case, the only control on this Pocket Multimeter is a single push button that switches the unit on and off, and cycles through the various tests:

1. Powers up in "automatic mode"
 - AC voltage
 - DC voltage
 - Resistance
2. Manual selection of each function
 - Continuity
 - Electric Field (EF) (voltage detector)
 - Volts AC
 - Volts DC
3. 6000 Count large digit LCD
 - Resistance
 - Frequency
 - Capacitance



1390 Aspen Way Vista, CA • 92081 TC-PM-100 06/20

Latin America Phone : 1.760.510.0558 | EMEA Phone: +44 (0) 1633 927050

©2019 Tempo Communications Inc. • An ISO 9001 Company

EMEA Address: Tempo Communications Limited • Brecon House,
William Brown Close, Cwmbran • NP44 3AB, UK

TempoCom.com | tel 800.642.2155 | sales@tempocom.com

 **TEMPO**
COMMUNICATIONS

Renewed Vision. Innovation Forward.



Follow us on Social Media
@TempoComms

PM-100 POCKET MULTIMETER

SPECIFICATIONS:

Display:	6000-count LCD
Polarity:	Automatic
Display Update Rate:	5 per second
Temperature Coefficient:	Nominal 0.15 x (specified accuracy) per °C below 18 °C or above 28 °C
Intelligent Automatic Power Off:	After 3 minutes of inactivity (approximately)
Noise Rejection:*	Common Mode Rejection Ratio: > 60 dB from 0 Hz to 60 Hz when measuring ACV
	Common Mode Rejection Ratio: > 100 dB at 0 Hz, 50 Hz, and 60 Hz when measuring DCV
	Normal Mode Rejection Ratio: > 30 dB at 50 Hz and 60 Hz when measuring DCV
Operating Conditions:	Temperature: 0 °C to 40 °C (32 °F to 104 °F)
Relative Humidity (non-condensing):	80% maximum for temperatures up to 31 °C (88 °F), decreasing linearly to 50% maximum at 40 °C (104 °F)
Altitude:	2000 m (6500') maximum
Pollution Degree:	2
Storage Conditions:	-20 °C to 60 °C (-4 °F to 140 °F), 0% to 80% relative humidity (non-condensing)
Battery:	3 V standard button battery (IEC-CR2032; ANSI-NEDA-54004LC)
Low Battery:	Below 2.4 VDC
Overvoltage Protection:	450 VDC/VAC RMS, 50/60 Hz
Measurement Categories:	Cat II, 450 V
	Cat III, 300 V

* Noise rejection is the ability to reject unwanted signals, or noise.

- Normal mode voltages are AC signals that can cause inaccurate DC measurements. NMRR (Normal Mode Rejection Ratio) is a measure of the ability to filter out these signals.
- Common mode voltages are signals present at the COM and + input terminals, with respect to ground, that can cause digit rattle or offset in voltage measurements. CMRR (Common Mode Rejection Ratio) is a measure of the ability to filter out these signals.

ACCURACY:

FREQUENCY

Range	Accuracy	Specified at
10.00 Hz to 30.00 kHz	± (0.5% + 4d)	less than 20 V sine RMS

DCV

Range	Accuracy
6.000 V	± (0.5% + 0.003 V)
60.00 V	± (1.0% + 0.05 V)
450.0 V	± (1.2% + 0.5 V)

RESISTANCE (AUTO V-Ω MODE)

Range	Accuracy
6.000 kΩ	± (1.2% + 0.006 kΩ)*
60.00 kΩ	± (1.0% + 0.04 kΩ)
600.0 kΩ	± (1.0% + 0.4 kΩ)
6.000 MΩ	± (2.0% + 0.004 MΩ)

CAPACITANCE

Range	Accuracy
100.0 nF	± (3.5% + 0.6 nF)
1000 nF	± (3.5% + 6 nF)
10.00 μF	± (3.5% + 0.06 μF)
100.0 μF	± (3.5% + 0.6 μF)

ACV

Range (50 to 60 Hz)	Accuracy
6.000 V	± (1.5% + 0.005 V)
60.00 V	± (1.5% + 0.05 V)
450.0 V	± (1.5% + 0.5 V)

WIRELESS ELECTRIC FIELD DETECTION (EF)

Typical Voltage	Bar graph indication
15 V to 55 V	-
30 V to 85 V	--
45 V to 145 V	---
75 V to 190 V	----
above 105 V	-----

1390 Aspen Way Vista, CA • 92081 TC-PM-100 06/20

Latin America Phone : 1.760.510.0558 | EMEA Phone: +44 (0) 1633 927050

©2019 Tempo Communications Inc. • An ISO 9001 Company

EMEA Address: Tempo Communications Limited • Brecon House,
William Brown Close, Cwmbran • NP44 3AB, UK

TempoCom.com | tel 800.642.2155 | sales@tempocom.com



TEMPO
COMMUNICATIONS

Renewed Vision. Innovation Forward.



Follow us on Social Media
@TempoComms

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Digital Multimeters](#) category:

Click to view products by [Tempo Semiconductor](#) manufacturer:

Other Similar products are found below :

[FS881](#) [40705X](#) [P 8100](#) [FLUKE 117/323 KIT](#) [IBT6K](#) [30XR](#) [34XR](#) [35XP](#) [TESTO 745](#) [0590 7450](#) [TESTO 760-2](#) [0590 7602](#) [TESTO 760-3](#)
[0590 7603](#) [440012](#) [AX-155](#) [AX-174](#) [AX-178](#) [AX-18B](#) [AX-190A](#) [AX-503](#) [AX-507B](#) [AX-594](#) [AX-LCR42A](#) [AX-MS8221A](#) [AX-MS8250](#)
[AX-PDM01](#) [AX-T520](#) [AX-T901](#) [AX-T903](#) [BAT-250-EUR](#) [BM525S](#) [BM805S](#) [BM807S](#) [BM817S](#) [BM827S](#) [BM829S](#) [BM857S](#) [BM859S](#)
[BM867S](#) [33XR](#) [UNITEST TESTFIX 9023](#) [37XR](#) [UT58C](#) [UT71A](#) [UT71E](#) [KIT BRUA-19X](#) [38XR](#) [77-4/EUR](#) [VP-450-E](#) [LCR55](#) [DM78A](#)
[05005655001](#)