

CST306K

Description:

This kit contains representative samples of our high frequency current sense transformers. They are useful for a variety of developmental needs including circuit simulation, circuit testing, prototyping and agency evaluations. All items in this kit meet specifications listed in the catalog section referring to the product. This kit is housed in an easy to see, easy to store clear polycarbonate box with a convenient snap closing hinged lid.



Electrical Specifications (@25C):

Part No.	ET V μ Sec REF 20kHz	Turns Count	Min. Ind. mH	DCR Max. Ω	Pri. Amps
CST306-1A	500	50	3.5	.340	35.0 RMS
CST306-1T	500	50 CT	3.5	.340	35.0 RMS
CST306-2A	1000	100	14.0	1.55	25.0 RMS
CST306-2T	1000	100 CT	14.0	1.55	25.0 RMS
CST306-3A	2000	200	55.0	3.75	25.0 RMS
CST306-3T	2000	200 CT	55.0	3.75	25.0 RMS

Dimensions:

Height = 2.0"

Width = 3.75"


Length = 2.5"

Weight = 0.25 Lbs.

For more detailed specifications on individual parts, click on the part number or visit us at www.TriadMagnetics.com

RoHS Compliance: As of manufacturing date February 2005, all standard products meet the requirements of 2002/95/EC, known as the RoHS initiative.

* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Current Transformers](#) category:

Click to view products by [Triad](#) manufacturer:

Other Similar products are found below :

[MP3500](#) [BV UI 302 0156](#) [45029](#) [BV EI 302 2863](#) [BV EI 303 2809](#) [BV EI 303 3060](#) [BV EI 306 3604](#) [BV EI 422 1302](#) [BV EI 481 1295](#) [BV EI 481 1324](#) [BV EI 481 1325](#) [BV UI 301 0133](#) [BV UI 302 0144](#) [BV UI 304 0019](#) [BV UI 304 0129](#) [BV UI 304 0173](#) [TI-EF16-2X4V-4W](#)
[SPCT62/40150/5AVA3CL1](#) [SPCT62/30100/5AVA1CL1](#) [SPCT62/3075/5AVA1CL3](#) [SPCT62/40150/5AVA1.5CL1](#)
[SPCT62/40200/5AVA2.5CL0.5](#) [SPCT62/40300/5AVA3CL0.5](#) [CTD-KIT](#) [44013](#) [44017](#) [44021](#) [44024](#) [44098](#) [44101](#) [44134](#) [44140](#) [44171](#)
[44174](#) [44176](#) [44178](#) [44180](#) [44248](#) [44250](#) [44251](#) [44278](#) [44339](#) [44340](#) [44373](#) [44375](#) [44376](#) [44378](#) [44379](#) [44436](#) [44678](#)