

TURCK

Network Media Products

DeviceNet™, Terminating Resistors

- Terminating Resistors Stabilize and Minimize Reflections on the Bus Line
- A Terminating Resistor is Required at the Beginning and End of the Main Bus Line



Housing	Part Number	Specs	Application	Pinouts
	RSM 57-TR2	Nickel Plated Brass or Stainless Steel 300 VDC -40° to +80°C IP 67	minifast ® Terminating Resistor <ul style="list-style-type: none"> • Male minifast connector • 120 Ohms, 1/2 W internal resistance 	Male
	RSM 57-TR2/VM	Nickel Plated Brass or Stainless Steel 250 VAC/300 VDC -40° to +80°C IP 67	minifast Terminating Resistor with Voltage Monitoring <ul style="list-style-type: none"> • Male minifast connector • Led indication: Red - reverse polarity Green-okay • 120 Ohms, 1/2 W internal resistance 	Male
	RKM 57-TR2	Nickel Plated Brass or Stainless Steel 300 VDC -40° to +80°C IP 67	minifast Terminating Resistor <ul style="list-style-type: none"> • Female minifast connector • 120 Ohms, 1/2 W internal resistance 	Female
	RSE 57-TR2	Nickel Plated CuZn or Stainless Steel 10-30 VDC -40° to +80°C IP 68	eurofast ® Terminating Resistor <ul style="list-style-type: none"> • Male eurofast connector • 120 Ohms, 1/2 W internal resistance 	Male
	RKE 57-TR2	Nickel Plated CuZn or Stainless Steel 10-30 VDC -40° to +80°C IP 68	eurofast Terminating Resistor <ul style="list-style-type: none"> • Female eurofast connector • 120 Ohms, 1/2 W internal resistance 	Female
	RSE 57-TR2/VM	Nickel Plated CuZn or Stainless Steel 10-30 VDC -40° to +80°C IP 68	eurofast Terminating Resistor with Voltage Monitoring <ul style="list-style-type: none"> • Male eurofast connector • Led indication: Red - reverse polarity Green-okay • 120 Ohms, 1/2 W internal resistance 	Male

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [turck](#) manufacturer:

Other Similar products are found below :

[BI10-M30-AP6X-H1141](#) [BI2-G12-AZ33X-7M](#) [BS4151-0/13.5](#) [NI12U-G18-ADZ30X2-B1331](#) [NI12U-M18-AN4X](#) [BI1.5-G08K-AN6X](#) [BI5-G18-AZ3X](#) [BI5-G18-AZ3X-B1331-50MM](#) [VB20](#) [B 5143-0](#) [BI 2-EG08K-AP6X-V1131](#) [BMWS 8151-0/9](#) [BI30U-CK40-AP6X2-H1141](#) [NI12U-M18-AP6X-H1141](#) [NI4U-EG08-AN6X-H1341](#) [NI5-G12-AP6X-H1141](#) [NI14-G18-ADZ30X2](#) [BC10-QF5.5-RN6X2](#) [PKG 3M-4/S90](#) [B1N360V-Q20L60-2LU3-H1151](#) [FKFD 4.5](#) [RK40-2M](#) [BI5-G18-AP6X-B1441/S34](#) [RK 4T-10](#) [BI4-M12-AN6X-H1141](#) [NI3-EG08K-Y1-H1341](#) [BCF5-S18-RP4X/S90](#) [BI5-M18-Y0X-H1141](#) [NI35U-CK40-ADZ30X2-B3131](#) [W/BS4](#) [WK 4T-2](#) [IM1-22EX-T](#) [NI12U-MT18-AP4X-H1141](#) [BI1.5-EG08-AP6X-H1341](#) [BC 5-Q08-AP6X2-V1131](#) [BC5-S18-Y1X](#) [CT 2-A30/M](#) [C10-T13X/024VDC](#) [FDN20-4S-4XSG-E](#) [FKV-CC](#) [FSFD 8](#) [NI4U-EG08-RP6X-V1131](#) [CMBS 8141-0](#) [FEN20-16DXP](#) [BI10-M30-AN6X-H1141](#) [VB80-P7X9-8/CS12](#) [FKFD 8](#) [RI360P0-QR24M0-INCRX2-H1181](#) [PKW 3M-6](#) [NI8-M18E-VN4X](#) [WK 4.5T-2/S618](#)