

Item no.: 224-104
 Product description: LIGHTING CONNECTOR VERSION FOR INCREASED CONTINUOUS SERVICE TEMPERATURE OF 120°C



Produkt kann von Bild abweichen / product may differ

Packing unit 100 pieces

Product group	7 (Push Wire Conn.)
Cross section [mm ²]	1 - 2.5 mm ²
Cross section [AWG]	14 - 12 AWG
Wiring method	e
Connection method	CAGE CLAMP® CONNECTION
Cross section [mm ²]	0.5 - 2.5 mm ²
Cross section [AWG]	20 - 16 AWG
Wiring method	e+f
Measured voltage EN	400 V
Measured shock voltage	4 kV
Pollution degree	2
Current intensity EN	24 A
Weight	2.34 g
Color	black
Wiring type	Side-entry
No. of connection Points	2
No. of potentials	1
Height	15.5 mm
Height	0.61 in
Width	8.5 mm

Width
Depth

0.335 in
20.5 mm



Depth	0.807 in
Strip length from	9 mm
Strip length to	11 mm
Strip length	0.39 in



Item no.	Admission office	Approval no.	Voltage [V]	Current [A]	Cross section [mm ²]
224-104	ABS	04-HG476172/1-PDA	400	24	1-2,5/0,5-2,5
224-104	BV	11914/BO	300	24	2,5
224-104	CCA	DK2527	400	24	2,5
224-104	CSA	154112-1059435	300		14-12
224-104	DEMKO	143835-01	400	24	2,5
224-104	DNV	E-9215	400	24	2,5
224-104	FIMKO	163400-01			2,5
224-104	GL	17294-00HH	300	24	2,5
224-104	KEMA	96.1739.01	400	24	2,5
224-104	LR	04/20013(E3)	400	24	2,5
224-104	NEMKO	P96191377			2,5
224-104	ÖVE	1193-032-02	400	24	1-2,5/0,5-2,5
224-104	PSE	JET0695-43040-1001	300	20	14-12
224-104	RMR	11130002	400	24	1-2,5/0,5-2,5
224-104	SEMKO	9617079			2,5
224-104	UL	E69654	300	20	14-12

Sorting criteria: admission office - approval number

© WAGO Kontakttechnik GmbH & Co. KG

Specifications are subject to changes and errors may be expected

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Wago manufacturer](#):

Other Similar products are found below :

[0207-1331](#) [0207-1332](#) [0207-1333](#) [0233-0505](#) [0233-0506](#) [0233-0510](#) [0233-0524](#) [0236-0404](#) [0256-0402](#) [0256-0403](#) [0256-0404](#) [0256-0405](#)
[0256-0406](#) [0256-0408](#) [0280-0681](#) [0280-0687](#) [0280-0833](#) [0280-0907](#) [0281-0611](#) [0281-0611/0281-0418/RN01-0000](#) [0281-0623](#) [0281-](#)
[0623/0281-0418/RN01-0000](#) [0281-0681](#) [0281-0907](#) [0282-0402](#) [0282-0681](#) [0282-0687](#) [0282-0696](#) [0282-0901](#) [0283-0402](#) [0283-0671](#) [0283-](#)
[0901](#) [0285-0635](#) [0721-0104/0026-0000/RN01-0000](#) [0733-0102](#) [0733-0108](#) [0733-0110](#) [0733-0112](#) [0745-0302](#) [145-261](#) [2000-1201](#) [2000-](#)
[1203](#) [2000-1204](#) [2000-1205](#) [2000-1207](#) [2000-1291](#) [2000-1292](#) [2000-1307](#) [2000-1401](#) [2000-1403](#)