

B F&F Filipowski sp. j. Konstantynowska 79/81 95-200 Pabianice phone/fax: (+48 42) 215 23 83 / 227 09 71 POLAND http://www.fif.com.pl e-mail: fij@fi.com.pl

BISTABLE RELAY

BIS-408i

WARRANTY. The F&F products are covered by a warranty of the 24 months from the date of purchase. Effective only with proof of purchase. Contact your dealeror directly with us. More information how to make a compliant can be found on the website:

www.fif.com.pl/reklamacie






Do not dispose of this device to a garbage bin with other unsorted wast in accordance with the Waste Electrical and Electronic Equipment A any household electro-waste can be turned in free of charge and in ar quantity to a collection point established for this purpose, as well as to th store in the event of purchasing new equipment (as per the old for new ruli regardless of brand). Electro-waste thrown in the garbage bin or abandone in the boson of nature nose a threat to the environment and human bealth.

Purpose


Electronic bistable impulse relay allows switching of lighting or other equipment from several different points of using the control buttons are connected in parallel.



Relay version "i" is to pin adapted to cooperate with the receivers with high starting current, such as LED fluorescent lamps, ESL fluorescent lamps, electronic transformers, discharge lamps, etc.

- 1 -

Wiring diagram



Power table

χ	Ď-	=	====		
incand	descent	halogen	fluorescent	energy-saving	LED
200	now	1250W	1000W	500W	250W

The above data are indicative and will depend to a large extent on the design of a specific receiver (especially for LED bulbs, energy saving lamps, electronic transformers and pulse power supplies), switching frequency and working conditions.

- 3 -

For more information visit: www.fif.com.pl.

Functioning

The receiver is after the current pulse caused by pressing any (bell) connected to the relay. Exclusion the receiver will be the next pulse.

The relay does not have a "memory" of the contact position, ie. in the case of power failure and the subsequent return, contact the relay will be set in the off.

This prevents the automatic switching of loads without supervision after a prolonged power failure.



Assembly

- 1. Disconnect the power supply.
- 2. The relay mounted in flush-mounted box.
- 3. Connect the power supply to a group of PWR: L phase wire to terminal 5 or 6. The N neutral to terminal 3 or 4.
- 4. At the same momentary switches connected to terminal 1 and the L phase conductor.
- Powered receiver connected in series to terminal 2 and the N neutral conductor.

Note!

BIS-408i can be used with illuminated buttons.

- 2 -

Specifications

power supply contact / load current AC-1 current L control pulse	100÷265V AC 1NO / <16A <5mA
response delay	0.1÷0.2s
supply signalling	green LED
power consumption	
standby	0.15W
on	0.6W
working temperature	-25÷50°C
terminal	2.5mm ² screw terminals
tightening torque	0.4Nm
dimensions	Ø54 (□48×43mm), h= 20mm
mounting	in the Ø60 flush-mounted box
ingress protection	IP20

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for General Purpose Relays category:

Click to view products by F&F manufacturer:

Other Similar products are found below:

APF30318 JVN1AF-4.5V-F PCN-105D3MHZ 5JO-10000S-SIL 5JO-1000CD-SIL 5JO-400CD-SIL LY2S-AC220/240 LYQ20DC12
6031007G 6131406HQ 6-1393099-3 6-1393099-8 6-1393122-4 6-1393123-2 6-1393767-1 6-1393843-7 6-1415012-1 6-1419102-2 61423698-4 6-1608051-6 6-1608067-0 6-1616170-6 6-1616248-2 6-1616282-3 6-1616348-2 6-1616350-1 6-1616350-8 6-1616358-7 61616359-9 6-1616360-9 6-1616931-6 6-1617039-1 6-1617052-1 6-1617090-2 6-1617090-5 6-1617347-5 6-1617353-3 6-1617801-8 61617802-2 6-1618107-9 6-1618248-4 M83536/1-027M CX-4014 MAHC-5494 MAVCD-5419-6 703XCX-120A 7-1393100-5 7-1393111-7
7-1393144-5 7-1393767-8