
Introduction

The TA131 is a passive high impedance probe, designed for use with oscilloscopes. It is calibrated to work effectively with instruments that have an input impedance of 1M Ohm, shunted by 18 pF. You can also use it with oscilloscopes that have an input capacitance of 10-35pF, if you make an adjustment to compensate. In the head of the probe is a two position slide switch which allows you to select the attenuation you require: either X1or X10. The small box adjacent to the BNC plug contains two adjustable resistors that enable high frequency trimming. This is usually not required.

Frequency compensation adjustment

Connect the probe to an oscilloscope and a 1KHz square waveform source. Move the attenuation switch on the probe to the X10 position. Set the oscilloscope to display two to three cycles, and two to six vertical divisions. Carefully adjust the compensation trimmer tool on the head of the probe until the waves displayed on the oscilloscope are perfectly square.





Specifications:

Position X10

Attenuation Ratio 10:1

Bandwidth DC to 250MHz Rise time 1.4ns

Input Resistance 10M when used with

oscilloscopes with 1M input

Input Capacitance Approx.11pF Compensation Range 10 to 35pF

Working Voltage 600VDC incl. Peak AC

derating with frequency (see Fig.1)

Position X1

Attenuation Ratio 1:1
Bandwidth DC to 10MHz


Rise Time 35ns

Input Resistance 1M(Oscilloscope Input) Input Capacitance 46pF plus oscilloscope

capacitance
Working Voltage 600V DC incl. Peak AC
Derating with frequency

Safety conformed IEC-1010 CAT II

Cable Length 1.2Meter




Update:22-04-2011

Introduction

The TA132 is a passive high impedance probe, designed for use with oscilloscopes. It is calibrated to work effectively with instruments that have an input impedance of 1M Ohm, shunted by 18 pF. You can also use it with oscilloscopes that have an input capacitance of 10-35pF, if you make an adjustment to compensate. In the head of the probe is a two position slide switch which allows you to select the attenuation you require: either X1or X1o. The small box adjacent to the BNC plug contains two adjustable resistors that enable high frequency trimming. This is usually not required.

Frequency compensation adjustment

Connect the probe to an oscilloscope and a 1KHz square waveform source. Move the attenuation switch on the probe to the X10 position. Set the oscilloscope to display two to three cycles, and two to six vertical divisions. Carefully adjust the compensation trimmer tool on the head of the probe until the waves displayed on the oscilloscope are perfectly square.





Specifications:

Position X10

Attenuation Ratio 10:1

Bandwidth DC to 150MHz

Rise time 2.33ns
Input Resistance 10M when used with

oscilloscopes with 1M input

Input Capacitance Approx.11pF

Compensation Range 10 to 35pF Working Voltage 600VDC incl. Peak AC

derating with frequency (see Fig. 1)

Position X1

Attenuation Ratio 1:1

Bandwidth DC to 10MHz

Rise Time 35ns

Input Resistance 1M(Oscilloscope Input)
Input Capacitance 46pF plus oscilloscope

capacitance
Working Voltage 600V DC incl. Peak AC

Derating with frequency
Safety conformed IEC-1010 CAT II

Cable Length 1.2Meter

Voltage derating curve 700 600 500 400 300 200 100 0 10KHz 10KHz 1MHz 10MHz 10MHz 1GHz

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for pico manufacturer:

Other Similar products are found below:

MI136 PA149 PICO CONNECT 442 SE050 SE055 SE056 SE057 SE058 PICOCONNECT 910 KIT TA328 TA155 MI078 81170 SE049 SE054 MI106 TA384 TA385 100501 SE053 44740M2735659 PICOLOG 1216 TA139 TA313 TA089 TC-08 BUNDLE PICOSCOPE 5442D TA050 TA018 42345M2735662 75005 TA090 PS010 TA058 SE028 TC-08 PICOSCOPE 2204A