



ELECTRONICS, INC.
 44 FARRAND STREET
 BLOOMFIELD, NJ 07003
 (973) 748-5089

**NTE5322/NTE5324/
 NTE5326/NTE5327/NTE5328
 Silicon Bridge Rectifier, Single-Phase, 25 Amp**

Features:

- Superior Thermal Design
- Surge Overload Rating: 400A (Peak)
- Hole Through for #8 Screw
- Silverplated Copper Terminals

Maximum Ratings & Electrical Characteristics Per Leg:

(T_A = +25°C unless otherwise specified, Single Phase, Full Wave, 60Hz, Resistive or Inductive Load.
 For Capacitive Load, Derate Current by 20%)

Maximum Recurrent Peak Reverse Voltage, P_{RV}

NTE5322	200V
NTE5324	400V
NTE5326	600V
NTE5327	800V
NTE5328	1000V

Maximum RMS Bridge Input Voltage

NTE5322	140V
NTE5324	280V
NTE5326	420V
NTE5327	560V
NTE5328	700V

Maximum DC Blocking Voltage

NTE5322	200V
NTE5324	400V
NTE5326	600V
NTE5327	800V
NTE5328	1000V

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Bridge Rectifiers](#) category:

Click to view products by [NTE manufacturer](#):

Other Similar products are found below :

[G3SBA60-E351](#) [GBJ1504-BP](#) [GBU10B-BP](#) [GBU15J-BP](#) [GBU15K-BP](#) [GBU4A-BP](#) [GBU4D-BP](#) [GBU6B-E3/45](#) [GSIB680-E3/45](#) [DB101-BP](#) [DF10SA-E345](#) [RMB2S](#) [RCG](#) [APT30DF100HJ](#) [APT60DF20HJ](#) [B2S-E3/80](#) [BU1506-E351](#) [BU15085S-E345](#) [BU1508-E3/45](#) [BU1510-E3/45](#) [RS404GL-BP](#) [RS405GL-BP](#) [G3SBA20-E3/51](#) [G5SBA20-E3/51](#) [G5SBA60-E3/51](#) [GBJ1502-BP](#) [GBL02-E351](#) [GBL10-E3/45](#) [GBU10J-BP](#) [GBU4J-BP](#) [GBU4K-BP](#) [GBU8B-E3/45](#) [GBU8D-BP](#) [GBU8J-BP](#) [GSIB1520-E3/45](#) [MB1510](#) [MB352W](#) [MB6M-G](#) [B2M-E345](#) [B40C7000A](#) [B500C7000A](#) [MP5010W-BP](#) [MP501W-BP](#) [MP502-BP](#) [BR1005-BP](#) [BR101-BP](#) [BU1006-E345](#) [BU12065S-E3/45](#) [BU1508-E3/51](#) [BU2006-E3/45](#) [BU2008-E345](#)