

Data Sheet

5 MHz Sweep Function Generator Model 4012A



Model 4012A is a popular 5 MHz generator for general bench and lab use with an ideal mixture of features and sweep function at a compelling price.

Features & Benefits

- 0.5 Hz to 5 MHz
- Sine, Square, Triangle, Pulse, and Ramp output
- Coarse and fine tuning knobs
- 4-digit LED display
- Linear and log sweep
- Variable duty cycle
- Variable DC offset
- Variable 20 Vpp output into open circuit (10 Vpp into 50 Ω)

Specifications	4012A
Frequency Characteristics	
Waveforms	Sine, Square, Triangle, \pm Pulse, \pm Ramp
Range	0.5 Hz to 5 MHz in 7 ranges
Resolution	4 digits
Tuning Range	10:1
Fine	$\pm 5\%$ of coarse setting
Variable Duty Cycle	15:85:15 cont variable
Operating Modes	Normal, Sweep, VCG
Output Characteristics	
Impedance	50 Ω $\pm 10\%$
Level	20 V p-p Open circuit, 10 V p-p into 50 Ω
Amplitude	Variable, 20 dB range typical
Attenuation	-20 dB ± 1 dB
DC Offset	Preset: ± 0.1 V typical Variable: ± 10 V open-circuit ± 5 into 50 Ω
Sine Wave	
Distortion	<3% typical at 1 kHz
Flatness (Into 50 Ω)	$\pm 5\%$ $\pm (.45$ dB) 0.5 Hz to 5 MHz
Square Wave	
Symmetry	0.1 Hz to 100 kHz <2%
Rise time (Into 50 Ω)	≤ 120 nS
Triangle Wave	
Linearity	$\geq 98\%$ to 100 kHz
TTL Output	
Level	0.8 V to 2.4 V
Rise time	≤ 20 nS
Duty Cycle	50% typical
CMOS Output	
Max. Frequency	2 MHz
Level	4 V to 14 V ± 0.5 V p-p continuously variable
Rise Time	≤ 120 nS (Open circuit)
VCG (Voltage controlled generator)	
Input Voltage	0-10 V ± 1 V causes a 100:1 frequency change
Impedance	10 k Ω $\pm 5\%$
Sweep Operation	
Mode	LIN/LOG
Width	100:1 continuously variable
Rate	0.5 s to 30 s continuously variable
Frequency Counter	
Accuracy	Time base accuracy ± 1 count
Time Base Accuracy	± 10 ppm (23 $^{\circ}$ C ± 5 $^{\circ}$ C)
Display	4 digit LED
General	
AC Input	120/230 VAC $\pm 10\%$, 50/60 Hz, internal jumper selectable
Dimensions (W x H x D)	10.5" x 4.5" x 12.25" (266.7 x 114.3 x 311.15 mm)
Weight	4 lbs (1.8 kg)
Two-Year Warranty	
Included Accessories	Instruction manual, output cable (BNC to alligator clips)

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Function Generators & Synthesisers](#) category:

Click to view products by [B&K Precision](#) manufacturer:

Other Similar products are found below :

[3001](#) [CT3734](#) [4047B](#) [4010A](#) [SFG-210](#) [SFG-205](#) [33502A/903](#) [4013B](#) [AD9166BBPZ](#) [CT3736](#) [FIT0778](#) [28II](#) [3446GPBU](#) [EDU33211A](#)
[EDU33212A](#) [U2010A](#) [MOKU:GO M1 \(STORM\)](#) [MOKU:GO M0 \(STORM\)](#) [MOKU:GO M2 \(STORM\)](#) [MOKU:GO M0 \(WHITE\)](#)
[MOKU:GO M1 \(WHITE\)](#) [MOKU:GO M2 \(WHITE\)](#) [IZD0024](#) [114991659](#) [T3AFG10](#) [T3AFG500](#) [T3AFG5](#) [T3AFG30](#) [T3AFG60](#) [T3AFG80](#)
[W09-4A-12V](#) [33509B](#) [33519B](#) [33512B](#) [33520B](#) [33522B](#) [AFG31051](#) [AFG31101](#) [AFG31152](#) [AFG31251](#) [AFG31252](#) [CT3733](#) [33510B/903](#)
[4011A](#) [33509B/903](#) [33511B/903](#) [33612A](#) [4010](#) [4053](#) [4001A](#)