

**UC-357** 






## **RoHS** Compliant



# uPCI 1xRS232 + 1xRS422/485 1MBaud

# "SERIAL CARDS ENGINEERED TO EXCEED EXPECTATIONS"



#### Features

- 2 port RS232 + RS422/485
- PCI 3.0
- 128 Byte Tx and 128 Byte Rx FIFOs
- Up to 921,600 Baud
- DB9 connector (9 Pin Male)
- Drivers for all popular operating systems
- Sample Programs, Test & Terminal software
- Lifetime Support
- Lifetime Warranty (registration required)

#### Options



UC-357: uPCI 1xRS232 + 1xRS422/485 1MBaud

#### Description

Universal PCI providing one RS232 port and one RS422/485 serial port. Data transfer rates up to 921,600 baud rates and the 128 byte deep transmit and 128 byte receive FIFOS, coupled with 1Mbit/s line drivers deliver uncompromising performance on your PC.Includes drivers for all Windows 32 bit and 64 bit Operating Systems, including Windows 7.

With Brainboxes industry renowned Lifetime Warranty and Lifetime Support!

#### Software

Microsoft signed drivers (easy installation & robust operation) for:

- Windows 7 32 bit 64 bit Editions
- Windows Server 2008 32 bit 64 bit Editions
- Windows Vista 32 bit 64 bit editions
- Windows Server 2003 32 bit 64 bit Editions

As well as: full product documentation, a thorough troubleshooting guide and terminal software. Detailed sample source code for many popular programming languages. Further OS support on next page.





ORDER Description uPCl 1xRS232 + 1xRS422/485 1MBaud

Code UC-357

UC-357



# uPCI 1xRS232 + 1xRS422/485 1MBaud

#### UC-357Full Specification

Port	Ports	2 x RS232 + RS422/485
RS422/485   RS232 Pinout (9 Pin)	Connector	DB9 Connector - 9 Pin Male
Pin 2 TXD+ RXD Pin 3 RTS- TXD	FIFO size	128 RX FIFO + 128 TX FIFO
Pin 4 RTS+ DTR Pin 5 GND GND	Operating Distance	RS422/485 Standard 4000 ft : 1200 metres / EIA - RS232 Standard
Pin 6 RXD- DSR Pin 1 Pin 6   Pin 7 RXD+ RTS Pin 8 CTS CTS	Cable	No Cable; Integrated Connector
Pin 9 CTS+ RI		
Port Settings	Baud Rate	921,600
921,600	Data Bits	5,6,7 or 8
$\rangle \rangle \rangle \rangle \rangle$	Parity	Odd, Even, None, Mark or Space
baud	Stop Bits	1, 1.5 or 2
	Flow Control	
	Tx/Rx Modes	Point to Point RS232, Full Duplex, Half Duplex Autogating, Hardware Autogating, TxD always/ RTS true enabled, RxD always enabled, RxD RTS true disabled, CTS forced true RS422/485
Interface	OS Compatibility	Microsoft Windows 7 32 bit 64 bit Editions
		Windows Server 2008 32 bit 64 bit Editions Windows Vista 32 bit 64 bit Editions
PCI°		Windows Server 2003 32 bit 64 bit Editions
PUI		Windows XP 32 bit 64 bit Editions
		Microsoft Windows 2000 DOS
	BUS	PCI : Universal PCI is fully compatible with both 3.3Volt and 5Volt PCI
		slots.
Approvals	Industry Approvals	AEO C-TPAT C-Tick Microsoft Certified Gold Partner WEEE RoHS EMC: CE TAA
	Microsoft Approvals	Windows 7 32 bit 64 bit Editions
		Windows Server 2008 32 bit 64 bit editions Windows Vista 32 bit 64 bit editions
		Windows Vista 32 bit 64 bit editions Windows Server 2003 32 bit 64 bit editions
		Windows XP 32 bit 64 bit editions
General	PCB Layers	4
	Power Consumption	550mA @ 5V
	Weight	0.08 kg
	Size	136l x 18w x 120h mm
Box Content	Packaging	Installation CD including manual, Microsoft signed drivers & utilities
	Card	uPCI 1xRS232 + 1xRS422/485 1MBaud
		No Cable; Integrated Connector
Product Support	Warranty	Lifetime (online registration required)
CETTA CETTA	Support	Lifetime Web, Email and Phone Support from fully qualified, friendly
		staff who work in and alongside the Product Development Team
Additional	OEM option	Available for bulk buy OEM
	Made In	Manufactured in the UK by Brainboxes Winner 2005 European Electronics Industry Awards "Manufacturer of the Year"
WINNER Manufacturer of the Year	Customisable	Brainboxes operate a "Perfect Fit Custom Design" policy for volume
Other PCI Cards: 1xRS232 2xRS2	32   4xRS232   8xRS232   1xRS4	22)3895.   2007 22/3895.   20085 2 20 20 20 20 20 20 20 20 20 20 20 20 2
+44(0) 151 220 2		· · · · · · · · · · · · · · · · · · ·
+44(0) 151 220 2500   sales@brainboxes.com   www.brainboxes.com		

### **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Interface Modules category:

Click to view products by Brainboxes manufacturer:

Other Similar products are found below :

8500-003 IFD8520 422CON ATX6022/14GP7 ATX6022/8 AX93221-24/48 OPT8AP-AE 60006-016 96RMKVM-19V1C-A 60016-011 60016-014 60006-008 60016-015 60011-075 HPCI-14S12U cBP-3208 cBP-3062A FAB205-6P5 ATX6022/6 60016-012 96RMKVM-17V1C-A PCE-DP10-00A1E MOS-1120Y-0201E 96RMLCD-17V1-A 96RMKVM-17V8C-A 60004-005 60016-017 60006-019 60006-009 60016-035 60016-034 60016-031 60016-030 60016-026 60016-025 60016-024 60016-021 60016-018 60016-007 60016-006 60016-005 60016-004 60007-002 60006-018 60006-010 AXX10GBTWLHW3 382-BBEH 555-BDCL K6CMISZBI52 426451401-3