

E-LINE TRANSISTORS

TABLE 5: HIGH PERFORMANCE E-LINE TRANSISTORS (P_D=1 Watt)

The transistors shown in this table have been designed to operate and provide useful gain at current levels up to 1 Amp with power dissipation capabilities of 1 Watt at 25°C ambient temperature. Typical application areas include audio frequency drivers and output stages, relay drivers etc.

| PART NO. | V _{CBO} V | V _{CEO} V | I _C A | I _{CM} A | V _{CE(sat)} max @ V | I _C mA | | h _{FE} min @ | I _C mA | V _{CE} V | h _{FE} min @ | I _C A | | f _T min @ MHz | I _C mA | PIN OUT 123 |
|------------|-----------------------|-----------------------|---------------------|----------------------|------------------------------------|----------------------|----------------------|--------------------------|----------------------|----------------------|--------------------------|---------------------|----------------------|--------------------------------|----------------------|-------------------|
| | | | | | | I _B mA | I _C mA | | | | | I _C A | V _{CE} V | | | |
| NPN | | | | | | | | | | | | | | | | |
| ZTX458 | 400 | 400 | 0.3 | 0.5 | 0.5 | 50 | 6 | 100 | 50 | 10 | 15 | 0.1 | 10 | 50 | 10 | CBE |
| ZTX457 | 300 | 300 | 0.5 | 1 | 0.3 | 100 | 10 | 50 | 50 | 10 | 25 | 0.1 | 10 | 75 | 50 | CBE |
| ZTX456 | 200 | 200 | 0.5 | 1 | 0.3 | 100 | 10 | 50 | 50 | 10 | 25 | 0.1 | 10 | 75 | 50 | CBE |
| ZTX455 | 160 | 140 | 1 | 2 | 0.7 | 150 | 15 | 100 | 150 | 10 | 10 [#] | 1 | 10 | 100 | 50 | CBE |
| FXT455 | 160 | 140 | 1 | 2 | 0.7 | 150 | 15 | 100 | 150 | 10 | 10 [#] | 1 | 10 | 100 | 50 | BCE |
| ZTX454 | 140 | 120 | 1 | 2 | 0.7 | 150 | 15 | 100 | 150 | 10 | 30 | 0.2 | 1 | 100 | 50 | CBE |
| ZTX453 | 120 | 100 | 1 | 2 | 0.7 | 150 | 15 | 40 | 150 | 10 | 10 | 1 | 10 | 150 | 50 | CBE |
| FXT453 | 120 | 100 | 1 | 2 | 0.7 | 150 | 15 | 40 | 150 | 10 | 10 | 1 | 10 | 150 | 50 | BCE |
| ZTX452 | 100 | 80 | 1 | 2 | 0.7 | 150 | 15 | 40 | 150 | 10 | 10 | 1 | 10 | 150 | 50 | CBE |
| ZTX451 | 80 | 60 | 1 | 2 | 0.35 | 150 | 15 | 50 | 150 | 10 | 10 | 1 | 10 | 150 | 50 | CBE |
| FXT451 | 80 | 60 | 1 | 2 | 0.35 | 150 | 15 | 50 | 150 | 10 | 10 | 1 | 10 | 150 | 50 | BCE |
| ZTX450 | 60 | 45 | 1 | 2 | 0.25 | 150 | 15 | 100 | 150 | 10 | 15 | 1 | 10 | 150 | 50 | CBE |
| FXT450 | 60 | 45 | 1 | 2 | 0.25 | 150 | 15 | 100 | 150 | 10 | 15 | 1 | 10 | 150 | 50 | BCE |
| ZTX449 | 50 | 30 | 1 | 2 | 0.5 | 1000 | 100 | 100 | 500 | 2 | 40 | 2 | 2 | 150 | 50 | CBE |
| FXT449 | 50 | 30 | 1 | 2 | 0.5 | 1000 | 100 | 100 | 500 | 2 | 40 | 2 | 2 | 150 | 50 | BCE |
| PNP | | | | | | | | | | | | | | | | |
| ZTX558 | -400 | -400 | -0.2 | -0.5 | -0.5 | -50 | -6 | 100 | -50 | -10 | 15 | -0.1 | -10 | 50 | -10 | CBE |
| ZTX557 | -300 | -300 | -0.5 | -1 | -0.3 | -50 | -5 | 50 | -10 | -10 | 50 | -0.05 | -10 | 75 | -50 | CBE |
| FXT557 | -300 | -300 | -0.5 | -1 | -0.3 | -50 | -5 | 50 | -10 | -10 | 50 | -0.05 | -10 | 75 | -50 | BCE |
| ZTX576 | -200 | -200 | -1 | -2 | -0.3 | -100 | -10 | 50 | -10 | -10 | 50 | -0.3 | -10 | 100 | -50 | CBE |
| ZTX556 | -200 | -200 | -0.5 | -1 | -0.3 | -50 | -5 | 50 | -10 | -10 | 50 | -0.05 | -10 | 75 | -50 | CBE |
| ZTX555 | -160 | -150 | -1 | -2 | -0.3 | -100 | -10 | 50 | -10 | -10 | 50 | -0.3 | -10 | 100 | -50 | CBE |
| FXT555 | -160 | -150 | -1 | -2 | -0.3 | -100 | -10 | 50 | -10 | -10 | 50 | -0.3 | -10 | 100 | -50 | BCE |
| ZTX554 | -140 | -125 | -1 | -2 | -0.3 | -100 | -10 | 50 | -10 | -10 | 50 | -0.3 | -10 | 100 | -50 | CBE |
| ZTX553 | -120 | -100 | -1 | -2 | -0.25 | -150 | -15 | 40 | -150 | -10 | 10 | -1 | -10 | 150 | -50 | CBE |
| FXT553 | -120 | -100 | -1 | -2 | -0.25 | -150 | -15 | 40 | -150 | -10 | 10 | -1 | -10 | 150 | -50 | BCE |
| ZTX552 | -100 | -80 | -1 | -2 | -0.25 | -150 | -15 | 40 | -150 | -10 | 10 | -1 | -10 | 150 | -50 | CBE |
| ZTX551 | -80 | -60 | -1 | -2 | -0.35 | -150 | -15 | 50 | -150 | -10 | 10 | -1 | -10 | 150 | -50 | CBE |
| FXT551 | -80 | -60 | -1 | -2 | -0.35 | -150 | -15 | 50 | -150 | -10 | 10 | -1 | -10 | 150 | -50 | BCE |
| ZTX550 | -60 | -45 | -1 | -2 | -0.25 | -150 | -15 | 100 | -150 | -10 | 15 | -1 | -10 | 150 | -50 | CBE |
| FXT550 | -60 | -45 | -1 | -2 | -0.25 | -150 | -15 | 100 | -150 | -10 | 15 | -1 | -10 | 150 | -50 | BCE |
| ZTX549A | -35 | -30 | -1 | -2 | -0.5 | -1000 | -100 | 150 | -500 | -2 | 40 | -2 | -2 | 100 | -100 | CBE |
| ZTX549 | -35 | -30 | -1 | -2 | -0.5 | -1000 | -100 | 100 | -500 | -2 | 40 | -2 | -2 | 100 | -100 | CBE |
| FXT549 | -35 | -30 | -1 | -2 | -0.5 | -1000 | -100 | 100 | -500 | -2 | 40 | -2 | -2 | 100 | -100 | BCE |

#Typical Values

TABLE 6: MEDIUM POWER TRANSISTORS

General purpose transistors designed for amplification from d.c. to radio frequencies.

| PART NO. | V _{CBO} V | V _{CEO} V | I _C A | V _{CE(sat)} max @ V | I _C mA | | h _{FE} min @ | I _C mA | V _{CE} V | h _{FE} min @ | I _C mA | | f _T min @ MHz | I _C mA | PIN OUT 123 |
|------------|-----------------------|-----------------------|---------------------|------------------------------------|----------------------|----------------------|--------------------------|----------------------|----------------------|--------------------------|----------------------|----------------------|--------------------------------|----------------------|-------------------|
| | | | | | I _B mA | I _C mA | | | | | I _C mA | V _{CE} V | | | |
| NPN | | | | | | | | | | | | | | | |
| 2N6718 | 100 | 80 | 1 | 0.35 | 250 | 25 | 50 | 250 | 1 | 20 | 500 | 1 | 50 | 50 | CBE |
| 2N6731 | 100 | 100 | 1 | 0.35 | 350 | 35 | 100 | 10 | 2 | 100 | 350 | 2 | 50 | 200 | CBE |
| 2N6717 | 80 | 80 | 1 | 0.35 | 250 | 25 | 50 | 250 | 1 | 20 | 500 | 1 | 50 | 50 | CBE |
| MPSA06 | 80 | 80 | 0.5 | 0.25 | 100 | 10 | 50 | 10 | 1 | 50 | 100 | 1 | 100 | 10 | CBE |
| 2N6716 | 60 | 60 | 1 | 0.35 | 250 | 25 | 50 | 250 | 1 | 20 | 500 | 1 | 50 | 50 | CBE |
| ZTX337C | 50 | 45 | 0.8 | 0.7 | 500 | 50 | 250 | 100 | 1 | 170 | 300 | 1 | 200 [#] | 10 | CBE |
| 2N6715 | 50 | 40 | 1 | 0.5 | 1000 | 100 | 60 | 100 | 1 | 50 | 1000 | 1 | 50 | 50 | CBE |
| 2N6714 | 40 | 30 | 1 | 0.5 | 1000 | 100 | 60 | 100 | 1 | 50 | 1000 | 1 | 50 | 50 | CBE |
| PNP | | | | | | | | | | | | | | | |
| 2N6730 | -100 | -100 | -1 | -0.35 | -250 | -25 | 50 | -250 | -1 | 20 | -500 | -1 | 50 | -50 | CBE |
| 2N6732 | -100 | -80 | -1 | -0.35 | -350 | -35 | 100 | -10 | -2 | 100 | -350 | -2 | 50 | -200 | CBE |
| 2N6729 | -80 | -80 | -1 | -0.35 | -250 | -25 | 50 | -250 | -1 | 20 | -500 | -1 | 50 | -50 | CBE |
| MPSA56 | -80 | -80 | -0.5 | -0.25 | -100 | -10 | 50 | -10 | -1 | 50 | -100 | -1 | 100 | -10 | CBE |
| 2N6728 | -60 | -60 | -1 | -0.35 | -250 | -25 | 50 | -250 | -1 | 20 | -500 | -1 | 50 | -50 | CBE |
| ZTX537C | -50 | -45 | -0.8 | -0.7 | -500 | -50 | 250 | -100 | -1 | 170 | -300 | -1 | 200 [#] | -10 | CBE |
| 2N6727 | -50 | -40 | -1 | -0.5 | -1000 | -100 | 60 | -100 | -1 | 50 | -1000 | -1 | 50 | -50 | CBE |
| 2N6726 | -40 | -30 | -1 | -0.5 | -1000 | -100 | 60 | -100 | -1 | 50 | -1000 | -1 | 50 | -50 | CBE |

#Typical Values

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Bipolar Transistors - BJT category](#):

Click to view products by [Diodes Incorporated manufacturer](#):

Other Similar products are found below :

[619691C](#) [MCH4017-TL-H](#) [BC546/116](#) [BC557/116](#) [BSW67A](#) [NTE187A](#) [NTE195A](#) [NTE2302](#) [NTE2330](#) [NTE63](#) [C4460](#) [2SA1419T-TD-H](#)
[2SA1721-O\(TE85L,F\)](#) [2SA2126-E](#) [2SB1204S-TL-E](#) [2SC5488A-TL-H](#) [2SD2150T100R](#) [SP000011176](#) [FMMTA92QTA](#) [2N2369ADCSM](#)
[2SC2412KT146S](#) [2SC5490A-TL-H](#) [2SD1816S-TL-E](#) [2SD1816T-TL-E](#) [CMXT2207 TR](#) [CPH6501-TL-E](#) [MCH4021-TL-E](#) [US6T6TR](#)
[732314D](#) [CMXT3906 TR](#) [CPH3121-TL-E](#) [CPH6021-TL-H](#) [873787E](#) [UMX21NTR](#) [EMT2T2R](#) [MCH6102-TL-E](#) [FP204-TL-E](#) [NJL0302DG](#)
[2N3583](#) [2SA1434-TB-E](#) [2SC3143-4-TB-E](#) [2SD1621S-TD-E](#) [30A02MH-TL-E](#) [NSV40301MZ4T1G](#) [NTE13](#) [NTE15](#) [NTE16001](#) [NTE16006](#)
[NTE26](#) [NTE320](#)