# Low Voltage Audio Power Amplifier

#### FEATURES

- · Battery operation
- · Minimum external parts
- Wide supply voltage range 4V to 12V
- Low quiescent current drain 4mA (Typ.)
- Voltage gains from 20 to 200
- ESD Protection 2kV
- · Ground referenced input
- · Self-centering output quiescent voltage
- · Low distortion

### **APPLICATIONS**

- · AM-FM radio amplifier
- Portable tape player amplifiers
- Intercoms
- TV sound systems
- · Line drivers
- Ultrasonic drivers
- Small servo drivers
- Power converters

### DESCRIPTION

SOP-8

#### ORDERING INFORMATION

Device	Package
LM386D	SOP-8
LM386N	DIP-8

The LM386 is a power amplifier designed for use in low voltage consumer applications. The gain is internally set to 20 to keep external part count low, but the addition of an external resistor and capacitor between pins 1 and 8 will increase the gain to any value up to 200. The inputs are ground referenced while the output is automatically biased to one half the supply voltage. The quiescent power drain is only 24 milliwatts when operating from a 6V supply, making the LM386 ideal for battery operation.

#### ABSOLUTE MAXIMUM RATINGS (Note 1)

CHARACTERISTIC	SYMBOL	MIN.	MAX.	UNIT
Supply Voltage	V <sub>CC</sub>	-	15	V
Input Voltage	V <sub>IN</sub>	-0.4	0.4	V
Operating Ambient Temperature Range	T <sub>A</sub>	-40	85	°C
Junction Temperature	TJ	-	125	°C

Note1. Stresses beyond those listed under *Absolute Maximum Ratings* may cause permanent damage to the device. These are stress ratings only and functional operation of the device at these or any other conditions beyond those indicated under *Recommended Operating Conditions* is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

### **RECOMMENDED OPERATING CONDITIONS** (Note 2)

CHARACTERISTIC	SYMBOL	MIN.	MAX.	UNIT
Supply Voltage	V <sub>CC</sub>	4	12	V
Operating Free-Air Temperature Range	T <sub>A</sub>	0	70	°C

Note 2. The device is not guaranteed to function outside its operating ratings.

### **ORDERING INFORMATION**

Package	Order No.	Description	Supplied As	Status
SOP-8	LM386D	Low Voltage Audio Power Amplifier	Tape & Reel	Active
DIP-8	LM386N	Low Voltage Audio Power Amplifier	Tube	Active

# Low Voltage Audio Power Amplifier

# **PIN CONFIGURATION**

SOP-8		DI	P-8
GAIN 1 IN1(-) 2 IN1(+) 3 GND 4	8 GAIN 7 BYPASS 6 VCC 5 VOUT	GAIN 1 IN1(-) 2 IN1(+) 3 GND 4	8 GAIN 7 BYPASS 6 VCC 5 VOUT

# **PIN DESCRIPTION**

Pin	No.		Pin Function	
SOP-8	DIP-8	Pin Name		
1	1	GAIN	Gain Setting	
2	2	INPUT (-)	Inverting Input	
3	3	INPUT (+)	Noninverting Input	
4	4	GND	Ground	
5	5	VOUT	Output	
6	6	VCC	Power Supply Voltage	
7	7	BYPASS	Bypass Decoupling Path	
8	8	GAIN	Gain Setting	

# FUNCTIONAL BLOCK DIAGRAM



### **ELECTRICAL CHARACTERISTICS**

Specifications with standard type face are for  $T_A = 25^{\circ}C$ , RL=8 $\Omega$ , VCC = 6V, f=1kHz unless otherwise noted.

SYMBOL	PARAMETER	TEST CONDITION	MIN	TYP	MAX	UNIT
V <sub>cc</sub>	Operating Supply Voltage		4	-	12	V
Ι <sub>Q</sub>	Quiescent Current	$V_{IN} = 0V$	-	4	8	mA
Pout Output Po	Output Dowor	V <sub>CC</sub> = 6V, THD = 10%	250	325	-	
	Output Power	V <sub>CC</sub> = 9V, THD = 10%	500	700	-	mvv
A <sub>V</sub> Voltage Gain		Pin 1 and Pin 8 Open	-	26	-	
		10µF from Pin 1 to Pin 8	-	46	-	aв
D)A/		10µF from Pin 1 to Pin 8	-	60	-	
BW Bandwidth	Bandwidth	Pin 1 and Pin 8 Open	-	300	-	КПZ
THD	Total Harmonic Distortion	P <sub>OUT</sub> = 125mW, Pin 1 and Pin 8 Open	-	0.2	-	%
R <sub>IN</sub>	Input Resistance		-	120	-	kΩ
I <sub>BIAS</sub>	Input Bias Current	Pin 2 and Pin 3 Open	-	250	-	nA

# Low Voltage Audio Power Amplifier

#### **APPLICATION INFORMATION**

The LM386 is a mono low voltage amplifier that can be used in a variety of applications. It can drive loads from  $4\Omega$  to  $32 \Omega$ . The gain is internally set to 20 but it can be modified from 20 to 200 by placing a resistor and capacitor between pins 1 and 8. This device comes in three different 8-pin packages as DIP-8 and SOP-8 to fit in different applications. As this is an Op Amp it can be used in different configurations to fit in several applications. The internal gain setting resistor allows the LM386 to be used in a very low part count system. In addition, a series resistor can be placed between pins 1 and 5 to modify the gain and frequency response for specific applications.



< Amplifier with Gain=50 >

# TYPICAL OPERATING CHARACTERISTICS

T.B.D.

## **REVISION NOTICE**

The description in this datasheet is subject to change without any notice to describe its electrical characteristics properly.

# **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Audio Amplifiers category:

Click to view products by HTC Korea manufacturer:

Other Similar products are found below :

LV47002P-E MP7747DQ-LF-P AZ386MTR-E1 NCP2811AFCT1G NCP2890AFCT2G NJM8068RB1-TE1 NJW1194V-TE1 LA4282-E LA4814JA-AE LC706200CM SSM2377ACBZ-R7 FDA2100LV TDA2541 TDA7385H TDA7391LV TDA7575BPDTR TDA7718NTR IS31AP2121-LQLS1 IS31AP4915A-QFLS2-TR LA74309FA-BH 421067X 480263C NCP2820FCT2G STPA001 TDA1515AQ TDA1520B TDA1591T TDA2051H TDA4850 TDA7391PDUTR TDA7563BH TDA7718B LA4425F-E LA4742-E TDA7391PDU TDA7491MV13TR TDA749213TR TDA7563AH TDA7850H STK433-070GN-E E-TDA7391PDTR SSM2529ACBZ-R7 SSM2518CBZ-R7 MAX9890BEBL+T MAX98303EWE+T MAX98358EWL+ MAX98304DEWL+T MAX97220DETE+T TS4962MEIJT TS4990EIJT