


## FEATURES

- \* Ideal for printed circuit board
- \* Reliable low cost construction utilizing molded plastic technique
- \* High surge current capability
- \* Polarity: Symbol molded on body
- \* Mounting position: Any







### **Internal Structure**

## Package Marking and Ordering Information

Product ID	Pack	Marking	Qty(PCS)		
ABS2-ABS10	ABS	ABS*	5000		


\*:From 2-10


## MAXIMUM RATINGS (Ta=25 unless otherwise noted)


Type Number	Symbol	ABS2	ABS4	ABS6	ABS8	ABS10	Units
Maximum Recurrent Peak Reverse Voltage	V <sub>RRM</sub>	200	400	600	800	1000	V
Maximum RMS Voltage	V <sub>RMS</sub>	140	280	420	560	700	V
Maximum DC Blocking Voltage	V <sub>DC</sub>	200	400	600	800	1000	V
Maximum Average Forward Rectified Current On glass-epoxy P.C.B. On aluminum substrate	I <sub>(AV)</sub>			1.0			А
Peak Forward Surge Current, 8.3 ms Single Half Sine-wave Superimposed on Rated Load (JEDEC method )	I <sub>FSM</sub>	30					А
Maximum Instantaneous Forward Voltage @ 0.4A	V <sub>F</sub>	1.0					V
Maximum DC Reverse Current @ $T_A$ =25 °C at Rated DC Blocking Voltage @ $T_A$ =125 °C	I <sub>R</sub>	10 150					uA uA
Typical Thermal resistance Junction to Lead On aluminum substrate On Glass-Epoxy substrate	R <sub>θJL</sub> R <sub>θJA</sub>	25 62.5 80					°C/W
Operating Temperature Range	ТJ		°C				
Storage Temperature Range	T <sub>STG</sub>		°C				



#### **Typical Characteristics**










## **ABS Package Outline Dimensions**



Dimensions in inches and (millimeters)



#### **Attention**

Any and all HUA XUAN YANG ELECTRONICS products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your HUA XUAN YANG ELECTRONICS representative nearest you before using any HUA XUAN YANG ELECTRONICS products described or contained herein in such applications.

• HUA XUAN YANG ELECTRONICS assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all HUA XUAN YANG ELECTRONICS products described or contained herein.

• Specifications of any and all HUA XUAN YANG ELECTRONICS products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.

■ HUA XUAN YANG ELECTRONICS CO.,LTD. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could

give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.

• In the event that any or all HUA XUAN YANG ELECTRONICS products(including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.

• No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of HUA XUAN YANG ELECTRONICS CO.,LTD.

Information (including circuit diagrams and circuit parameters) herein is for example only ; it is not guaranteed for volume production.
HUA XUAN YANG ELECTRONICS believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the HUA XUAN YANG ELECTRONICS product that you intend to use.

# **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Bridge Rectifiers category:

Click to view products by HXY MOS manufacturer:

Other Similar products are found below :

 MB2510
 MB252
 MB356G
 MB358G
 GBJ1504-BP
 GBU10B-BP
 GBU15K-BP
 GBU4A-BP
 GBU4D-BP
 GBU6B-E3/45
 DB101-BP
 DF01

 DF10SA-E345
 BU1508-E3/45
 BU1510-E3/45
 KBPC50-10S
 RS405GL-BP
 GBJ1502-BP
 GBU6M
 GSIB1520-E3/45
 36MB140A
 TB102M

 MB1510
 MB86
 TL401G
 MDA920A2
 TU602
 TU810
 MP5010W-BP
 MP501W-BP
 MP502-BP
 BR84DTP204
 BU1508-E3/51
 KBPC25-02

 VS-110MT120KPBF
 VS-60MT120KPBF
 VS-60MT80KPBF
 DB105-BP
 DF1510S
 VS-40MT160PAPBF
 VISKBU8K-E4/51

 36MT100
 GBU4G-BP
 GBU6B-E3/51
 DF15005S-E3/77
 GSIB15A80-E3/45
 DB104-BP
 D3SB60
 TB354