



# Si-MMIC-Amplifier in SIEGET® 25-Technologie

- Cascadable 50 Ω-gain block
- Unconditionally stable
- Gain  $|S_{21}|^2 = 13$  dB at 1.8 GHz  $IP_{3out} = +13$  dBm at 1.8 GHz  $(V_D = 3 \text{ V}, I_D = \text{typ. 6.7 mA})$
- Noise figure NF = 2.2 dB at 1.8 GHz
- Reverse isolation > 28 dB and return loss IN / OUT > 12 dB at 1.8 GHz
- Pb-free (RoHS compliant) package



**Circuit Diagram** 





#### ESD (Electrostatic discharge) sensitive device, observe handling precaution!

Туре	Marking		Pin Conf	figuration	1	Package
BGA420	BLs	1, IN	2, GND	3, OUT	4, VD	SOT343

### **Maximum Ratings**

Parameter	Symbol	Value	Unit
Device current	I <sub>D</sub>	15	mA
Device voltage	$V_{D}$	6	V
Total power dissipation	P <sub>tot</sub>	90	mW
<i>T</i> <sub>S</sub> = 110 °C			
RF input power	$P_{RFin}$	0	dBm
Junction temperature	$T_{\rm j}$	150	°C
Ambient temperature	T <sub>A</sub>	-65 <b>1</b> 50	
Storage temperature	T <sub>stg</sub>	-65 150	

#### Junction - soldering point<sup>1)</sup>

**Thermal Resistance** 

K/W

≤ 410

 $R_{thJS}$ 


 $<sup>^{1}</sup>$ For calculation of  $R_{\mathrm{thJA}}$  please refer to Application Note Thermal Resistance



**Electrical Characteristics** at  $T_{\rm A}$  = 25 °C, unless otherwise specified.

Parameter	Symbol		Values		Unit
		min.	typ.	max.	
<b>AC</b> characteristics $V_D = 3 V$ , $Z_0 = 50 \Omega$	·				
Device current	$I_{D}$	5.4	6.7	8	mA
Insertion power gain	$ S_{21} ^2$				dB
f = 0.1 GHz		17	19	_	
f = 1 GHz		15	17	_	
f = 1.8 GHz		11	13	-	
Reverse isolation	S12	25	28	-	
<i>f</i> = 1.8 GHz					
Noise figure	NF				
f = 0.1 GHz		-	1.9	2.3	
f = 1 GHz		-	2.2	2.6	
f = 1.8 GHz		-	2.3	2.7	
Intercept point at the output	IP <sub>3out</sub>	10	13	-	dBm
f = 1 GHz	D	-6	-2.5	_	
1dB compression point f = 1 GHz	$P_{-1dB}$	-0	-2.5	_	
Return loss input	<i>RL</i> <sub>in</sub>	8	11	_	dB
f = 1.8 GHz	/ <b>`~</b> IN				
Return loss output	RLout	12	16	-	
<i>f</i> = 1.8 GHz					

### Typical biasing configuration



Note: 1) Large-value capacitors should be connected from pin 4 to ground right at the device to provide a low impedance path.

2) The use of plated through holes right at pin 2 is essential for pc-board-applications. Thin boards are recommended to minimize the parasitic inductance to ground.

2




Typical S-Parameters at  $T_{\rm A}$  = 25 °C

f	S <sub>11</sub>			S <sub>21</sub>		S <sub>12</sub>		S <sub>22</sub>
GHz	MAG	ANG	MAG	ANG	MAG	ANG	MAG	ANG
$V_{\rm D} = 3$	$3 \text{ V}, Z_0 = 50$	Ο Ω						
0.1	0.5686	-8.5	9.314	170.6	0.0268	12.7	0.2808	-8.6
0.5	0.5066	-19.2	8.393	149.4	0.0248	11.7	0.2613	-3.8
8.0	0.4404	-28.7	7.352	135.2	0.0236	25.6	0.2361	-6.7
1	0.3904	-34.6	6.69	126.8	0.024	35.9	0.2144	-9
1.5	0.2841	-50.5	5.244	111.1	0.0314	57.2	0.1398	-15
1.8	0.2343	-60.6	4.567	104	0.0378	63.5	0.0979	-18.2
1.9	0.2136	-64.1	4.355	102	0.0406	66.1	0.0838	-21.5
2	0.2062	-68.4	4.165	99.7	0.0426	67.2	0.0689	-22.2
2.4	0.1688	-89.7	3.417	91.7	0.0549	71.4	0.0224	-48
3	0.1558	-104.9	2.861	85.3	0.0682	73.1	0.0284	-147.5

3

## Spice-model BGA 420



T1	T501
R <sub>1</sub>	14.5kΩ
$R_2$	140Ω
R <sub>3</sub>	2.4kΩ
C <sub>1</sub>	2.3pF
C <sub>P1</sub>	0.2pF
C <sub>P2</sub>	0.2pF
C <sub>P2</sub>	0.6pF
C <sub>P4</sub>	0.1pF



#### Transistor Chip Data T1 (Berkley-SPICE 2G.6 Syntax) :


IS =	0.21024	fA	BF =	83.23	-	NF =	1.0405	-
VAF =	39.251	V	IKF =	0.16493	Α	ISE =	15.761	fA
NE =	1.7763	-	BR =	10.526	-	NR =	0.96647	-
VAR =	34.368	V	IKR =	0.25052	Α	ISC =	0.037223	fA
NC =	1.3152	-	RB =	15	$\Omega$	IRB =	0.21215	Α
RBM =	1.3491	$\Omega$	RE =	1.9289		RC =	0.12691	Ω
CJE =	3.7265	fF	VJE =	0.70367	V	MJE =	0.37747	-
TF =	4.5899	ps	XTF =	0.3641	-	VTF =	0.19762	V
ITF =	1.3364	mA	PTF =	0	deg	CJC =	96.941	fF
VJC =	0.99532	V	MJC =	0.48652	-	XCJC =	0.08161	-
TR =	1.4935	ns	CJS =	0	fF	VJS =	0.75	V
MJS =	0	-	XTB =	0	-	EG =	1.11	eV
XTI =	3	-	FC =	0.99469	_	TNOM	300	K

#### C'-E'-Diode Data (Berkley-SPICE 2G.6 Syntax) :

|--|

All parameters are ready to use, no scaling is necessary

#### Package Equivalent Circuit:



Extracted on behalf of Infineon Technologies AG by: Institut für Mobil-und Satellitentechnik (IMST)


For examples and ready to use parameters please contact your local Infineon Technologies distributor or sales office to obtain a Infineon Technologies CD-ROM or see Internet: http://www.infineon.com/silicondiscretes

4




# Insertion power gain $|S_{21}|^2 = f(f)$

## $V_{\rm D}$ , $I_{\rm D}$ = parameter



### Noise figure NF = f(f)


# $V_{\rm D}$ , $I_{\rm D}$ = parameter



# Insertion power gain $|S_{21}|^2 = f(f)$

$$V_{\rm D} = 3 \, {\rm V}$$


 $T_A$  = parameter



## Noise figure NF = f(f)

$$V_D = 3V$$

 $T_A$  = parameter






## Intercept point at the output

$$IP_{3out} = f(f)$$


 $V_{\rm D}$ ,  $I_{\rm D}$  = parameter



## Intercept point at the output

$$IP_{3out} = f(f), V_D = 3V$$

$$T_A$$
 = parameter




2011-07-26


6




### Package Outline








#### Foot Print




### Marking Layout (Example)



## Standard Packing

Reel ø180 mm = 3.000 Pieces/Reel Reel ø330 mm = 10.000 Pieces/Reel





#### Edition 2009-11-16

Published by Infineon Technologies AG 81726 Munich, Germany

© 2009 Infineon Technologies AG All Rights Reserved.

#### **Legal Disclaimer**

The information given in this document shall in no event be regarded as a guarantee of conditions or characteristics. With respect to any examples or hints given herein, any typical values stated herein and/or any information regarding the application of the device, Infineon Technologies hereby disclaims any and all warranties and liabilities of any kind, including without limitation, warranties of non-infringement of intellectual property rights of any third party.

#### Information

For further information on technology, delivery terms and conditions and prices, please contact the nearest Infineon Technologies Office (<a href="www.infineon.com">www.infineon.com</a>).

#### Warnings

Due to technical requirements, components may contain dangerous substances. For information on the types in question, please contact the nearest Infineon Technologies Office.

Infineon Technologies components may be used in life-support devices or systems only with the express written approval of Infineon Technologies, if a failure of such components can reasonably be expected to cause the failure of that life-support device or system or to affect the safety or effectiveness of that device or system. Life support devices or systems are intended to be implanted in the human body or to support and/or maintain and sustain and/or protect human life. If they fail, it is reasonable to assume that the health of the user or other persons may be endangered.

8

# **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

Click to view similar products for RF Amplifier category:

Click to view products by Infineon manufacturer:

Other Similar products are found below:

A82-1 BGA622H6820XTSA1 BGA 728L7 E6327 BGB719N7ESDE6327XTMA1 HMC397-SX HMC405 HMC561-SX HMC8120-SX HMC8121-SX HMC-ALH382-SX HMC-ALH476-SX SE2433T-R SMA3101-TL-E SMA39 A66-1 A66-3 A67-1 LX5535LQ LX5540LL MAAM02350 HMC3653LP3BETR HMC549MS8GETR HMC-ALH435-SX SMA101 SMA32 SMA411 SMA531 SST12LP17E-XX8E SST12LP19E-QX6E WPM0510A HMC5929LS6TR HMC5879LS7TR HMC1126 HMC1087F10 HMC1086 HMC1016 SMA1212 MAX2689EWS+T MAAMSS0041TR MAAM37000-A1G LTC6430AIUF-15#PBF CHA5115-QDG SMA70-2 SMA4011 A231 HMC-AUH232 LX5511LQ LX5511LQ-TR HMC7441-SX HMC-ALH310