

600 W Half-Bridge LLC evaluation board

EVAL_600W_LLC_12V_C7_D
digital & analog



Table of contents

1

General description

2

Efficiency results

3

Design concept

General

Description:

The “**EVAL_600W_LLC_12V_C7**” - evaluation board shows how to design a Half-Bridge LLC stage of a server SMPS with the target to meet 80+ Titanium standard efficiency requirements. On this purpose there has been applied latest CoolMOS™ technology [IPP60R180C7](#) 600 V power MOSFET on the primary side and OptiMOS™ low voltage power MOSFET in SuperSO8 [BSC010N04LS](#) in the synchronous rectification secondary stage, in combination with QR CoolSET™ [ICE2QR2280Z](#), hi-low side driver [2EDL05N06PF](#), low-side Gate Driver [2EDN7524F](#) and a LLC Controller [ICE2HS01G](#) for the analog or [XMC4200](#) in the digital version.

Summary of features:

- › Output voltage: 12 V
- › Output current: 50 A
- › Efficiency @ 10% load > 95%
- › Peak efficiency @ 50% load > 97,8%



The following variants are available:

- › 600W 12V LLC **analog** version with CoolMOS™ C7, [IPP60R180C7](#), EVAL_600W_LLC_12V_C7
- › 600W 12V LLC **digital** version with CoolMOS™ C7, [IPP60R180C7](#), EVAL_600W_LLC_12V_C7_D

Example of system understanding: Infineon demo solution for Titanium HV DC/DC stage



Half-Bridge LLC with synchronous rectification in center tap configuration

V_{in}	350-410 V _{DC}
V_{in_nom}	380 V _{DC}
V_{out_nom}	12 V _{DC}
I_{out}	50 A
P_o	600 W
$f_{res}=f_0$	157 kHz
f_{min}	90 kHz
f_{max}	210 kHz
Transformer turns ratio	16:1
C_r	66 nF
L_r	15.5 uH
L_m	195 uH

Primary HV MOSFETs

CoolMOS™ IPP60R180C7

Reduced gate charge (Q_g)

- › Reduced E_{off}
- › High body diode ruggedness

SR MOSFETs

OptiMOS™ BSC010N04LS

New generation

- › Best FOM $R_{DS(on)} \times Q_g$
- › Best FOM $R_{DS(on)} \times Q_{oss}$

HB Gate Drive IC

2EDL05N06PF

Non isolated LS Gate Drive

2EDN7524F

LLC controller


Digital **XMC4200** / Analog **ICE2HS01G**

Bias QR Flyback controller

ICE2QR2280Z

SR MOSFETs

BSC010N04LS



Resonant inductor
RM12 core


Transformer
PQ35/35 core

Control board analog & digital

Two possible solution to control Infineon's 600 W LLC evaluation board


Analog - ICE2HS01G

- › Resonant mode controller for Half-Bridge LLC resonant converter with synchronous rectification drives
- › Driving signal for synchronous rectification which support full operation of Half-Bridge LLC resonant converter
- › 20-pin DSO package
- › 30 kHz to 1MHz switching frequency
- › 50% duty cycle for both primary and secondary gate drives
- › Adjustable dead time with high accuracy




Digital - XMC4200-Q48K256 AB


- › ARM® Cortex®-M4, 80 MHz, incl. single cycle DSP MAC and floating point unit (FPU)
- › 8-channel DMA + dedicated DMA for USB
- › USB 2.0 full-speed device
- › CPU Frequency: 80 MHz
- › eFlash: 256 kB including hardware ECC
- › 40 kB SRAM
- › Package: PG-LQFP-48




PCB boards layout: main power board and control and bias daughter boards




Main power board schematic (digital)




Bias board schematic





Analog control board schematic




Digital control board schematic



PCB structure



PCB-Stackup



The diagram illustrates the stackup of the PCB, showing the sequence of layers from bottom to top:

- Layer 1: Green
- Layer 2: Red
- Layer 15: Green
- Layer 16: Red

Nr	Copper	Isolation
1	0.07mm	0.15mm
2	0.07mm	0.93mm
15	0.07mm	0.15mm
16	0.07mm	

Gesamt: 1.51mm

BOM (rework from digital to analog)

Part	Value	Pcs	Tolerance	Device	Package	Description	Assembling info	Supplier
C3	470n/50V	1		C-EU_C0805	C0805	CAPACITOR	Replace 10n/50V with 470n/50V	
R19	4K3	1	$\pm 1\%$	R-EU_R0805	R0805	RESISTOR	Replace 330R with 4K3	
R20	4K3	1	$\pm 1\%$	R-EU_R0805	R0805	RESISTOR	Replace 330R with 4K3	
R36	56R	1	$\pm 1\%$	R-EU_R0805	R0805	RESISTOR	Assemble n.a. with 56R	
IC1	Board	1		Board	PCB	Analog_Controlcard		IFX





Table of contents

- I General description
- II Efficiency results
- III Design concept


Automated efficiency measurement

**Combination of converter design
(resonant tank, transformer) and
proper HV device election**

**Proper selection of SR LV device and
secondary side**



- › Output voltage: 12 V_{DC}
- › Output current: 50 A
- › Efficiency: > 95% @ 10% load, V_{in} = 380 V_{DC}
- › Efficiency max: 97.8%, V_{in} = 380 V_{DC}



0.1% Total accuracy

Table of contents

1

General description

2

Efficiency results

3

Design concept

Design procedure: input data

$$n = \frac{V_{in_nom}}{2 \cdot V_{out_nom}}$$

$$M_{\min} \equiv K_{\min}(Q, m, F_x) = \frac{n \cdot V_{o_min}}{\overbrace{V_{in_max}}^2}$$

$$M_{\max} \equiv K_{\max}(Q, m, F_x) = \frac{n \cdot V_{o_max}}{\overbrace{V_{in_min}}^2}$$


Resonant tank components and related resonant frequencies

- › $n = V_{in_nom} / (2 \times V_o) = 380 / (2 * 12) \approx 16$
- › $L_m = 195 \mu H$
- › $L_r = 15.5 \mu H$
- › $L_n = L_m / L_r = 12.5$
- › $C_r = 66 nF$

$$f_o = \frac{1}{2\pi \cdot \sqrt{L_r \cdot C_r}} = 157 kHz$$

$$f_p = \frac{1}{2\pi \cdot \sqrt{(L_r + L_m) \cdot C_r}} = 42.7 kHz$$

Gain curves



Energy related calculations (Ref. IPP60R180C7 device parameters)


$$I_{mag_min} = \frac{2 \cdot \sqrt{2}}{\pi} \cdot \frac{n \cdot V_o}{2\pi \cdot f_{sw_max} \cdot L_m} = 0.672 \text{ A}$$

$$En_{res_min} = \frac{1}{2} \cdot (L_m + L_r) \cdot I^2_{mag_min} = 95.1 \mu J$$

$\Rightarrow En_{res_min} > En_{cap_max}$

$$En_{cap_max} = \frac{1}{2} \cdot (2Co(er)) \cdot V^2_{DS_max} \approx 9 \mu J$$

Q_{oss} , $I_{mag,pk}$, $t_{dead,min}$, t_{ecs} relationship



Time related calculations (Ref. IPP60R180C7 device parameters)

$$I_{mag_min} = \frac{2 \cdot \sqrt{2}}{\pi} \cdot \frac{n \cdot V_o}{2\pi \cdot f_{sw_max} \cdot L_m} = 0.672 \text{ A}$$

$$I_{mag_max} = \frac{2 \cdot \sqrt{2}}{\pi} \cdot \frac{n \cdot V_o}{2\pi \cdot f_{sw_min} \cdot L_m} = 1.66 \text{ A}$$

$$t_{dead, min} = \frac{t_{ecs}}{2} + \frac{2 \cdot Q_{oss, @ 400V}}{I_{mag, max}} \approx 130 \text{ nsec}$$

$$t_{dead, max} = \frac{t_{ecs}}{2} + \frac{2 \cdot Q_{oss, @ 400V}}{I_{mag, min}} \approx 311 \text{ nsec}$$

Main transformer structure: PQ35/35 core with TDK PC95 ferrite material

Wind.	Conductor	N°. of Turns	Rope	Output pin	Winding layer	N° layer	Sleeves			Notes																																															
							Col.	Ref. M.L.	Total length mm.		Free length mm.																																														
N1a	2xLitz 90x0.10 Ref.3	0 8	+	2-3 +	8	1	Re Re	8 8	20 20	/ /	2 wires in 1 sleeve.																																														
Insulation: 3 turns of polyester adhesive tape Ref.6																																																									
N2	Copper foil 0.50x0.20 Ref.4	0 1	+	A C	1	1	/ /	/ /	67	60	Taping the exits with 3 turn of kapton ref.9																																														
N3							/ /	/ /																																																	
Insulation: 1 turns of polyester adhesive tape Ref.6 + 1 piece as showed in pictures																																																									
N1b	2xLitz 90x0.10 Ref.3	0 8	+	* 4-5	8	1	Re	8	20	/	2 wires in 1 sleeve. Don't need correspondence																																														
Insulation: 3 turns of polyester adhesive tape Ref.6																																																									
<p>Insert piece of tape after the insulation of N2-N3. Wind N1b. Refold tape, block and connect the wires to pin</p>																																																									
Positioning coilformer - pin side				Bottom view				Electrical diagram																																																	
<p>Smooth the inner part</p>				<p>Remove</p>																																																					
<p>Copper foil preparation</p> <p>tinned</p> <p>Dimensions: 23, 17, 6, 67, 60, 10, 145</p> <p>Annotations: A, B, C, 4, 6, 7, 9</p> <p>Text: Taping the exits with 3 turn of kapton ref.9 Solder the exits A-B-C ref. 5 on copper foil ref.4 Insulate the foil with tape ref.7 and the welding with tape ref.6</p>																																																									
<p>finished part</p>																																																									
<table border="1"> <tr> <td>J.</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> <tr> <td>C.</td> <td>02 21.07.15</td> <td>Inserted label and pictures</td> <td>C. Picciani</td> <td>D. Di Giorgio</td> </tr> <tr> <td>E.</td> <td>01 24.01.14</td> <td>Release</td> <td>C. Picciani</td> <td>D. Di Giorgio</td> </tr> <tr> <td colspan="2">REV APPR DATE</td> <td>REF. MOD.</td> <td colspan="2">DESCRIPTION OF MODIFICATION</td> <td>EDITING</td> <td>CHECKING AND APPROVAL</td> </tr> <tr> <td colspan="2">TRANSFORMERS</td> <td>Mod. AQ 05.09</td> <td colspan="2">Trasformatore PQ35/35 600W LLC converter (130705)</td> <td></td> <td></td> </tr> <tr> <td colspan="2">DESCRIPTION</td> <td>DOCUMENT TYPE</td> <td>CODE</td> <td>REVISION</td> <td>RELEASE DATE</td> <td>PAGE</td> </tr> <tr> <td colspan="2"></td> <td>P.F.</td> <td>8065.0703.001</td> <td>02</td> <td>24.01.14</td> <td>1 of 2</td> </tr> </table>												J.								C.	02 21.07.15	Inserted label and pictures	C. Picciani	D. Di Giorgio	E.	01 24.01.14	Release	C. Picciani	D. Di Giorgio	REV APPR DATE		REF. MOD.	DESCRIPTION OF MODIFICATION		EDITING	CHECKING AND APPROVAL	TRANSFORMERS		Mod. AQ 05.09	Trasformatore PQ35/35 600W LLC converter (130705)				DESCRIPTION		DOCUMENT TYPE	CODE	REVISION	RELEASE DATE	PAGE			P.F.	8065.0703.001	02	24.01.14	1 of 2
J.																																																									
C.	02 21.07.15	Inserted label and pictures	C. Picciani	D. Di Giorgio																																																					
E.	01 24.01.14	Release	C. Picciani	D. Di Giorgio																																																					
REV APPR DATE		REF. MOD.	DESCRIPTION OF MODIFICATION		EDITING	CHECKING AND APPROVAL																																																			
TRANSFORMERS		Mod. AQ 05.09	Trasformatore PQ35/35 600W LLC converter (130705)																																																						
DESCRIPTION		DOCUMENT TYPE	CODE	REVISION	RELEASE DATE	PAGE																																																			
		P.F.	8065.0703.001	02	24.01.14	1 of 2																																																			

Resonant choke:

RM12 core, material N87

Wind.	Conductor type	N. of windings	R otat ion	output pin	Winding Layer	N. of Layer	Tube			Notes
							Color	Ref.	Length mm	
N1	Litz 120x0.10 Ref. 4	0 9	+	7+8+9 10+11	9	1	/ Red	/ 6	/ 20	Perpendicular crossing on tape ref.5
Insulation: 2 turns polyester tape Ref.5										

Bill of materials	
Ref.	Description
1	Coil Former RM12 12pins (B65816-C1512-T1 Epcos mat.Valox420 E45329)
2	Ferrite core RM12 gap 1.1mm (B65815-R87 Epcos)
3	RM12 clamp (B65816-A2002 Epcos)
4	Litz wire 120x0.100mm G1 (155°C E125660 or equivalent)
5	Polyester adhesive tape H=16mm thickness 0.06mm (P31 E178430 or equivalent)
6	Tube glass/silicone Ø1.5mm 4KV 20mm (GVES2500 E311983 or equivalent)
7	Activator for epoxy resin (IN1005 or equivalent)
8	Epoxy resin (36T or equivalent)
9	PVC label 24x12mm
10	Insulating varnish classH (AC43 E317427 or equivalent)
11	Polyestere label 4.7x14mm (7816 MH16411 or equivalent)

Winding rotation	Bottom View	Electrical drawing

* Serial number
ICEAANNNN * ⑪

max 25.5 - 4.8-0.3

33.02

Fix core/coilformer with ref. 7+8

0.8

max 46

5x5.08

max 41

ICEE 130521 www.ketronformers.com


Varnish with ref.10

Dimensions in millimeter
RoHS compliant

Electrical test		
N°	Test type	Test conditions
1	Inductance	7+8+9-10+11 @ 10 kHz - 100 mV from 11.9 to 16.1 µH

I.	02 21.07.15	Inserted new label	C. Picciani	D. Di Giorgio			
C.	01 23.01.14	Release	C. Picciani	D. Di Giorgio			
E.	REV	Appr. date	Ref. Mod.	Modification description	Editing	Checked and Approved	
DESCRIPTION Inductance RM12 LLC resonant choke (130521)							
TRANSFORMERS		Mod.	DOCUMENT TYPE	CODE	REVISION	EMISSION DATE	PAGE
		AQ 05.09	P.F.	8017.0901.012	02	23.01.14	1 of 1

Evaluation board EVAL_600W_12V_LLC_C7



Support slides

600W LLC evaluation board



Evaluation board page

- Technical description
- Datasheets
- Parameters
- Related material
- Videos

The screenshot shows the Infineon website product page for the EVAL_600W_12V_LLC_C7. It includes sections for Description, Summary of Features, Benefits, and a Selection Finder tool.

[EVAL 600W 12V LLC C7](#)

Product family pages

- Product brief
- Application notes
- Selection guides
- Datasheets and portfolio
- Videos
- Simulation models

The screenshot shows the Infineon website product family page for the 600V CoolMOS™ C7. It includes sections for the product brief, selection guides, and other resources.

- [650V CoolMOS™ C7](#)
- [XMC 32-Bit Industrial Microcontroller](#)
- [Resonant Mode Controller](#)
- [OptiMOS™ 5 40V and 60V](#)





Part of your life. Part of tomorrow.



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Power Management IC Development Tools category:

Click to view products by Infineon manufacturer:

Other Similar products are found below :

[EVB-EP5348UI](#) [MIC23451-AAAYFL EV](#) [MIC5281YMME EV](#) [124352-HMC860LP3E](#) [DA9063-EVAL](#) [ADP122-3.3-EVALZ](#) [ADP130-0.8-EVALZ](#) [ADP130-1.8-EVALZ](#) [ADP1740-1.5-EVALZ](#) [ADP1870-0.3-EVALZ](#) [ADP1874-0.3-EVALZ](#) [ADP199CB-EVALZ](#) [ADP2102-1.25-EVALZ](#) [ADP2102-1.875EVALZ](#) [ADP2102-1.8-EVALZ](#) [ADP2102-2-EVALZ](#) [ADP2102-3-EVALZ](#) [ADP2102-4-EVALZ](#) [AS3606-DB](#) [BQ25010EVM](#) [BQ3055EVM](#) [ISLUSBI2CKIT1Z](#) [LM2734YEVAL](#) [LP38512TS-1.8EV](#) [EVAL-ADM1186-1MBZ](#) [EVAL-ADM1186-2MBZ](#) [ADP122UJZ-REDYKIT](#) [ADP166Z-REDYKIT](#) [ADP170-1.8-EVALZ](#) [ADP171-EVALZ](#) [ADP1853-EVALZ](#) [ADP1873-0.3-EVALZ](#) [ADP198CP-EVALZ](#) [ADP2102-1.0-EVALZ](#) [ADP2102-1-EVALZ](#) [ADP2107-1.8-EVALZ](#) [ADP5020CP-EVALZ](#) [CC-ACC-DBMX-51](#) [ATPL230A-EK](#) [MIC23250-S4YMT EV](#) [MIC26603YJL EV](#) [MIC33050-SYHL EV](#) [TPS60100EVM-131](#) [TPS65010EVM-230](#) [TPS71933-28EVM-213](#) [TPS72728YFFEVM-407](#) [TPS79318YEQEVM](#) [UCC28810EVM-002](#) [XILINXPWR-083](#) [LMR22007YMINI-EVM](#)