

## **FEATURES**

New!!!

- 300 watts Maximum power
- Operates in Constant current, Constant resistance or Constant power modes
- 1mA current setting resolution
- Voltage, Current and Power are displayed on the back lit display
- Back light LCD
- Values may be enter from key board of rotary dial
- RS232 interface and control software
- Small size and light weight

## **SPECIFICATIONS**

Inputs	1
Input Volts	0 to 360V
Input Current	0 to 30A
Input Power	0 to 300W
Operating Modes	Constant current, Constant Resistance or Constant power
Voltage Resolutions	0.000V to 3.999V ±(0.2% +3mV)
	4.00V to 35.999V ±(0.2% +30mV)
	36.0V to 360.0V ±(0.2% +30mV)
Current Resolutions	0.000A to 2.999A ±(0.2% +3mA)
	3.00A to 35.999 A ±(0.2% +3mA)
Current Setting Resolution	1mA (0 to 2.999A), 10mA (3.00A to 30A)
Power Setting Resolution	0.1W (0 to 300W)
Resistance Setting Resolution	$0.01\Omega$ (0 to 99.99Ω), $0.1\Omega$ (100 to $500\Omega$ )
Minimum Resistance	< 0.08Ω
Ripple	< 10mV p-p
Protection	Over Voltage, Over Current, Over power, Over Heating and Reverse polarity
Power	120/220V, 50/60 Hz
Communication	RS232 or RS485
Memory	10 setups may be stored and recalled
Software	Monitor software CD.
	Active X modules for VC++, Visual basic, Delphi and Lab View upon request
Size	3.5 H x 8.3 W x 9.8 D (inches)
Weight	11 lbs
Accessories	RS232 cable, Control software, RS232 adapter, Manual, AC line cord. Rack mounting
	brackets and hardware.



## **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Bridge Rectifiers category:

Click to view products by IXYS manufacturer:

Other Similar products are found below:

G3SBA60-E351 GBJ1504-BP GBU10B-BP GBU15J-BP GBU15K-BP GBU4A-BP GBU4D-BP GBU6B-E3/45 GSIB680-E3/45 DB101-BP DBA100G DBA150G DBA20G DBA250G DBA40G DBD10G-TM-E DBF10G DBF250G DBG150G DBG250G DF10SA-E345 RMB2S RCG APT30DF100HJ APT60DF20HJ B2S-E3/80 BU1506-E351 BU15085S-E345 BU1508-E3/45 BU1510-E3/45 RS404GL-BP RS405GL-BP G3SBA20-E3/51 G5SBA20-E3/51 G5SBA60-E3/51 GBJ1502-BP GBL02-E3/51 GBL10-E3/45 GBU10J-BP GBU4J-BP GBU4K-BP GBU8B-E3/45 GBU8D-BP GBU8J-BP GSIB1520-E3/45 MB1510 MB352W MB6M-G B2M-E345 B40C7000A B500C7000A