


#### 1. Introduction



UV click<sup>™</sup> is a simple solution for adding an ultraviolet light sensor to your design. It carries the ML8511 IC UV sensor with analog voltage output and a MCP3201 ADC. UV click<sup>™</sup> can output either analog or digital signals (determined by the position of the A/D SEL jumper). Therefore, it communicates with the target board either through **mikroBUS**<sup>™</sup> SPI (CS, SCK, MISO), or AN lines; additionally, the sensor can be enabled or disabled from the MCU through the RST (EN) pin. UV click<sup>™</sup> uses a 3.3V power supply.

# 2. Soldering the headers

Before using your click<sup>™</sup> board, make sure to solder 1x8 male headers to both left and right side of the board. Two 1x8 male headers are included with the board in the package.






Turn the board upside down so that the bottom side is facing you upwards. Place shorter pins of the header into the appropriate soldering pads.



Turn the board upward again. Make sure to align the headers so that they are perpendicular to the board, then solder the pins carefully.



## 4. Essential features

With UV click", you can measure ultraviolet light intensity both indoors and outdoors. The photodiode on the ML8511 IC is sensitive to UV-A (365-315 nm) and UV-B (315-280 nm) rays. You can use UV click" to design devices that protect the user against excesive sun exposure, or for industrial purposes where UV light is used for sterilization. When using UV click", be careful not to rub or press the surface of the ML8511 IC.




3. Plugging the board in


Once you have soldered the headers your board is ready to be placed into the desired mikroBUS<sup>TM</sup> socket. Make sure to align the cut in the lower-right part of the board with the markings on the silkscreen at the mikroBUS<sup>TM</sup> socket. If all the pins are aligned correctly, push the board all the way into the socket.



### 5. UV click™ board schematic



## 6. A/D SEL jumpers



To switch between analog and digital output options, resolder the onboard **J1** SMD jumper (zero-ohm resistor). By default, it's soldered in the ADC position.

# 7. Code examples

Once you have done all the necessary preparations, it's time to get your click<sup>™</sup> board up and running. We have provided examples for mikroC<sup>™</sup>, mikroBasic<sup>™</sup> and mikroPascal<sup>™</sup> compilers on our **Libstock** website. Just download them and you are ready to start.



## 8. Support

MikroElektronika offers **free tech support** (www.mikroe.com/support) until the end of the product's lifetime, so if something goes wrong, we're ready and willing to help!



# **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Optical Sensor Development Tools category:

Click to view products by MikroElektronika manufacturer:

Other Similar products are found below:

416015300-3 ISL29102IROZ-EVALZ TSL2581CS-DB TMD3700-DB NANOUSB2.2 MARS1-MAX9295A-GEVK MARS1-MAX9296B-GEVB ISL29112IROZ-EVALZ TCS3430-DB AR0130CSSM00SPCAH-GEVB AR0330CM1C00SHAAH3-GEVB EVALZ-ADPD2212

TMD2772EVM TMG3993EVM MIKROE-2103 TSL2672EVM 1384 SEN0043 SEN0162 TMD2771EVM TMD3782EVM TSL4531EVM

1918 AS7225 DEMO KIT SEN0097 SEN0228 AR0134CSSC00SUEAH3-GEVB AP0100AT2L00XUGAH3-GEVB 725-28915 SEN-14347

PIEZO-01 MIKROE-3330 MT9M114EBLSTCZD3-GEVK LF-9MT024NV-EVN SI1102EK 1334 1356 1777 1980 1981 2748 2899 3779

4162 4698 ALS-GEVB AS7263 DEMO KIT V3.0 AS7261 DEMO KIT V3.0 AS7264N DEMO KIT AS7265x Demo Kit Housing