

RTC 5 click



1. Introduction

RTC5 click carries MCP79510. a realtime clock/calendar with an SPI interface [mikroBUS[™] MISO, MOSI, SCK and CS pins] and a programmable interrupt for system output. The clock frequency is derived from an onboard 32.768KHz oscillator. For backup power, RTC5 click has a coincell Lithium polymer battery connector. The board is designed to use a 3.3V power supply only.

2. Soldering the headers

9

Before using your click board[™], make sure to solder 1x8 male headers to both left and right side of the board. Two 1x8 male headers are included with the board in the package.

Turn the board upside down so that

the bottom side is facing you upwards.

Place shorter pins of the header into the

appropriate soldering pads.







4. Essential features

For storing data, the chip onboard RTC5 click has 64-bytes of battery-backed SRAM and 1 kbit of EEPROM, along with 128 bits of protected space for storing a unique ID. The SPI interface has clock speeds of up to 5 MHz which is enough for a millisecond alarm. The clock/calendar automatically compensates for leap years and months shorter than 31 days. The interrupt pin can be used to set up alarms or events.

Turn the board upward again. Make sure to align the headers so that they are perpendicular to the board, then solder the pins carefully.



Once you have soldered the headers your board is ready to be placed into the desired mikroBUS[™] socket. Make sure to align the cut in the lower-right part of the board with the markings on the silkscreen at the mikroBUS™ socket. If all the pins are aligned correctly, push the board all the way into the socket.



5. Schematic



8. Code examples

Once you have done all the necessary preparations, it's time to get your click board[™] up and running. We have provided examples for mikroC[™], mikroBasic[™] and mikroPascal[™] compilers on our **Libstock** website. Just download them and you are ready to start.



9. Support

MikroElektronika offers **free tech support** (www.mikroe.com/support) until the end of the product's lifetime, so if something goes wrong, we're ready and willing to help!



6. Dimensions



	mm	mils
LENGTH	42.9	1690
WIDTH	25.4	1000
HEIGHT*	3.9	154

* without headers

7. RTC5 click[™] alternatives

RTC5 click, as the name implies, is the fifth click board[™] with a real time clock module. Visit the click board[™] page to see all available alternatives. Including RTC click which can also work on a 5V power supply.

www.mikroe.com/click

10. Disclaimer

MikroElektronika assumes no responsibility or liability for any errors or inaccuracies that may appear in the present document. Specification and information contained in the present schematic are subject to change at any time without notice.

Copyright © 2015 MikroElektronika. All rights reserved.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Clock & Timer Development Tools category:

Click to view products by MikroElektronika manufacturer:

Other Similar products are found below :

AD9530/PCBZ DSC400-0333Q0032KE1-EVB TDGL013 ADCLK946/PCBZ EKIT01-HMC1032LP6G RV-2251-C3-EVALUATION-BOARD RV-3029-C2-EVALUATION-BOARD-OPTION-B SKY72310-11-EVB EV1HMC6475LC4B EV1HMC8364LP6G EV1HMC8362LP6G RV-8263-C7-EVALUATION-BOARD EVK9FGV1002 EVK9FGV1008 EV1HMC6832ALP5L EVAL01-HMC911LC4B EVAL01-HMC987LP5E EVAL01-HMC988LP3E TS3002DB 125605-HMC702LP6CE MIKROE-2481 2045 EKIT01-HMC835LP6G EKIT01-HMC834LP6GE TS3006DB 105811-HMC440QS16G DSC-TIMEFLASH2-KIT1 110227-HMC510LP5 110227-HMC513LP5 AD9515/PCBZ AC164147 DFR0469 127102-HMC856LC5 127270-HMC765LP6CE 127272-HMC783LP6CE 127283-HMC807LP6CE 127900-HMC765LP6CE 129021-HMC838LP6CE ADM00791 DC2254A-B 3296 DC1959A-C DC2254A-A DC1562B-G DC2073A-G 129020-HMC838LP6CE 129467-HMC820LP6CE 129470-HMC821LP6CE 129472-HMC822LP6CE 129874-HMC910LC4B