

MIKROELEKTRONIKA D.O.O, Batajnički drum 23, 11000 Belgrade, Serbia VAT: SR105917343 Registration No. 20490918 Phone: + 381 11 78 57 600 Fax: + 381 11 63 09 644 E-mail: office@mikroe.com

www.mikroe.com

Charger 3 Click





PID: MIKROE-4449

Charger 3 Click is a compact add-on board that represents a standalone battery charger with thermal regulation. This board features the TP4056, a complete constant-current/constantvoltage linear charger for single-cell lithium-ion batteries from Nanling Top Power ASIC Corp. The charge voltage of the TP4056 is specified at 4.2V with the charge current programmable via an onboard digital potentiometer, automatically terminating the charge cycle when the charging current drops to 1/10th the programmed value. It also features current monitoring, under-voltage lockout, automatic recharge, and two LEDs to indicate charge termination and the presence of an input voltage. This Click board™ is a perfect solution for the development of multiple Li-ion battery cell charging applications.

Charger 3 Click is supported by a mikroSDK compliant library, which includes functions that simplify software development. This Click board™ comes as a fully tested product, ready to be used on a system equipped with the mikroBUS[™] socket.

How does it work?

Charger 3 Click is based on the TP4056, a complete constant-current/constant-voltage linear charger for single-cell lithium-ion batteries from NanJing Top Power ASIC Corp. This standalone battery charger automatically terminates the charge cycle when the charge current drops to 1/10th of the programmed value after reaching the final float voltage. Thermal feedback regulates the charging current to limit the die temperature during high power operation or high ambient temperature. It also features current monitoring, under-voltage lockout, automatic recharge, and two LEDs to indicate charge termination and the presence of an input voltage.

Mikroe produces entire development toolchains for all major microcontroller architectures. Committed to excellency, we are dedicated to helping engineers bring the project development up to speed and achieve outstanding results.







MIKROELEKTRONIKA D.O.O, Batajnički drum 23, 11000 Belgrade, Serbia VAT: SR105917343 Registration No. 20490918 Phone: + 381 11 78 57 600 Fax: + 381 11 63 09 644 E-mail: office@mikroe.com www.mikroe.com



The charge voltage of the TP4056 is specified at 4.2V with 1.5% accuracy, with the charge current pin programmable up to 1000mA via an onboard single-channel digital potentiometer, the AD5175 from Analog Devices, controllable through the I2C compatible digital interface. When the TP4056 is in a pre-charge mode, this pins voltage is regulated to 0.2V, while in constant-charge current mode voltage is regulated to 2V. During the charging process, the voltage on this pin can be used to measure the charge current.

Charger 3 Click has the possibility of connecting an external temperature sensor on the onboard header labeled as NTC. If the voltage of this pin is below 45% or above 80% of supply voltage for more than 0.15s, this means that the battery's temperature is too high or too low, suspending the charging process. Alongside this feature, this Click board™ also has two LEDs to indicate charge termination and the presence of an input voltage, red LED labeled as CHG indicating charging process, and green LED labeled as STB for 'charged' status.

This Click board™ is designed to operate with both 3.3V and 5V logic voltage levels selected via the VCC SEL jumper. It allows for both 3.3V and 5V capable MCUs to use the I2C communication lines properly. However, the Click board™ comes equipped with a library that contains functions and an example code that can be used, as a reference, for further development.

Specifications

Туре	Battery charger
Applications	Can be used for the development of multiple Li- ion battery cell charging applications
On-board modules	TP4056 - complete constant-current/constant- voltage linear charger for single-cell lithium- ion batteries from NanJing Top Power ASIC Corp AD5175 - single-channel digital potentiometer from Analog Devices
Key Features	Programmable charge current up to 1000mA, complete linear charger for single-cell Lithium-lon batteries, constant-current/constant-voltage, two charge status indicators, and more
Interface	I2C

Committed to excellency, we are dedicated to helping engineers bring the project development up to speed and achieve outstanding results.









MIKROELEKTRONIKA D.O.O, Batajnički drum 23, 11000 Belgrade, Serbia VAT: SR105917343 Registration No. 20490918
Phone: + 381 11 78 57 600 Fax: + 381 11 63 09 644 E-mail: office@mikroe.com

www.mikroe.com

Feature	No ClickID
Compatibility	mikroBUS™
Click board size	S (28.6 x 25.4 mm)
Input Voltage	3.3V or 5V

Pinout diagram

This table shows how the pinout on Charger 3 Click corresponds to the pinout on the mikroBUS™ socket (the latter shown in the two middle columns).

Notes	Pin	mikro™ BUS				Pin	Notes
	NC	1	AN	PWM	16	NC	
	NC	2	RST	INT	15	NC	
	NC	3	CS	RX	14	NC	
	NC	4	SCK	TX	13	NC	
	NC	5	MISO	SCL	12	SCL	I2C Clock
	NC	6	MOSI	SDA	11	SDA	I2C Data
Power Supply	3.3V	7	3.3V	5V	10	5V	Power Supply
Ground	GND	8	GND	GND	9	GND	Ground

Onboard settings and indicators

Label	Name	Default	Description
LD1	PWR	-	Power LED Indicator
LD2	CHG	-	Charging State LED Indicator
LD3	STB	-	Standby State LED Indicator
JP1	VCC SEL	Left	Logic Level Voltage Selection 3V3/5V: Left position 3V3, Right position 5V
J1	NTC	Populated	External Temperature Sensor Header

Charger 3 Click electrical specifications

Description	Min	Тур	Max	Unit
Supply Voltage	3.3	-	5	V
Battery Charge Current Range	130	-	1000	mA
Operating Temperature Range	-40	+25	+85	°C

Software Support

We provide a library for the Charger 3 Click as well as a demo application (example), developed using MikroElektronika compilers. The demo can run on all the main MikroElektronika development boards.

Package can be downloaded/installed directly from NECTO Studio Package

Mikroe produces entire development toolchains for all major microcontroller architectures.

Committed to excellency, we are dedicated to helping engineers bring the project development up to speed and achieve outstanding results.









MIKROELEKTRONIKA D.O.O, Batajnički drum 23, 11000 Belgrade, Serbia VAT: SR105917343 Registration No. 20490918

Phone: + 381 11 78 57 600 Fax: + 381 11 63 09 644 E-mail: office@mikroe.com www.mikroe.com

Manager(recommended way), downloaded from our LibStock™ or found on mikroE github account.

Library Description

This library contains API for Charger 3 Click driver.

Key functions:

- void charger3 cfg setup (charger3 cfg t *cfg); Config Object Initialization function.
- CHARGER3 RETVAL charger3 init (charger3 t *ctx, charger3 cfg t *cfg); Initialization function.
- void charger3 default cfg (charger3 t *ctx); Click Default Configuration function.

Examples description

This example demonstrates the utilization of Charger 3 Click.

The demo application is composed of two sections:

While the resistance of the AD5175 can be directly set and read, the total resistance value on the PROG pin should be accounted for (this means an additional 1kohm in series) setting of the battery charging current.

The full application code, and ready to use projects can be installed directly from NECTO Studio Package Manager(recommended way), downloaded from our LibStock™ or found on mikroE github account.

Other mikroE Libraries used in the example:

- MikroSDK.Board
- MikroSDK.Log
- Click.Charger3

Additional notes and informations

Depending on the development board you are using, you may need <u>USB UART click</u>, <u>USB UART</u> 2 click or RS232 click to connect to your PC, for development systems with no UART to USB interface available on the board. The terminal available in all MikroElektronika compilers, or any other terminal application of your choice, can be used to read the message.

mikroSDK


This Click board™ is supported with mikroSDK - MikroElektronika Software Development Kit. To ensure proper operation of mikroSDK compliant Click board[™] demo applications, mikroSDK should be downloaded from the LibStock and installed for the compiler you are using.

For more information about mikroSDK, visit the official page.

Mikroe produces entire development toolchains for all major microcontroller architectures.

Resources

mikroBUS™



ISO 14001: 2015 certification of environmental OHSAS 18001: 2008 certification of occupational health and safety management system.





MIKROELEKTRONIKA D.O.O, Batajnički drum 23, 11000 Belgrade, Serbia VAT: SR105917343 Registration No. 20490918

Phone: + 381 11 78 57 600 Fax: + 381 11 63 09 644 E-mail: office@mikroe.com www.mikroe.com

mikroSDK

Click board™ Catalog

Click boards™

Downloads

Charger 3 click 2D and 3D files

TP4056 datasheet

AD5175 datasheet

Charger 3 click schematic

Charger 3 click example on Libstock

Mikroe produces entire development toolchains for all major microcontroller architectures. Committed to excellency, we are dedicated to helping engineers bring the project development up to speed and achieve outstanding results.







health and safety management system.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Power Management IC Development Tools category:

Click to view products by MikroElektronika manufacturer:

Other Similar products are found below:

EVB-EP5348UI ISLUSBI2CKIT1Z ISL8002AEVAL1Z ISL91108IIA-EVZ NCP10671B05GEVB SAMPLEBOXILD8150TOBO1

AP61100Z6-EVM AP62300Z6-EVM BTS7030-2EPA TLT807B0EPV BTS71033-6ESA EV13N91A EV55W64A Si8285_86v2-KIT

AP33772S-EVB EVALM7HVIGBTPFCINV4TOBO1 ROA1286023/1 REFSHA35IMD111TSYSTOBO1 150037482 TDINV3000W50B
KIT NCP1681CCM1KWGEVB APEK89303KET-01-T NCP1681MM500WGEVB SI83401BAA-KIT SI83402BAA-KIT SI83411BAA-KIT

SI83412BAA-KIT MIKROE-5294 MIKROE-5451 MIKROE-5374 APEK49406GES-01-T AP61300QZ6-EVM MIKROE-5019

BTG70902EPLDAUGHBRDTOBO1 5650 TAB-48017 APEK89307KET-01-T MIKROE-5510 64010 EVAL6EDL04I065PRTOBO1

LT8648SJV#WPBF LT8648SEV#WPBF EVB81340-100W RTKA489EPRDK0010BU RB-TO2S2 RB-TSR1S2 RDP-02 RDP-11 AS-212

MCP1630RD-NMC1