

## The Big Deal

- Patented design eliminates in band spurs
- Pass band cut-off up to 21 GHz
- Stop band up to 35 GHz
- Excellent repeatability through IPD\* process



Available in Low Pass, High Pass and Band Pass designs

## **Product Overview**

Mini-Circuits' *X-Series* reflectionless filters employs a novel filter topology which absorbs and terminates stop band signals internally rather than reflecting them back to the source. This new capability enables unique applications for filter circuits beyond those suited to traditional approaches. Traditional filters are reflective in the stop band, sending signals back to the source at 100% of the power level which interact with neighboring components and often result in intermodulation and other interferences. Reflectionless filters eliminate stop band reflections, allowing them to be paired with sensitive devices and used in applications that otherwise require circuits such as isolation amplifiers or attenuators.

Key Features	Advantages
Easy integration with sensitive reflective components, e.g. mixers, multipliers	Reflectionless filters absorb unwanted signals, preventing reflections back to the source. This reduces generation of additional unwanted signals without the need for extra components like attenuators, improving system dynamic range and saving board space.
Enables stable integration of wideband amplifiers	Because reflectionless filters maintain good impedance in the stop band; they can be integrated with high gain, wideband amplifiers without the risk of creating instabilities in these out of band regions.
Cascadable	Reflectionless filters can be cascaded in multiple sections to provide sharper and higher attenuation, while also preventing any standing waves that could affect pass band signals.
Excellent power handling in a tiny surface mount device	High power handling extends the usability of these filters to the transmit path for inter-stage filtering.
Small size, 3x3mm QFN	Allows replacement of filter/attenuator pairs with a single reflectionless filter, sav- ing board space.
Excellent repeatability of RF performance	Through semiconductor IPD process, X-series filters are inherently repeatable for large volume production.
Excellent stability over temperature	With $\pm 0.3$ dB variation over temperature ideal for use in wide temperature range applications without the need for additional temperature compensation.
Operating temperature up to 105°C	Suitable for operation close to high power components.

\*IPD - Integrated Passive Device, is a GaAs semiconductor process

# Reflectionless Low Pass Filter

50Ω DC to 7600 MHz

#### Features

- $\bullet$  Match to 50  $\!\Omega$  in the stop band, eliminates undesired reflections
- Cascadable
- Excellent Power handling
- Temperature stable, up to 105°C
- Small size, 3 x 3 mm
- Protected by US Patent No. 8,392,495

### Applications

- Harmonics Rejection
- Satellite
- Radar
- Military & Space

## **General Description**



Generic nhoto used for illustration numoses onl

CASE STYLE: DQ1225


XLF-762+


Available Tape and Reel at no extra cost					
Reel Size	Devices/Reel				
7"	20, 50, 100, 200, 500, 1000, 2000				

Mini-Circuits' XLF-762+ reflectionless filter employs a novel filter topology which absorbs and terminates stop band signals internally rather than reflecting them back to the source. This new capability enables unique applications for filter circuits beyond those suited to traditional approaches. Traditional filters are reflective in the stop band, sending signals back to the source at 100% of the power level. These reflections interact with neighboring components and often result in inter-modulation and other interferences. Reflectionless filters eliminate stop band reflections, allowing them to be paired with sensitive devices and used in applications that otherwise require circuits such as isolation amplifiers or attenuators.

OUT

### simplified schematic and pad description





Function	Pad Number	Description
RF-IN	2	RF Input Pad
RF-OUT	8	RF Output Pad
GND	1,3,7,9, Paddle	Connected to ground
NC (GND Externally)	4,5,6,10,11,12	No internal connection



## Electrical Specifications<sup>1</sup> at 25°C

Pa	rameter	F#	Frequency (MHz)	Min.	Тур.	Max.	Unit
Pass Band	Insertion Loss Frequency Cut-off	DC - F1 F2	DC - 7600 11000	_	1.1 3.0	1.6 —	dB dB
	VSWR	DC - F1	DC - 7600	_	1.3	_	:1
	Rejection	F3 - F5	13100 - 23000	12	15	_	dB
Stop Band		F3 - F4	13100 - 20000	—	1.7	_	:1
	VSWR	F4 - F5	20000 - 23000	—	2.7	—	:1

1 Measured on Mini-Circuits Characterization Test Board TB-844-762+

## Absolute Maximum Ratings<sup>4</sup>

Parameter	Ratings	
Operating Temperature	-55°C to +105°C	
Storage Temperature	-65°C to +150°C	
RF Power Input, Passband (DC-F1) <sup>2</sup>	2W at 25°C	
RF Power Input, Stopband (F2-F5) <sup>3</sup>	100mW at 25°C	

<sup>2</sup> Passband rating derates linearly to 1W at 105°C ambient


Stopband rating derates linearly to 50mW at 105°C ambient
 Permanent damage may occur if any of these limits are exceeded.

#### **ESD** rating

Human body model (HBM): Class 1A (250 to <500V) in accordance with ANSI/ESD 5.1-2001

#### MSL rating


Moisture Sensitivity: MSL1 in accordance with IPC/JEDEC J-STD-020D



## lMini-Circuits®


www.minicircuits.com P.O. Box 350166, Brooklyn, NY 11235-0003 (718) 934-4500 sales@minicircuits.com


#### Specification Definition




# XLF-762+

## **Outline Drawing**





Demo Board MCL P/N: TB-844-762+ (without connectors) TB-844-762C+ (with connectors) B20-118-F1+ Connector sold separately Suggested PCB Layout: PL-451+




## Outline Dimensions ( inch )

J	н	G	F	E	D	С	В	А
.016		.009	.057	.057	.008	.035	.118	.118
0.41		0.23	1.45	1.45	0.20	0.89	3.00	3.00
wt		R	Q	Р	Ν	М	L	К
grams		.049	.020	.010	.049	.127	.127	.020
0.02		1.24	0.51	0.25	1.24	3.23	3.23	0.51

## **Tape & Reel Packaging**

DEVICE ORIENTATION IN T&R

## **Product Marking**




DIRECTION	OF	FEED
-----------	----	------

Tape Width, mm	Device Cavity Pitch, mm	Reel Size, inches	Devices	
8	4	7	Small quantity standard	20 50 100 200 500
		7	Standard	1000, 2000



## **Application Circuit Example**

Pairing mixers with reflectionless filters to improve system dynamic range



Test block diagram: IF output reflection spectrum with single input frequency





Figure 1. IF output reflection spectrum without filter

An application circuit was assembled to measure the IF reflection spectrum at the output of a mixer when the mixer was paired with a conventional filter versus a reflectionless filter.

While the conventional filter reduces the reflections present when the mixer is used alone (no filter), the reflectionless filter virtually eliminates those reflections altogether.

The reflected signal at marker 1 in the figures above exhibits a reduction of more than 20 dB from -28.7 dBm to -50.3 dBm when the reflectionless filter is used as compared to the conventional filter, thus eliminating unwanted spurious mixing products and improving-system dynamic range.

For more information, refer to application note AN-75-007








Figure 3. IF output reflection spectrum with reflectionless filter

#### Additional Notes

- A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.
- B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.
- C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp



## **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Signal Conditioning category:

Click to view products by Mini-Circuits manufacturer:

Other Similar products are found below :

MAPDCC0001 MAPDCC0004 PD0409J5050S2HF 880157 HHS-109-PIN DC1417J5005AHF AFS14A30-2185.00-T3 AFS14A35-1591.50-T3 DS-323-PIN B39321R801H210 1A0220-3 JP510S LFB212G45SG8C341 LFB322G45SN1A504 LFL182G45TC3B746 SF2159E 30057 FM-104-PIN CER0813B MAPDCC0005 3A325 40287 41180 ATB3225-75032NCT BD0810N50100AHF BD2425J50200AHF C5060J5003AHF JHS-115-PIN JP503AS DC0710J5005AHF DC2327J5005AHF DC3338J5005AHF 43020 LFB2H2G60BB1C106 LFL15869MTC1B787 X3C19F1-20S XC3500P-20S 10013-20 SF2194E CDBLB455KCAX39-B0 TGL2208-SM, EVAL RF1353C PD0922J5050D2HF 1E1305-3 1G1304-30 B0922J7575AHF 2020-6622-20 TP-102-PIN TP-103-PIN BD1222J50200AHF