DISCRETE SEMICONDUCTORS

DATA SHEET

BYC5-600 Rectifier diode ultrafast, low switching loss

Product specification

September 2018



WeEn Semiconductors **Product specification**


Rectifier diode ultrafast, low switching loss

BYC5-600

FEATURES

- · Extremely fast switching
- Low reverse recovery current
- · Low thermal resistance
- Reduces switching losses in associated MOSFET

SYMBOL



QUICK REFERENCE DATA

$$V_{R} = 600 \text{ V}$$

$$V_{F} \leq 1.75 \text{ V}$$

$$I_{F(AV)} = 5 \text{ A}$$

$$t_{rr} = 19 \text{ ns (typ)}$$

APPLICATIONS


- Active power factor correction
- Half-bridge lighting ballastsHalf-bridge/ full-bridge switched mode power supplies.

The BYC5-600 is supplied in the SOD59 (TO220AC) conventional leaded package.

PINNING

PIN	DESCRIPTION	
1	cathode	
2	anode	
tab	cathode	

SOD59 (TO220AC)



LIMITING VALUES

Limiting values in accordance with the Absolute Maximum System (IEC 134).

SYMBOL	PARAMETER	CONDITIONS	MIN.	MAX.	UNIT
V_{RRM}	Peak repetitive reverse voltage		-	600	V
V _{RWM}	Crest working reverse voltage		-	600	V
V _B	Continuous reverse voltage	T _{mb} ≤ 110 °C	-	500	V
I _{F(AV)}	Average forward current	$\delta = 0.5$; with reapplied $V_{RRM(max)}$;	-	5	Α
I _{FRM}	Repetitive peak forward current	$\begin{array}{l} T_{mb} \leq 89 \ ^{\circ}C \\ \delta = 0.5; \mbox{ with reapplied } V_{RRM(max)}; \\ T_{mb} \leq 89 \ ^{\circ}C \end{array}$	-	10	А
I _{FSM}	Non-repetitive peak forward	t = 10 ms	-	40	Α
	current.	t = 8.3 ms sinusoidal; T _j = 150°C prior to surge	-	44	A
1-	04	with reapplied V _{RWM(max)}	40	450	
stg	Storage temperature		-40	150	,C
T _i	Operating junction temperature		-	150	, C

THERMAL RESISTANCES

SYMBOL	PARAMETER	CONDITIONS	MIN.	TYP.	MAX.	UNIT
R _{th j-mb}	Thermal resistance junction to mounting base		-	-	2.5	K/W
R _{th j-a}		in free air.	-	60	-	K/W

WeEn Semiconductors Product specification

Rectifier diode ultrafast, low switching loss

BYC5-600

ELECTRICAL CHARACTERISTICS

 $T_i = 25$ °C unless otherwise stated

SYMBOL	PARAMETER	CONDITIONS	MIN.	TYP.	MAX.	UNIT
V _F	Forward voltage	I _F = 5 A; T _i = 150°C I _F = 10 A; T _i = 150°C	-	1.4	1.75	V
		$I_F = 10 \text{ A}; T_j = 150 ^{\circ}\text{C}$	-	1.75	2.2	V
l ,	Reverse current	$I_F = 5 \text{ A};$ $V_B = 600 \text{ V}$	-	2.0 9	2.9 100	μA
I _R	Tieverse current	$V_{R} = 500 \text{ V};$ $T_{j} = 100 \text{ °C}$	-	0.9	3.0	mΑ
t _{rr}	Reverse recovery time	$I_F = 1 \text{ A}; V_B = 30 \text{ V}; dI_F/dt = 50 \text{ A/}\mu\text{s}$	-	30	50	ns
t _{rr}	Reverse recovery time	$I_{\rm F} = 5 \text{ A}; V_{\rm B} = 400 \text{ V};$	-	19	-	ns
t _{rr}	Reverse recovery time	$dI_F/dt = 500 \text{ A/}\mu\text{s}$ $I_F = 5 \text{ A}; V_R = 400 \text{ V};$ $dI_F/dt = 500 \text{ A/}\mu\text{s}; T_j = 100 ^{\circ}\text{C}$	-	25	30	ns
I _{rrm}	Peak reverse recovery current	$I_F = 5 \text{ A}; V_R = 400 \text{ V};$	-	0.7	3	Α
I _{rrm}	Peak reverse recovery current	$I_F = 5 \text{ A}; V_R = 400 \text{ V};$ $dI_F/dt = 50 \text{ A/}\mu\text{s}; T_i = 125 ^{\circ}\text{C}$ $I_F = 5 \text{ A}; V_R = 400 \text{ V};$ $dI_F/dt = 500 \text{ A/}\mu\text{s}; T_j = 125 ^{\circ}\text{C}$	-	8	11	Α
V _{fr}	Forward recovery voltage	$I_F = 10 \text{ A}; dI_F/dt = 100 \text{ A}/\mu\text{s}$	-	9	11	V




Fig.1. Typical application, output rectifier in boost converter power factor correction circuit. Continuous conduction mode, where the transistor turns on whilst forward current is still flowing in the diode.




Fig.2. Typical application, freewheeling diode in half bridge converter. Continuous conduction mode, where each transistor turns on whilst forward current is still flowing in the other bridge leg diode.

BYC5-600




Fig.3. Maximum forward dissipation as a function of average forward current; rectangular current waveform where $I_{F(AV)} = I_{F(RMS)} \times \sqrt{D}$.




Fig.6. Origin of switching losses in transistor due to diode reverse recovery.




Fig.4. Typical reverse recovery switching losses in diode, as a function of rate of change of current dl_F/dt.




Fig.7. Typical reverse recovery time t_{rr} , as a function of rate of change of current dl_{r}/dt .




Fig.5. Typical switching losses in transistor due to reverse recovery of diode, as a function of of change of current dl_p/dt.






Fig.8. Typical peak reverse recovery current, I_{rrm} as a function of rate of change of current dI_F/dt .


WeEn Semiconductors Product specification


Rectifier diode ultrafast, low switching loss


BYC5-600





















Rectifier diode ultrafast, low switching loss

BYC5-600

MECHANICAL DATA



Legal information

Data sheet status

Document status [1][2]	Product status [3]	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

- Please consult the most recently issued document before initiating or completing a design.
- [2] The term 'short data sheet' is explained in section "Definitions".
- The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the Internet at URL http://www.ween-semi.com.

Definitions

Draft — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. WeEn Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

Short data sheet — A short data sheet is an extract from a full data sheet with the same product type number(s and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local WeEn Semiconductors sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

Product specification — The information and data provided in a Product data sheet shall define the specification of the product as agreed between WeEn Semiconductors and its customer, unless WeEn Semiconductors and customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the WeEn Semiconductors product is deemed to offer functions and qualities beyond those described in the Product data sheet.

Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, WeEn Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. WeEn Semiconductors takes no responsibility for the content in this document if provided by an information source outside of WeEn Semiconductors.

In no event shall WeEn Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges whether or not such damages are based on tort (including negligence, warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, WeEn Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the *Terms and conditions of commercial sale* of WeEn Semiconductors.

Right to make changes — WeEn Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — WeEn Semiconductors products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of an WeEn Semiconductors product can reasonably be expected to result in personal rijury, death or severe property or environmental damage. WeEn Semiconductors and its suppliers accept no liability for inclusion and/or use of WeEn Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Quick reference data — The Quick reference data is an extract of the product data given in the Limiting values and Characteristics sections of this document, and as such is not complete, exhaustive or legally binding.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. WeEn Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using WeEn Semiconductors products, and WeEn Semiconductors accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the WeEn Semiconductors product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

WeEn Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using WeEn Semiconductors products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). WeEn does not accept any liability in this respect.

Limiting values — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

No offer to sell or license — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

Non-automotive qualified products — Unless this data sheet expressly states that this specific WeEn Semiconductors product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. WeEn Semiconductors accepts no liability for inclusion and/or use of non-automotive qualified products in automotive equipment or applications.

In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without WEEn Semiconductors' warranty of the product for such automotive applications, use and specifications, and (b) whenever customer uses the product for automotive applications beyond WEEn Semiconductors' specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies WeEn Semiconductors for any liability, damages or failed product claims resulting from customer design and use of the product for automotive applications beyond WeEn Semiconductors' standard warranty and WeEn Semiconductors' product specifications.

Translations — A non-English (translated version of a document is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Rectifiers category:

Click to view products by NXP manufacturer:

Other Similar products are found below:

70HFR40 RL252-TP 150KR30A 1N5397 NTE5841 NTE6038 SCF5000 1N4002G 1N4005-TR JANS1N6640US VS-80-7161 481235F RRE02VS6SGTR 067907F MS306 70HF40 T85HFL60S02 US2JFL-TP A1N5404G-G CRS04(T5L,TEMQ) ACGRA4007-HF ACGRB207-HF CLH03(TE16L,Q) ACGRC307-HF ACEFC304-HF NTE6356 NTE6359 NTE6002 NTE6023 NTE6039 NTE6077 85HFR60 40HFR60 1N1186RA 70HF120 85HFR80 D126A45C SCF7500 D251N08B SCHJ22.5K SM100 SCPA2 SCH10000 SDHD5K VS-12FL100S10 ACGRA4001-HF D1821SH45T PR D1251S45T NTE5990 NTE6358