Audio ICs

Ground isolation amplifier BA3121 / BA3121F / BA3121N

The BA3121, BA3121F and BA3121N are ground isolation amplifiers developed for use in car audio applications. These ICs efficiently eliminate problems caused by wiring resistance, and remove noise generated by the electrical devices used in automobiles. The capacitance values of the external capacitors required for the ICs are small to allow compact and reliable set design.

ApplicationsCar audio systems

Features

- 1) Large capacitors not required
- High common-mode rejection ratio (57dB typ. at f = 1kHz).
- 3) Low noise ($V_{NO} = 3.5 \mu V rms Typ.$).

- 4) Low distortion (THD = 0.002% Typ.).
- 5) Two channels.

Absolute	maximum	ratings	(Ta =	25°C)
----------	---------	---------	-------	-------

Parameter	Symbol	Limits	Unit
Power supply voltage	Vcc	18	V
		800 (BA3121)*	
Power dissipation	Pd	450 (BA3121F)*	mW
		900 (BA3121N)*	
Operating temperature	Topr	-30~+85	°C
Storage temperature	Tstg	-55~+125	Ĵ

* Reduced by 8.0mW (BA3121), 4.5mW (BA3121F), and 9.0mW (BA3121N) for each increase in Ta of 1°C over 25°C.

• Recommended operating conditions (Ta = 25° C)

Parameter	Symbol	Min.	Тур.	Max.	Unit
Power supply voltage	Vcc	4	12	18	V

Block diagrams



-			,	,	,	, , ,
Parameter	Symbol	Min.	Тур.	Max.	Unit	Conditions
Quiescent current	la	5.6	9.0	14.0	mA	VIN=0Vrms
Output noise voltage	V _{NO}	—	3.5	8.0	μ V _{rms}	BPF=20Hz~20kHz
Voltage gain	Gv	-1.5	-0.04	1.5	dB	$V_0 = -10 dBm, R_g = 0 \Omega$
Maximum output voltage	Vом	1.8	2.0	—	Vrms	THD=0.1%, Vcc=8V
Total harmonic distortion	THD	-	0.002	0.02	%	Vo=0.7Vrms
Common-mode rejection ratio	CMRR	41	57	—	dB	
Common-mode voltage	Vсм	2.5	3.75	—	Vrms	Vcc=8V, CMRR=40dB
Ripple rejection ratio	RR	72	80	_	dB	f_BR=100Hz, V_BR=-10dBm, Rg=0 Ω
Channel separation	CS	_	82	_	dB	Vin=−10dBm, Rg=1.8kΩ/OPEN
Slew rate	SR	_	2.0	_	V/µs	
Input resistance	RIN	44	55	66	kΩ	

•Electrical characteristics (unless otherwise noted, Ta = 25° C, Vcc = 12V, f = 1kHz, R_g = 1.8k Ω)

ONot designed for radiation resistance.



Measurement circuits BA3121/BA3121F



BA3121N







Circuit operation



Fig. 3 Flow of noise in car-audio systems

Car-audio systems are earthed to the car body, and for this reason, electrical noise generated by the car electrics can enter the power amplifier input via the chassis, and become audible.

The BA3121 makes use of the common-mode rejection characteristics of an operational amplifier to eliminate this noise. Without the BA3121 noise enters the power amplifier input directly, when used, the CMMR of operational amplifiers 1-A and 2-A eliminates the noise. Principles of noise elimination:

To obtain the output voltage (e_o)

$$V_{i} = \frac{R_{4}}{(R_{3} + R_{4})} \cdot e_{2} \qquad (1)$$
$$e_{0} = -\frac{R_{2}}{R_{1}} e_{1} + \frac{R_{1} + R_{2}}{R_{1}} \cdot V_{i} (2)$$

From (1) and (2)

$$e_{0} = -\frac{R_{2}}{R_{1}} e_{1} + \frac{R_{1} + R_{2}}{R_{1}} \cdot \frac{R_{4}}{(R_{3} + R_{4})} \cdot e_{2}$$
$$= -\frac{R_{2}}{R_{1}} \cdot (e_{1} - e_{2}) + \frac{R_{1}R_{4} - R_{2}R_{3}}{R_{1}(R_{3} + R_{4})} \cdot e_{2}$$

Ideally, if $R_1R_4 = R_2R_3$, and $e_1 = e_2$, the noise voltage will become zero. However, due to mismatching between the resistors, difference in the noise voltages (e_1 and e_2), and tolerances in the operational amplifier, a noise voltage does result.



With the BA3121, the elimination level of the noise is expressed as: CMMR = 20log (e_0/e_i) $(e_i = e_1 = e_2)$ Therefore, CMRR \ge 41dB can be guaranteed.

Operation notes

(1) Maintain a ratio of 2: 1 for the values of the capacitors connected to pin 2 (V_{m1}) and pin 6 (V_{m2}) to keep the ripple rejection ratio stable. If this ratio is maintained, the ripple rejection ratio will not vary significantly even if the capacitance values are halved.

(2) If the value of the capacitor connected to pin 2 (V_{m1}) in the example is doubled, the bass-region CMMR will be +6dB, and if it is halved, it will be -6dB (see Fig. 16).



•Application example

BA3121/BA3121F



Fig. 5





Fig. 6



ROHM

BA3121 / BA3121F / BA3121N



External dimensions (Units: mm)



MEMO



MEMO



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Audio Amplifiers category:

Click to view products by ROHM manufacturer:

Other Similar products are found below :

LV47002P-E NCP2811AFCT1G NCP2890AFCT2G SSM2377ACBZ-R7 IS31AP4915A-QFLS2-TR NCP2820FCT2G TDA1591T TDA7563AH SSM2529ACBZ-R7 SSM2518CBZ-R7 MAX9890AETA+T TS2012EIJT NCP2809BMUTXG NJW1157BFC2 SSM2375CBZ-REEL7 IS31AP4996-GRLS2-TR STPA002OD-4WX NCP2823BFCT1G MAX9717DETA+T MAX9717CETA+T MAX9724AEBC+TG45 LA4450L-E IS31AP2036A-CLS2-TR MAX9723DEBE+T TDA7563ASMTR AS3561-DWLT SSM2517CBZ-R7 MP1720DH-12-LF-P SABRE9601K THAT1646W16-U MAX98396EWB+ PAM8965ZLA40-13 BD37532FV-E2 BD5638NUX-TR BD37512FS-E2 BD37543FS-E2 BD3814FV-E2 TPA3140D2PWPR TS2007EIJT IS31AP2005-DLS2-TR SSM2518CPZ-R7 AS3410-EQFP-500 FDA4100LV MAX98306ETD+T TS4994EIJT NCP2820FCT1G NCP2823AFCT2G NCS2211MNTXG CPA2233CQ16-A1 OPA1604AIPWR