

RGTVX2TS65 650V 60A Field Stop Trench IGBT

V _{CES}	650V
Ι _{C (100°C)}	60A
V _{CE(sat) (Typ.)}	1.5V
P _D	319W

Features

- 1) Low Collector Emitter Saturation Voltage
- 2) High Speed Switching & Low Switching Loss
- 3) Short Circuit Withstand Time 2µs
- 4) Pb free Lead Plating ; RoHS Compliant

Application

Solar Inverter

UPS

Welding

IH

PFC

Outline TO-247N



Inner Circuit





Packaging Specifications

	Packaging	Tube
Туре	Reel Size (mm)	-
	Tape Width (mm)	-
	Basic Ordering Unit (pcs)	450
	Packing Code	C11
	Marking	RGTVX2TS65

•Absolute Maximum Ratings (at T_C = 25°C unless otherwise specified)

U	1 ,			
Parameter		Symbol	Value	Unit
Collector - Emitter Voltage		V _{CES}	650	V
Gate - Emitter Voltage		V _{GES}	±30	V
Collector Current	$T_c = 25^{\circ}C$	Ι _C	111	A
Collector Current	$T_{\rm C} = 100^{\circ}{\rm C}$	$_{\rm C} = 100^{\circ}{\rm C}$ $I_{\rm C}$ (А
Pulsed Collector Current		I _{CP} ^{*1}	240	A
Power Discinction	$T_{\rm C} = 25^{\circ}{\rm C}$	P _D	319	W
Power Dissipation	$T_{\rm C} = 100^{\circ}{\rm C}$	P _D	159	W
Operating Junction Temperature		Tj	-40 to +175	°C
Storage Temperature		T _{stg}	-55 to +175	°C

*1 Pulse width limited by T_{imax.}

•Thermal Resistance

Parameter	Symbol	Values			Linit
Falameter	Symbol	Min.	Тур.	Max.	Onit
Thermal Resistance IGBT Junction - Case	$R_{\theta(j\text{-}c)}$	-	-	0.47	°C/W

●IGBT Electrical Characteristics (at T_i = 25°C unless otherwise specified)

Paramotor	Symbol	Conditions	Values			Linit	
	Symbol	Conditions	Min.	Тур.	Max.	Unit	
Collector - Emitter Breakdown Voltage	BV _{CES}	$I_{\rm C}$ = 10µA, $V_{\rm GE}$ = 0V	650	-	-	V	
Collector Cut - off Current	I _{CES}	$V_{CE} = 650V, V_{GE} = 0V$	-	-	10	μΑ	
Gate - Emitter Leakage Current	I _{GES}	$V_{GE} = \pm 30 V$, $V_{CE} = 0 V$	-	-	±200	nA	
Gate - Emitter Threshold Voltage	V _{GE(th)}	V _{CE} = 5V, I _C = 41.9mA	5.0	6.0	7.0	V	
Collector - Emitter Saturation Voltage	V _{CE(sat)}	$I_{C} = 60A, V_{GE} = 15V,$ $T_{j} = 25^{\circ}C$ $T_{j} = 175^{\circ}C$	-	1.5 1.85	1.9	V	

RGTVX2TS65

•IGBT Electrical Characteristics (at $T_j = 25^{\circ}C$ unless otherwise specified)

Demonster	Symbol	Conditions		1.111		
Parameter			Min.	Тур.	Max.	Unit
Input Capacitance	C _{ies}	V _{CE} = 30V,	-	3610	-	
Output Capacitance	C _{oes}	$V_{GE} = 0V,$	-	140	-	pF
Reverse transfer Capacitance	C _{res}	f = 1MHz	-	58	-	
Total Gate Charge	Qg	V _{CE} = 400V,	-	123	-	
Gate - Emitter Charge	Q_{ge}	I _C = 60A,	-	22	-	nC
Gate - Collector Charge	Q _{gc}	V _{GE} = 15V	-	48	-	
Turn - on Delay Time	t _{d(on)}		-	49	-	
Rise Time	t _r	$I_{\rm C} = 60$ A, $V_{\rm CC} = 400$ V,	-	23	-	~~~
Turn - off Delay Time	t _{d(off)}	$V_{GE} = 13^{\circ}V, 1X_{G} = 10\Omega_{2},$ $T_{i} = 25^{\circ}C$	-	150	-	ns
Fall Time	t _f	Inductive Load	-	34	-	
Turn - on Switching Loss	Eon	*E _{on} include diode reverse recoverv	-	2.08	-	mJ
Turn - off Switching Loss	E _{off}		-	1.15	-	
Turn - on Delay Time	t _{d(on)}		-	46	-	
Rise Time	t _r	$I_{\rm C} = 60$ A, $V_{\rm CC} = 400$ V,	-	28	-	
Turn - off Delay Time	t _{d(off)}	$V_{GE} = 150^{\circ}, R_{G} = 100^{\circ}, T_{i} = 175^{\circ}C$	-	164	-	ns
Fall Time	t _f	Inductive Load	-	79	-	
Turn - on Switching Loss	E _{on}	*E _{on} include diode reverse recoverv	-	2.11	-	
Turn - off Switching Loss	E _{off}		-	1.55	-	mJ
		I _C = 240A, V _{CC} = 520V,				
Reverse Bias Safe Operating Area	RBSOA	$V_{P} = 650V, V_{GE} = 15V,$	FULL SQUARE		-	
		R _G = 100Ω, T _j = 175°C				
		$V_{CC} \leq 360 V$,				
Short Circuit Withstand Time	t _{sc}	V _{GE} = 15V,	2	-	-	μs
		$T_j = 25^{\circ}C$				



Fig.3 Forward Bias Safe Operating Area











Fig.6 Typical Output Characteristics









Fig.17 Typical IGBT Transient Thermal Impedance

8/9

Inductive Load Switching Circuit and Waveform



Fig.18 Inductive Load Circuit



Fig.19 Inductive Load Waveform

 The information contained herein is subject to change without notice. Before you use our Products, please contact our sales representative and verify the latest specifications. Although ROHM is continuously working to improve product reliability and quality, semiconductors can break down and malfunction due to various factors. Therefore, in order to prevent personal injury or fire arising from failure, please take safety measures such as complying with the derating characteristics, implementing redundant and fire prevention designs, and utilizing backups and fail-safe procedures. ROHM shall have no responsibility for any damages arising out of the use of our Poducts beyond the rating specified by ROHM. Examples of application circuits, circuit constants and any other information contained herein are provided only to illustrate the standard usage and operations of the Products. The peripheral conditions must be taken into account when designing circuits for mass production. The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any license to use or exercise intellectual property or other rights held by ROHM or any other parties. ROHM shall have no responsibility whatsoever for any dispute arising out of the use of such technical information. The Products are intended for use in general electronic equipment (i.e. AV/OA devices, communication, consumer systems, gaming/entertainment sets) as well as the applications indicated in this document. The Products specified in this document are not designed to be radiation tolerant. For use of our Products in applications requiring a high degree of reliability (as exemplified below), please contact and consult with a (AHM representative): transmission systems. Do not use our Products in applications requiring extrem		Notes
 Before you use our Products, please contact our sales representative and verify the latest specifications. Although ROHM is continuously working to improve product reliability and quality, semicon-ductors can break down and malfunction due to various factors. Therefore, in order to prevent personal injury or fire arising from failure, please take safety measures such as compilying with the derating characteristics, implementing redundant and fire prevention designs, and utilizing backups and fail-safe procedures. ROHM shall have no responsibility for any damages arising out of the use of our Poducts beyond the rating specified by ROHM. Examples of application circuits, circuit constants and any other information contained herein are provided only to illustrate the standard usage and operations of the Products. The peripheral conditions must be taken into account when designing circuits for mass production. The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any licerase to use or exercise intellectual property or other rights held by ROHM or any other partices. ROHM shall have no responsibility whatsoever for any dispute arising out of the use of such technical information. The Products are intended for use in general electronic equipment (i.e. AV/OA devices, communication, consumer systems, gaming/entertainment sets) as well as the applications indicated in this document. For use of our Products in applications requiring a high degree of reliability (as exemplified below), please contact and consult with a ROHM representative : transportation equipment (i.e. cars, ships, trains), primary communication equipment traffic lights, fire/crime prevention, safety equipment, nuclear power control systems, and submarine repeaters. Do not use our Products in applications requiring extre	1)	The information contained herein is subject to change without notice.
 Although ROHM is continuously working to improve product reliability and quality, semiconductors can break down and malfunction due to various factors. Therefore, in order to prevent personal injury or fire arising from failure, please take safety measures such as complying with the derating characteristics, implementing redundant and fire prevention designs, and utilizing backups and fail-asfe procedures. ROHM shall have no responsibility for any damages arising out of the use of our Poducts beyond the rating specified by ROHM. Examples of application circuits, circuit constants and any other information contained herein are provided only to illustrate the standard usage and operations of the Products. The peripheral conditions must be taken into account when designing circuits for mass production. The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any license to use or exercise intellectual property or other rights held by ROHM or any other parties. ROHM shall have no responsibility whatsoever for any dispute arising out of the use of such technical information. The Products specified for use in general electronic equipment (i.e. AV/OA devices, communication, consumer systems, gaming/entertainment sets) as well as the applications indicated in this document. For use of our Products in applications requiring a high degree of reliability (as exemplified be low), please contact and consult with a ROHM representitive : transportation equipment (i.e. cars, ships, trains), primary communication equipment, traffic lights, fire/crime prevention, safety equipment, medical systems, servers, solar cells, and power transmission systems. Do not use our Products in applications requiring extremely high reliability, such as aerospace equipment, medical systems, servers, solar cells, including ROHS comp	2)	Before you use our Products, please contact our sales representative and verify the latest specifica- tions.
 Examples of application circuits, circuit constants and any other information contained herein are provided only to illustrate the standard usage and operations of the Products. The peripheral conditions must be taken into account when designing circuits for mass production. The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any license to use or exercise intellectual property or other rights held by ROHM or any other parties. ROHM shall have no responsibility whatsoever for any dispute arising out of the use of such technical information. The Products are intended for use in general electronic equipment (i.e. AV/OA devices, communication, consumer systems, gaming/entertainment sets) as well as the applications indicated in this document. The Products specified in this document are not designed to be radiation tolerant. For use of our Products in applications requiring a high degree of reliability (as exemplified below), please contact and consult with a ROHM representative : transportation equipment (i.e. cars, ships, trains), primary communication equipment, traffic lights, fire/crime prevention, safety equipment, nuclear power control systems, and submarine repeaters. Do not use our Products in applications requiring extremely high reliability, such as aerospace equipment, nuclear power control systems, and submarine repeaters. ROHM shall have no responsibility for any damages or injury arising from non-compliance with the recommended usage conditions and specifications contained herein. ROHM has used reasonable care to ensure the accuracy of the information contained in this document. However, ROHM does not vary applicable environmental laws and regulations, such as the ROHM shall have no responsibility for any damages or losses resulting non-compliance with a	3)	Although ROHM is continuously working to improve product reliability and quality, semicon- ductors can break down and malfunction due to various factors. Therefore, in order to prevent personal injury or fire arising from failure, please take safety measures such as complying with the derating characteristics, implementing redundant and fire prevention designs, and utilizing backups and fail-safe procedures. ROHM shall have no responsibility for any damages arising out of the use of our Poducts beyond the rating specified by ROHM.
 5) The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any license to use or exercise intellectual property or other rights held by ROHM or any other parties. ROHM shall have no responsibility whatsoever for any dispute arising out of the use of such technical information. 6) The Products are intended for use in general electronic equipment (i.e. AV/OA devices, communication, consumer systems, gaming/entertainment sets) as well as the applications indicated in this document. 7) The Products specified in this document are not designed to be radiation tolerant. 8) For use of our Products in applications requiring a high degree of reliability (as exemplified below), please contact and consult with a ROHM representative : transportation equipment (i.e. cars, ships, trains), primary communication equipment, traffic lights, fire/crime prevention, safety equipment, medical systems, servers, solar cells, and power transmission systems. 9) Do not use our Products in applications requiring extremely high reliability, such as aerospace equipment, nuclear power control systems, and submarine repeaters. 10) ROHM shall have no responsibility for any damages or injury arising from non-compliance with the recommended usage conditions and specifications contained herein. 11) ROHM has used reasonable care to ensure the accuracy of the information contained in this document. However, ROHM does not warrants that such information is error-free, and ROHM shall have no responsibility for any damages arising from any inaccuracy or misprint of such information. 12) Please use the Products in accordance with any applicable environmental laws and regulations, such as the ROHS Directive. For more details, including ROHS compatibility, please contact a ROHM shall have no responsibility for any	4)	Examples of application circuits, circuit constants and any other information contained herein are provided only to illustrate the standard usage and operations of the Products. The peripheral conditions must be taken into account when designing circuits for mass production.
 6) The Products are intended for use in general electronic equipment (i.e. AV/OA devices, communication, consumer systems, gaming/entertainment sets) as well as the applications indicated in this document. 7) The Products specified in this document are not designed to be radiation tolerant. 8) For use of our Products in applications requiring a high degree of reliability (as exemplified below), please contact and consult with a ROHM representative : transportation equipment (i.e. cars, ships, trains), primary communication equipment, traffic lights, fire/crime prevention, safety equipment, medical systems, servers, solar cells, and power transmission systems. 9) Do not use our Products in applications requiring extremely high reliability, such as aerospace equipment, nuclear power control systems, and submarine repeaters. 10) ROHM shall have no responsibility for any damages or injury arising from non-compliance with the recommended usage conditions and specifications contained herein. 11) ROHM has used reasonable care to ensure the accuracy of the information contained in this document. However, ROHM does not warrants that such information is error-free, and ROHM shall have no responsibility for any damages arising from any inaccuracy or misprint of such information. 12) Please use the Products in accordance with any applicable environmental laws and regulations, such as the ROHS Directive. For more details, including ROHS compatibility, please contact a ROHM sabile soffice. ROHM shall have no responsibility for any damages or losses resulting non-compliance with any applicable laws or regulations. 13) When providing our Products and technologies contained in this document to other countries, you must abide by the procedures and provisions stipulated in all applicable export laws and regulations, including without limitation the US Export Administration Regulations and the Foreign Exchange and Foreign Trade	5)	The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any license to use or exercise intellectual property or other rights held by ROHM or any other parties. ROHM shall have no responsibility whatsoever for any dispute arising out of the use of such technical information.
 7) The Products specified in this document are not designed to be radiation tolerant. 8) For use of our Products in applications requiring a high degree of reliability (as exemplified below), please contact and consult with a ROHM representative : transportation equipment (i.e. cars, ships, trains), primary communication equipment, traffic lights, fire/crime prevention, safety equipment, medical systems, servers, solar cells, and power transmission systems. 9) Do not use our Products in applications requiring extremely high reliability, such as aerospace equipment, nuclear power control systems, and submarine repeaters. 10) ROHM shall have no responsibility for any damages or injury arising from non-compliance with the recommended usage conditions and specifications contained herein. 11) ROHM has used reasonable care to ensure the accuracy of the information contained in this document. However, ROHM does not warrants that such information is error-free, and ROHM shall have no responsibility for any damages arising from any inaccuracy or misprint of such information. 12) Please use the Products in accordance with any applicable environmental laws and regulations, such as the RoHS Directive. For more details, including RoHS compatibility, please contact a ROHM sales office. ROHM shall have no responsibility for any damages or losses resulting non-compliance with any applicable laws or regulations. 13) When providing our Products and technologies contained in this document to other countries, you must abide by the procedures and provisions stipulated in all applicable export laws and regulations, including without limitation the US Export Administration Regulations and the Foreign Exchange and Foreign Trade Act. 14) This document, in part or in whole, may not be reprinted or reproduced without prior consent of ROHM. 	6)	The Products are intended for use in general electronic equipment (i.e. AV/OA devices, communi- cation, consumer systems, gaming/entertainment sets) as well as the applications indicated in this document.
 For use of our Products in applications requiring a high degree of reliability (as exemplified below), please contact and consult with a ROHM representative : transportation equipment (i.e. cars, ships, trains), primary communication equipment, traffic lights, fire/crime prevention, safety equipment, medical systems, servers, solar cells, and power transmission systems. Do not use our Products in applications requiring extremely high reliability, such as aerospace equipment, nuclear power control systems, and submarine repeaters. ROHM shall have no responsibility for any damages or injury arising from non-compliance with the recommended usage conditions and specifications contained herein. ROHM has used reasonable care to ensure the accuracy of the information contained in this document. However, ROHM does not warrants that such information is error-free, and ROHM shall have no responsibility for any damages arising from any inaccuracy or misprint of such information. Please use the Products in accordance with any applicable environmental laws and regulations, such as the RoHS Directive. For more details, including RoHS compatibility, please contact a ROHM sale office. ROHM shall have no responsibility for any damages or losses resulting non-compliance with any applicable laws or regulations. When providing our Products and technologies contained in this document to other countries, you must abide by the procedures and provisions stipulated in all applicable export laws and regulations, including without limitation the US Export Administration Regulations and the Foreign Exchange and Foreign Trade Act. This document, in part or in whole, may not be reprinted or reproduced without prior consent of ROHM. 	7)	The Products specified in this document are not designed to be radiation tolerant.
 Do not use our Products in applications requiring extremely high reliability, such as aerospace equipment, nuclear power control systems, and submarine repeaters. ROHM shall have no responsibility for any damages or injury arising from non-compliance with the recommended usage conditions and specifications contained herein. ROHM has used reasonable care to ensure the accuracy of the information contained in this document. However, ROHM does not warrants that such information is error-free, and ROHM shall have no responsibility for any damages arising from any inaccuracy or misprint of such information. Please use the Products in accordance with any applicable environmental laws and regulations, such as the RoHS Directive. For more details, including RoHS compatibility, please contact a ROHM sales office. ROHM shall have no responsibility for any damages or losses resulting non-compliance with any applicable laws or regulations. When providing our Products and technologies contained in this document to other countries, you must abide by the procedures and provisions stipulated in all applicable export laws and regulations, including without limitation the US Export Administration Regulations and the Foreign Exchange and Foreign Trade Act. This document, in part or in whole, may not be reprinted or reproduced without prior consent of ROHM. 	8)	For use of our Products in applications requiring a high degree of reliability (as exemplified below), please contact and consult with a ROHM representative : transportation equipment (i.e. cars, ships, trains), primary communication equipment, traffic lights, fire/crime prevention, safety equipment, medical systems, servers, solar cells, and power transmission systems.
 ROHM shall have no responsibility for any damages or injury arising from non-compliance with the recommended usage conditions and specifications contained herein. ROHM has used reasonable care to ensure the accuracy of the information contained in this document. However, ROHM does not warrants that such information is error-free, and ROHM shall have no responsibility for any damages arising from any inaccuracy or misprint of such information. Please use the Products in accordance with any applicable environmental laws and regulations, such as the RoHS Directive. For more details, including RoHS compatibility, please contact a ROHM sales office. ROHM shall have no responsibility for any damages or losses resulting non-compliance with any applicable laws or regulations. When providing our Products and technologies contained in this document to other countries, you must abide by the procedures and provisions stipulated in all applicable export laws and regulations, including without limitation the US Export Administration Regulations and the Foreign Exchange and Foreign Trade Act. This document, in part or in whole, may not be reprinted or reproduced without prior consent of ROHM. 	9)	Do not use our Products in applications requiring extremely high reliability, such as aerospace equipment, nuclear power control systems, and submarine repeaters.
 ROHM has used reasonable care to ensure the accuracy of the information contained in this document. However, ROHM does not warrants that such information is error-free, and ROHM shall have no responsibility for any damages arising from any inaccuracy or misprint of such information. Please use the Products in accordance with any applicable environmental laws and regulations, such as the ROHS Directive. For more details, including ROHS compatibility, please contact a ROHM sales office. ROHM shall have no responsibility for any damages or losses resulting non-compliance with any applicable laws or regulations. When providing our Products and technologies contained in this document to other countries, you must abide by the procedures and provisions stipulated in all applicable export laws and regulations, including without limitation the US Export Administration Regulations and the Foreign Exchange and Foreign Trade Act. This document, in part or in whole, may not be reprinted or reproduced without prior consent of ROHM. 	10)	ROHM shall have no responsibility for any damages or injury arising from non-compliance with the recommended usage conditions and specifications contained herein.
 Please use the Products in accordance with any applicable environmental laws and regulations, such as the RoHS Directive. For more details, including RoHS compatibility, please contact a ROHM sales office. ROHM shall have no responsibility for any damages or losses resulting non-compliance with any applicable laws or regulations. When providing our Products and technologies contained in this document to other countries, you must abide by the procedures and provisions stipulated in all applicable export laws and regulations, including without limitation the US Export Administration Regulations and the Foreign Exchange and Foreign Trade Act. This document, in part or in whole, may not be reprinted or reproduced without prior consent of ROHM. 	11)	ROHM has used reasonable care to ensure the accuracy of the information contained in this document. However, ROHM does not warrants that such information is error-free, and ROHM shall have no responsibility for any damages arising from any inaccuracy or misprint of such information.
 13) When providing our Products and technologies contained in this document to other countries, you must abide by the procedures and provisions stipulated in all applicable export laws and regulations, including without limitation the US Export Administration Regulations and the Foreign Exchange and Foreign Trade Act. 14) This document, in part or in whole, may not be reprinted or reproduced without prior consent of ROHM. 	12)	Please use the Products in accordance with any applicable environmental laws and regulations, such as the RoHS Directive. For more details, including RoHS compatibility, please contact a ROHM sales office. ROHM shall have no responsibility for any damages or losses resulting non-compliance with any applicable laws or regulations.
14) This document, in part or in whole, may not be reprinted or reproduced without prior consent of ROHM.	13)	When providing our Products and technologies contained in this document to other countries, you must abide by the procedures and provisions stipulated in all applicable export laws and regulations, including without limitation the US Export Administration Regulations and the Foreign Exchange and Foreign Trade Act.
	14)	This document, in part or in whole, may not be reprinted or reproduced without prior consent of ROHM.



Thank you for your accessing to ROHM product informations. More detail product informations and catalogs are available, please contact us.

ROHM Customer Support System

http://www.rohm.com/contact/

General Precaution

- 1. Before you use our Products, you are requested to care fully read this document and fully understand its contents. ROHM shall not be in an y way responsible or liable for failure, malfunction or accident arising from the use of a ny ROHM's Products against warning, caution or note contained in this document.
- 2. All information contained in this docume nt is current as of the issuing date and subj ect to change without any prior notice. Before purchasing or using ROHM's Products, please confirm the latest information with a ROHM sale s representative.
- 3. The information contained in this document is provided on an "as is" basis and ROHM does not warrant that all information contained in this document is accurate an d/or error-free. ROHM shall not be in an y way responsible or liable for any damages, expenses or losses incurred by you or third parties resulting from inaccuracy or errors of or concerning such information.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for ROHM manufacturer:

Other Similar products are found below :

BP5034D24BP5013BP5011BP5718A12RPI-441C1RN142ZST2RSML-012VTT86ARB055LA-40TRRB886YT2RRB851YT2RISS400GT2RMCR100JZHF30R1MCR100JZHJ150MCR50JZHFLR820MCR50JZHJ330ML610Q793-SDKMNR34J5ABJ223BD750L2FP-EVK-301BD9009HFP-EVK-001BD9285F-GE2SCT2H12NZGC11RB168L-60TE25MCR100JZHF1301MCR100JZHJ4R3MCR100JZHJ513MCR100JZHJ683BD9B300MUV-EVK-001MNR12ERAPJ100MNR34J5ABJ221BD9060HFP-EVK-001BD9611MUV-EVK-001BD9C601EFJ-EVK-001BD9D321EFJ-EVK-101BD9G341AEFJ-EVK-101BA7603F-E2BD95820N-LBBD9A100MUV-EVK-001BD9C501EFJ-EVK-001BU90005GWZ-E2-EVK-101BH1715FVC-TRLA-401XDRSX301L-30TE25BH1790GLC-EVK-001BU33UV7NUX-EVK-101BD9B301MUV-EVK-101BA7071F-E2SK-AD01-D62Q1367TBBM2P129TF-EVK-001RB-D62Q1577TB100RB-D62Q1552GA64RB-D62Q1552GA64RB-D62Q1552GA64RB-D62Q1552GA64