# 2.5V Drive Pch MOSFET

# RTF010P02

#### Structure

Silicon P-channel MOSFET

#### ● Features

- 1) Low on-resistance. (570m $\Omega$  at 2.5V)
- 2) High power package.
- 3) High speed switching.
- 4) Low voltage drive. (2.5V)


# Applications

DC-DC converter


### Packaging specifications

	Package	Taping
Type	Code	TL
	Basic ordering unit (pieces)	3000
RTF010P02	0	

#### ●Dimensions (Unit:mm)



# ●Equivalent circuit



# ● Absolute maximum ratings (Ta=25°C)

Parameter		Symbol	Limits	Unit	
Drain-source voltage		V <sub>DSS</sub>	-20	V	
Gate-source voltage		V <sub>GSS</sub>	±12	V	
Drain current	Continuous	I <sub>D</sub>	±1	Α	
Diam current	Pulsed	I <sub>DP</sub> *1	±4	Α	
Source current	Continuous	Is *1	-0.4	Α	
(Body diode)	Pulsed	I <sub>SP</sub>	-4	Α	
Total power dissipation		P <sub>D</sub> *2	0.8	W	
Channel temperature	Tch	150	°C		
Range of Storage temperature	Tstg	-55 to +150	°C		

<sup>\*1</sup> Pw≤10μs, Duty cycle≤1% \*2 Mounted on a ceramic board

### ●Thermal resistance

Parameter	Symbol	Limits	Unit
Channel to ambient	Rth(ch-a) *	156	°C / W

<sup>\*</sup> Mounted on a ceramic board.

#### ●Electrical characteristics (Ta=25°C)

Parameter	Symbol	Min.	Тур.	Max.	Unit	Conditions
Gate-source leakage	Igss	-	-	±10	μА	Vgs=±12V, Vps=0V
Drain-source breakdown voltage	V <sub>(BR)</sub> DSS	-20	_	_	V	I <sub>D</sub> = -1mA, V <sub>GS</sub> =0V
Zero gate voltage drain current	IDSS	_	_	-1	μΑ	V <sub>DS</sub> = -20V, V <sub>GS</sub> =0V
Gate threshold voltage	V <sub>GS (th)</sub>	-0.7	_	-2.0	V	V <sub>DS</sub> = -10V, I <sub>D</sub> = -1mA
	*	-	280	390	mΩ	I <sub>D</sub> = -1A, V <sub>G</sub> S= -4.5V
Static drain-source on-state resistance	R <sub>DS (on)</sub>	-	310	430	mΩ	I <sub>D</sub> = -1A, V <sub>G</sub> = -4V
resistance		-	570	800	mΩ	I <sub>D</sub> = -0.5A, V <sub>G</sub> S= -2.5V
Forward transfer admittance	Y <sub>fs</sub> *	0.7	_	_	S	V <sub>DS</sub> = -10V, I <sub>D</sub> = -0.5A
Input capacitance	Ciss	-	150	_	pF	V <sub>DS</sub> = -10V
Output capacitance	Coss	_	20	_	pF	Vgs=0V
Reverse transfer capacitance	Crss	_	20	_	pF	f=1MHz
Turn-on delay time	t <sub>d (on)</sub> *	-	9	_	ns	ID= -0.5A
Rise time	tr *	-	8	_	ns	V <sub>DD</sub> ≒ −15V
Turn-off delay time	t <sub>d (off)</sub> *	_	25	_	ns	Vgs= -4.5V RL=30Ω
Fall time	t <sub>f</sub> *	-	10	_	ns	R <sub>G</sub> =10Ω
Total gate charge	Qg *	_	2.1	_	nC	V <sub>DD</sub> ≒-15V R <sub>L</sub> =15Ω
Gate-source charge	Q <sub>gs</sub> *	_	0.5	-	nC	V <sub>GS</sub> = -4.5V R <sub>G</sub> =10Ω
Gate-drain charge	Q <sub>gd</sub> *	_	0.5	-	nC	I <sub>D</sub> =-1A

\*Pulsed

# ●Body diode characteristics (Source -drain) (Ta=25°C)

					_	
Parameter	Symbol	Min.	Тур.	Max.	Unit	Conditions
Forward voltage	Vsd	-	4	-1.2	V	I <sub>S</sub> = -0.4A, V <sub>GS</sub> =0V



#### •Electrical characteristic curves




Fig.1 Typical Transfer Characteristics




Fig.2 Static Drain-Source On-State Resistance vs. Drain Current




Fig.3 Static Drain-Source On-State Resistance vs. Drain Current




Fig.4 Static Drain-Source On-State Resistance vs. Drain Current




Fig.5 Static Drain-Source On-State Resistance vs. Drain Current




Fig.6 Reverse Drain Current vs. Source-Drain Voltage




Fig.7 Typical Capacitance vs. Drain-Source Voltage




Fig.8 Switching Characteristics




Fig.9 Dynamic Input Characteristics

#### ●Measurement circuits




Fig.10 Switching Time Measurement Circuit




Fig.11 Switching Waveforms




Fig.12 Gate Charge Measurement Circuit




Fig.13 Gate Charge Waveforms

#### Notes

- 1) The information contained herein is subject to change without notice.
- Before you use our Products, please contact our sales representative and verify the latest specifications:
- 3) Although ROHM is continuously working to improve product reliability and quality, semiconductors can break down and malfunction due to various factors.

  Therefore, in order to prevent personal injury or fire arising from failure, please take safety measures such as complying with the derating characteristics, implementing redundant and fire prevention designs, and utilizing backups and fail-safe procedures. ROHM shall have no responsibility for any damages arising out of the use of our Poducts beyond the rating specified by ROHM.
- 4) Examples of application circuits, circuit constants and any other information contained herein are provided only to illustrate the standard usage and operations of the Products. The peripheral conditions must be taken into account when designing circuits for mass production.
- 5) The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any license to use or exercise intellectual property or other rights held by ROHM or any other parties. ROHM shall have no responsibility whatsoever for any dispute arising out of the use of such technical information.
- 6) The Products are intended for use in general electronic equipment (i.e. AV/OA devices, communication, consumer systems, gaming/entertainment sets) as well as the applications indicated in this document.
- 7) The Products specified in this document are not designed to be radiation tolerant.
- 8) For use of our Products in applications requiring a high degree of reliability (as exemplified below), please contact and consult with a ROHM representative: transportation equipment (i.e. cars, ships, trains), primary communication equipment, traffic lights, fire/crime prevention, safety equipment, medical systems, servers, solar cells, and power transmission systems.
- Do not use our Products in applications requiring extremely high reliability, such as aerospace equipment, nuclear power control systems, and submarine repeaters.
- 10) ROHM shall have no responsibility for any damages or injury arising from non-compliance with the recommended usage conditions and specifications contained herein.
- 11) ROHM has used reasonable care to ensur the accuracy of the information contained in this document. However, ROHM does not warrants that such information is error-free, and ROHM shall have no responsibility for any damages arising from any inaccuracy or misprint of such information.
- 12) Please use the Products in accordance with any applicable environmental laws and regulations, such as the RoHS Directive. For more details, including RoHS compatibility, please contact a ROHM sales office. ROHM shall have no responsibility for any damages or losses resulting non-compliance with any applicable laws or regulations.
- 13) When providing our Products and technologies contained in this document to other countries, you must abide by the procedures and provisions stipulated in all applicable export laws and regulations, including without limitation the US Export Administration Regulations and the Foreign Exchange and Foreign Trade Act.
- 14) This document, in part or in whole, may not be reprinted or reproduced without prior consent of ROHM



Thank you for your accessing to ROHM product informations. More detail product informations and catalogs are available, please contact us.

# ROHM Customer Support System

http://www.rohm.com/contact/

# **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

Click to view similar products for MOSFET category:

Click to view products by ROHM manufacturer:

Other Similar products are found below:

614233C 648584F IRFD120 JANTX2N5237 FCA20N60\_F109 FDZ595PZ 2SK2545(Q,T) 405094E 423220D TPCC8103,L1Q(CM MIC4420CM-TR VN1206L SBVS138LT1G 614234A 715780A NTNS3166NZT5G SSM6J414TU,LF(T 751625C BUK954R8-60E NTE6400 SQJ402EP-T1-GE3 2SK2614(TE16L1,Q) 2N7002KW-FAI DMN1017UCP3-7 EFC2J004NUZTDG ECH8691-TL-W FCAB21350L1 P85W28HP2F-7071 DMN1053UCP4-7 NTE221 NTE2384 NTE2903 NTE2941 NTE2945 NTE2946 NTE2960 NTE2967 NTE2969 NTE2976 NTE455 NTE6400A NTE2910 NTE2916 NTE2956 NTE2911 DMN2080UCB4-7 TK10A80W,S4X(S SSM6P69NU,LF DMP22D4UFO-7B DMN1006UCA6-7