

# SANYO Semiconductors DATA SHEET

N-Channel Silicon MOSFET

# **FSS275** — General-Purpose Switching Device **Applications**

# **Features**

- · Low ON-resistance.
- · 4V drive.

## **Specifications**

#### Absolute Maximum Ratings at Ta=25°C

Parameter	Symbol	Conditions	Ratings	Unit
Drain-to-Source Voltage	VDSS		60	٧
Gate-to-Source Voltage	VGSS		±20	V
Drain Current (DC)	ID		6	Α
Drain Current (PW≤10s)	ID	Duty cycle≤1%	6.5	Α
Drain Current (PW≤10μs)	IDP	Duty cycle≤1%	24	Α
Allowable Power Dissipation	PD	Mounted on a ceramic board (2000mm²X0.8mm), PW≤10s	1.9	W
Channel Temperature	Tch		150	°C
Storage Temperature	Tstg		-55 to +150	°C

#### Electrical Characteristics at Ta=25°C

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	Offic
Drain-to-Source Breakdown Voltage	V(BR)DSS	ID=1mA, VGS=0V	60			V
Zero-Gate Voltage Drain Current	IDSS	V <sub>DS</sub> =60V, V <sub>GS</sub> =0V			1	μΑ
Gate-to-Source Leakage Current	IGSS	V <sub>GS</sub> =±16V, V <sub>DS</sub> =0V			±10	μΑ
Cutoff Voltage	VGS(off)	V <sub>DS</sub> =10V, I <sub>D</sub> =1mA	1.2		2.6	V
Forward Transfer Admittance	yfs	V <sub>DS</sub> =10V, I <sub>D</sub> =3A	3.4	5.8		S
Static Drain-to-Source On-State Resistance	R <sub>DS</sub> (on)1	I <sub>D</sub> =3A, V <sub>GS</sub> =10V		33	43	mΩ
	RDS(on)2	ID=3A, VGS=4V		44	62	mΩ

Marking: S275 Continued on next page.


- Any and all SANYO Semiconductor Co.,Ltd. products described or contained herein are, with regard to "standard application", intended for the use as general electronics equipment (home appliances, AV equipment, communication device, office equipment, industrial equipment etc.). The products mentioned herein shall not be intended for use for any "special application" (medical equipment whose purpose is to sustain life, aerospace instrument, nuclear control device, burning appliances, transportation machine, traffic signal system, safety equipment etc.) that shall require extremely high level of reliability and can directly threaten human lives in case of failure or malfunction of the product or may cause harm to human bodies, nor shall they grant any guarantee thereof. If you should intend to use our products for applications outside the standard applications of our customer who is considering such use and/or outside the scope of our intended standard applications, please consult with us prior to the intended use. If there is no consultation or inquiry before the intended use, our customer shall be solely responsible for the use.
- Specifications of any and all SANYO Semiconductor Co.,Ltd. products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.

Continued from preceding page.


Parameter	Symbol	Conditions		Ratings		
	Symbol		min	typ	max	Unit
Input Capacitance	Ciss	V <sub>DS</sub> =20V, f=1MHz		1100		pF
Output Capacitance	Coss	V <sub>DS</sub> =20V, f=1MHz		110		pF
Reverse Transfer Capacitance	Crss	V <sub>DS</sub> =20V, f=1MHz		70		pF
Turn-ON Delay Time	t <sub>d</sub> (on)	See specified Test Circuit.		16		ns
Rise Time	t <sub>r</sub>	See specified Test Circuit.		27		ns
Turn-OFF Delay Time	t <sub>d</sub> (off)	See specified Test Circuit.		90		ns
Fall Time	tf	See specified Test Circuit.		50		ns
Total Gate Charge	Qg	V <sub>DS</sub> =30V, V <sub>GS</sub> =10V, I <sub>D</sub> =6A		21		nC
Gate-to-Source Charge	Qgs	VDS=30V, VGS=10V, ID=6A		3.1		nC
Gate-to-Drain "Miller" Charge	Qgd	V <sub>DS</sub> =30V, V <sub>GS</sub> =10V, I <sub>D</sub> =6A		3.7		nC
Diode Forward Voltage	V <sub>SD</sub>	I <sub>S</sub> =6A, V <sub>G</sub> S=0V		0.82	1.2	V


## **Package Dimensions**


unit : mm (typ) 7005-002





# **Switching Time Test Circuit**











Note on usage : Since the FSS275 is a MOSFET product, please avoid using this device in the vicinity of highly charged objects.

- SANYO Semiconductor Co.,Ltd. assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO Semiconductor Co.,Ltd. products described or contained herein.
- SANYO Semiconductor Co.,Ltd. strives to supply high-quality high-reliability products, however, any and all semiconductor products fail or malfunction with some probability. It is possible that these probabilistic failures or malfunction could give rise to accidents or events that could endanger human lives, trouble that could give rise to smoke or fire, or accidents that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO Semiconductor Co.,Ltd. products described or contained herein are controlled under any of applicable local export control laws and regulations, such products may require the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written consent of SANYO Semiconductor Co.,Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO Semiconductor Co.,Ltd. product that you intend to use.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production.
- Upon using the technical information or products described herein, neither warranty nor license shall be granted with regard to intellectual property rights or any other rights of SANYO Semiconductor Co.,Ltd. or any third party. SANYO Semiconductor Co.,Ltd. shall not be liable for any claim or suits with regard to a third party's intellectual property rights which has resulted from the use of the technical information and products mentioned above.

This catalog provides information as of March, 2007. Specifications and information herein are subject to change without notice.

# **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

Click to view similar products for sanyo denki manufacturer:

Other Similar products are found below:

9A0812G401 9A0824H401 9G0824H102 9GA0812P1H61 9GA0812P1S61 9GL1212F101 9GV1412P1G001 9GV3612G301
9WG1212H102 9WG1224G101 SM2861-5255 9GT0912P1M001 9GV0312E302 9S1212F4011 9SG5748P5H01 9WG1212E101 489-007L21 103H5208-5240 103H7126-1740 103H7822-5740 109-1001F13 109-1003M30 109-313 109L1748H501 109L5712H501
109P1412M101 109R0824S4D01 109-1069 109BF24HD2 9L0412H301 9GA0812P1S61P 9G1212P4G03 9G0612P1G03
9CRB0812P8G001 103H8221-5141 103H8223-6340 9LG1248P1H001 SH1603-5240 9GA0812P1H611 9BD12SC6-1 109P0824H701 109-049C 103H7123-5740 9AH0912P4H03 9G1224G1D01 9GV1212P4G011 9G1224M4D011 9GV0824P1G03 109P0624W602
9WF0924S201