
# Matrix LED TinyShield - ASD2413-R

tinycircuits.com/collections/leds-displays/products/matrix-led-tinyshield



### **DESCRIPTION**

The Matrix LED TinyShield is a 6 x 9 grid of LEDs (54 total LEDs) that are individually addressable, which lets you scroll text, draw images, and do all sorts of other things. This TinyShield is compatible with the popular **Arduino LoL** (Lots of LEDs) Shield Library created by Jimmie Rodgers.

The LEDs are arranged using Charlieplexing, which is a technique to allow for control of multiple LEDs using fewer I/O signals. Available with Red, Green, and Amber LED color options.

To learn more about the TinyDuino Platform, click here

### **TECHNICAL DETAILS**

To see what other TinyShields this will work with or conflict with, check out the **TinyShield Compatibility Matrix** 

#### **LED Specs**

- 54 Top Facing LEDs in a 6×9 Matrix
- Charlieplexed IO on 8 signals
- · Available in Green, Amber or Red

#### **TinyDuino Power Requirements**

- Voltage: 3.0V 5.5V
- Current:
  - 1.5mA per LED (3.0V)
  - 5.0mA per LED (5.0V)
  - Due to the low current, this board can be run using the TinyDuino coin cell option

#### **Pins Used**

Pins 2, 3, 4, 5, 6, 7, 8, and 9 are used, see schematic or sample code for connections

#### **Dimensions**

- 20mm x 20mm (.787 inches x .787 inches)
- Max Height (from lower bottom TinyShield Connector to upper top TinyShield Connector): 3.31mm (0.130 inches)
- Weight: .75 grams (.027 ounces)

### **Notes**

- This TinyShield uses a lot of IO pins and will conflict with many other TinyShields. If you're planning on using
  other TinyShields with it, be sure to check the TinyShield Compatibility Matrix to make sure they can be
  used at the same time.
- The LEDs are hooked up using Charlieplexing, a technique for driving many LEDs with only a few IO signals. See the tutorial to learn more about this and how to use the open source library to control these easily.

## **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Daughter Cards & OEM Boards category:

Click to view products by TINY CIRCUITS manufacturer:

Other Similar products are found below:

ADZS-21262-1-EZEXT 27911 MPC5777C-416DS KITMPC5744DBEVM SPC56ELADPT144S TMDXRM46CNCD DM160216 EV-ADUCM350GPIOTHZ EV-ADUCM350-BIO3Z ATSTK521 1130 MA160015 MA240013 MA240026 MA320014 MA330014 MA330017 TMDSCNCD28054MISO MIKROE-2152 MIKROE-2154 MIKROE-2381 TSSOP20EV MIKROE-1108 MIKROE-1516 SPS-READER-GEVK AC244049 AC244050 AC320004-3 2077 ATSMARTCARD-XPRO EIC - Q600 -230 ATZB-212B-XPRO SPC560PADPT100S SPC560BADPT64S MA180018 EIC - Q600 -220 AC164134-1 BOB-12035 BB-BONE-BATT-01 STM8/128-D/RAIS AC164127-6 AC164127-4 AC164134-3 AC164156 MA320021 MA320024 DFR0285 DFR0312 DFR0356 MA320023