

## Precision with Programmable 200 Watt Output DC Power Supply

**40V/5A programmable supply**  
With high resolution output and 200 test setup memories

### Features:

- High resolution (1mV and 1mA) user programmable output and two fixed outputs of 5V and 3.3V
- Selectable constant Voltage or Current modes
- Auto output of up to 200 steps with programmable Voltage, Current and time
- Programmable over Voltage protection
- 0 to 60 second programmable overload delay timer
- Storage/Recall memory for 200 test setups
- High stability with low ripple and noise
- Forced air cooling fan
- Bi-directional PC interface commands allow setup and readback using Windows<sup>®</sup> HyperTerminal or similar PC communications programs
- Dual output terminal for source and monitor connections
- Dual high contrast LCD display with backlighting

### Applications:

- Precision R & D Voltage and Current source
- Repetitive production tests using setup recall feature
- Prototype board initial power-up with overload protection
- General purpose high power lab requirements



Specifications:	Range	Resolution	Accuracy
Programmable Voltage Output	0 to 40V	1mV	0.05% ±9mV
Programmable Current Output	0 to 5A	1mA	0.2% ±9mA
Fixed Outputs	5V/2A and 3.3V/3A		
Ripple & Noise	Voltage (mVrms): 3mV Current (mArms): 3mA		
Power Source	110 or 220VAC, 50/60Hz		
Dimensions	12.2 x 9.9 x 5.3" (310 x 250 x 135mm)		
Weight	8.4lbs (3.8kg)		

### Ordering Information:

382280 .....40V/5A Precision Programmable DC Power Supply



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Bench Top Power Supplies](#) category:*

*Click to view products by [Extech](#) manufacturer:*

Other Similar products are found below :

[NL200](#) [PR20](#) [ZUPNC403](#) [Z60-7-L-U](#) [ZUPNC402](#) [GDM-8342](#) [GPIB](#) [PSW 250-4.5](#) [CPX200DP](#) [AX-8450A](#) [TPM-3003](#) [HMP2020](#)  
[HMP2030](#) [HMP4040](#) [1320](#) [1350](#) [UT804](#) [1405](#) [1410](#) [1513](#) [1514](#) [1513](#) [1550](#) [1651A](#) [1665](#) [1666](#) [1667](#) [SDP-2405-000G](#) [1673](#) [1693](#) [1694](#)  
[MX100TP](#) [1737](#) [1739](#) [1762](#) [1788](#) [TPM-3005](#) [1900](#) [1902B](#) [9174B](#) [GDM-8245](#) [GDM-8255A](#) [GDM-8341](#) [PSW 160-7.2](#) [PSW 30-36](#) [PSW](#)  
[80-13.5](#) [Z10-20-LAN-U](#) [PSW 30-72](#) [QL355P SII](#) [Z36-6-LAN-U](#) [HCS-3400-USB](#)